USB Connection & Selection

J1
USB_C_Receptacle_USB2.0_14P
VBUS
CC1
CC2
D-
D-
D+
D+
SHIELD
GND
A4
A5
B5
A7
B7
A6
B6
A1
B4
B12
USB_D-
USB_D+
5k1 R1
5k1 R3
R7 22
R8 22
D-
D+
S1
VBUS
PWR_FLAG
C5 10u
C6 100n
GND

Power Supply

VBUS
U5
NCP1117-3.3_SOT223
VI
VO
GND
3.3V
C34 10u
C35 10u
PWR_FLAG

POWER LED

EMERALD GREEN
R29 1K
3.3V
Changed to emerald green

PD LED

RED
R30 1K
PWDN

UART

Conn_01x05_Pin
TX
RX
CTS
RTS

RESET

S2
TS-1088-AR02016
RESET
100n C5
Replaced button to basic component

C33 100n 1.2V
C16 1u 1.2V
C14 100n 1.2V
C15 10u 1.2V
C8 100n 1.2V
C11 1u 3.3V
C10 10u 3.3V
C17 100n 3.3V
C21 100n 3.3V
C22 100n 3.3V
C23 100n 3.3V
C24 100n 3.3V
C25 100n 3.3V
C2 1u 3.3V
C12 1u 3.3V
Added lcsc tags for 1v2 caps
Changed name to match footprint of c10
Added lcsc tags for missing places

RP2350B

R5 1K
R21 10K
RESET
R4 200
C4 2.2u
C1 2.2u
L4 DFE252012F-3R3M=P2
12MHz_10pF_50ohm
Y1
R23 1K
C26 20p
C27 20p
Chnaged load caps to 20p

RP2350
80-Pin
X4

/RUN 35
IOVDD 68
USB_OTP_VDD 61
VREG_AVDD 59
ADC_AVDD 64
VREG_VIN 63
DVDD 65
VREG_LX 62
VREG_FB
VREG_PGND
XIN 30
XOUT 31
GPIO32/MISO0/TX0/SDA0/PWM8A 40
GPIO33/CS0/RX0/SCL0/PWM8B 42
GPIO34/SCK0/CTS0/SDA1/PWM9A 43
GPIO35/MOSI0/RTS0/SCL1/PWM9B 44
GPIO36/MISO0/TX1/SDA0/PWM10A 45
GPIO37/CS0/RX1/SCL0/PWM10B 46
GPIO38/SCK0/CTS1/SDA1/PWM11A 47
GPIO39/MOSI0/RTS1/SCL1/PWM11B 48
GPIO40/ADC0/MISO1/TX1/SDA0/PWM8A 49
GPIO41/ADC1/CS1/TX1/SCL0/PWM8B 52
GPIO42/ADC2/SCK1/CTS1/SDA1/PWM9A 53
GPIO43/ADC3/MOSI1/RTS1/SCL1/PWM9B 54
GPIO44/ADC4/MISO1/TX0/SDA0/PWM10A 55
GPIO45/ADC5/CS1/RX0/SCL0/PWM10B 56
GPIO46/ADC6/SCK1/CTS0/SDA1/PWM11A 57
GPIO47/ADC7/MOSI1/RTS0/SCL1/PWM11B 58
PSRAM_CS
QSPI_IOVDD 69
QSPI_SCK 71
QSPI_CS 75
QSPI_SD0 72
QSPI_SD1 74
QSPI_SD2 73
QSPI_SD3 70
GND 81

XPI_CS1/MISO0/TX0/SDA0/PWM0A/GPIO0 77 DATA2
CS0/RX0/SCL0/PWM0B/GPIO1 78 DATA3
SCK0/CTS0/SDA1/PWM1A/GPIO2 79 DATA4
MOSI0/RTS0/SCL1/PWM1B/GPIO3 80 DATA5
MISO0/TX1/SDA0/PWM2A/GPIO4 1 DATA6
CS0/RX1/SCL0/PWM2B/GPIO5 2 DATA7
SCK0/CTS1/SDA1/PWM3A/GPIO6 3 DATA8
MOSI0/RTS1/SCL1/PWM3B/GPIO7 4 DATA9
XIP_CS1/MISO1/TX1/SDA0/PWM4A/GPIO8 6 EXT_XCLK
CS1/RX1/SCL0/PWM4B/GPIO9 7 HSYNC
SCK1/CTS1/SDA1/PWM5A/GPIO10 8 VSYNC
MOSI1/RTS1/SCL1/PWM5B/GPIO11 9 PCLK
HSTX/MISO1/TX0/SDA0/PWM6A/GPIO12 11
HSTX/CS1/RX0/SCL0/PWM6B/GPIO13 12
HSTX/SCK1/CTS0/SDA1/PWM7A/GPIO14 13
HSTX/MOSI1/RTS0/SCL1/PWM7B/GPIO15 14
HSTX/MISO0/TX0/SDA0/PWM0A/GPIO16 16 TX
HSTX/CS0/RX0/SCL0/PWM0B/GPIO17 17 RX
HSTX/SCK0/CTS0/SDA1/PWM1A/GPIO18 18 CTS
HSTX/MOSI0/RTS0/SCL1/PWM1B/GPIO19 19 RTS
SDA 20
SCL 21
CAM_RESET 22
PWDN 23
USBBOOT 25
GPIO26 27
USB_D- 66 D-
USB_D+ 67 D+
SWCLK 33 SWCLK
SWDIO 34 SWDIO

PSRAM BANK SWITCHING

R6 10K
C48 1u
U4
74LVC1G19
GPIO26
PSRAM_CS
R16 10K
C7 1u
U7
APS1604M-3SQRx-SN
U1
APS1604M-3SQRx-SN
QSPI_SCK
QSPI_DATA[0]
QSPI_DATA[1]
QSPI_DATA[2]
QSPI_DATA[3]
SI/SIO0
SO/SIO1
SIO2
SIO3
C9 1u

CAN BUS

C45 100n
CAN_STBY
R32 10K
C29 0.1uF
C28 10uF
R15 2.2K
L6
RED
U3
MCP2515-xST
U6
SN65HVD230
CAN_TX
CAN_RX
CAN_STBY
CANH
CANL
JP3
CAN_TERM
R31 120
J4
CAN
MH1
MH2
CAN_MOSI
CAN_MISO
CAN_CS
CAN_SCK
CAN_OSC2
CAN_OSC1
RXCAN
TXCAN
CAN_RX
CAN_TX
CAN_INT
D1
1N4148WT
R14 10K
C20 0.1uF
16MHz
Y2
C46 12pF
C47 12pF

CAMERA

DEBUGOA
SWCLK
SWDIO
JST_SH3

Power supply

U8
TLV74328
C29 10uF
C30 10uF
C31 1uF
C32 10uF
C33 10uF
C34 0.1uF
2.8V
U9
TLV74315
C41 10uF
C42 1u
C43 10uF
1.5V

I2C Pullups & Shift

R9 10K
U2
W25Q128JVS
QSPI_CS
QSPI_SCK
QSPI_DATA[0]
QSPI_DATA[1]
QSPI_DATA[2]
QSPI_DATA[3]
HOLD/RESET/IO3
C13 1u
R26 1K
D3 1N4148
USBBOOT
TESTPOINTROUND1.5MMNO
S1
TS-1088-AR02016
Replaced button to basic component

I2C Pullups & Shift

FB1
Ferrite
C36 1u
C39 0.1uF
R10 10K
R12 10K
R13 10K
R11 10K
C40 0.1uF
SCL
SDA
XCLK
CAM_RESET
PWDN
STROBE
TESTPOINTROUND1.5MM
SJ1
SOLDERJUMPER_2WAY
EXT_XCLK
INT_XCLK
C44 22pF
SJ2
SOLDERJUMPER
24MHz 3.3V Oscillator

Sheet: /
File: Adafruit Metro RP2350.kicad_sch
Title: Nagyonmeno cucmurucc
Size: A2 | Date: | Rev: 0.067
KiCad E.D.A. 10.0.6 | Id: 1/1