

Android Interface Documentation

1. Introduction

This Android SDK Interface Programming Manual describes how to connect to printers via Bluetooth and Wi-Fi and send content to the printer.

2. Creating Printer Connections

Creating a USB Connection `val name = data?.getStringExtra(UsbDevicesActivity.USB_NAME)`

```
tvState.text = "Connecting..."
```

```
val usb: PrinterDevices? = Build()
```

```
.setContext(this)
```

```
.setDeviceType(DeviceType.USB)
```

```
.setUsbDevice(getUsbDeviceFromName(this, name))
```

```
.build()
```

```
printerManager.connectPrinter(usb)
```

Creating a Bluetooth Connection `val bluetooth = PrintDevices.Build()`

```
.setDeviceType(DeviceType.BLUETOOTH)
```

```
.setMacAddress("12:34:56:78:9A:3C")
```

```
.build()
```

```
val portManager= SppBluetoothPort(bluetooth)
```

```
portManager.openPort()
```

Creating a Wi-Fi Connection `val wifi = PrintDevices.Build()`

```
.setDeviceType(DeviceType.WIFI)
```

```
.setIp("1792.168.12.13")
```

```
.setPort("9100")
```

```
.build()
```

```
val portManager = EthernetPort(wifi)
```

```
portManager.openPort()
```

```
openPort()
```

This method may block the thread, so it is recommended to call it in a worker thread to prevent ANR.

3. Print

```
portManager.writeDataImmediately(data:ByteArray,isReadReceive:Boolean)
```

```
portManager.writeDataImmediately(data:Vector<Byte>,isReadReceive:Boolean)
```

4. Turn off the printer

```
portManager.closePort()
```

5. Enumeration class DeviceType

Variable	Description
BLUETOOTH	Bluetooth Type

WIF	Network Type
USB	USB Type
BLE_BLUETOOTH	BLE Type

6. setCallbackListener

void setCallbackListener(PortCallbackListener callbackListener)

【Parameter】

A listener

```
public interface PortCallbackListener {  
    default void onConnecting(){}  
    default void onSuccess(PrintDevices printDevices){}  
    default void onReceive(byte[] data){}  
    default void onFailure(String failure){}  
    default void onDisconnect(PrintDevies printDevices){}  
}
```

Method	Description
onConnecting	Start connecting
onSuccess	Connection successful
onReceive	Device returns information
onFailure	Connection failed
onDisconnect	Connection disconnected

 ■ PrintDevices

Object passed for device connection

 ■ data

Information returned by the device

 ■ faiore

Prompt message for device connection failure

7. isConnect

Get printer connection status

8. writeDataImmediatly

void writeDataImmediatly(Vector<Byte> data,boolean isReadReceive)

void writeDataImmediatly(byte[] data ,boolean isReadReceive)

【Parameter】

data Send printer data

isReadReceive Whether to read the printer's returned information (returned via the onReceive method in PortCallbackListener)

Note: This method is a time-consuming operation and will block the thread.

9. readData

nt readData(byte[] data)

Note: This method is a time-consuming operation and will block the thread.

【Parameter】 data Data payload

【Return value】 Data returned by the printer

10. colsePort

Close connection

void colsePort()

Note: This method is a time-consuming operation and will block the thread.