


Combinational ATPG

- Introduction
- Deterministic Test Pattern Generation
 - ◆ Boolean difference approach*
 - ◆ Path sensitization method**
 - ◆ D-Algorithm [Roth 1966] **
 - ◆ PODEM [Goel 1981] **
 - ◆ FAN [Fujiwara 1983]**
 - ◆ SAT-based [Larrabee 1992] *
- Acceleration Techniques
- Concluding Remarks


*Boolean-based methods

**path-based methods




D → PODEM → FAN

- D-algorithm decision at **internal nodes** → too many decisions, slow!
- PODEM decision at **PI** → too little information, mistake-prone!
- FAN decision at **head lines** and **fanout stems** → good trade-off




D-alg.

too many decisions



FAN

good trade-off



PODEM

too little information

— decision points

FAN [Fujiwara 1983]


- ***FANout-oriented test generation***
- **Four improvements over PODEM**
 - ◆ #1. Make decision at head lines or fanout stem
 - ◆ #2. Forward/backward Implications
 - ◆ #3. Unique sensitization
 - ◆ #4. Multiple backtraces



<https://insights.ubuntu.com>

Justify Head Line Is Easy

- Justification inside **FFC** (*fanout-free cone*) is **linear time**
 - ♦ Guaranteed to find an answer
- Example: a, b, c, e, f are PI, k is *head line*
 - ♦ objective $k = 1$




**Can Make Decision at Head Line
Instead of PI**

Head Line


- **Bound line**: line fed directly (*i, k*) or indirectly (*m*) by fanout stem
- **Free Line**: line that is not Bound (*a~f, h, j*)
- **Head Line**: free line that is either
 - ♦ Fanout stem (*j*), or
 - ♦ Input to a gate with bound output (*h*)

In CPP code, a line, a gate output and the gate itself are bound together. This means, if a gate output connect to a bound/free/head line directly, the gate



#1. Make Decision at Head Lines

- FFC can be isolated from rest of circuit by cutting head lines
- Assignment of PI's that feed head lines are
 - ♦ deferred until other objectives have been achieved
 - * Reduce search space




Head Lines Reduces Search Space

Example


- PODEM decision tree is **big**

- ♦ $A=1, B=0$
 - * No test, backtrack
- ♦ $B=1, C=0$
 - * No test, backtrack
- ♦ $C=1$




- FAN decision tree is **small**

- ♦ $J=0$
 - * No test, backtrack
- ♦ $J=1$



PODEM




FAN

Quiz

Q: Which are bound lines? free lines? head lines?



A: LEFHJK ABCE AE



#2. Forward/backward Implication


Note 1: Implication means NO choice. Note 2: Implication can be done any time a decision is made.

- PODEM does not assign internal values
 - ♦ Only forward implication, no backward implication
- FAN assigns internal values when they are uniquely implied
 - ♦ Both forward and backward implication
- Example: *L* SA1 fault
- FAN
 - ♦ Bwd: $JKE=1, H=0, A=1, B=1$
 - ♦ Fwd: $G=1$
 - ♦ Bwd: $K=1, C=0$
 - ♦ no backtrack needed
- PODEM
 - ♦ Backtrace to $B=0$
 - ♦ Forward implication
 - ♦ Wrong! backtrack



FAN Example

.....headlines



Headlines: a b c e f G4 (dashed lines)

Initial objective: G1 output =1

Implication: assign a = 1; b=1

Implication

Objective: propagate through G3, objective G2=0

Implication: assign c = 1; e=1

Propagate through G5, objective G4=1

Assign headline G4 = 1

Make decision
at head line

G5=D, Objective achieved.

Justify head line G4 = 1 → h=1


Justify head
lines at end

Test generated abcehjf = 11111xx

Quiz

Q: If we want $K=1$, apply implication to determine head lines
 $A=?$ $E=?$

ANS:



FAN


- **Four improvements over PODEM**
 - ◆ #1. Make decision at head lines or fanout stem
 - ◆ #2. Forward/backward Implications
 - ◆ #3. Unique sensitization
 - ◆ #4. Multiple backtraces



www.walmart.com


#3. Unique Sensitization

- When there is only one gate in D-frontier
 - ♦ if unique path exists, set side inputs to non-controlling values
- Example:
 - ♦ FAN
 - * **G2** is unique D-frontier, only one path to *H*
 - * $G1 = 1, E = 1, F = 1, A = 1 \rightarrow B = 0 \rightarrow$ success!
 - ♦ PODEM
 - * Initial objective: $G1 = 1 \rightarrow$
 - * backtrace to $A = 0 \rightarrow$ X-path disappear!




#4. Multiple Backtraces

- PODEM uses **depth-first search (DFS)**
 - ♦ One single backtrace at a time
- FAN uses **breadth first search (BFS)**
 - ♦ Multiple parallel search at a time
- Example
 - ♦ PODEM needs **6 backtraces**
 - ♦ FAN needs only **1 multiple backtrace**





PODEM



FAN


Rules for Multiple Backtraces

- Objective: (x, n_0, n_1)
 - ◆ number of backtraced zeros (n_0) and ones (n_1) on signal x
- For AND gate
 - ◆ Easiest unspecified input x_1
 - * $(x_1, n_0, n_1) = (y, n_0, n_1)$
 - ◆ Other inputs x_2, x_3
 - * $(x_2, n_0) = 0$
 - * $(x_2, n_1) = (y, n_1)$
- For fanout Stem
 - * $(x, n_0) = \text{sum of } (y_i, n_0)$
 - * $(x, n_1) = \text{sum of } (y_i, n_1)$



Example

- Starting from $(K,0,5)$, multiple backtrace to head lines A and E
 - So we get two assignments $A=0$, $E=1$




I think I understand why this algorithm is rarely used in the industry. In C++ code, a gate is bound to a line that connects to its output. Even if a gate is a sequential element with two outputs, it is split into two one-output gates, each bound to an output line. This means that processing fan-out branches becomes challenging.

I think I understand why there are virtual gates. These gates can occupy all fanout branches, allowing us to store information about these branches within them.

Quiz


Q: Starting from $(K, 5, 0)$, multiple backtrace to head lines
 $(E, n_0, n_1)=?$ $(A, n_0, n_1)=?$ Suppose H is chosen over J

A:



Multiple Backtrace Conflict

- What if change G_2 to OR gate?
- Want $K=1$, perform multiple backtrace to headlines A and E
 - ♦ conflicting values at E !



- How to handle a conflict ?
 - ♦ assign a value **most requested**, then start next backtrace
 - ♦ will backtrack if it is wrong

Multiple Backtrace (1/2)

```
MultipleBacktrace (Initial_objectives, Fanout_objectives) {  
  Current_objectives = Initial_objectives  
  while (Current_objectives  $\neq \emptyset$  or Fanout_objectives  $\neq \emptyset$ ) {  
    dequeue entry  $(k, v_k)$  from Current or Fanout_objectives  
    switch (type of entry) {
```

// (k, v_k) = want v_k on signal k

1. **HEAD_LINE:**

add (k, v_k) to **Headline_objectives**

2. **FANOUT_BRANCH:**

The first two kinds of objects will initially be added to Current_objectives. They will then be moved to either Headline_objectives or Fanout_objectives.

$j = \text{stem}(k);$

increment n_0 or n_1 at j for v_k ; //sum of n_0, n_1

add j to **Fanout_objectives**

3. **GATE:**

//page 15

$i = \text{inversion of } k; c = \text{controlling value of } k;$

if $((v_k \oplus i) == c)$ {

select easiest input j with unknown value

add (j, c) to **Current_objectives**;

else {

for every input j of k with value

add (j, c') to **Current_objectives**; }

} // switch

Multiple Backtrace (2/2)

(cont'd from previous page)

*simplified from Fig. 8 of FAN paper


This code is incomplete and lacks certain repetitive operations.

```
if(Fanout_objectives  $\neq \phi$ ) {  
    dequeue highest-level stem ( $k$ ) from Fanout_Objectives  
     $v_k = 0$  or  $1$ , depends on which of ( $n_0, n_1$ ) is larger  
    if there is no conflict on  $k$  {  
        add ( $k, v_k$ ) to Current_objectives // continue backtrace  
    else { return ( $k, v_k$ ) as the Final_objective // stop backtrace  
    else { // no fanout objective  
        dequeue ( $k, v_k$ ) from Headline_objectives  
        return ( $k, v_k$ ) as the Final_objective }  
    } // while  
} // MultipleBacktrace
```

MultipleBacktrace

final_objective


(either a fanout or a headline)



initial_objectives


fanout_objectives

Multiple Backtrace Example (1/3)



Current Obj.	processed entry	Fanout Obj.	Headline Obj.
$(m,1)(g_2,1)(q,1)$	$(m,1)$	-	$(h,1)$
$(g_2,1)(q,1)(g_1,1)$	$(g_2,1)$	$(g, n_1=1)$	$(h,1)$
$(q,1)(g_1,1)$	$(q,1)$	$(g, n_1=1)$	$(h,1)$
$(g_1,1)(f_2,0)$	$(g_1,1)$	$(g, n_1=2)$	$(h,1)$
$(f_2,0)$	$(f_2,0)$	$(g, n_1=2) (f, n_0=1)$	$(h,1)$
-	$(g,1)$ consistent	$(f, n_0=1)$	$(h,1)$
$(g,1)$	$(g,1)$	$(f, n_0=1)$	$(h,1)(a,1)$
$(f_1,1)$	$(f_1,1)$	$(f, n_0=1 \ n_1=1)$	$(h,1)(a,1)$
-	f conflict!	-	$(h,1)(a,1)$


Multiple Backtrace Example (2/3)



because $n_0=n_1=1$, just choose randomly
suppose we assign $f = 0$
forward implication
inconsistent with initial objectives!
backtrack to $f=1$

**Decision at Fanout Stem
Detects Inconsistency Earlier**


Multiple Backtrace Example (3/3)



Multiple Backtrace is Fast


PODEM v.s. FAN

PODEM



FAN


HL = head line; FO = fanout




Difference highlighted in **Blue**

Summary

- 1. Make decision at **head lines** and **fanout stem**
 - ♦ Reduce search space
- 2. Forward/**backward Implications**
 - ♦ More information to make correct decision
- 3. **Unique sensitization**
 - ♦ Unique path to output
- 4. **Multiple backtraces**
 - ♦ BFS to search many paths together



Flowchart of PODEM



Flowchart of FAN

*simplified from Fig. 9 of FAN paper

