

# BENCHMARK COMPLIANCE AUDIT REPORT

CIS | NIST SP 800-53 | DISA STIG | ISO 27001

Generated: 2026-09-10 15:21:05

Devices Audited: 2

AUDIT SUMMARY

| Device | Vendor | Score | Passed | Failed | Risk |
|--------|--------|-------|--------|--------|------|
|--------|--------|-------|--------|--------|------|

|                 |         |       |         |    |    |        |
|-----------------|---------|-------|---------|----|----|--------|
| juniper_srx.cfg | Juniper | JunOS | 140/184 | 40 | 21 | MEDIUM |
|-----------------|---------|-------|---------|----|----|--------|

|         |       |     |        |    |    |      |
|---------|-------|-----|--------|----|----|------|
| ASA.txt | Cisco | ASA | 82/184 | 30 | 31 | HIGH |
|---------|-------|-----|--------|----|----|------|

|       |  |           |         |    |    |  |
|-------|--|-----------|---------|----|----|--|
| TOTAL |  | 2 devices | 222/368 | 70 | 52 |  |
|-------|--|-----------|---------|----|----|--|

## DEVICE 1/2: juniper\_srx.cfg

**Config File:** /Users/kkrishnabhanushali/Documents/sih26155-poc/uploads/juniper\_srx.cfg

**Vendor:** Juniper JunOS

**Total Rules:** 61

**Score:** 140 / 184

**Risk Level:** MEDIUM

### PASSED RULES (40)

**PASS AUTH-001** Enable AAA new-model for centralized authentication, authorization, and accounting

Evidence: Line 3: set system authentication-order radius | Line 4: set system authentication-order password | Line 20: set system ...

**PASS AUTH-002** AAA authentication must be configured for SSH, login, or enable access

Evidence: Line 3: set system authentication-order radius | Line 4: set system authentication-order password | Line 18: set system ...

**PASS AUTH-003** AAA authentication login history should be enabled for audit trail

Evidence: Line 7: set system login retry-options tries-before-disconnect 3 | Line 8: set system login retry-options logout-period...

**PASS AUTH-004** Cleartext 'enable password' should not be used; use 'enable secret' with strong hashing instead

Evidence: Not present (compliant)

**PASS AUTH-005** Password encryption service must be enabled to protect stored passwords

Evidence: Line 10: set system login password minimum-length 15 | Line 11: set system login password minimum-upper-cases 1 | Line 1...

**PASS AUTH-006** Local user accounts must use strong passwords (min 8 chars, not easily guessable)

Evidence: Line 18: set system login user admin class super-user

**PASS AUTH-007** AAA accounting must be configured to log all administrative actions

Evidence: Line 31: set system syslog host 10.0.0.10 any info | Line 32: set system syslog host 10.0.0.11 any info | Line 35: set s...

**PASS AUTH-008** AAA authorization must be configured for command-level access control

Evidence: Line 16: set system login class ADMIN permissions all

**PASS ACCESS-001** Telnet must be disabled on all VTY lines; use SSH only

Evidence: Not present (compliant)

**PASS ACCESS-002** SSH must be configured as the only remote access method on VTY lines

Evidence: Line 22: set system services ssh protocol-version v2 | Line 23: set system services ssh connection-limit 3 | Line 24: se...

**PASS ACCESS-003** SSH access must be restricted to specific subnets/interfaces

Evidence: Line 28: set system services ssh root-login deny | Line 50: set firewall family inet filter RESTRICT\_MGMT\_ACCESS term AL...

**PASS ACCESS-004** SSH strict host key checking should be enabled to prevent MITM attacks

Evidence: Line 25: set system services ssh macs hmac-sha2-256 | Line 29: set system services ssh hostkey-algorithm ssh-rsa

**PASS ACCESS-005** SSH session timeout must be configured to prevent idle sessions

Evidence: Line 9: set system login idle-timeout 10 | Line 17: set system login class ADMIN idle-timeout 5 | Line 23: set system se...

**PASS ACCESS-006** SSH key exchange must use strong groups (dh-group14-sha256 or higher); dh-group1...

Evidence: Line 25: set system services ssh macs hmac-sha2-256

**PASS ACCESS-007** Console timeout must be set to a non-zero value to prevent unauthorized access from idle sessions

Evidence: Line 9: set system login idle-timeout 10

**PASS ACCESS-008** Telnet timeout configuration suggests Telnet may be in use; Telnet should be completely disabled

Evidence: Not present (compliant)

**PASS ACCESS-009** VTY lines should have access-class applied to restrict management access to trusted IPs

Evidence: Line 49: set interfaces lo0 unit 0 family inet filter input RESTRICT\_MGMT\_ACCESS | Line 50: set firewall family inet fil...

**PASS ACCESS-010** Exec timeout must be set on console and VTY lines to auto-disconnect idle sessions

Evidence: Line 9: set system login idle-timeout 10 | Line 17: set system login class ADMIN idle-timeout 5

**PASS ACCESS-011** SSH version 2 must be enforced; SSH version 1 has known vulnerabilities

Evidence: Line 22: set system services ssh protocol-version v2

**PASS SNMP-001** Default SNMP community string 'public' must not be used

Evidence: Not present (compliant)

**PASS SNMP-002** Default SNMP community string 'private' must not be used

Evidence: Not present (compliant)

**PASS SNMP-003** SNMPv3 should be configured for encrypted and authenticated SNMP communications

Evidence: Line 55: set snmp v3 usm local-engine user snmpuser authentication-sha authentication-password "securepass" | Line 56: s...

**PASS LOG-001** Syslog server must be configured for centralized log collection and analysis

Evidence: Line 31: set system syslog host 10.0.0.10 any info | Line 32: set system syslog host 10.0.0.11 any info

**PASS LOG-002** Local logging buffer must be configured for on-device log retention

Evidence: Line 33: set system syslog file messages any notice | Line 34: set system syslog file messages authorization info | Line...

**PASS LOG-003** Log messages must include timestamps with date/time for accurate forensic analysis

Evidence: Line 2: set system time-zone UTC | Line 39: set system syslog time-format year millisecond

**PASS LOG-004** Logging trap level should be configured for appropriate syslog message filtering

Evidence: Line 31: set system syslog host 10.0.0.10 any info | Line 32: set system syslog host 10.0.0.11 any info | Line 33: set s...

**PASS CRYPTO-002** CA trustpool policy should be configured for certificate validation

Evidence: Line 64: set security pki ca-profile CA-PROFILE ca-identity "Enterprise-CA"

**PASS CRYPTO-003** RSA keys must be generated with a minimum modulus of 2048 bits for SSH

Evidence: Line 25: set system services ssh macs hmac-sha2-256 | Line 26: set system services ssh ciphers aes256-cbc | Line 29: set...

**PASS MGMT-001** Login banner must be configured to display legal/warning notice before authentication

Evidence: Line 5: set system login message "Authorized access only. All activity is monitored."

**PASS MGMT-002** MOTD banner should be configured to display operational warnings

Evidence: Line 6: set system login announcement "Maintenance window: Sundays 02:00-04:00 UTC"

**PASS MGMT-003** Hostname must be set for device identification in logs and management

Evidence: Line 1: set system host-name JUNIPER-FW01

**PASS THREAT-001** Basic threat detection must be enabled to identify common attack patterns

Evidence: Line 61: set security screen ids-option untrust-screen tcp syn-flood alarm-threshold 1024 | Line 62: set security screen...

**PASS THREAT-002** Threat detection ACL statistics should be enabled for monitoring denied traffic patterns

Evidence: Line 61: set security screen ids-option untrust-screen tcp syn-flood alarm-threshold 1024 | Line 62: set security screen...

**PASS THREAT-003** TCP intercept statistics should be enabled for SYN flood detection

Evidence: Line 61: set security screen ids-option untrust-screen tcp syn-flood alarm-threshold 1024 | Line 62: set security screen...

**PASS INTF-001** Unused interfaces should be administratively shut down to reduce attack surface

Evidence: Line 47: set interfaces ge-0/0/2 disable

**PASS INTF-002** Management interface should be restricted to management traffic only

Evidence: Line 49: set interfaces lo0 unit 0 family inet filter input RESTRICT\_MGMT\_ACCESS

**PASS NTP-001** NTP server must be configured for accurate time synchronization across all log sources

Evidence: Line 40: set system ntp server 10.0.0.1 prefer | Line 41: set system ntp server 10.0.0.2

**PASS NTP-002** NTP authentication must be enabled to prevent time-source spoofing

Evidence: Line 42: set system ntp authentication-key 1 type md5 value "\$9\$encrypted" | Line 43: set system ntp trusted-key [1 2]

**PASS ROUTE-001** OSPF authentication must be enabled to prevent unauthorized route injection

Evidence: Line 58: set protocols ospf area 0.0.0.0 interface ge-0/0/0.0 authentication md5 1 key "\$9\$encrypted"

**PASS ROUTE-002** BGP neighbor authentication must be configured to prevent unauthorized peering

Evidence: Line 59: set protocols bgp group EBGP-PEERS peer-as 65001 | Line 60: set protocols bgp group EBGP-PEERS authentication-k...

**FAILED RULES (21)****FAIL LOW SNMP-004** SNMP location should be cleared or set to a non-revealing value to avoid in...

Evidence: Configuration not found

Remediation: no snmp-server location

**FAIL LOW SNMP-005** SNMP contact should be cleared or set to a non-revealing value to avoid inf...

Evidence: Configuration not found

Remediation: no snmp-server contact

**FAIL HIGH SVC-001** HTTP server must be disabled to prevent unencrypted management access

Evidence: Configuration not found

Remediation: no ip http server

**FAIL MEDIUM SVC-002** HTTPS server should be disabled unless explicitly required for device management

Evidence: Configuration not found

Remediation: no ip http secure-server

**FAIL MEDIUM SVC-003** CDP should be disabled globally or on untrusted interfaces to prevent infor...

Evidence: Configuration not found

Remediation: no cdp run

**FAIL MEDIUM SVC-004** LLDP should be disabled to prevent network topology disclosure

Evidence: Configuration not found

Remediation: no lldp run

**FAIL HIGH SVC-005** IP source routing must be disabled to prevent routing manipulation attacks

Evidence: Configuration not found

Remediation: no ip source-route

**FAIL HIGH SVC-006** IP directed broadcasts must be disabled to prevent smurf amplification attacks

Evidence: Configuration not found

Remediation: no ip directed-broadcast

**FAIL MEDIUM SVC-007** Finger service must be disabled to prevent user enumeration

Evidence: Configuration not found

Remediation: no service finger

**FAIL MEDIUM SVC-008** BOOTP server must be disabled to prevent unauthorized network booting

Evidence: Configuration not found

Remediation: no ip bootp server

**FAIL MEDIUM SVC-009** Proxy ARP must be disabled to prevent traffic interception

Evidence: Configuration not found

Remediation: no ip proxy-arp

**FAIL LOW SVC-010** TCP keepalives (inbound) should be enabled to clean up dead sessions

Evidence: Configuration not found

Remediation: service tcp-keepalives-in

**FAIL LOW SVC-011** TCP keepalives (outbound) should be enabled to clean up dead sessions

Evidence: Configuration not found

Remediation: `service tcp-keepalives-out`

**FAIL LOW SVC-012** FTP passive mode should be configured for secure file transfers

Evidence: Configuration not found

Remediation: `ftp mode passive`

**FAIL LOW SVC-013** ASDM history should be disabled if ASDM is not in active use

Evidence: Configuration not found

Remediation: `no asdm history enable`

**FAIL MEDIUM SVC-014** Call-home and anonymous reporting should be disabled to prevent information disclosure

Evidence: Configuration not found

Remediation: `no call-home reporting anonymous`

**FAIL LOW SVC-015** ICMP unreachable messages should be rate-limited to mitigate reconnaissance

Evidence: Configuration not found

Remediation: `icmp unreachable rate-limit 1 burst-size 1`

**FAIL LOW SVC-016** ARP rate limiting should be configured to mitigate ARP flooding attacks

Evidence: Configuration not found

Remediation: `arp rate-limit 16384`

**FAIL MEDIUM SVC-017** Non-connected ARP entries should be denied to prevent ARP spoofing

Evidence: Configuration not found

Remediation: `no arp permit-nonconnected`

**FAIL MEDIUM CRYPTO-001** IPsec SA PMTU aging should be configured for proper tunnel maintenance

Evidence: Configuration not found

Remediation: `crypto ipsec security-association pmtu-aging infinite`

**FAIL LOW DAP-001** Dynamic access policy should be configured for VPN access control

Evidence: Configuration not found

Remediation: `dynamic-access-policy-record DfltAccessPolicy`

## UNKNOWN COMMANDS - NEEDS HUMAN REVIEW (0)

*All commands recognized.*

## DEVICE 2/2: ASA.txt

**Config File:** /Users/kkrishnabhanushali/Documents/sih26155-poc/uploads/ASA.txt

**Vendor:** Cisco ASA

**Total Rules:** 61

**Score:** 82 / 184

**Risk Level:** **HIGH**

### PASSED RULES (30)

**PASS AUTH-001** Enable AAA new-model for centralized authentication, authorization, and accounting

Evidence: Line 80: aaa authentication ssh console LOCAL | Line 81: aaa authentication login-history

**PASS AUTH-002** AAA authentication must be configured for SSH, login, or enable access

Evidence: Line 80: aaa authentication ssh console LOCAL | Line 81: aaa authentication login-history

**PASS AUTH-003** AAA authentication login history should be enabled for audit trail

Evidence: Line 81: aaa authentication login-history

**PASS AUTH-006** Local user accounts must use strong passwords (min 8 chars, not easily guessable)

Evidence: Line 97: username Marcraft privilege 15 password Marcraft1

**PASS ACCESS-001** Telnet must be disabled on all VTY lines; use SSH only

Evidence: Not present (compliant)

**PASS ACCESS-002** SSH must be configured as the only remote access method on VTY lines

Evidence: Line 89: ssh 192.168.5.0 255.255.255.0 inside

**PASS ACCESS-003** SSH access must be restricted to specific subnets/interfaces

Evidence: Line 89: ssh 192.168.5.0 255.255.255.0 inside

**PASS ACCESS-004** SSH strict host key checking should be enabled to prevent MITM attacks

Evidence: Line 88: ssh stricthostkeycheck

**PASS ACCESS-005** SSH session timeout must be configured to prevent idle sessions

Evidence: Line 90: ssh timeout 15

**PASS ACCESS-009** VTY lines should have access-class applied to restrict management access to trusted IPs

Evidence: Line 89: ssh 192.168.5.0 255.255.255.0 inside

**PASS ACCESS-010** Exec timeout must be set on console and VTY lines to auto-disconnect idle sessions

Evidence: Line 90: ssh timeout 15 | Line 92: console timeout 0

**PASS SNMP-001** Default SNMP community string 'public' must not be used

Evidence: Not present (compliant)

**PASS SNMP-002** Default SNMP community string 'private' must not be used

Evidence: Not present (compliant)

**PASS SNMP-004** SNMP location should be cleared or set to a non-revealing value to avoid information disclosure

Evidence: Line 82: no snmp-server location

**PASS SNMP-005** SNMP contact should be cleared or set to a non-revealing value to avoid information disclosure

Evidence: Line 83: no snmp-server contact

**PASS SVC-012** FTP passive mode should be configured for secure file transfers

Evidence: Line 61: ftp mode passive

**PASS SVC-013** ASDM history should be disabled if ASDM is not in active use

Evidence: Line 65: no asdm history enable

**PASS SVC-014** Call-home and anonymous reporting should be disabled to prevent information disclosure

Evidence: Line 101: no call-home reporting anonymous | Line 104: no active

**PASS SVC-015** ICMP unreachable messages should be rate-limited to mitigate reconnaissance

Evidence: Line 64: icmp unreachable rate-limit 1 burst-size 1

**PASS SVC-016** ARP rate limiting should be configured to mitigate ARP flooding attacks

Evidence: Line 68: arp rate-limit 16384

**PASS SVC-017** Non-connected ARP entries should be denied to prevent ARP spoofing

Evidence: Line 67: no arp permit-nonconnected

**PASS CRYPTO-001** IPsec SA PMTU aging should be configured for proper tunnel maintenance

Evidence: Line 85: crypto ipsec security-association pmtu-aging infinite

**PASS CRYPTO-002** CA trustpool policy should be configured for certificate validation

Evidence: Line 86: crypto ca trustpool policy

**PASS MGMT-003** Hostname must be set for device identification in logs and management

Evidence: Line 3: hostname ciscoasa | Line 100: prompt hostname context

**PASS THREAT-001** Basic threat detection must be enabled to identify common attack patterns

Evidence: Line 93: threat-detection basic-threat

**PASS THREAT-002** Threat detection ACL statistics should be enabled for monitoring denied traffic patterns

Evidence: Line 94: threat-detection statistics access-list

**PASS THREAT-003** TCP intercept statistics should be enabled for SYN flood detection

Evidence: Line 95: no threat-detection statistics tcp-intercept

**PASS INTF-001** Unused interfaces should be administratively shut down to reduce attack surface

Evidence: Line 13: shutdown | Line 19: shutdown | Line 25: shutdown

**PASS INTF-002** Management interface should be restricted to management traffic only

Evidence: Line 55: management-only

**PASS DAP-001** Dynamic access policy should be configured for VPN access control

Evidence: Line 96: dynamic-access-policy-record DfltAccessPolicy

**FAILED RULES (31)****FAIL HIGH AUTH-004** Cleartext 'enable password' should not be used; use 'enable secret' with st...

Evidence: VIOLATION FOUND - Line 4: enable password Marcraft1

Remediation: no enable password

**FAIL HIGH AUTH-005** Password encryption service must be enabled to protect stored passwords

Evidence: Configuration not found

Remediation: service password-encryption

**FAIL MEDIUM AUTH-007** AAA accounting must be configured to log all administrative actions

Evidence: Configuration not found

Remediation: aaa accounting exec default start-stop group tacacs+

**FAIL MEDIUM AUTH-008** AAA authorization must be configured for command-level access control

Evidence: Configuration not found

Remediation: aaa authorization exec default local



**FAIL HIGH ACCESS-006** SSH key exchange must use strong groups (dh-group14-sha256 or higher); dh-g...

Evidence: VIOLATION - Line 91: ssh key-exchange group dh-group1-sha1

Remediation: `ssh key-exchange group dh-group14-sha256`

**FAIL HIGH ACCESS-007** Console timeout must be set to a non-zero value to prevent unauthorized acc...

Evidence: VIOLATION - Line 92: console timeout 0

Remediation: `console timeout 5`

**FAIL HIGH ACCESS-008** Telnet timeout configuration suggests Telnet may be in use; Telnet should b...

Evidence: VIOLATION FOUND - Line 87: telnet timeout 5

Remediation: `no telnet timeout`

**FAIL HIGH ACCESS-011** SSH version 2 must be enforced; SSH version 1 has known vulnerabilities

Evidence: Configuration not found

Remediation: `ip ssh version 2`

**FAIL MEDIUM SNMP-003** SNMPv3 should be configured for encrypted and authenticated SNMP communications

Evidence: Configuration not found

Remediation: `snmp-server group <group-name> v3 priv`

**FAIL HIGH SVC-001** HTTP server must be disabled to prevent unencrypted management access

Evidence: Configuration not found

Remediation: `no ip http server`

**FAIL MEDIUM SVC-002** HTTPS server should be disabled unless explicitly required for device management

Evidence: Configuration not found

Remediation: `no ip http secure-server`

**FAIL MEDIUM SVC-003** CDP should be disabled globally or on untrusted interfaces to prevent infor...

Evidence: Configuration not found

Remediation: `no cdp run`

**FAIL MEDIUM SVC-004** LLDP should be disabled to prevent network topology disclosure

Evidence: Configuration not found

Remediation: `no lldp run`

**FAIL HIGH SVC-005** IP source routing must be disabled to prevent routing manipulation attacks

Evidence: Configuration not found

Remediation: `no ip source-route`

**FAIL HIGH SVC-006** IP directed broadcasts must be disabled to prevent smurf amplification attacks

Evidence: Configuration not found

Remediation: `no ip directed-broadcast`

**FAIL MEDIUM SVC-007** Finger service must be disabled to prevent user enumeration

Evidence: Configuration not found

Remediation: `no service finger`

**FAIL MEDIUM SVC-008** BOOTP server must be disabled to prevent unauthorized network booting

Evidence: Configuration not found

Remediation: `no ip bootp server`

**FAIL MEDIUM SVC-009** Proxy ARP must be disabled to prevent traffic interception

Evidence: Configuration not found

Remediation: `no ip proxy-arp`

**FAIL LOW SVC-010** TCP keepalives (inbound) should be enabled to clean up dead sessions

Evidence: Configuration not found

Remediation: `service tcp-keepalives-in`

**FAIL LOW SVC-011** TCP keepalives (outbound) should be enabled to clean up dead sessions

Evidence: Configuration not found

Remediation: `service tcp-keepalives-out`

**FAIL HIGH LOG-001** Syslog server must be configured for centralized log collection and analysis

Evidence: Configuration not found

Remediation: logging host &lt;syslog-server-ip&gt;

**FAIL MEDIUM LOG-002** Local logging buffer must be configured for on-device log retention

Evidence: Configuration not found

Remediation: logging buffered informational

**FAIL MEDIUM LOG-003** Log messages must include timestamps with date/time for accurate forensic analysis

Evidence: Configuration not found

Remediation: service timestamps log datetime msec localtime show-timezone

**FAIL MEDIUM LOG-004** Logging trap level should be configured for appropriate syslog message filtering

Evidence: Configuration not found

Remediation: logging trap informational

**FAIL HIGH CRYPTO-003** RSA keys must be generated with a minimum modulus of 2048 bits for SSH

Evidence: Configuration not found

Remediation: crypto key generate rsa modulus 2048

**FAIL MEDIUM MGMT-001** Login banner must be configured to display legal/warning notice before authentication

Evidence: Configuration not found

Remediation: banner login @

**FAIL LOW MGMT-002** MOTD banner should be configured to display operational warnings

Evidence: Configuration not found

Remediation: banner motd @

**FAIL HIGH NTP-001** NTP server must be configured for accurate time synchronization across all log sources

Evidence: Configuration not found

Remediation: ntp server &lt;ntp-server-ip&gt;

**FAIL MEDIUM NTP-002** NTP authentication must be enabled to prevent time-source spoofing

Evidence: Configuration not found

Remediation: ntp authenticate

**FAIL MEDIUM ROUTE-001** OSPF authentication must be enabled to prevent unauthorized route injection

Evidence: Configuration not found

Remediation: interface &lt;interface&gt;

**FAIL MEDIUM ROUTE-002** BGP neighbor authentication must be configured to prevent unauthorized peering

Evidence: Configuration not found

Remediation: router bgp &lt;as-number&gt;

**UNKNOWN COMMANDS - NEEDS HUMAN REVIEW (2)****UNKNOWN L66** arp timeout 14400

Needs human review

**UNKNOWN L84** service sw-reset-button

Needs human review