

Experiment No. 1

FLASHING OF LED USING AT89C51 MICROCONTROLLER USING PROTEUS

Objectives

1. To study the basic operation of AT89C51 microcontroller.
2. To interface an LED with microcontroller.
3. To generate LED blinking using a software delay.

Program:

ORG 0000H

UP: SETB P2.0

ACALL DELAY

CLR P2.0

ACALL DELAY

SJMP UP

DELAY: MOV R4,#35

H1:MOV R3,#255

H2:DJNZ R3,H2

DJNZ R4,H1

RET

END

Output:

