
ADVANTEST®**ADVANTEST CORPORATION**

ASX/U-51

SYSTEST TESTUTL ATLworks

UPDATE NOTICE

REV 6.03

MANUAL NUMBER 8262527-58b

Applicable Products

PASX51-93****
PASX51-92****
PASX51-91****
PASX51-85****
PASX51-81****
PASX51-77****
PASX51-75****
PASX51-71****
PASX51-70****
PASX51-36****

PREFACE

ADVANTEST, ADVANsite, ATLworks and ATL are trademarks of ADVANTEST Corporation.

Sun, Sun Microsystems, the Sun Logo, SunOS and Solaris are trademarks or registered trademarks of Sun Microsystems, Inc. in the United States and other countries.

All other marks referenced herein are trademarks or registered trademarks of their respective owners.

RECORD OF REVISIONS

Manual Rev	Date	Remarks (Software REV)	Manual Rev	Date	Remarks (Software REV)
56	Mar 7/03	(REV 6.01)			
57	May 15/03	(REV 6.02)			
58	Jul 25/03	(Obsolete)			
58a	Sep 22/03	(Obsolete)			
58b	Oct 31/03	(REV 6.03)			

TABLE OF CONTENTS

1. SUMMARY OF REVISION	1-1
2. ENHANCED FUNCTIONS	2-1
2.1 T5377 Compatibility	2-1
2.2 The T5376 and T5375 Socket Program	2-2
2.3 The T5593 Socket Program	2-2
2.4 CFM 4 Kwords Compatibility	2-2
2.5 32-Character Compatibility of Various Names of Pattern Programs	2-3
2.6 Expanding Category Numbers	2-4
2.7 Expanding Test Numbers	2-5
2.8 Enlarged Character Header (/HD1, /HD2, /TITLE)	2-6
2.9 ATLworks	2-6
2.10 Adding the Path Name for Online Manuals	2-6
3. IMPROVED ITEMS	3-1
3.1 Tester Driver Controller	3-1
3.1.1 Changing the LV Driver Setting Range	3-1
3.1.2 VS Statement	3-2
3.1.3 Pin Statement	3-3
3.1.4 SEND DBM and SEND CBM Statements	3-4
3.1.5 READ CNT Statement	3-4
3.2 Tester Utility Program	3-4
3.2.1 Pattern Tracer (/MTRACE)	3-4
3.2.2 Two-Dimensional Shmoo Plot (SHM2)	3-5
3.2.3 Handler Control Program with GPIB Interface (/STHAND)	3-5
3.2.4 Debugger (/DEBUG)	3-5
3.2.5 Operation Panel	3-6
3.2.6 Utility which Writes Individual Data for Each DUT	3-6
3.2.7 Driver Output Setting Utility for Individual DUTs	3-6
3.2.8 Utility that Uses the Universal Buffer Memory	3-7
3.3 ATLworks	3-7
3.4 Hybrid Controller	3-7

1. SUMMARY OF REVISION

(1) Revision number

- ASX/U-51 REV 6.03

(2) Applicable systems

- T5593
- T5592
- T5591/T5591R
- T5586/T5585
- T5581/T5581H
- T5581P/T5571P
- T5377
- T5376/T5375
- T5371
- T5336/T5311

(3) Related manual revised

- | | |
|--|------------|
| • ATL-51 TEST PLAN PROGRAM REFERENCE MANUAL | 8431498-05 |
| • ATL-51 SOCKET PROGRAM REFERENCE MANUAL | 8256293-20 |
| • ATL-51 SCRAMBLE PROGRAM REFERENCE MANUAL | 8256294-17 |
| • ATL-51 PATTERN PROGRAM REFERENCE MANUAL (T5500) | 8256292-27 |
| • ATL-51 PATTERN PROGRAM REFERENCE MANUAL
(T5377/T5376/T5375/T5371/T5336/T5311) | 8289058-16 |
| • T5500 SERIES TESTER UTILITY PROGRAM REFERENCE MANUAL | 8256295-36 |
| • T5500 SERIES CONTROLLER COMMAND REFERENCE MANUAL | 8256297-23 |
| • T5300 SERIES FLASH MEMORY PARALLEL MEASUREMENT
FUNCTION DESCRIPTION | 8239605-15 |
| • ATLworks TOOL USER'S MANUAL | 8311174-14 |
| • ASX/U-51 BASIC SYSTEM SOFTWARE SOFTWARE
SPECIFICATIONS | 8256273-14 |
| • ASX/U-51 HYBRID CONTROLLER USER'S MANUAL | 8409598-08 |
| • ASX/U-51 HYBRID CONTROLLER REFERENCE MANUAL | 8409600-07 |
| • ERROR CODE TABLE REFERENCE MANUAL | 8141091-74 |
| • ADVANsite TEST SYSTEM SOFTWARE INSTALLATION/SYSTEM
START USER'S MANUAL VOL1 BASIC OS INSTALLATION | 8227728-21 |

1. SUMMARY OF REVISION

- ADVANsite TEST SYSTEM SOFTWARE INSTALLATION/SYSTEM
START USER'S MANUAL VOL2 TESTER ENVIRONMENT
SOFTWARE INSTALLATION 8227729-21
- Online Manual Reference Manual 8431523-06

(4) Reason of revision

- Addition of functions
- Improvement of functions

(5) Products revised

Products revised in this revision are shown below:

Product code	Product name		
PASX51-93****	SYSTEST51SU	TESTUTL51SU	ATW51SU
PASX51-92****			
PASX51-91****			
PASX51-85****			
PASX51-81****			
PASX51-77****			
PASX51-75****			
PASX51-71****			
PASX51-70****			
PASX51-36****			

ASX/U-51 SYSTEST TESTUTL ATLworks UPDATE NOTICE REV 6.03

1. SUMMARY OF REVISION

(6) List of revisions

The revision list shows the revision correspondence of the basic software the SYSTEST51SU, TESTUTL51SU and ATW51SU of ASX/U-51.

<Explanation of the revisions' list>

- (a) “*” shows the product revised in the revision.
- (b) “–” shows the product that does not exist to the whole revision.

ASX/U-51				
ASX/U-51 Overall Revision	Revision for each product			SunOS Revision
	SYSTEST51SU	TESTUTL51SU	ATW51SU	
5.04A	5.04A *	5.04A *	–	Solaris 2.5.1 Solaris 7
5.04A1	5.04A1 *	5.04A1 *	–	Solaris 2.5.1 Solaris 7
5.04A2	5.04A2 *	5.04A1	–	Solaris 2.5.1 Solaris 7
5.04A3	5.04A3 *	5.04A1	–	Solaris 2.5.1 Solaris 7
5.04A4	5.04A4 *	5.04A2 *	–	Solaris 2.5.1 Solaris 7
5.05(Note1)	5.05 *	5.05 *	5.05 *	Solaris 8
6.00	6.00 *	6.00 *	6.00 *	Solaris 2.5.1 Solaris 7 Solaris 8
6.00-1	6.00-1 *	6.00-1 *	6.00-1 *	Solaris 2.5.1 Solaris 7 Solaris 8
6.00-2	6.00-2 *	6.00-1	6.00-1	Solaris 2.5.1 Solaris 7 Solaris 8
6.00A	6.00A *	6.00A *	6.00A *	Solaris 2.5.1 Solaris 7 Solaris 8
6.00A1	6.00A1 *	6.00A1 *	6.00A	Solaris 2.5.1 Solaris 7 Solaris 8

ASX/U-51 SYSTEST TESTUTL ATLworks UPDATE NOTICE REV 6.03

1. SUMMARY OF REVISION

ASX/U-51				
ASX/U-51 Overall Revision	Revision for each product			SunOS Revision
	SYSTEST51SU	TESTUTL51SU	ATW51SU	
6.00B	6.00B *	6.00B *	6.00B *	Solaris 2.5.1 Solaris 7 Solaris 8
6.00C	6.00C *	6.00C *	6.00C *	Solaris 2.5.1 Solaris 7 Solaris 8
6.00C1	6.00C1 *	6.00C1 *	6.00C	Solaris 2.5.1 Solaris 7 Solaris 8
6.01(Note2)	6.01 *	6.01 *	6.01 *	Solaris 8
6.02	6.02 *	6.02 *	6.02 *	Solaris 2.5.1 Solaris 7 Solaris 8
6.03	6.03 *	6.03 *	6.03 *	Solaris 2.5.1 Solaris 7 Solaris 8

Note1: REV 5.05 is used for the T5375.

Note2: REV 6.01 is used for the T5593.

2. ENHANCED FUNCTIONS

2.1 T5377 Compatibility

This software can now be used with the T5377.

The T5377 is now includes a function which tests the maximum of 256 DUTs (x8-bit configuration) in parallel (128-DUT per station) in the AFM double-speed mode and a function which counts the number of cycles in which a failure occurs during the functional test (the READ AFM Failure Cycle Count statement).

The following programs have been updated depending on their compatibility with the T5377:

- Tester driver controller
- Pin monitor (/PM)
- Data set (/Unit name)
- Data scan (/DS)
- 2-dimension shmoo plot (SHM2)
- 3-dimension shmoo plot (SHM3)
- Pattern tracer (/MTRACE)
- Data log (/DTLOG)
- Error code utility (/ERR)
- Voltage measurement program (VMEAS)
- Extension pin monitor (/EPM)
- MARGIN program (/MARGIN)
- Fail bit map (FBMAP)
- Fail memory data transfer (/FMXFER)
- Utility which writes individual data for each DUT
- Utility which sets driver output individually for each DUT
- Utility which reads system information (RDSYSTEM)
- Utility which measures the pulse count (PULSECNT)
- Utility which uses the universal buffer memory
- M command
- T command
- P command
- ATLworks

Compatible compilers: XATL/U-51(PXTL51-36S***) REV 3.02 or later

The following programs cannot be used with the T5377:

- Memory redundancy subroutine (FMSEARCH)
- Memory redundancy subroutine (FMSCAN)

2.2 The T5376 and T5375 Socket Program

The following parallel test functions have been added.

- Multiple-DUT parallel testing which uses child pins A1, A5, B1, B5, C1, C5, D1, D5, E1, E5, F1, F5, G1, G5, H1, and H5 as I/O channels.
- Multiple-DUT parallel testing which uses child pins A1, A3, A5, A7, B1, B3, B5, B7 through H1, H3, H5, and H7 as I/O channels instead of using pins whose pin number is equal to or larger than 97 when PIN MODE=B is specified.

For more information, refer to “ATL-51 SOCKET PROGRAM REFERENCE MANUAL.”

The following program has been upgraded due to this function enhancement:

- Tester driver controller

Relevant test systems: T5376 and T5375

Compatibility compiler: XATL/U-51(PXTL51-36S***) REV 3.02 or later

2.3 The T5593 Socket Program

The following parallel test functions have been added.

- 256-DUT parallel test (128 DUTs per station) performed by specifying PIN MODE=B; 16 DUTs per child pin and by assigning I/O channels P33-41 and P51-53, and I/O channels P42-50 and P54-56 to different DUTs.

For more information, refer to “ATL-51 SOCKET PROGRAM REFERENCE MANUAL.”

The following program has been upgraded due to this function enhancement:

- Tester driver controller
- Data log (/DTLOG)
- DQS test utility
- DFM simultaneous capture utility
- M command

Relevant test systems: T5593

Compatibility compiler: XATL/U-51(PXTL51-00S***) REV 6.03 or later

2.4 CFM 4 Kwords Compatibility

CFM capacity has been expanded from 256 words to 4 Kwords when BBM is not used.

For more information, refer to “ATL-51 TEST PLAN PROGRAM REFERENCE MANUAL.”

The following program has been upgraded due to this function enhancement:

- Tester driver controller

Relevant test systems: T5376 and T5375

2.5 32-Character Compatibility of Various Names of Pattern Programs

Various names of the pattern program can now be specified by using up to 32 characters as shown below.

An underscore (`_`) has been added to the character types that can be used to specify the following names.

Name	Number of characters	Character type
Label	32	Alphanumeric characters and underscores (<code>_</code>)
Burst block name	32	Alphanumeric characters and underscores (<code>_</code>)
Mnemonic defined in the SDEF statement	32	Alphanumeric characters and underscores (<code>_</code>)
Packet name specified in the PKT statement	32	Alphanumeric characters and underscores (<code>_</code>)

For more information, refer to “ATL-51 PATTERN PROGRAM REFERENCE MANUAL.”

The following program has been upgraded due to this function enhancement:

- Tester driver controller

Relevant test systems: T5593, T5592, T5591, T5591R, T5586, T5585, T5581, T5581H, T5581P, T5571P, T5376, T5375, T5371, T5336, and T5311

Compatibility compiler: XATL/U-51(PXTL51-00S***) REV 6.03 or later
XATL/U-51(PXTL51-36S***) REV 3.02 or later

2.6 Expanding Category Numbers

The category number specification range has been expanded from 1 through 200 to 1 through 999.

The following user areas can now be used due to this function enhancement:

Test system Number of DUTs in parallel	T5591, T5591R, T5581, T5581H, T5581P, T5571P, T5336, T5311	T5593, T5592, T5586, T5585, T5376, T5375, T5371
64-DUT parallel test on 1 station	Approx. 5.3 MB (Approx. 5.0 MB)	Approx. 9.5 MB (Approx. 9.2 MB)
128-DUT parallel test on 1 station	-	Approx. 8.7 MB (Approx. 8.2 MB)
256-DUT parallel test on 1 station	-	Approx. 7.2 MB (Approx. 6.2 MB)
128-DUT parallel test on 2 stations	Approx. 4.9 MB (Approx. 4.4 MB)	Approx. 9.1 MB (Approx. 8.6 MB)
256-DUT parallel test on 2 stations	-	Approx. 7.9 MB (Approx. 6.9 MB)
512-DUT parallel test on 2 stations	-	Approx. 5.7 MB (Approx. 3.6 MB)

Note: *The free area after allocating the wafer counter area is shown in parentheses.
The wafer counter area is allocated when **PROBER** is written in the socket program.*

The following program has been upgraded due to this category number expansion:

- Tester driver controller
- Hybrid controller
- Communication control library
- Parallel test monitor program (/MPDISP)
- Yield report (/YIELD)
- Handler control program with GPIB interface (/STHAND)
- Category and sort data output program (lcommand)
- C command
- L command
- ATLworks

Relevant test systems: T5593, T5592, T5591, T5591R, T5586, T5585, T5581, T5581H, T5581P, T5571P, T5376, T5375, T5371, T5336, and T5311

Compatibility compiler: XATL/U-51(PXTL51-00S***) REV 6.03 or later
XATL/U-51(PXTL51-36S***) REV 3.02 or later

2.7 Expanding Test Numbers

The test number specification range has been expanded from 0 through 9999 to 0 through 99999 and the test number range which retains PASS/FAIL information has been expanded from 0 through 999 to 0 through 9999.

The following user areas can now be used due to this function enhancement:

Test system Number of DUTs in parallel	T5591, T5591R, T5581, T5581H, T5581P, T5571P, T5336, T5311	T5593, T5592, T5586, T5585, T5376, T5375, T5371
64-DUT parallel test on 1 station	Approx. 5.3 MB (Approx. 5.0 MB)	Approx. 9.5 MB (Approx. 9.2 MB)
128-DUT parallel test on 1 station	-	Approx. 8.7 MB (Approx. 8.2 MB)
256-DUT parallel test on 1 station	-	Approx. 7.2 MB (Approx. 6.2 MB)
128-DUT parallel test on 2 stations	Approx. 4.9 MB (Approx. 4.4 MB)	Approx. 9.1 MB (Approx. 8.6 MB)
256-DUT parallel test on 2 stations	-	Approx. 7.9 MB (Approx. 6.9 MB)
512-DUT parallel test on 2 stations	-	Approx. 5.7 MB (Approx. 3.6 MB)

Note: The free area after allocating the wafer counter area is shown in parentheses.
The wafer counter area is allocated when **PROBER** is written in the socket program.

The following program has been upgraded due to this test number expansion:

- Tester driver controller
- Hybrid controller
- Communication control library
- 2-dimension shmoo plot (SHM2)
- 3-dimension shmoo plot (SHM3)
- Fail test display (/FTDISP, /FTLIST)
- Data log (/DTLOG)
- Partial test (/PART)
- Extension pin monitor (/EPM)
- Pin monitor for each MEAS statement (/PMSET)
- Fail bit map (FBMAP)
- O command
- M command
- .T command

- C command
- L command
- N command
- A command
- CTRL/B command
- ATLworks

Relevant test systems: T5593, T5592, T5591, T5591R, T5586, T5585, T5581, T5581H, T5581P, T5571P, T5376, T5375, T5371, T5336, and T5311

Compatibility compiler: XATL/U-51(PXTL51-00S**) REV 6.03 or later
XATL/U-51(PXTL51-36S**) REV 3.02 or later

2.8 Enlarged Character Header (/HD1, /HD2, /TITLE)

Alphabetic characters can now be output in lower case.

For more information, refer to "T5500 SERIES TESTER UTILITY PROGRAM REFERENCE MANUAL."

Relevant test systems: T5593, T5592, T5591, T5591R, T5586, T5585, T5581, T5581H, T5581P, T5571P, T5376, T5375, T5371, T5336, and T5311

2.9 ATLworks

The Category Window of the Control Panel can now display up to 999 due to the category number expansion.

Relevant test systems: T5593, T5592, T5591, T5591R, T5586, T5585, T5581, T5581H, T5581P, T5571P, T5376, T5375, and T5371

2.10 Adding the Path Name for Online Manuals

Executing the tester environment setting script (set-testenv) sets environment to use the tester controller.

The search path for the acroread command which is used to display online manuals has been added to the environment settings set by the set-testenv command.

For more information, refer to Section, "ADVANSite TEST SYSTEM SOFTWARE INSTALLATION/ SYSTEM START USER'S MANUAL VOL2 TESTER ENVIRONMENT SOFTWARE INSTALLATION."

Relevant test systems: T5593, T5592, T5591, T5591R, T5586, T5585, T5581, T5581H, T5581P, T5571P, T5376, T5375, T5371, T5336, and T5311

3. IMPROVED ITEMS

3.1 Tester Driver Controller

3.1.1 Changing the LV Driver Setting Range

(1) INH Statement

If the INH high level voltage value specified for the LV driver channel was specified within the following range, a runtime error (code = 3111) occurred.

$$0 \text{ V} \leq \text{Voltage value} < 0.5 \text{ V}$$

Improved ➡ The specified value is now correctly set.

Relevant revisions: REV 5.05 through REV 6.02

Relevant test systems: T5375

(2) Two-dimensional shmoo plot (SHM2) and three-dimensional shmoo plot (SHM3)

If voltage for the unit name HINH was set within the following range for INH specified for the LV driver channel, question marks (?) were displayed in the plot.

$$0 \text{ V} \leq \text{Voltage value} < 0.5 \text{ V}$$

Improved ➡ The PASS/FAIL results are now correctly displayed.

Relevant revisions: REV 5.05 through REV 6.02

Relevant test systems: T5375

(3) Utility which sets driver output individually for each DUT

If the INH high level voltage value specified for the LV driver channel was specified within the following range, an error (code = 5) occurred.

$$0 \text{ V} \leq \text{Voltage value} < 0.5 \text{ V}$$

Improved ➡ The specified value is now correctly set.

Relevant revisions: REV 5.05 through REV 6.02

Relevant test systems: T5375

3.1.2 VS Statement

If one of the following options; a, b, or c was specified after the MVM mode was set for the VS_n by using the VS statement when more than 70 channels of the PPS numbers 1 through 128 or the PPS numbers 129 through 256 had been assigned to one VS_n (Note) by using the socket program or the SELECT VS PPS statement, a system error (FATAL TEST SYSTEM ERROR) occurred and the system power was turned off.

- (a) Modes other than MVM were specified by using the S statement
- (b) OPEN was specified by using the S statement
- (c) The SELECT VS PPS statement was specified when parallel testing was not specified in a socket program

Note: *Unassigned PPS numbers were assigned to VS1.*

Example:

```
SELECT VS1 PPS1-70
SELECT VS2 PPS71-128
```

```
TIME1=3MS:VS1,VS2
VS1=MVM,M(16V)
VS2=5V,R(5V),M(4UA)
SR0N
:
SR0F
```

```
VS1=5V,R(5V),M(4UA) → A system error occurred and the system power was turned off
```

Improved ➡ No system error occurs and the system power is not turned off.

Relevant revisions: REV 5.05 through REV 6.02

Relevant test systems: T5376 and T5375

3.1.3 Pin Statement

- (1) If the difference between the driver high and low level voltages was within the following range after the connection conditions for channel number 56, 120, 184, or 248 was changed during the WET status when the T5593 test system in which the high-speed clock driver was not installed, a runtime error (code = 3111) occurred.

$V_{IH} - V_{IL} > 2.0 \text{ V}$

Example:

```
IN1 = 2.002V 0V      ←  $V_{IH} - V_{IL} > 2.0 \text{ V}$ 
```

```
SET WET
RON
```

```
P56 = IN1,BCLK1,CCLK1,RZ0,HSCMAIN,LINIT,<C0> → A runtime error
                                         (code = 3111) occurred.
```

Improved ➡ This problem has been fixed.

Relevant versions: REV 6.01 through REV 6.02

Relevant test system: T5593

- (2) If the difference between the driver high and low level voltages was within the following range after the connection conditions for channel number 55, 119, 183, or 247 was changed during the WET status when the T5593 test system in which the high-speed clock driver was installed, a runtime error (code = 3111) did not occur.

$V_{IH} - V_{IL} > 2.0 \text{ V}$

Example:

```
IN1 = 2.002V 0V      ←  $V_{IH} - V_{IL} > 2.0 \text{ V}$ 
```

```
SET WET
RON
```

```
P55 = IN1,BCLK1,CCLK1,RZ0,HSCMAIN,LINIT,<C0> → A runtime error (code =
                                         3111) did not occur.
```

Improved ➡ A runtime error (code = 3111) now occurs.

Relevant versions: REV 6.01 through REV 6.02

Relevant test system: T5593

3.1.4 SEND DBM and SEND CBM Statements

If a pattern program, whose DBM patterns and CBM patterns existed in multiple modules, was continuously transferred by using the SEND DBM and SEND CBM statement, either a runtime error (code = 12245) occurred when a pattern program was transferred for the 2nd time or later or a pattern, whose module was different from the module specified in REG MPAT PC, was transferred.

Example:

```
REG MPAT PC=#10
SEND DBM DBMPAT → The transfer was correctly performed.

REG MPAT PC=#20
SEND DBM DBMPAT → A runtime error (code = 12245)
                  occurred or a pattern, whose module was different
                  from the module specified in REG MPAT PC, was
                  transferred.
```

Improved ➡ The patterns of the specified module are now correctly transferred.

Relevant version: REV 6.02

Relevant test systems: T5592, T5591, T5591R, T5586, T5585, T5581, T5581H, T5581P, and T5571P

3.1.5 READ CNT Statement

If the counter number, 0 to 51, was specified in the READ CNT statement, the contents of the counter number, 1151 to 1300 (category 51 to 200 counter), was read followed by the contents of the specified counter number to the counter number 51 (category 50 counter).

Improved ➡ The contents of the specified counter number to the counter number 51 are now read.

Relevant version: REV 1.01 through REV 6.02

Relevant test systems: T5591, T5591R, T5581, T5581H, T5581P, T5571P, T5336, and T5311

3.2 Tester Utility Program

3.2.1 Pattern Tracer (/MTRACE)

- (1) If the XALD instruction was specified when tracing the X addresses, addresses output by using the XALD instruction were traced regardless of which output data was selected to be traced.

Improved ➡ The X address is now traced only when the address data output through the prescrambler is selected as the output data to be traced.

Relevant revisions: REV 6.01 through REV 6.02

Relevant test systems: T5593

- (2) If the DUT was not specified in the SELECT PRESCRAM ADDRESS statement, the address data output through the prescrambler could not be traced even though the address data output through the prescrambler was selected as the output data to be traced.

Improved ➡ The address data output through the prescrambler is now traced regardless of the specification in the SELECT PRESCRAM ADDRESS statement.

Relevant versions: REV 1.00 through REV 6.02

Relevant test systems: T5593, T5592, T5591, T5591R, T5586, T5585, T5581, T5581H, T5581P, T5571P, T5376, T5375, and T5371

3.2.2 Two-Dimensional Shmoo Plot (SHM2)

DC shmoo performed measurement only once, regardless of the number of times the measurement is specified in the MEAS DC, START DC, MEAS VS, or START VS statement.

Improved ➡ DC shmoo now measures the average value for the specified number of times the measurement is performed.

Relevant versions: REV 1.00 through REV 6.02

Relevant test systems: T5593, T5592, T5591, T5591R, T5586, T5585, T5581, T5581H, T5581P, T5571P, T5376, T5375, T5371, T5336, and T5311

3.2.3 Handler Control Program with GPIB Interface (/STHAND)

If the DUT automatic recognition mode was used when diagnosis performance board was mounted, the following error message was displayed when the controller was started or ST-HAND was finished.

DUT NUMBER SELECT setting on the tester does not match the setting on the STNn handler.

Change DUTNUMSEL Function to Tester Side on the STNn handler, or check DUT NUMBER SELECT STNn Handler for the correct setting on the tester.

Improved ➡ The message is not displayed.

Relevant revisions: REV 5.00 through REV 6.02

Relevant test systems: T5593, T5592, T5591, T5591R, T5586, T5585, T5581, T5581H, T5581P, T5571P, T5376, T5375, T5371, T5336, and T5311

3.2.4 Debugger (/DEBUG)

If an output unit was specified in the \$V command, the output unit was enabled for both the \$V command and the \$B command.

Improved ➡ VKT is always the output unit for the \$B command.

Relevant revisions: REV 6.02

Relevant test systems: T5593, T5592, T5591, T5591R, T5586, T5585, T5581, T5581H, T5581P, T5571P, T5376, T5375, T5371, T5336, and T5311

3.2.5 Operation Panel

If a program which is executed from the Load sub window by selecting Load from the File menu was set, the program was not set even though the program was specified using between 9 and 32 characters.

Improved ➡ The program is now set to be executed by the specified program.

Relevant version: REV 6.02

Relevant test systems: T5593, T5592, T5591, T5591R, T5586, T5585, T5581, T5581H, T5581P, T5571P, T5376, T5375, T5371, T5336, and T5311

3.2.6 Utility which Writes Individual Data for Each DUT

(1) MFMSSEND

When MFMSSEND was executed, even though the program terminated correctly, an error (ERR=11) occurred.

Improved ➡ MFMSSEND executes correctly.

Relevant version: REV 6.02

Relevant test systems: T5376 and T5375

(2) IDSELFIM

When IDSELFIM was executed, a pin, whose pin number was different from the DUT pin number specified in PIN, was specified as a pin that uses the data transferred from the AFM. In addition, a pin, whose pin number was different from the DUT pin number specified in FD49PIN, was specified as the pin that uses the pin 49 data transferred from the AFM.

Improved ➡ A pin, which uses the DUT pin number specified in PIN, is specified. Also, the pin, whose pin number is specified in FD49PIN, is specified as the pin that uses the pin 49 data transferred from the AFM.

Relevant version: REV 6.02

Relevant test systems: T5376 and T5375

3.2.7 Driver Output Setting Utility for Individual DUTs

If 1(INH) was specified in UNT in LEVELSET, even though the program terminated correctly, an error (ERR=6) occurred.

Improved ➡ The program executes correctly.

Relevant revision: REV 6.02

Relevant test systems: T5376 and T5375

3.2.8 Utility that Uses the Universal Buffer Memory

When 1 (UBM is used for the UBM driver pattern generation) was specified to ARG2 in IIDSELUBM, a pin, whose pin number was different from the DUT pin number specified in ARG6, was specified as the pin that uses the written data.

Improved ➡ When 1 (UBM is used for the UBM driver pattern generation) was specified in ARG2 in IIDSELUBM, a pin, whose pin number is specified in ARG6, is specified as the pin that uses the written data.

Relevant revision: REV 6.02

Relevant test systems: T5376 and T5375

3.3 ATLworks

Variables equal to or more than 32 characters could not be referred to while debugging the C program in ASXDebugger.

Improved ➡ Variables equal to or more than 32 characters can now be referred to.

Relevant revisions: REV 6.00A through REV 6.02

Relevant test systems: T5593, T5592, T5586, T5585, T5376, and T5375

3.4 Hybrid Controller

If a variable of the C program was passed to the ATL subroutine as an argument and the argument was specified as the argument of one of the following utility program in the ATL subroutine, the utility program either did not correctly read the results for variables that were specified in the argument or did not correctly set the conditions specified in the argument.

Improved ➡ The results are now correctly read and the conditions are now correctly set.

- Relevant utility programs: DQS test utility
 - (a) A utility which reads PASS/FAIL COUNTER
 - (b) A utility which reads FAIL COUNTER
 - (c) A utility which reads PASS/FAIL COUNTER and FAIL COUNTER condition information

Relevant version: REV 6.00A through REV 6.02

Relevant test systems: T5593 and T5586

- Relevant utility programs: Auto scan mode utility
 - (a) A utility which reads AUTOSCAN COUNTER

Relevant version: REV 6.02

Relevant test systems: T5593

- Relevant utility programs: A utility which sets driver output individually for each DUT
 - (a) LEVELSET

Relevant version: REV 6.00 through REV 6.02

Relevant test systems: T5376 and T5375

- Relevant utility programs: A utility which writes individual data for each DUT
 - (a) MFMSSEND
 - (b) IDSELFMT

Relevant version: REV 6.00 through REV 6.02

Relevant test systems: T5376 and T5375
- Relevant utility programs: Time measurement program (TMEAS) and voltage measurement program (VMEAS)

Relevant version: REV 6.01 through REV 6.02

Relevant test system: T5593
- Relevant utility programs: A utility which uses the universal buffer memory
 - (a) IDSELUBMT

Relevant version: REV 6.00 through REV 6.02

Relevant test systems: T5376 and T5375