

实现对键盘事件的监听 (Linux)

- 按键码对照表: <https://git.kernel.org/pub/scm/linux/kernel/git/torvalds/linux.git/tree/include/uapi/linux/input-event-codes.h> 或 [lvgl_100ask_course_v9/part3/02_codes/lesson_4-2/input-event-codes.h](#)

hook_kb.c (lvgl_100ask_course_v9\part3\02_codes\lesson_4-2\hook_kb.c)

```
#include <stdio.h>
#include <stdlib.h>
#include <unistd.h>
#include <string.h>
#include <sys/types.h>
#include <fcntl.h>
#include <errno.h>
#include <time.h>
#include <linux/input.h>

/*
# 编译
export PATH=$PATH:/home/ubuntu/100ask/T113s4_Lvgl9-Class_TinaSDK-
V1/prebuilt/rootfsbuilt/arm/toolchain-sunxi-glibc-gcc-830/toolchain/bin
export CROSS_COMPILE=arm-openwrt-linux-gnueabi
export STAGING_DIR=/home/ubuntu/100ask/T113s4_Lvgl9-Class_TinaSDK-
V1/out/t113_s4/100ask_lvgl9/openwrt/staging_dir/target

arm-openwrt-linux-gnueabi-gcc hook_kb.c -o hook_kb

# 确定节点命令: cat /proc/bus/input/devices

# 在ubuntu连接开发板的adb
adb push ./hook_kb /mnt/UDISK

# 运行
./hook_kb
*/
int main(void)
{
    int keys_fd;
    char ret[2];
    struct input_event t;
    keys_fd = open("/dev/input/event6", O_RDONLY);
    if (keys_fd <= 0)
    {
        printf("open /dev/input/event6 device error!\n");
        return 0;
    }

    while (1)
    {
```

```

    if (read(keys_fd, &t, sizeof (t)) == sizeof (t))
    {
        if (t.type == EV_KEY)
        if (t.value == 0 || t.value == 1)
        {
            // 键码表:
            https://git.kernel.org/pub/scm/linux/kernel/git/torvalds/linux.git/tree/include/uapi/linux/in
            put-event-codes.h
            // 或 lvgl_100ask_course_v9/part3/02_codes/lesson_4-2/input-event-codes.h
            printf("key %d %s\n", t.code, (t.value) ? "Pressed" : "Released");
            if (t.code == KEY_ESC)
                break;
        }
    }
}

close(keys_fd);

return 0;
}

```

技术交流学习

欢迎加入讨论：

- 社区交流： <https://forums.100ask.net>
- QQ技术交流群（如群满，请加qq：401684796 验证备注：LVGL）：962138234
- 微信交流群：添加微信：baiwenkeji_fae 验证备注：LVGL

拓展阅读

- <https://lvgl.100ask.net/master/porting/display.html#rotation>