

# OS LAB MANUAL (CS23431)

Roll No:230701254

EX.NO:8

## PRODUCER CONSUMER USING SEMAPHORES

Aim: To write a C program to do Inter Process Communication (IPC) using shared memory between sender process and receiver process

Program:

```
#include<stdio.h>

#include<stdlib.h>

int mutex = 1, full = 0, empty = 3, x = 0;

int wait(int s) {
    return (--s);
}

int signal(int s) {
    return (++s);
}

void producer() {
    mutex = wait(mutex);
    full = signal(full);
    empty = wait(empty);
    x++;
    printf("\nProducer produces item %d", x);
    mutex = signal(mutex);
}

void consumer() {
    mutex = wait(mutex);
    full = wait(full);
    empty = signal(empty);
    printf("\nConsumer consumes item %d", x);
    x--;
```

```

    mutex = signal(mutex);
}

int main() {
    int n;

    printf("\n1.Producer\n2.Consumer\n3.Exit");

    while(1) {
        printf("\nEnter your choice: ");

        scanf("%d", &n);

        switch(n) {
            case 1:
                if ((mutex == 1) && (empty != 0))
                    producer();
                else
                    printf("Buffer is full!!");
                break;
            case 2:
                if ((mutex == 1) && (full != 0))
                    consumer();
                else
                    printf("Buffer is empty!!");
                break;
            case 3:
                exit(0);
            default:
                printf("Invalid choice!");
        }
    }

    return 0;
}

```

Input:

1. Producer
2. Consumer
3. Exit

Output:

```
Enter your choice: 1

Producer produces item 1
Enter your choice: 2

Consumer consumes item 1
Enter your choice: 2

Buffer is empty!!
Enter your choice: 2

Buffer is empty!!
Enter your choice: 1

Producer produces item 1
Enter your choice: 1

Producer produces item 2
Enter your choice: 2

Consumer consumes item 2
Enter your choice: 2

Consumer consumes item 1
Enter your choice: 2

Buffer is empty!!
```