IF--- ELSE

1]
Write a program to check given number is odd and it should be divisible by 3. Both condition should satisfy. If both condition meet then print that number otherwise print invalid.
Example---: input num=36
Output----invalid

2]
Write a program to check largest number from the given four numbers. Take input from user.
Example: input a=10, b=8, c=9, d=18
Output----: Largest =18

3]
Write a program to check both nth and (n+2)th bit from the given number is set or not. If both are set then print SET if both are clear or if any of the bit is clear then print CLEAR.
Take number and n value from user.
Example----: input num=10 n=3 (Assume count from 0)
00000000 00000000 00000000 00001010
Output----- CLEAR

4]
Write a program to check given number is divisible by 2 or divisible by 3. If any of the condition meet then print Divisible otherwise print Not Divisible.
Example------:input num= 9
Output--- Divisible

5]
Write a program to check given number is present between 0---9 if it is present then print that number in word. If number is not between 0-9 then print invalid.
Example---: input num= 1
Output------ONE

6]
Write a program to check first and last digit of a given four digit number are odd or not.If both are odd then print ODD otherwise print NOT ODD.
Exapmle---: input num=3285
Output----ODD

7]
Write a program to check nth (n+1)th and (n+2)th bit are clear or set. If all bits are set then clear all bits. If all bits are clear then set all the bits. If some bits are clear and some are set then toggle all the bits.
Example---: Input num=31 n=2 (Assume count from zero) (2,3,4 all bits are set so clear all bits)
00000000 00000000 00000000 00011111
Output--- 00000000 00000000 00000000 00000011 in decimal 3
8]
Write a program to reverse first three bits in a given integer binary if in the first three bits any bit is zero. Otherwise toggle first three bits.
Take number from user.
Example---:input num=11;
00000000 00000000 00000000 00001011 (zero present in first three bits then reverse)
Output---:00000000 00000000 00000000 00001110 Decimal----14

9]
Write a program to check decimal data corresponding to third nibble is even and it is divisible by 3 or not. If Both condition are true then print the decimal number in third byte. If the number is only divisible by 3 then print quotient. If the number is even only then print Even.
Take input from user.
Example---: input num=768;
00000000 00000000 00000011 00000000
Decimal data corresponding to third nibble is 0011 which is only divisible by 3 so we need to print quotient (3/3) so quotient is 1.
Output-----: 1

10]
Write a program to swap first and second nibble if decimal data corresponding to first and second nibble is odd. If any of the decimal data is not odd then clear first and second nibble.
Example---: input num=353
00000000 00000000 00000001 01100001
Data corresponding to second nibble is 0110 which is 6 in decimal
Data corresponding to first nibble is 0001 which is 1 in decimal
Output:--- 00000000 00000000 00000001 00000000 in decimal 256
input num=49
00000000 00000000 000000000 00110001
Data corresponding to second nibble is 0011 which is 3 in decimal
Data corresponding to first nibble is 0001 which is 1 in decimal.
Outout:-----00000000 00000000 00000000 00010011 in decimal 19.