1]
Write a program to add first and last digit of a given three digit number without using loop.
Example: int num=283;
Output-------2+3=5

2]
Write a program to swap first and last digit of a given three digit number without using loop.
Example: int num=129;
Output----------921

3]
Write a program to swap first two digit from left of a given three digit number without using loop.
Example: int num=256
Output--------- 526

4]
Write a program to swap last two digit of a given three digit number without using loop.
Example: int num=256
Output--------- 265

5]
Write a program to add all digits of a given three digit number and if the result is even and divisible by 4 then only print the sum otherwise print **No result** on terminal.
Example int num=222;
Here sum is 6 which is even but not divisible by 4 so output is **No result**
int num=242;
Here sum is 8 which is even and divisible by 4 so output is **Result is 8**
Check sum is even and divisible by 4 using conditional operator.

6]
Write a program to set n bits from a given position. Take n value and position from user if any bit already set in that n bits then that bit should be clear.

7]
Write a program to print the value of the second byte in a given integer.
Example int num=0xABCD0312;
10101011 11001101 00000011 00010010
So data in second byte is 00000011
Output----------3

8]
Write a program to form a character using 2nd nibble and 3rd nibble.
Example int num=0xABCD0312;
10101011 11001101 00000011 00010010
So data in 2nd nibble is 0001 and data in 3rd nibble is 0011
so character should have data 00110001
Output----------0011001 that is in decimal 49

9]
Write a program to check data in third nibble is odd or even.
To check odd or even use conditional operator.
Example int num=0xABCD0312;
10101011 11001101 00000011 00010010
So data in 3rd nibble is 0011 that is 3 in decimal.
So data is 3 in decimal so pritnt **Odd** on terminal

10]
Write a program to reverse 2nd and 3rd digit of a given four digit number without using loop.
Example int num=1234
Output---------- 1324