Face Capture 1:1 — App Test Cases

Oct 15, 2026 · @M Jawad

These are end-to-end app test cases for the 1:1 face verification release, grouped by area, not by Cursor task. Run them on a debug build first, then repeat the device matrix on the release build.

Setup

Before testing: the backend changes (app config bars, authenticated face photo route, submit audit) must be deployed to the test server. Leave all `elrace.face_verify_*` parameters empty unless a case says otherwise, and reset them after each config case.

Devices: recent iPhone, small iPhone (SE size), iPad, mid-range Android phone, low-end Android phone, Android tablet.

Test data:

Code	Who	Needed for
F1	Foreman on project P1, Your Team of 6 or more	Most cases
L1–L6	F1's labors with good, recent HR photos	Genuine matches
L7	F1's labor with no HR photo	No-photo cases
L8	F1's labor with a low-resolution HR photo (face under 90 px)	Low-res cases
O1	Employee on P1 but in another foreman's team	Other-team rejection
S1	Person not in HR at all	Stranger rejection
LA	A look-alike of L1, if available	Look-alike case
F2 / L9	Foreman on project P2 with a team of one (L9), fewer than 5 other labors on P2	Small-team cases
U1	Plain labor login (non-foreman)	Photo route access

Logs to watch (debug build): `FaceVerify:`, `ProfilePhotoMatch:`, `ProfilePhotoQuality:`, `FacePreprocess:`, `AppConfigService:`, `AntiSpoof L1:`, `BurstVerification:`.

Recording: fill the Result column with Pass, Fail or Blocked plus the device. For any failure, paste the matching `FaceVerify:` log line in a comment on that row.

Core verification

The selected labor must be accepted with only their own name shown, on both camera entry points.

ID	Case	Steps	Expected	Result
VER-01	Labor camera, correct labor	Dashboard → L1 → camera. L1 faces camera in good light.	Badge "Verifying L1…" then green "L1 ✓". Auto-capture fires, green card, L1 added. Log `outcome=verified align=5pt`.	
VER-02	Project camera, correct labor	Day hub → P1 → camera. L1 selected in strip. L1 faces camera.	Same as VER-01, then auto-advance to the next labor.	
VER-03	Manual shutter	Labor camera for L1. Tap shutter instead of waiting.	Full anti-spoof burst runs, L1 verified and added.	
VER-04	Accessories	L1 with glasses, cap, then site helmet.	Verified, or verified on Try again within 2 attempts. Record scores.	
VER-05	Hard light	L1 backlit at site gate, then in low light.	Verified, or "Doesn't match L1" with Try again. Never another name. Record scores.	
VER-06	Slight angle	L1 turns head about 15°.	Verified.	

ID	Case	Steps	Expected	Result
VER-07	Whole team pass	Verify L1–L6 once each.	All verified. Copy target score and lead per labor from the log into a comment (used to tune the bars).	
VER-08	Front camera	Flip to front camera, L1 verifies themself.	Verified, same as back camera.	

Rejection

Anyone other than the selected labor must be rejected, and no other employee's name may appear anywhere on the capture screen.

ID	Case	Steps	Expected	Result
REJ-01	Same-team labor	Target L1. L2 faces camera.	Held card "Doesn't match L1" with L1's photo. L2's name appears nowhere (badge, card, snackbar, notice). Not added.	
REJ-02	Other-team employee	Target L1. O1 faces camera.	Same as REJ-01.	
REJ-03	Stranger	Target L1. S1 faces camera.	Same as REJ-01.	
REJ-04	Look-alike	Target L1. LA faces camera.	Rejected. If accepted, log it with scores as a known limitation.	
REJ-05	Wrong person on live stream	Target L1. L2 stands in frame for 10 s.	Badge stays neutral "Verifying L1…". No red badge, no other name, no alarm on the stream. Any capture is rejected.	
REJ-06	Repeated attempts	Repeat REJ-01 five times with Try again.	Never added. No crash, card and alarm behave the same each time.	

ID	Case	Steps	Expected	Result
REJ-07	Name leak sweep	During REJ-01 to REJ-05, check every visible element on a release build.	No employee name other than the target is ever shown.	
REJ-08	False-accept count	Across REJ-01 to REJ-03, run at least 50 wrong-person attempts in total, mixed devices.	0 accepted. Record the count in the results log.	

Small team and cohort

These cases cover the old one-person bypass: a small team must not let strangers through.

ID	Case	Steps	Expected	Result
SMALL-01	Team of one, stranger	Log in as F2 on P2. Target L9. S1 faces camera.	Rejected. Log `usedNoCohortBar=true` with cohort size under 5.	
SMALL-02	Team of one, genuine	Same setup. L9 faces camera.	Verified. If repeatedly rejected, record scores for tuning the no-cohort bar.	
SMALL-03	Templates still building	F1 on P1 right after a fresh install, only 1–2 templates ready. Target L1, S1 faces camera.	Rejected.	
SMALL-04	Low-res photos left out of cohort	F1 on P1 (L8 is low-res). Verify L1.	Log cohort size excludes L8. L1 is not rejected as `notDistinct` because of L8.	
SMALL-05	Cohort uses whole project	Verify L1 on P1.	Log cohort size is larger than F1's team size (other-team project labor included).	

Profile photos and templates

A labor with a missing or bad photo must never be added without a face check, and the foreman must always have a way forward.

ID	Case	Steps	Expected	Result
PHO-01	No HR photo	Select L7.	Card "L7's photo isn't available for face match. Ask HR to add a profile photo." Buttons Try again and Add a new request (plus Next labor on the project camera). No button adds L7 directly.	
PHO-02	Add a new request	From PHO-01 tap Add a new request, then go back.	Request page opens prefilled with project, task, date and L7. Back returns to the camera, same target, camera not re-initialised.	
PHO-03	Photo added later	HR uploads a photo for L7 while the app is open. Tap Try again after the cooldown.	Template builds and L7 verifies.	
PHO-04	Fresh install	Install, log in as F1, open the P1 camera.	Templates build team first, then the rest of the project. Log shows the new pipeline version and the `ProfilePhotoQuality` summary.	
PHO-05	Upgrade over old build	Install over the previous build that has cached templates. Open the camera twice.	First open rebuilds all templates once. Second open reuses the cache, no re-download.	
PHO-06	Template still building	Open the camera immediately and select a labor whose chip shows building.	Labor moves to the front of the build queue. Badge stays "Verifying…" until ready, then verifies. No crash.	

ID	Case	Steps	Expected	Result
PHO-07	Low-res target	Target L8. L8 faces camera.	Verifies or shows "Doesn't match L8". Never another name. Record scores.	
PHO-08	Unusable photo	Labor whose HR photo has no face or two faces.	Template marked failed. Same card as PHO-01.	

Labor picker and auto-advance

The project camera must stay fast at the morning gate: pick, verify, move on.

ID	Case	Steps	Expected	Result
PCK-01	Strip on open	Open the P1 project camera.	Strip shows Your Team, uncaptured first. First labor with a ready template is selected.	
PCK-02	Auto-advance	Verify L1, then L2, then L3 without touching the strip.	After each green card, the next uncaptured labor is selected automatically.	
PCK-03	Captured chips	After PCK-02.	L1–L3 show as done, move to the end, cannot be selected.	
PCK-04	Manual switch	While L4 is selected, tap L6.	Target switches at once, badge resets, camera does not flicker or restart.	
PCK-05	All captured	Verify every labor with a template.	"All labors captured" shown, submit available, no further auto-capture.	
PCK-06	PM with no team	Log in as a PM without Your Team, open the P1 camera.	Strip shows all project labor.	
PCK-07	Labor camera has no strip	Dashboard → L1 → camera.	No strip. "Pick another labor" is hidden on cards.	

ID	Case	Steps	Expected	Result
PCK-08	Nothing to verify	Reopen the camera after everyone is captured.	No verification and no capture fire.	
PCK-09	Long team	Foreman with 30+ labors.	Strip scrolls smoothly, selected chip stays visible.	

Held cards and actions

Every held card must show only the target, pause auto-capture, and resume cleanly from each action.

ID	Case	Steps	Expected	Result
CARD-01	Try again	Trigger "Doesn't match L1", tap Try again, L1 faces camera.	Same target, camera resumes, a new full anti-spoof burst runs, L1 verified.	
CARD-02	Pick another labor	Trigger "Doesn't match L1" on the project camera, tap Pick another labor.	Card closes, strip scrolls to L1, target stays L1 until another chip is tapped.	
CARD-03	Auto-capture paused	Leave a held card on screen for 15 s with a face in frame.	No capture fires while the card is shown.	
CARD-04	Dismiss	Close or swipe away a held card.	Camera resumes normally.	
CARD-05	Card content	Inspect each card type (mismatch, no photo, already attended).	Only the target's photo and name are shown.	
CARD-06	Next labor on no-photo card	Project camera, select L7, tap Next labor.	Next uncaptured labor selected. L7 stays uncaptured in the strip.	

Already attended and anti-spoof

These behaviours were not meant to change; any difference from the previous build is a regression.

ID	Case	Steps	Expected	Result
ATT-01	Already attended	Capture L1, reopen the labor camera for L1, L1 faces camera.	Blue "already attended" card. L1 not added twice.	
ATT-02	Phone screen replay	Show a photo of L1 on another phone.	Blocked as a presentation attack. Not added.	
ATT-03	Printed photo	Hold a printed photo of L1.	Blocked by anti-spoof before verification. Not added.	
ATT-04	Video replay	Play a video of L1 on a screen.	Blocked. Not added.	
ATT-05	Too close	Face fills more than half the frame width.	"Move back a little". No capture.	
ATT-06	Anti-spoof unchanged	Run ATT-02 to ATT-04 on the previous build and the new build, same device.	Same outcome. `AntiSpoof L1:` and `BurstVerification:` logs show the same frame counts and thresholds.	

Odoo config tuning

Every verification bar must be changeable from Odoo System Parameters without an app release. Apply each change by restarting the app or bringing it back from background, and reset the parameter afterwards.

ID	Case	Steps	Expected	Result
CFG-01	Defaults	All `elrace.face_verify_*` empty. Start the app.	`AppConfigService:` log shows score 0.30, lead 0.05, no-cohort 0.40, cohort 5, face px 80.	
CFG-02	Score bar	Set `elrace.face_verify_min_score` = 0.90. Verify L1. Reset, verify again.	Rejected as `lowScore`, then verified after reset.	

ID	Case	Steps	Expected	Result
CFG-03	Lead bar	Set `elrace.face_verify_min_lead` = 0.30. Verify L1 on P1.	Rejected as `notDistinct`.	
CFG-04	Cohort size	Set `elrace.face_verify_min_cohort` = 50. Verify L1.	Log `usedNoCohortBar=true`.	
CFG-05	No-cohort bar	Set `elrace.face_verify_min_score_no_cohort` = 0.90. F2 verifies L9.	Rejected. Verified after reset.	
CFG-06	Face size	Set `elrace.face_verify_min_face_px` = 200. Capture L1 from normal distance, then closer.	"Come closer to the camera" first, verified when closer.	
CFG-07	Bad value	Set `elrace.face_verify_min_score` = 2.	Ignored, default 0.30 used, no crash.	
CFG-08	Offline start	Set a value, open the app once online, then start it offline.	Cached value applied (log).	
CFG-09	Old keys ignored	Change `elrace.face_match_min_score` only.	Capture camera behaviour unchanged.	

Face photo route and session

Face templates must come only from the logged-in route, and a photo download must never log the foreman out.

ID	Case	Steps	Expected	Result
AUTH-01	New route used	Fresh install, open the P1 camera.	Log shows downloads from `/api/v2/employee/face_image/`, never `/public/employee/image/` for templates.	
AUTH-02	Avatars still load	Check the strip chips, cards, dashboard and approvals screens.	All avatars show as before.	

ID	Case	Steps	Expected	Result
AUTH-03	Re-login mid-build	Start a fresh template build, log out and log in as F1 again.	Build continues with the new token.	
AUTH-04	Expired session mid-build	Revoke F1′s session in Odoo during a template build.	Build stops, templates stay pending (not failed). The photo build does not log F1 out; the next normal API call handles the expiry.	
AUTH-05	No access	Employee the caller may not fetch (e.g. another company, if test data exists).	Template failed with "no access". No retry loop.	
AUTH-06	No photo on server	L7.	Template failed with "no photo". Card as PHO-01.	
AUTH-07	Labor login blocked	Call the route with U1′s token for another employee (Postman).	HTTP 403.	

Submit and audit

Each face-verified timesheet line must carry its verification record in Odoo, and existing submit rules must not change.

ID	Case	Steps	Expected	Result
SUB-01	Audit stored	Verify L1–L3, add L7 through a request, submit.	L1–L3 lines in Odoo: verified = true, score, lead, cohort size, liveness = pass, method = profile_1to1, app version. L7′s line has no audit values.	

ID	Case	Steps	Expected	Result
SUB-02	Values match	Compare SUB-01 Odoo values with the `FaceVerify:` log lines.	Score, lead and cohort size match.	
SUB-03	Offline submit	Capture offline, submit, go online.	Queued, then submitted with audit intact.	
SUB-04	Old queue	Leave unsubmitted captures on the previous build, install the new build, submit.	Submits without crash. Those lines have no audit values.	
SUB-05	Submit rules	Try a duplicate same-day entry, a locked month, and an employee on leave.	Same block messages as before.	
SUB-06	Edit keeps audit	Edit an existing verified line without recapturing.	Audit values unchanged.	
SUB-07	Location	Submit from site.	Geofence coordinates stored as before.	

Devices, layout and performance

The camera worked well on every device before this change; these cases confirm it still does with the new strip, cards and alignment.

ID	Case	Steps	Expected	Result
DEV-01	Device matrix	Run VER-01, REJ-01, PCK-02 and ATT-02 on all six devices.	Same results on every device.	
DEV-02	Both lenses	Repeat VER-01 with back and front camera on every device.	Verified on both.	
DEV-03	Tablets landscape	Hold the iPad and Android tablet in landscape.	Preview not stretched, orientation stays locked, strip, oval and shutter don't overlap.	

ID	Case	Steps	Expected	Result
DEV-04	Small screen	SE-size iPhone with strip, held card and shutter all visible.	Everything fits, no overflow or clipped text.	
DEV-05	Low-end speed	Low-end Android, 10 captures.	`pre…ms` and `emb…ms` within the previous build's range. Capture to green card time recorded. No freeze.	
DEV-06	Large text and dark mode	Enable large system font and dark mode.	Cards and strip readable.	
DEV-07	Camera permission	Deny camera permission, then grant it.	Existing permission handling, then the camera works.	
DEV-08	Background and return	Send the app to background mid-capture, return.	Camera resumes, same target selected.	
DEV-09	Gate session	30-minute continuous session, 40+ captures.	No crash, no slowdown, memory stable.	

Offline and session restore

Sites often have weak signal, so verification must keep working from cached templates.

ID	Case	Steps	Expected	Result
OFF-01	Offline with cache	Open the P1 camera once online, then go offline and verify L1.	Verified from cached templates.	
OFF-02	Offline, no cache	Fresh install, offline, open the camera.	Chips show building or failed, clear message, no crash.	
OFF-03	Restore session	Capture 3 labors, kill the app, reopen the camera.	Those 3 show as done in the strip.	

ID	Case	Steps	Expected	Result
OFF-04	Network drop mid-build	Turn off network during a template build, turn it back on.	Build resumes, no duplicate templates.	

Legacy AT2 camera

The AT2 camera keeps its old team-identification behaviour; it must work as before, now with the aligned crop.

ID	Case	Steps	Expected	Result
AT2-01	From Add Request hub	Add Request hub → capture mode → camera. L1 faces camera.	Identifies L1 as before.	
AT2-02	From Task detail	Task detail → capture mode → camera.	Same as AT2-01.	
AT2-03	Aligned crop	During AT2-01, check the log.	`align=5pt` on the probe. Scores same as or higher than the previous build.	
AT2-04	Through to submit	AT2 → summary → submit.	Submits as before.	

Exit criteria

The build is ready to release when all of these hold:

- [ ] No employee name other than the target ever appears on the capture camera (REJ-07).
- [ ] Zero wrong-person accepts in at least 50 attempts (REJ-08), including the small-team cases.
- [ ] Every genuine labor in VER-07 verifies within 2 attempts, and at most 1 in 10 first attempts is rejected.
- [ ] All anti-spoof and already-attended cases pass with no change from the previous build.

- [ ] Device matrix (DEV-01) passes on all six devices.
- [ ] Score table from VER-07 and SMALL-02 is shared, so the Odoo bars can be tuned before rollout.

Results log

Date	Tester	Device	App build	Cases run	Failed IDs	Notes