



## PART K Quick Reference Cards

Seven one-page cards: rig layout, desk layout, DMX and network, specials and looks, system connections, first-time setup, and session start-up and shut-down.

Revision R13.1 · 28 September 2026

# 1 Rig layout

One FOH truss, two stage bars (LX1, LX2) and a floor boom in each wing. Projector centre stage towards the back, throwing upstage onto the screen.

| Position            | Fixtures (desk numbers)                                                                    | Qty |
|---------------------|--------------------------------------------------------------------------------------------|-----|
| FOH truss           | 8 × Lightsky C42 #1–8 (#1–6 faces, #7 SP1 Ariel, #8 SP2 Spirit)                            | 8   |
| LX1 — downstage bar | 4 × C42 #9–12 (SP3 Octavia, SP4 Shell, V1 Dame, V2 Flanders) · 6 × Zoom #13–18 colour wash | 10  |
| LX2 — upstage bar   | 2 × Zoom #19–20 (V3 Theodore, V4 Marina) · 7 × TourCOB #23–28, 39 · 6 × PixBar #33–38      | 15  |
| SR floor boom       | Zoom #21 high · TourCOB #29 mid, #30 shin                                                  | 3   |
| SL floor boom       | Zoom #22 high · TourCOB #31 mid, #32 shin                                                  | 3   |
| Floor, upstage      | Hazer #40                                                                                  | 1   |
| Optional            | Pinspots #41–42 on the FOH truss ends (mirror ball only)                                   | (2) |

## THE RULES

Faces come from FOH (C42 #1–6). LX1 = colour top wash. LX2 = backlight + PixBars, focused downstage and never onto the screen (R-25). Booms = side colour across the stage (R-26). Every fixture keeps its desk number and address wherever it hangs. Proposed wet zone mid-stage audience-left — confirm at the site walk.

## 2 Desk layout

LSC Mantra Lite + 2 wings · TLM\_SHOW\_2026\_R13\_FLASHY\_SCENE\_SPLIT.mtr · QLab fires every cue — the desk is the backup.

| Page                                 | Purpose                                                                  | Memories                                                                                                                                                 |
|--------------------------------------|--------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>P1</b>                            | Venue / rig base                                                         | M1 STAGE WORK · M2 FULL WHITE · M3 WARM · M4 COOL · M5 BLUE · M6 RED · M9 PIXBAR WASH · M10 CURTAIN CALL                                                 |
| <b>P2</b>                            | Act One — scene sections                                                 | M1 Q1–11 · M2 Q12–17 · M3 ship/storm Q18–27.5 · M4 shore/duet Q28–30.5 · M5 bar/transformation Q31–37 · M6 interval Q38 · M9 WORK/FOCUS · M10 SAFE LIGHT |
| <b>P3</b>                            | Act Two — scene sections                                                 | M1 palace Q39–44 · M2 jellyfish Q45–49 · M3 lair/voice/haywire Q50–58.5 · M4 dry land Q59–59.7 · M5 wedding Q60–63.5 · M6 bows/end Q64–65                |
| <b>P4</b>                            | Songs                                                                    | M1 S1 Rock Lobster ... M10 S10 He's a Pirate                                                                                                             |
| <b>P5</b>                            | FX / chases                                                              | M1 WARM CHASE · M2 COOL CHASE · M3 PARTY CHASE · M4 HAZE · M5 HAYWIRE · M6 JELLY PULSE                                                                   |
| <b>P6</b>                            | Look library                                                             | M01 BLACKOUT ... M10 MAGIC                                                                                                                               |
| <b>P7</b>                            | Look library                                                             | M11 LAIR ... M16 BOWS · M7 = M17 SAFE LIGHT                                                                                                              |
| <b>P8</b>                            | Backup / reference                                                       | M1 = the full 153-position list (BACKUP - 01 PRESHOW ...)                                                                                                |
| Control                              | Use                                                                      |                                                                                                                                                          |
| <b>P2 M10 SAFE LIGHT</b>             | Emergency face light (QLab E3 fires it too)                              |                                                                                                                                                          |
| <b>Next Cue on a P2/P3/P4 memory</b> | Backup only, if QLab or the network fails — press again after each flash |                                                                                                                                                          |
| <b>P5 M4 HAZE</b>                    | Hazer #40 on its fader (50 %, fan 50 %)                                  |                                                                                                                                                          |
| <b>P5 M5 HAYWIRE</b>                 | QLab starts it at Q57 and stops it at Q57b                               |                                                                                                                                                          |
| <b>P5 M6 JELLY PULSE</b>             | Bump for extra Q47 repeats                                               |                                                                                                                                                          |
| <b>O · A then L · T then S</b>       | All Cues Off · Clear All · Save                                          |                                                                                                                                                          |

### NO LINK TIMES

No link times are set on the desk: QLab fires every flash return (Q21, Q23, Q25 +0.2 s · Q35 +0.3 s · Q47 +1 s · Q57b +0.3 s) and releases each memory as it leaves it.

### 3 DMX and network

Universe 1 on the desk XLR, universe 2 over Ethernet to a node. One chain per universe, terminated.

| U                  | Addresses                                                                     | Fixtures                   |
|--------------------|-------------------------------------------------------------------------------|----------------------------|
| U1                 | 1–36                                                                          | PixBars #33–38 (6 ch)      |
| U1                 | 37–38                                                                         | Pinspots #41–42 (optional) |
| U1                 | 301–420                                                                       | Zooms #13–22 (12 ch)       |
| U1                 | 421–486                                                                       | TourCOB #23–32, #39 (6 ch) |
| U1                 | 487–488                                                                       | Hazer #40 (2 ch)           |
| U2                 | 101–232                                                                       | Lightsky C42 #1–12 (11 ch) |
| Item               | Setting                                                                       |                            |
| <b>Desk</b>        | 2.0.0.1 / 255.0.0.0, DHCP off · Art-Net + sACN on (turn off the unused one)   |                            |
| <b>U1 route</b>    | Desk XLR → LX1 → LX2 → SR boom → SL boom → hazer · terminate                  |                            |
| <b>U2 route</b>    | Desk Ethernet → switch → node 2.0.0.10 → FOH C42 #1–8 → LX1 #9–12 · terminate |                            |
| <b>Node</b>        | sACN universe 2, or Art-Net 0-0-1                                             |                            |
| <b>QLab → desk</b> | OSC Play Memory, UDP 2.0.0.1 port 8000 (add the trigger on the desk)          |                            |

#### KEEP AT 0

Control, Strobe, Reset, Auto speed, Other, Default, Zoom (except in focus), CCT and Colour macro. Modes: C42 11 ch · Zoom 12 ch · COB 6 ch · PixBar 6 ch · hazer 2 ch.

4 Specials, looks and critical sequences

| Special | Character        | Fixture             | Mark              |
|---------|------------------|---------------------|-------------------|
| SP1     | Ariel            | #7 C42 FOH          | DSC               |
| SP2     | Spirit           | #8 C42 FOH          | DS audience-left  |
| SP3     | Octavia          | #9 C42 LX1          | US audience-right |
| SP4     | Shell            | #10 C42 LX1         | Plinth            |
| V1–V2   | Dame, Flanders   | #11–12 C42 LX1      | Voice marks 1–2   |
| V3–V4   | Theodore, Marina | #19–20 Zoom 13° LX2 | Voice marks 3–4   |

| Look           | Desk  | Colour      |
|----------------|-------|-------------|
| M01 BLACKOUT   | P6 M1 | <div></div> |
| M02 HOUSE      | P6 M2 | <div></div> |
| M03 UNDERWATER | P6 M3 | <div></div> |
| M04 COMEDY     | P6 M4 | <div></div> |
| M05 ROYAL      | P6 M5 | <div></div> |
| M06 SHIP       | P6 M6 | <div></div> |
| M07 SHORE      | P6 M7 | <div></div> |
| M08 STORM      | P6 M8 | <div></div> |
| M09 LIGHTNING  | P6 M9 | <div></div> |

| Look            | Desk   | Colour      |
|-----------------|--------|-------------|
| M10 MAGIC       | P6 M10 | <div></div> |
| M11 LAIR        | P7 M1  | <div></div> |
| M12 VOICE SHELL | P7 M2  | <div></div> |
| M13 JELLYFISH   | P7 M3  | <div></div> |
| M14 DRYLAND     | P7 M4  | <div></div> |
| M15 WEDDING     | P7 M5  | <div></div> |
| M16 BOWS        | P7 M6  | <div></div> |
| M17 SAFE LIGHT  | P7 M7  | <div></div> |

| Sequence       | Cues     | Desk  | Note                                                            |
|----------------|----------|-------|-----------------------------------------------------------------|
| Storm          | Q20–27.5 | P2 M3 | Flashes 21/23/25 return +0.2 s (QLab)                           |
| Transformation | Q33–36   | P2 M5 | 35 white hit → 35b +0.3 s                                       |
| Voice transfer | Q52–57b  | P3 M3 | Shell → Dame → Flanders → Theodore → Marina; HAYWIRE Q57 → Q57b |
| Jellyfish      | Q45–49   | P3 M2 | 47 pulse returns +1 s; repeats on P5 M6                         |

## 5 System connections

How QLab, the Mantra, the StudioLive, the node and the projector link. Subnet 255.0.0.0 for everything.

| Device                              | IP                                                              | Settings                                                                        |
|-------------------------------------|-----------------------------------------------------------------|---------------------------------------------------------------------------------|
| Mantra Lite                         | 2.0.0.1                                                         | Art-Net + sACN · OSC Play Memory trigger port 8000                              |
| Art-Net / sACN node                 | 2.0.0.10                                                        | Universe 2                                                                      |
| QLab Mac                            | 2.0.0.20                                                        | Manual IPv4 · Wi-Fi off · MANTRA patch → 2.0.0.1:8000 on the Ethernet interface |
| Backup Mac                          | 2.0.0.21                                                        | Optional — songs as plain files (R-08)                                          |
| StudioLive 16                       | 2.0.0.30                                                        | Optional — iPad / UC Surface                                                    |
| Link                                | Carries                                                         |                                                                                 |
| QLab → StudioLive (USB)             | Playback on ch 11–12 · backup playback ch 13–14 · radios ch 1–8 |                                                                                 |
| QLab → projector (HDMI via HDBaseT) | Backdrops · VID-99 black                                        |                                                                                 |
| Stream Deck → QLab (USB)            | GO · Panic · F13/F14/F15 → E2/E3/E1                             |                                                                                 |
| Desk XLR / Ethernet                 | Universe 1 DMX · universe 2 Art-Net/sACN via node               |                                                                                 |

### TEST IN THIS ORDER

1 Sound: any QLab cue — level on ch 11–12. 2 Lights: QLab E3 SAFE LIGHT — desk plays P2 M10; then Q4 — desk plays P2 M1 cue 4. 3 Universe 2: C42 #1 up. 4 Video: Q4 — BG-02 fades up; E2 → black.

## 6 First-time setup

Once, at the first venue session. About three hours with the rig hung.

### 1 Rig and patch

1. Hang and focus (card 1); booms weighted; projector on the bar with its bond.
2. Check modes and addresses (Part C); cable U1 and U2; terminate both.

### 2 Network

1. Mantra, node and QLab Mac on the show switch. No internet, no Wi-Fi.
2. Mac: Network > Ethernet > TCP/IP > Manually 2.0.0.20 / 255.0.0.0, router blank. Node 2.0.0.10.

### 3 Mantra

1. Tools > Export Show (venue backup).
2. Tools > Import Show > TLM\_SHOW\_2026\_R13\_FLASHY\_SCENE\_SPLIT.mtr. Check P2 Act One, P3 Act Two, P4 songs, P5 FX, P8 backup.
3. Tools > Setup > Remote Triggers > Add > OSC · Play Memory · port 8000. Turn off Art-Net or sACN (whichever the node doesn't use).
4. Save (T S) and set as Default Show. **No link times needed.**

### 4 QLab Mac

1. Harden the Mac (R-07); install QLab 5 and the licence.
2. Put TLM\_R13\_REBUILT\_Show\_Files on the Desktop (exact name). Open TLM\_Show\_R13\_1.qlab5.
3. Workspace Settings: Audio → StudioLive USB · Video Stage 1 → projector · Network MANTRA → Ethernet interface. Save.
4. Check no red cues; select Q4's audio — target ends in \_v2.wav.

### 5 StudioLive

1. USB to the Mac: ch 11–12 = USB (QLab), 13–14 = backup, radios 1–8.
2. Gains/EQ; principals on one DCA; save scene TLM SHOW.

### 6 Stream Deck

1. Import TLM QLab Show.streamDeckProfile.
2. In QLab give E2 hotkey F13, E3 F14, E1 F15 (Triggers tab); save.

### 7 Test and back up

1. Step through a cue-to-cue from Q1 (Part L); fix anything red.
2. Export the Mantra show to USB; copy the whole show folder to a second drive.

## 7 Start-up and shut-down — every session

| When                     | Do                                                                                                                                             |
|--------------------------|------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>T-90 power up</b>     | Mains/RCDs → fixtures, node, switch → Mantra (loads the Default Show) → projector → StudioLive (scene TLM SHOW) → amps last                    |
| <b>T-80 QLab Mac</b>     | Wi-Fi off, charger in. Open TLM_Show_R13_1.qlab5 from the Desktop folder. No red cues; Stream Deck profile; projector = Stage 1 (not mirrored) |
| <b>T-70 system check</b> | E3 SAFE LIGHT → desk plays P2 M10; ROW memories check every fixture; a QLab cue → ch 11–12; Q4 → BG-02; E2 → black                             |
| <b>T-45 reset</b>        | Esc (Panic) in QLab; Mantra O (All Cues Off). Playhead on Q1; Show Mode. Haze check and detector isolation logged (R-13)                       |
| <b>T-30 house open</b>   | SM calls Q1 → GO. From here every cue is one GO in QLab (Space or Stream Deck)                                                                 |
| Shut-down                |                                                                                                                                                |
| 1                        | QLab: Esc (Panic), then save                                                                                                                   |
| 2                        | Amps / speakers off first                                                                                                                      |
| 3                        | StudioLive off (save the scene if changed)                                                                                                     |
| 4                        | Projector standby — let the fan finish                                                                                                         |
| 5                        | Mantra: save if changed, export to USB, power off                                                                                              |
| 6                        | Fixtures, node, switch off; Mac off; hazer off and clean                                                                                       |

### IF SOMETHING FAILS MID-SHOW

Lights: the matching Mantra P2/P3/P4 memory with Next Cue (again after each flash) · SAFE LIGHT = P2 M10. Sound: backup playback ch 13–14. Video: E2 black or AV-mute. Keep going — the SM decides on any hold.