

BASE_SHOW_2026 — what is linked to what, and where

Read from BASE_SHOW_2026.qlab5 and BASE_SHOW_2026.mtr. Use the two together: QLab base on the Mac, base show on the Mantra. Fader number = fixture number.

1 The link, end to end

QLab cue	QLab network patch	Mantra (desk)	Memory → fixtures	DMX out
BASE_SHOW_2026: V1-V10, T1-T41, E1-E3 (a group per GO)	MANTRA · OSC over UDP to 2.0.0.1 port 8000. Message: /PlayMemory/Page=P/Memory=M/Cue=1/Level=L/Fade=ms (L 100 = play, 0 = release)	IP 2.0.0.1 · Tools › Setup › Remote Triggers: OSC · Play Memory · port 8000 (set on the desk)	Page P, memory M of BASE_SHOW_2026.mtr lights the fixtures listed in section 2	U1: desk DMX XLR out · U2: Art-Net / sACN → node 2.0.0.10 → FOH bar

Mantra pages in the base show

Page	What is on it	QLab cues that fire it (M1 → M10)	Label
P1	Venue looks · M1-6, 9-10	V1, V2, V3, V4, V5, V6, V9, V10	labels page 2, strip P1
P2	Rig test: one fixture per memory · M1-10	T1, T2, T3, T4, T5, T6, T7, T8, T9, T10	labels page 2, strip P2
P3	Rig test: one fixture per memory · M1-10	T11, T12, T13, T14, T15, T16, T17, T18, T19, T20	labels page 2, strip P3
P4	Rig test: one fixture per memory · M1-10	T21, T22, T23, T24, T25, T26, T27, T28, T29, T30	labels page 2, strip P4
P5	Rig test: one fixture per memory · M1-10	T31, T32, T33, T34, T35, T36, T37, T38, T39, T40	labels page 2, strip P5
P6	empty	—	—
P7	empty	—	—
P8	empty	—	—
P9	empty	—	—
P10	empty	—	—

Not linked to QLab: P1 M7-M8 (empty) and the area memories stored under internal IDs 100-106, 109 — LIGHTSKY ROW, ZOOM ROW, TOURCOB ROW, PIXBAR ROW, STAGE RIGHT, CENTRE STAGE, STAGE LEFT, BLACKOUT. They are not on a playback page, so no OSC message reaches them; use them from the desk only.

2 Every QLab cue → Mantra page / memory → fixtures

Cue	QLab name	Fires (page · memory · level · fade)	Mantra memory	Lights (fixture # at level)	Also releases
V1	STAGE WORK	P1 M1 · 100 % · 2.0 s	STAGE WORK	#1-39 at 100 %	P1 M2-6, 9-10
V2	FULL STAGE WHITE	P1 M2 · 100 % · 2.0 s	FULL STAGE WHITE	#1-32 at 80 %	P1 M1, 3-6, 9-10
V3	WARM STAGE	P1 M3 · 100 % · 2.0 s	WARM STAGE	#1-32 at 80 %	P1 M1-2, 4-6, 9-10
V4	COOL STAGE	P1 M4 · 100 % · 2.0 s	COOL STAGE	#1-32 at 80 %	P1 M1-3, 5-6, 9-10
V5	BLUE STAGE	P1 M5 · 100 % · 2.0 s	BLUE STAGE	#1-32 at 80 %	P1 M1-4, 6, 9-10
V6	RED STAGE	P1 M6 · 100 % · 2.0 s	RED STAGE	#1-32 at 80 %	P1 M1-5, 9-10
V9	PIXBAR WASH	P1 M9 · 100 % · 2.0 s	PIXBAR WASH	#33-38 at 100 %	P1 M1-6, 10
V10	CURTAIN CALL	P1 M10 · 100 % · 2.0 s	CURTAIN CALL	#1-39 at 100 %	P1 M1-6, 9
T1	TEST 01 LIGHTSKY	P2 M1 · 100 % · 0.0 s	TEST 01 LIGHTSKY	#1 C42 FOH at 100 %	—
T2	TEST 02 LIGHTSKY	P2 M2 · 100 % · 0.0 s	TEST 02 LIGHTSKY	#2 C42 FOH at 100 %	P2 M1
T3	TEST 03 LIGHTSKY	P2 M3 · 100 % · 0.0 s	TEST 03 LIGHTSKY	#3 C42 FOH at 100 %	P2 M2
T4	TEST 04 LIGHTSKY	P2 M4 · 100 % · 0.0 s	TEST 04 LIGHTSKY	#4 C42 FOH at 100 %	P2 M3
T5	TEST 05 LIGHTSKY	P2 M5 · 100 % · 0.0 s	TEST 05 LIGHTSKY	#5 C42 FOH at 100 %	P2 M4
T6	TEST 06 LIGHTSKY	P2 M6 · 100 % · 0.0 s	TEST 06 LIGHTSKY	#6 C42 FOH at 100 %	P2 M5
T7	TEST 07 LIGHTSKY	P2 M7 · 100 % · 0.0 s	TEST 07 LIGHTSKY	#7 C42 FOH at 100 %	P2 M6
T8	TEST 08 LIGHTSKY	P2 M8 · 100 % · 0.0 s	TEST 08 LIGHTSKY	#8 C42 FOH at 100 %	P2 M7
T9	TEST 09 LIGHTSKY	P2 M9 · 100 % · 0.0 s	TEST 09 LIGHTSKY	#9 C42 LX1 at 100 %	P2 M8
T10	TEST 10 LIGHTSKY	P2 M10 · 100 % · 0.0 s	TEST 10 LIGHTSKY	#10 C42 LX1 at 100 %	P2 M9
T11	TEST 11 LIGHTSKY	P3 M1 · 100 % · 0.0 s	TEST 11 LIGHTSKY	#11 C42 LX1 at 100 %	P2 M10
T12	TEST 12 LIGHTSKY	P3 M2 · 100 % · 0.0 s	TEST 12 LIGHTSKY	#12 C42 LX1 at 100 %	P3 M1
T13	TEST 13 ZOOM	P3 M3 · 100 % · 0.0 s	TEST 13 ZOOM	#13 ZOOM LX1 at 100 %	P3 M2
T14	TEST 14 ZOOM	P3 M4 · 100 % · 0.0 s	TEST 14 ZOOM	#14 ZOOM LX1 at 100 %	P3 M3
T15	TEST 15 ZOOM	P3 M5 · 100 % · 0.0 s	TEST 15 ZOOM	#15 ZOOM LX1 at 100 %	P3 M4
T16	TEST 16 ZOOM	P3 M6 · 100 % · 0.0 s	TEST 16 ZOOM	#16 ZOOM LX1 at 100 %	P3 M5
T17	TEST 17 ZOOM	P3 M7 · 100 % · 0.0 s	TEST 17 ZOOM	#17 ZOOM LX1 at 100 %	P3 M6
T18	TEST 18 ZOOM	P3 M8 · 100 % · 0.0 s	TEST 18 ZOOM	#18 ZOOM LX1 at 100 %	P3 M7
T19	TEST 19 ZOOM	P3 M9 · 100 % · 0.0 s	TEST 19 ZOOM	#19 ZOOM LX2 at 100 %	P3 M8
T20	TEST 20 ZOOM	P3 M10 · 100 % · 0.0 s	TEST 20 ZOOM	#20 ZOOM LX2 at 100 %	P3 M9
T21	TEST 21 ZOOM	P4 M1 · 100 % · 0.0 s	TEST 21 ZOOM	#21 ZOOM SR at 100 %	P3 M10
T22	TEST 22 ZOOM	P4 M2 · 100 % · 0.0 s	TEST 22 ZOOM	#22 ZOOM SL at 100 %	P4 M1
T23	TEST 23 TOURCOB	P4 M3 · 100 % · 0.0 s	TEST 23 TOURCOB	#23 COB LX2 at 100 %	P4 M2
T24	TEST 24 TOURCOB	P4 M4 · 100 % · 0.0 s	TEST 24 TOURCOB	#24 COB LX2 at 100 %	P4 M3
T25	TEST 25 TOURCOB	P4 M5 · 100 % · 0.0 s	TEST 25 TOURCOB	#25 COB LX2 at 100 %	P4 M4
T26	TEST 26 TOURCOB	P4 M6 · 100 % · 0.0 s	TEST 26 TOURCOB	#26 COB LX2 at 100 %	P4 M5
T27	TEST 27 TOURCOB	P4 M7 · 100 % · 0.0 s	TEST 27 TOURCOB	#27 COB LX2 at 100 %	P4 M6
T28	TEST 28 TOURCOB	P4 M8 · 100 % · 0.0 s	TEST 28 TOURCOB	#28 COB LX2 at 100 %	P4 M7
T29	TEST 29 TOURCOB	P4 M9 · 100 % · 0.0 s	TEST 29 TOURCOB	#29 COB SR at 100 %	P4 M8
T30	TEST 30 TOURCOB	P4 M10 · 100 % · 0.0 s	TEST 30 TOURCOB	#30 COB SR at 100 %	P4 M9
T31	TEST 31 TOURCOB	P5 M1 · 100 % · 0.0 s	TEST 31 TOURCOB	#31 COB SL at 100 %	P4 M10
T32	TEST 32 TOURCOB	P5 M2 · 100 % · 0.0 s	TEST 32 TOURCOB	#32 COB SL at 100 %	P5 M1
T33	TEST 33 PIXBAR	P5 M3 · 100 % · 0.0 s	TEST 33 PIXBAR	#33 PIX LX2 at 100 %	P5 M2

Cue	QLab name	Fires (page · memory · level · fade)	Mantra memory	Lights (fixture # at level)	Also releases
T34	TEST 34 PIXBAR	P5 M4 · 100 % · 0.0 s	TEST 34 PIXBAR	#34 PIX LX2 at 100 %	P5 M3
T35	TEST 35 PIXBAR	P5 M5 · 100 % · 0.0 s	TEST 35 PIXBAR	#35 PIX LX2 at 100 %	P5 M4
T36	TEST 36 PIXBAR	P5 M6 · 100 % · 0.0 s	TEST 36 PIXBAR	#36 PIX LX2 at 100 %	P5 M5
T37	TEST 37 PIXBAR	P5 M7 · 100 % · 0.0 s	TEST 37 PIXBAR	#37 PIX LX2 at 100 %	P5 M6
T38	TEST 38 PIXBAR	P5 M8 · 100 % · 0.0 s	TEST 38 PIXBAR	#38 PIX LX2 at 100 %	P5 M7
T39	TEST 39 TOURCOB	P5 M9 · 100 % · 0.0 s	TEST 39 TOURCOB	#39 COB LX2 at 100 %	P5 M8
T40	TEST 40 HAZE	P5 M10 · 100 % · 0.0 s	TEST 40 HAZE	#40 HAZE US at 50 %	P5 M9
T41	RIG TEST END	—	—	—	P5 M10
E1	STOP ALL (QLab panic)	—	—	nothing: QLab only (panics every QLab cue)	—
E2	ALL OFF (Mantra)	—	—	—	48 memories (P1-5)
E3	STAGE WORK (Mantra P1 M1)	P1 M1 · 100 % · 2.0 s	STAGE WORK	#1-39 at 100 %	—

3 Every fixture: where it is and what brings it up

#	Label	Desk fixture	Hung	Fader	DMX universe : address	Test memory	QLab test	Also in venue looks
1	C42 FOH	CX 42 NEW	FOH	Console 1	U2 : 101-111	P2 M1	T1	V1 V2 V3 V4 V5 V6 V10
2	C42 FOH	CX 42 NEW	FOH	Console 2	U2 : 112-122	P2 M2	T2	V1 V2 V3 V4 V5 V6 V10
3	C42 FOH	CX 42 NEW	FOH	Console 3	U2 : 123-133	P2 M3	T3	V1 V2 V3 V4 V5 V6 V10
4	C42 FOH	CX 42 NEW	FOH	Console 4	U2 : 134-144	P2 M4	T4	V1 V2 V3 V4 V5 V6 V10
5	C42 FOH	CX 42 NEW	FOH	Console 5	U2 : 145-155	P2 M5	T5	V1 V2 V3 V4 V5 V6 V10
6	C42 FOH	CX 42 NEW	FOH	Console 6	U2 : 156-166	P2 M6	T6	V1 V2 V3 V4 V5 V6 V10
7	C42 FOH	CX 42 NEW	FOH	Console 7	U2 : 167-177	P2 M7	T7	V1 V2 V3 V4 V5 V6 V10
8	C42 FOH	CX 42 NEW	FOH	Console 8	U2 : 178-188	P2 M8	T8	V1 V2 V3 V4 V5 V6 V10
9	C42 LX1	CX 42 NEW	LX1	Console 9	U2 : 189-199	P2 M9	T9	V1 V2 V3 V4 V5 V6 V10
10	C42 LX1	CX 42 NEW	LX1	Console 10	U2 : 200-210	P2 M10	T10	V1 V2 V3 V4 V5 V6 V10
11	C42 LX1	CX 42 NEW	LX1	Console 11	U2 : 211-221	P3 M1	T11	V1 V2 V3 V4 V5 V6 V10
12	C42 LX1	CX 42 NEW	LX1	Console 12	U2 : 222-232	P3 M2	T12	V1 V2 V3 V4 V5 V6 V10
13	ZOOM LX1	ZOOM 12 CHANNEL	LX1	Console 13	U1 : 301-312	P3 M3	T13	V1 V2 V3 V4 V5 V6 V10
14	ZOOM LX1	ZOOM 12 CHANNEL	LX1	Console 14	U1 : 313-324	P3 M4	T14	V1 V2 V3 V4 V5 V6 V10
15	ZOOM LX1	ZOOM 12 CHANNEL	LX1	Console 15	U1 : 325-336	P3 M5	T15	V1 V2 V3 V4 V5 V6 V10
16	ZOOM LX1	ZOOM 12 CHANNEL	LX1	Console 16	U1 : 337-348	P3 M6	T16	V1 V2 V3 V4 V5 V6 V10
17	ZOOM LX1	ZOOM 12 CHANNEL	LX1	Console 17	U1 : 349-360	P3 M7	T17	V1 V2 V3 V4 V5 V6 V10
18	ZOOM LX1	ZOOM 12 CHANNEL	LX1	Console 18	U1 : 361-372	P3 M8	T18	V1 V2 V3 V4 V5 V6 V10
19	ZOOM LX2	ZOOM 12 CHANNEL	LX2	Console 19	U1 : 373-384	P3 M9	T19	V1 V2 V3 V4 V5 V6 V10
20	ZOOM LX2	ZOOM 12 CHANNEL	LX2	Console 20	U1 : 385-396	P3 M10	T20	V1 V2 V3 V4 V5 V6 V10
21	ZOOM SR	ZOOM 12 CHANNEL	SR boom	Console 21	U1 : 397-408	P4 M1	T21	V1 V2 V3 V4 V5 V6 V10
22	ZOOM SL	ZOOM 12 CHANNEL	SL boom	Console 22	U1 : 409-420	P4 M2	T22	V1 V2 V3 V4 V5 V6 V10
23	COB LX2	TOURCOB PAR	LX2	Console 23	U1 : 421-426	P4 M3	T23	V1 V2 V3 V4 V5 V6 V10
24	COB LX2	TOURCOB PAR	LX2	Console 24	U1 : 427-432	P4 M4	T24	V1 V2 V3 V4 V5 V6 V10
25	COB LX2	TOURCOB PAR	LX2	Wing 1 · 25	U1 : 433-438	P4 M5	T25	V1 V2 V3 V4 V5 V6 V10
26	COB LX2	TOURCOB PAR	LX2	Wing 1 · 26	U1 : 439-444	P4 M6	T26	V1 V2 V3 V4 V5 V6 V10
27	COB LX2	TOURCOB PAR	LX2	Wing 1 · 27	U1 : 445-450	P4 M7	T27	V1 V2 V3 V4 V5 V6 V10
28	COB LX2	TOURCOB PAR	LX2	Wing 1 · 28	U1 : 451-456	P4 M8	T28	V1 V2 V3 V4 V5 V6 V10
29	COB SR	TOURCOB PAR	SR boom	Wing 1 · 29	U1 : 457-462	P4 M9	T29	V1 V2 V3 V4 V5 V6 V10
30	COB SR	TOURCOB PAR	SR boom	Wing 1 · 30	U1 : 463-468	P4 M10	T30	V1 V2 V3 V4 V5 V6 V10
31	COB SL	TOURCOB PAR	SL boom	Wing 1 · 31	U1 : 469-474	P5 M1	T31	V1 V2 V3 V4 V5 V6 V10
32	COB SL	TOURCOB PAR	SL boom	Wing 1 · 32	U1 : 475-480	P5 M2	T32	V1 V2 V3 V4 V5 V6 V10
33	PIX LX2	PIXBAR 6CH	LX2	Wing 1 · 33	U1 : 1-6	P5 M3	T33	V1 V9 V10
34	PIX LX2	PIXBAR 6CH	LX2	Wing 1 · 34	U1 : 7-12	P5 M4	T34	V1 V9 V10
35	PIX LX2	PIXBAR 6CH	LX2	Wing 1 · 35	U1 : 13-18	P5 M5	T35	V1 V9 V10
36	PIX LX2	PIXBAR 6CH	LX2	Wing 1 · 36	U1 : 19-24	P5 M6	T36	V1 V9 V10
37	PIX LX2	PIXBAR 6CH	LX2	Wing 2 · 37	U1 : 25-30	P5 M7	T37	V1 V9 V10
38	PIX LX2	PIXBAR 6CH	LX2	Wing 2 · 38	U1 : 31-36	P5 M8	T38	V1 V9 V10
39	COB LX2	TOURCOB PAR	LX2	Wing 2 · 39	U1 : 481-486	P5 M9	T39	V1 V10
40	HAZE US	HAZER 2CH	floor US	Wing 2 · 40	U1 : 487-488	P5 M10	T40	—

Universe 1 = desk DMX XLR out. Universe 2 = Art-Net / sACN → node 2.0.0.10 → FOH bar.