

6 First-time setup

Once, at the first venue session. About three hours with the rig hung.

1 Rig and patch

1. Hang and focus (card 1); booms weighted; projector on the bar with its bond.
2. Check modes and addresses (Part C); cable U1 and U2; terminate both.

2 Network

1. Mantra, node and QLab Mac on the show switch. No internet, no Wi-Fi.
2. Mac: Network > Ethernet > TCP/IP > Manually 2.0.0.20 / 255.0.0.0, router blank. Node 2.0.0.10.

3 Mantra

1. Tools > Export Show (venue backup).
2. Tools > Import Show > TLM_SHOW_2026_R13_FLASHY_SCENE_SPLIT.mtr. Check P2 Act One, P3 Act Two, P4 songs, P5 FX, P8 backup.
3. Tools > Setup > Remote Triggers > Add > OSC · Play Memory · port 8000. Turn off Art-Net or sACN (whichever the node doesn't use).
4. Save (T S) and set as Default Show. **No link times needed in R13.1.**

4 QLab Mac

1. Harden the Mac (R-07); install QLab 5 and the licence.
2. Put TLM_R13_REBUILT_Show_Files on the Desktop (exact name). Open TLM_Show_R13_1.qlab5.
3. Workspace Settings: Audio → StudioLive USB · Video Stage 1 → projector · Network MANTRA → Ethernet interface. Save.
4. Check no red cues; select Q4's audio — target ends in _v2.wav.

5 StudioLive

1. USB to the Mac: ch 11–12 = USB (QLab), 13–14 = backup, radios 1–8.
2. Gains/EQ; principals on one DCA; save scene TLM SHOW.

6 Stream Deck

1. Import TLM QLab Show.streamDeckProfile.
2. In QLab give E2 hotkey F13, E3 F14, E1 F15 (Triggers tab); save.

7 Test and back up

1. Step through a cue-to-cue from Q1 (Part L); fix anything red.
2. Export the Mantra show to USB; copy the whole show folder to a second drive.

7 Start-up and shut-down — every session

When	Do
T-90 power up	Mains/RCDs → fixtures, node, switch → Mantra (loads the Default Show) → projector → StudioLive (scene TLM SHOW) → amps last
T-80 QLab Mac	Wi-Fi off, charger in. Open TLM_Show_R13_1.qlab5 from the Desktop folder. No red cues; Stream Deck profile; projector = Stage 1 (not mirrored)
T-70 system check	E3 SAFE LIGHT → desk plays P2 M10; ROW memories check every fixture; a QLab cue → ch 11–12; Q4 → BG-02; E2 → black
T-45 reset	Esc (Panic) in QLab; Mantra O (All Cues Off). Playhead on Q1; Show Mode. Haze check and detector isolation logged (R-13)
T-30 house open	SM calls Q1 → GO. From here every cue is one GO in QLab (Space or Stream Deck)
Shut-down	
1	QLab: Esc (Panic), then save
2	Amps / speakers off first
3	StudioLive off (save the scene if changed)
4	Projector standby — let the fan finish
5	Mantra: save if changed, export to USB, power off
6	Fixtures, node, switch off; Mac off; hazer off and clean

IF SOMETHING FAILS MID-SHOW

Lights: the matching Mantra P2/P3/P4 memory with Next Cue (again after each flash) · SAFE LIGHT = P2 M10. Sound: backup playback ch 13–14. Video: E2 black or AV-mute. Keep going — the SM decides on any hold.