| W5100S Ethernet Shield V1.1 Partlist | | | | | |
|--------------------------------------|--|-----------------------------|---|----------------|---------|
| Item | Q.ty Reference | Part | Tech. Characteristics | Package | |
| 1 | 2 C1, C2 | 8pF | 50V-5% Ceramic | CASE 0603 | 1 |
| 2 | C3, C4, C5, C6, C19, C20, C21, C22, C23, C24, C25, C26, C27, C28, C31, C33, C34, C36, C37, C38, C39, C40, C41, C42, C43, C44 | 100nF | 50V-5% Ceramic | CASE 0603 | |
| 3 | 2 C32, C35 | 1uF | 50V-5% Ceramic | CASE 0603 | |
| 4 | 3 C13, C14, C15 | 10uF/16V | Tantal CAP A Size EIA/IECQ 3216 | EIA/IECQ 3216 | |
| 5 | 4 C7, C8, C29, C30 | 22uF/16V | Tantal CAP A Size EIA/IECQ 3216 | EIA/IECQ 3216 | |
| 6 | 1 C9 | 1nF/2kV | 1nF/2kV Ceramic | CASE 1803 | |
| 7 | 3 R21, R22, R23 | 0R | 1/10W-5% SMD | CASE 0603 | |
| 8 | 4 R14, R15, R16, R17 | 49.9R / 1% | 1/10W-1% SMD | CASE 0603 | |
| 9 | 9 R7, R8, R9, R10, R11, R12, R13, R18, R19 | 330R | 1/10W-5% SMD | CASE 0603 | |
| 10 | 1 R4 | 4.7k | 1/10W-5% SMD | CASE 0603 | |
| 11 | 1 R20 | 10k | 1/10W-5% SMD | CASE 0603 | |
| 12 | 1 R3 | 12k | 1/10W-1% SMD | CASE 0603 | |
| 13 | 1 R5 | 300R | 1/10W-5% SMD | CASE 0603 | |
| 14 | 1 R1 | 1M | 1/10W-5% SMD | CASE 0603 | |
| 15 | 2 R2, R30 | NC | | CASE 0603 | |
| 16 | 4 L1, L2, L3, L5 | HCB2012KF-300T30 | Bead for Power Line, 30[ohm] | CASE 0805 | |
| 17 | 1 Y1 | 25MHz (82J0626-25MHz) | X-tal 25MHz,3.2x2.5 SMD, CL=18pF | SMD3225, 4-PAD | |
| 18 | 3 LED2, LED3, LED4 | Chip GREEN LED | Chip GREEN LED | CASE 0603 | |
| 19 | 4 LED1, LED5, LED6, LED7 | Chip YELLOW LED | Chip YELLOW LED | CASE 0603 | _ |
| 20 | 1 P2 | 7MSDP-B0-1012 | MICRO SD CARD SOCKET-9P | SMD | _ |
| 21 | 1 P3 | 57-00013QL11-1 | RJ45 1x1 Tab Down, 10/100 Base-T, PoE | DIP | |
| 22 | 1 JP1 | 2.54mm 2x3 PinHeader Scoket | 2.54mm 2x3 PinHeader Scoket, Female | DIP | Bottom |
| 23 | 2 JP2, JP3 | Molex 5045 4Pin | Molex 5045 4Pin | DIP | |
| 24 | 4 JP5, JP4, JP6, JP7 | Molex 5045 3Pin | Molex 5045 3Pin | DIP | |
| 25 | 2 JP8, JP10 | 9299-11-1x8 F | 2.54mm 1x8 PinHeader Scoket, Female | DIP | |
| 26 | 1 JP9 | 9299-11-1x6 F | 2.54mm 1x6 PinHeader Scoket, Female | DIP | |
| 27 | 1 JP11 | 9299-11-1x10 F | 2.54mm 1x10 PinHeader Scoket, Female | DIP | |
| 28 | 1 JP12 | 2.54mm 1x2 PinHeader | 2.54mm 1x2 PinHeader Male | DIP | |
| 29 | 1 SW1 | YST1157(3.1) | SMD Type Tact Switch | SMD | |
| 30 | 1 U1 | W5100S | WIZnet W5100S | QFN48 | |
| 31 | 1 U2 | AME8815BEGT330 | 1.5A CMOS LDO | SOT-223 | 1 |
| 32 | 1 U3 | MIC811SUY | Supply Supervisors- Reset Controller | SOT143 | |
| 33 | 4 U4, U5, U6, U7 | SN74LVC1G125DCKR | Single Bus Buffer Gate With 3-State Output | SC70-5 | 1 |
| 34 | 1 | Jumper CAP | Jumper CAP | | JP12에 장 |
| 35 | 1 | РСВ | 2-Layer, 53.3mm x 68.6mm, PCB Color: White, Silk Color: E | Black | |