IPHONE 14 PRO SANDWICH INTERPOSER PINOUT & SIGNAL MAP

Double-Decker Logic Board Interconnect Matrix | Sheet 1 of 2

TOP BOARD (AP & MEMORY) INTERPOSER MATRIX

Power & Critical Handshake Signal Pads

Pads 1-8: PP_VDD_MAIN Primary system distribution (3.8V - 4.4V) | Diode: 395mV

Pads 9-16: PP_VDD_BOOST Camera & audio high-power line | Diode: 420mV

Pad 22: AP_BI_I2C0_SDA (1.8V bus communication to Bottom Board PMU)

Pad 23: AP_TO_I2C0_SCL (1.8V bus clock line)

Pad 35: RESET_1V8_L (System active-low master reset line) | Diode: 520mV

Pads 40-48: GND Shielded Ground Return Isolation Pads

CONFIDENTIAL - SALEN MOBILE GURU CHIP-LEVEL HARDWARE LAB

IPHONE 14 PRO SANDWICH INTERPOSER PINOUT & SIGNAL MAP

Double-Decker Logic Board Interconnect Matrix | Sheet 2 of 2

BOTTOM BOARD (BASEBAND & RF) INTERPOSER MATRIX

Cellular Transceiver & Antenna Switch Interfaces

Pads 60-66: PP_0V8_SMPS1 Baseband Core Supply (Qualcomm X65 5G Modem)

Pads 70-74: PP_1V8_LDO Modem I/O & Memory Rail | Diode: 460mV

Pad 85: BB_TO_AP_UART_TX (High-speed telemetry to A16 Bionic CPU)

Pad 86: AP_TO_BB_UART_RX (Baseband command line)

Separation Temp: 195 deg C on heating platform | Reball Paste: 158 deg C Sn64Bi35Ag1

Jig Testing: QianLi Mega-Idea iSocket middle-layer quick clamp before resoldering

CONFIDENTIAL - SALEN MOBILE GURU CHIP-LEVEL HARDWARE LAB