set_post_filter

Command: `set_post_filter`

Description

This operation is used to set a post-filter for RFID device, enabling the filtering of tags scanned by the device based on specific criteria.

Request

Request Fields

FIELD	TYPE	REQUIRED	DESCRIPTION	EXAMPLE
`command`	string	Yes	Specifies the name of the command to be executed. In this case, it is set_post_filter.	
`requestId`	string	Yes	A unique identifier for the request. This ensures traceability and prevents duplicate processing of the same request.	
`postFilterPayload`	object	No		
`postFilterPayload.operation`	string (enum)	No	Specifies the operation to perform on the filter such as add a new filter, remove and update an existing filter.	

FIELD	TYPE	REQUIRED	DESCRIPTION	EXAMPLE
`postFilterPayload.dataEpType`	string (enum)	No	Specifies the data endpoint to which the filter should be applied. Two data endpoints are supported for reporting filtered tag data.	
`postFilterPayload.matchPattern`	string	No	Defines the value to match for the filter. For prefix and suffix filters, only hexadecimal digits are allowed, and the number of digits must be even. When a prefix filter is used, select filters cannot be applied.	
`postFilterPayload.matchPatternMethod`	string (enum)	No	Specifies the method used to match the tag ID. `PREFIX`: Matches the beginning of the tag ID. `SUFIX`: Matches the end of the tag ID. `REGEX`: Matches the tag ID using a regular expression.	`REGEX`
`postFilterPayload.reportOperation`	string (enum)	No	Specifies the filter operation to apply. `INCLUDE`: Only tags matching the filter criteria will be reported. `EXCLUDE`: Tags matching the filter criteria will be excluded from reporting.	

FIELD	TYPE	REQUIRED	DESCRIPTION	EXAMPLE
`postFilterPayload.reportDuration`	integer	No	Specifies the duration (in seconds) to wait before reporting a tag again after it has already been reported. The filter ensures that as long as the tag is being read by the reader, it will not be reported again until the specified duration has elapsed.	
`postFilterPayload.seenCount`	integer	No	Specifies the number of times a tag must be detected before its data is sent out. This helps in filtering out tags that are inconsistently read.	
`postFilterPayload.tagList`	object	No		
`postFilterPayload.tagList.operation`	string (enum)	No	Specifies whether the tag should be blacklisted or whitelisted. `BLACKLIST`: Excludes tags matching the patterns from reporting. `WHITELIST`: Includes only tags matching the patterns for reporting.	`BLACKLIST`

FIELD	TYPE	REQUIRED	DESCRIPTION	EXAMPLE
`postFilterPayload.tagList.tagPatterns`	array	No	An array of tag patterns to be used for whitelisting or blacklisting. Multiple patterns can be provided to define the filter criteria.	
`postFilterPayload.rssiThreshold`	integer	No	Specifies the RSSI threshold (in dBm). Tags with an RSSI below this threshold will be ignored by the reader. The value must be between -88 dBm (minimum sensitivity) and -26 dBm (maximum sensitivity).	

Request Examples

Set post filter 1

```
{
  "command": "set_post_filter",
  "requestId": "abc123",
  "postFilterPayload": {
    "operation": "ADD",
    "dataEpType": "DATA_EP1",
    "matchPattern": "FFFFBBBBA500",
    "matchPatternMethod": "PREFIX",
    "reportOperation": "INCLUDE",
    "reportDuration": 0,
    "seenCount": 0,
    "rssiThreshold": -88
  }
}
```

Set post filter 2

```
{
  "command": "set_post_filter",
  "requestId": "abc123",
  "postFilterPayload": {
    "operation": "ADD",
    "dataEpType": "DATA_EP1",
    "matchPattern": "E280",
    "matchPatternMethod": "REGEX",
    "reportOperation": "EXCLUDE",
    "reportDuration": 0,
    "seenCount": 0,
    "rssiThreshold": -88
  }
}
```

Response

Response Fields

FIELD	TYPE	REQUIRED	DESCRIPTION	EXAMPLE
`command`	string	Yes		`set_post_filter`
`requestId`	string	Yes		`abc123`
`apiVersion`	string (enum)	Yes		`V1.1`
`response`	object	Yes	Status of the command execution — check `code` to confirm success (0) or identify the error.	

FIELD	TYPE	REQUIRED	DESCRIPTION	EXAMPLE
`response.code`	integer	Yes	Response code indicating success or failure. • **0** — Success • **1** — Command payload accepted • **2** — Invalid payload • **3** — Not able to retrieve information • **4** — Firmware update in progress • **5** — Can't reboot, inventory in progress • **6** — Region is not configured • **7** — Interface is not available • **8** — Insufficient flash size • **9** — File not found • **10** — Configuration already exists • **11** — Inventory in progress • **12** — No radio operation in progress • **13** — Firmware update failed • **14** — Battery too low for firmware update • **15** — WIFI: SSID not found	`0`

FIELD	TYPE	REQUIRED	DESCRIPTION	EXAMPLE
			• **16** — WIFI: Cannot delete active SSID • **17** — WIFI: SSID missing • **18** — WIFI: SSID already exists • **19** — WIFI: SSID count overflow • **20** — WiFi is not supported • **21** — Certificate not found • **22** — Advanced configuration not set • **23** — Invalid enum value • **24** — Max 32 prefilters limit exceeded • **25** — Max 3 publish topics exceeded • **26** — Max 1 subscribe topic exceeded • **27** — Invalid tenant ID length • **28** — Tag match pattern length exceeded	
`response.description`	string	Yes	Human-readable description of the response code (e.g. "Success", "Invalid payload").	`Success`

Response Examples

example1

```
{
  "command": "set_post_filter",
  "requestId": "abc123",
  "apiVersion": "V1.1",
  "response": {
    "code": 0,
    "description": "Success"
  }
}
```