

#	Threat: who, through what	L	I	Decision	Measure or justification
2	The root key is extracted from a sensor stolen from its pole	medium	low	reduce	One key per device: a theft compromises one sensor only. SWD port locked (point 2 (d), (j)).
3	An abusive configuration is sent (a 10 s interval that drains the battery)	low	medium	reduce	Configuration accepted only if authenticated by the LoRaWAN session; values bounded between 5 min and 24 h (point 2 (h)).
4	The cell is covered or turned away on site	medium	low	accept	Out of the device's reach. The platform compares readings with neighbouring sensors and with the theoretical irradiance.
5	The radio is jammed, readings are lost	low	low	accept	Lost readings have no safety consequence; the platform flags a silent sensor.
6	A known vulnerability affects a dependency (RTOS, LoRaWAN stack)	high	medium	reduce	SBOM for each release, continuous monitoring, fix delivered by radio update (Part II, points 1 and 2).
7	After an outage, the whole fleet tries to rejoin the network at once	medium	medium	reduce	Retries spaced out, with a growing delay and some randomness (point 2 (i)).

4. Annex I, Part I, point 2

Point	Applicable?	Implementation, or justification
(a) No known exploitable vulnerability	Yes	SBOM analysed before each release; no known exploitable vulnerability is shipped.
(b) Secure by default, reset to original state	Yes	No shared default secret; a cautious measurement interval (15 min). An internal button restores the factory configuration.
(c) Security updates	Yes	Signed radio updates, installed automatically by default; the operator can postpone them.
(d) Protection from unauthorised access	Yes	No local interface; SWD locked; only commands authenticated by the LoRaWAN session are accepted.
(e) Confidentiality	Yes, low stakes	Payload encrypted by LoRaWAN; no personal data.
(f) Integrity	Yes	Authenticated frames and frame counters; signed firmware; bounded configuration.
(g) Data minimisation	Yes	Only the three useful quantities are sent.
(h) Availability of essential functions	Yes	Watchdog; measuring does not depend on receiving commands; bounded configuration.
(i) No impact on other networks	Yes	Radio duty cycle respected; connection retries spaced out.
(j) Limited attack surface	Yes	A single external interface, the radio; SWD locked.
(k) Exploitation mitigation	Yes	Compiler and RTOS hardening (stack canaries, MPU memory protection).
(l) Logging and monitoring	Yes, in a reduced form	Restarts, failed joins and update results counted and sent in a daily status message, which can be turned off by configuration.
(m) Removal of data and settings	Yes	Factory reset erases the session, the configuration and pending readings. The root key is kept: it is the device's identity, not user data.

5. Annex I, Part I, point 1, and Part II

- **Target cybersecurity level: moderate.** The sensor processes no personal data and controls nothing; a wrong or lost reading only has an operational impact.
- **Vulnerability handling:** a CycloneDX SBOM for each release, continuous monitoring of dependencies, a published contact address with a disclosure policy, fixes delivered by radio update, published security advisories.

6. History

Date	Version	Change
2026-10-06	1.0	First assessment.