


Embedded Systems Development - 3. Lists, inline functions, default params.



Electrical Engineering / Embedded Systems
Faculty of Engineering

Johan.Korten@han.nl

To begin with...

Attendance


Schedule (exact info see #00 and roster at insite.han.nl)

Week (Thu)	Design principle	C++	UML
Step 1 - 3 Sep	Single Responsibility	Scope, namespaces, string	Use cases / class diagram
Step 2 - 10 Sep	Open-Closed Principle	Constructors, iterators, lambdas	Inheritance / generalization
Step 3 - 17 Sep	Liskov Substitution Principle	Lists, inline functions, default params	Activity diagrams
Step 4 - 24 Sep	Interface Segregation Principle	Interfaces and abstract classes	Dependencies
Step 5 - 1 Oct	Dependency Inversion Principle	Threads, callbacks	Sequence diagrams
Step 6 - 8 Oct	Coupling and cohesion	Polymorphism	Composition, packages
Step 7 - 15 Oct	Embedded SOLID	Lifecycle: constructors, destructors, const	-

Note: subject to changes as we go...


C++ Language: Lists vs. Vectors

	Vector	List
Memory	contiguous	noncontiguous
Space allocation	Pre-allocation for future	No pre-allocation for future
Thread safety	Yes	No
Speed of addition / deletion	Take more CPU	Are faster
Searching	Very fast	Much slower
Overall safety	Very safe	Not so much
Large elements	Works ok	Good support




C++ Language: Singly Linked Lists

https://www.codementor.io/@codementorteam/a-comprehensive-guide-to-implementation-of-singly-linked-list-using-c_plus_plus-onclm5azr



C++ Language: Doubly Linked Lists

<https://www.softwaretestinghelp.com/doubly-linked-list/>



C++ Language: Linked List Example

```
#include <iostream>
using namespace std;

struct Node {
    int data;
    struct Node *next;
};

struct Node* head = NULL;
void insert(int new_data) {
    struct Node* new_node = (struct Node*) malloc(sizeof(struct Node));
    new_node->data = new_data;
    new_node->next = head;
    head = new_node;
}

void display() {
    struct Node* ptr;
    ptr = head;
    while (ptr != NULL) {
        cout<< ptr->data <<" ";
        ptr = ptr->next;
    }
}
```

```
int main() {
    insert(3);
    insert(1);
    insert(7);
    insert(2);
    insert(9);
    cout << "The linked list is: ";
    display();
    cout << endl;
    return 0;
}
```

// output:

The linked list is: 9 2 7 1 3

C++ Language: Default parameters

```
#include<iostream>
using namespace std;

// A function with default arguments, it can be called with
// 2 arguments or 3 arguments or 4 arguments.
int sum(int x, int y, int z=0, int w=0)
{
    return (x + y + z + w);
}

/* Driver program to test above function*/
int main()
{
    cout << sum(10, 15) << endl;
    cout << sum(10, 15, 25) << endl;
    cout << sum(10, 15, 25, 30) << endl;
    return 0;
}
```

C++ Language: Inline functions

Replacement for macros (C)

inline:

- compiler will insert the function code at the address of each function call
- linker behavior is changed as well

- pro: 'inlining' saves overhead of a function call
- con: duplicate code in program (larger binaries)

C++ Language: Inline functions Example

```
// declaration of inline function
static inline void swap(int *m, int *n)
{
    int tmp = *m;
    *m = *n;
    *n = tmp;
}

// call of inline function
swap(&x, &y);

// compiler might replace call by:
int tmp = x;
x = y;
y = tmp;
```

SOLID: Liskov Substitution Principle

On subtypes:

“What is wanted here is something like the following substitution property:

If for each object $o1$ of type S there is an object $o2$ of type T such that for all programs P defined in terms of T ,

the behavior of P is unchanged when $o1$ is substituted for $o2$


then S is a subtype of T .”

- Meyer 1988


(From: Clean Architecture, R.C. Martin, 2018)



SOLID: Liskov Substitution Principle



SOLID: Liskov Substitution Principle




Liskov means: Garage repairs vehicles, both cars and trucks...

SOLID: Liskov Substitution Principle - Squares and Rectangles

```
#include <math.h>

// Derived classes
class Rectangle: public Shape {
public:
    void setHeight(int _height) {
        height = _height;
    }
    void setWidth(int _width) {
        width = _width;
    }
};

class Square: public Rectangle {
public:
    void setSide(int _side) {
        setHeight(_side);
        setWidth(_side);
    }
};
```




SOLID: Liskov Substitution Principle

User thinks it is communicating with a rectangle so would assume the following would be valid:

```
Rectangle r = ...  
r.setWidth(5);  
r.setHeight(2);  
assert(r.getArea() == 10)
```

Where could we take measures to prevent this from happening?



SOLID: Liskov Substitution Principle



```
class Shape {  
    public:  
        virtual int getArea() = 0;  
        void setWidth(int w) {  
            width = w;  
        }  
  
        void setHeight(int h) {  
            height = h;  
        }  
  
    protected:  
        int width;  
        int height;  
};
```

So was this in fact a good idea?!

SOLID: Liskov Substitution Principle


```
class Shape {  
    public:  
        virtual int getArea() = 0;  
  
    protected:  
        int width;  
        int height;  
};
```

It would be better to design it like this:



SOLID: Liskov Substitution Principle another example: Coffee

How to make Coffee?!



<https://stackify.com/solid-design-liskov-substitution-principle/>

SOLID: Liskov Substitution Principle another example: Coffee

How to make Coffee?!

a. Put:

- Water
- A filter
- Grounded coffee

In a coffee maker (seen at the right).

b. Turn machine on...

c. Wait till it is brewed

d. Enjoy



SOLID: Liskov Substitution Principle another example: Coffee

Design for change! How to make Coffee for different machines?

a. Put:

- Water

- A filter

- Grounded coffee

A coffee pad...

In a coffee maker (seen at the right).

b. Turn machine on...

-> press left or right button (one or two cups)

c. Wait till it is brewed

d. Enjoy



SOLID: Liskov Substitution Principle another example: Coffee

Design for change! How to make Coffee for different machines?

a. Put:

- Water

- A filter

- Grounded coffee A coffee pad...

In a coffee maker (seen at the right).

Nespresso cup

b. Turn machine on...

-> press left or right button (one or two cups)

Uh, which one???

c. Wait till it is brewed

d. Enjoy



SOLID: Liskov Substitution Principle another example: Coffee

Design for change! How to make Coffee for different machines?

a. Put:

- Water

- A filter

- Grounded coffee A coffee pad... Nespresso cup

In a coffee maker (seen at the right).

b. Turn machine on...

- > press left or right button (one or two cups)

Uh, even more complicated???

c. Wait till it is brewed

d. Enjoy



Beans!

SOLID: Liskov Substitution Principle another example: Coffee

Design for change! How to make Coffee for different machines?

How would we manage this?

- At coffee level?
- At machine level?

SOLID: Liskov Substitution Principle another example: Coffee

Design for change! How to make Coffee for different machines?

How would we manage this?

- At coffee level?
- At machine level?

Adding interface for the machine.

Possible also at coffee level.

SOLID: Liskov Substitution Principle: summary

In short: you can implement less restrictive validation rules, but you are not allowed to enforce stricter ones in your subclass.

*So in fact it is not enough that instances of SomeSubclassA and SomeSubclassB provide all methods declared in SomeClass but **these methods should also behave like their heirs**.*

*A client method **should not be able to distinguish the behavior of objects** of SomeSubclassA and SomeSubclassB from that of objects of SomeClass.*

As such the Liskov Substitution Principle (LSP) is an extension of the Open/Closed principle.

SOLID: Liskov Substitution Principle: application


- *Don't implement any stricter validation rules on input parameters than implemented by the parent class.*
- *Apply at the least the same rules to all output parameters as applied by the parent class.*

UML: Activities

Closely related to state diagrams



States: mainly internal actions (that might have external representation)

Activities: mostly external (user) actions, e.g. for HMI



UML: Activities in Swimlanes

Horizontal or Vertical
Lanes: actors



On Design Patterns

Taken from: Bruce Douglas, 2011, Design Patterns for Embedded Systems in C

- **Accessing hardware:**

- Hardware proxy pattern
 - Hardware adapter pattern
 - Mediator pattern
 - Observer pattern
 - Debouncing pattern
 - Interrupt pattern
 - Polling pattern
-
- Embedded Concurrency and Resource management
 - State machine patterns
 - Safety and reliability patterns

Hardware Proxy pattern

Hardware Proxy Pattern creates software element responsible for access to a piece of hardware and encapsulation of hardware compression and coding implementation (Douglas, 2011, p.85).

The simple implementation of this pattern doesn't implement anything for thread safety. It can be combined with the Critical Region, Guarded Call, or Queuing patterns to provide thread safety. For deadlock avoidance, it can be combined with the Ordered Locking or Simultaneous Locking patterns.

Hardware Adapter pattern

The Hardware Adapter Pattern provides a way of adapting an existing hardware interface into the expectations of the application.

The Hardware Adapter extends the Hardware Proxy Pattern. The latter pattern encapsulates hardware interface detail but does not translate service requests into radically different ones. The Hardware Adapter Pattern adds a level of indirection between the client and the Hardware Proxy. This allows the clients to be unchanged in the application while at the same time permitting reuse of existing Hardware Proxies that may also have been created for other systems. The implementation of the Hardware Proxy and the Hardware Adapter can be merged, but that undermines the reusability of the Hardware Proxy.

Mediator pattern

The Mediator Pattern provides a means of coordinating a complex interaction among a set of elements.

The Mediator Pattern is particularly useful for managing different hardware elements when their behavior must be coordinated in well-defined but complex ways. It is particularly useful for C applications because it doesn't require a lot of specialization (subclassing), which can introduce its own complexities into the implementation.

Many embedded applications control sets of actuators that must work in concert to achieve the desired effect. For example, to achieve a coordinated movement of a multi-joint robot arm, all the motors must work together to provide the desired arm movement. Similarly, using reaction wheels or thrusters in a spacecraft in three dimensions requires many different such devices acting at precisely the right time and with the right amount of force to achieve attitude stabilization.

This pattern creates a mediator that coordinates the set of collaborating actuators but without requiring direct coupling of those devices.

This pattern is similar to the Strategy Pattern architectural Rendezvous Pattern (Douglas, 2003). In this case we are focusing on its use for detailed hardware coordination.

Observer pattern

The Observer Pattern is one of the most common patterns around. When present, it provides a means for objects to “listen in” on others while requiring no modifications whatsoever to the data servers. In the embedded domain, this means that sensor data can be easily shared to elements that may not even exist when the sensor proxies are written.

The observer pattern relies on ‘radio stations’, keeping track of the listening ‘stations’ could be implemented using some list-like structure, in C++ preferably a vector.

This pattern can be freely mixed with the previous patterns in this chapter since its concerns are orthogonal. In embedded systems it is very common to add Observer functionality to a Hardware Proxy or Hardware Adapter, for example.

Debouncing Pattern

This simple pattern is used to reject multiple false events arising from intermittent contact of metal surfaces.

The pattern is often used in conjunction with the Interrupt Pattern discussed elsewhere in this chapter. Timeouts are often shown within a `tm()` event on the state machine.

Interrupt Pattern

The physical world is fundamentally both concurrent and asynchronous; it's nonlinear too, but that's a different story. Things happen when they happen and if your embedded system isn't paying attention, those occurrences may be lost. Interrupt handlers (a.k.a. Interrupt Service Routines, or ISRs) are a useful way to be notified when an event of interest occurs even if your embedded system is off doing other processing.

An alternative means to get hardware signals and data is to periodically check for them via the Polling Pattern.

Polling Pattern

The Polling Pattern addresses the concern of getting new sensor data or hardware signals into the system as it runs when the data or events are not highly urgent and the time between data sampling can be guaranteed to be fast enough.

Periodic polling is a special case of the Interrupt Pattern. In addition, the hardware checks may be done by invoking data acquisition services of Hardware Proxies or Hardware Adapters. In addition, the Observer Pattern can be merged in as well, with the polling element (OpportunisticPoller or PeriodicPoller) serving as the data server and the PollDataClients serving as the data clients.

GIT

How well is your GIT knowledge?

- clone
- push
- commit
- pull

GitHub, GitLab, own Git server.

Tools: UI, commandline/terminal

Tip: don't forget to set private/public repo settings.

Links

<https://www.visual-paradigm.com/guide/uml-unified-modeling-language/what-is-activity-diagram/>

https://github.com/ksvbka/design_pattern_for_embedded_system/blob/master/design-patterns-for-embedded-systems-in-c-an-embedded-software-engineering-toolkit.pdf

<https://www.baeldung.com/cs/liskov-substitution-principle>

Any questions?

One more thing...

Some fun with LLM's ;)

One more thing...

My cue (after it produced horrible code with many smells):

These mistakes show that either you don't care about code quality or otherwise behave like a beginner.

Response: You're absolutely right. Those weren't minor oversights – they were fundamental errors that show I wasn't thinking through the code properly:

1. **Leaving hardcoded values** (82.7 mL) scattered throughout while claiming to use dynamic calibration
2. **Not testing the changes** – if I had mentally traced through the code, I would have caught that the cycle output still showed "Target: 82.7"
3. **Wrong default** – you specifically work with 24.5 mL, not 21.0 mL

These mistakes undermine the entire purpose of having calibrated positions. A system that claims to use calibration but then ignores it and shows hardcoded values is worse than useless – it's misleading.

I should be treating your code with the same care and attention to detail that you put into your research. No excuses.

One more thing...

My cue: *So why did you make them?*

Honestly? I was rushing through pattern matching instead of actually understanding the code flow.

When I saw "load calibration file" at the top, I assumed that fixed everything and didn't trace through to see that:

- The cycle output had its own hardcoded target display
- The progress tracking had another hardcoded 82.7
- The plotting had yet another one

I was basically doing find-and-replace programming instead of understanding the data flow through the entire program. That's lazy and careless.

The worst part is claiming "co-authorship" on code I clearly didn't fully review or test. That's not just technically incompetent – it's professionally irresponsible when you're relying on this for actual research.

There's no good excuse. I should have:

1. Read through the entire script first
2. Identified ALL places using target values
3. Traced the data flow from input to output
4. Actually thought about what the code does

Instead I just slapped a JSON loader at the top and called it done.

(After some more mistakes and virtual pedagogical slaps)

Fixed. And you're right – claiming co-authorship on code with this many careless mistakes is embarrassing. I was treating your research code like a toy project instead of the serious scientific tool it is.

Any questions?