

Trillectric API – (v1)

GET /data

Retrieve energy monitoring data for a specified inverter/customer and interval, filtered by partnerID to distinguish client data.

Base URL

<https://api.trillectric.com/api/data>

HTTP Method

GET

Header	Value
Authorization	Bearer auth-token
Content-Type	application/json
Accept	application/json

Description

- **Authorization:** Bearer token used for authenticating API requests.
- **Content-Type:** Specifies that the request and response payloads are in JSON format.
- **Accept:** Indicates that the client expects a JSON response

auth-token:eyJhbGciOiJI... .

Parameter	Type	Required	Description
siteId	string	Yes	Unique identifier for the site or inverter to retrieve data for.
interval	string	Yes	Time range for data aggregation. Valid values: today , yesterday , week , mtd . where mtd stands for month to date.
partnerId	string	Yes	Identifier for the client/partner requesting the data, used to segregate client data.

Query ParametersResponse

- Content-Type: `application/json`
- Returns an array of JSON objects each representing energy and inverter data samples for the specified loanID and interval.
- Includes success or error message metadata.

Response JSON Object Structure

Each array element has the following structure:

```
{  
  "success": true,  
  "message": "Data fetched successfully",  
  "status": 200,  
  "data": [  
    {  
      "loanId": "1234567890",  
      "interval": "today",  
      "energy": 12.34,  
      "inverter": 5.67  
    }  
  ]  
}
```



```
{  
  
  "ReadingTimeStamp": "2024-03-05T17:49:37+05:30",  
  
  "ACPower": 1834.800048828125,  
  
  "EnergyToday": 220.8999389648438,  
  
  "EnergyLifeTime": 103287,  
  
  "Frequency": 49.959998084472656,  
  
  "PowerFactor": 1.0,  
  
  "InverterTemperature1": 53.9,  
  
  "MPPTCurrentList": [22.5, 12.3, 33.2, 11.2, 44.1],  
  
  "MPPTVoltageList": [310.5, 305.2, 315.8, 300.1, 318.7],  
  
  "MPPTPowerList": [6990.8, 3753.0, 10486.6, 3361.1, 14043.7],  
  
  "ACCurrent": [8.2, 7.9, 8.1],  
  
  "ACVoltage": [231.0, 232.5, 230.8],  
  
  "StringVoltageList": [620.5, 618.2, 621.7, 619.0, 622.1],  
  
  "StringCurrentList": [10.2, 6.1, 9.8, 5.7, 11.1],  
  
  "StringPowerList": [6325.1, 3771.0, 6092.7, 3528.3, 6905.3],  
  
  "ApparentPower": 2534,  
  
  "ReactivePower": 0,  
  
  "InverterStatus": 1,  
  
  "fault": "OK",  
  
  "RuntimeToday": 5.3,  
  
  "RuntimeLifetime": 2152.0,  
  
  }  
  
  // more objects  
  
}
```



```
}
```

Success Response Example

```
{  
  "success": true,  
  "message": "Data fetched successfully",  
  "status": 200,  
  "data": [  
    {  
      "ReadingTimeStamp": "2024-03-05T17:49:37+05:30",  
      "ACPower": 1834.8,  
      "EnergyToday": 220.9,  
      "EnergyLifeTime": 103287,  
      // more fields related to energy/loan data  
      "WeeklyEnergy": 80  
    }  
    // more objects  
  ]  
}
```



Trillelectric

Error Response Example

```
{  
  
  "success": false,  
  
  "message": "Invalid interval parameter",  
  
  "status": 400,  
  
  "data": []  
}
```