Fast Integral Transforms

Yin Li

Mar. 2017

This library computes common integral transforms with product kernels using the FFTLog algorithm [Tal78, Ham00]

$$G(y) = \int_0^\infty F(x)K(xy)\,\frac{\mathrm{d}x}{x} \tag{1}$$

or equivalently

$$g(y) = \int_0^\infty f(x)(xy)^q K(xy)\,\frac{\mathrm{d}x}{x} \tag{2}$$

where $K(xy)$ is the kernel function and q is a power-law tilt parameter. And with $f(x) \propto x^{-q}$, $g(y) \propto y^q$, one is free to choose q. We can tilt $f(x)$ to balance f at large and small x, in order to improve accuracy and reduce ringing.

The idea is to take advantage of the convolution theorem in $\ln x$ and $\ln y$. We approximate $f(x)$ with truncated Fourier series, and use the exact Fourier transform of the possibly oscillatory kernel. We can calculate the latter analytically via Mellin transform. This algorithm performs the best if f can be accurately approximated by a sum of finite Fourier modes and logarithmically uniform discretization, that is when $f(x)$ is smooth and spans a large range in $\ln x$.

Derivation largely follows [Ham00]. In Eq. (2) take $f(x)$ on $[x_{\min}, x_{\max}]$, impose periodicity $f(x_{\max}) = f(x_{\min})$ in $\ln x$, and then discretize it by $\ln x_n \equiv \ln x_{\min} + n\Delta$ and $\ln x_{\max}/x_{\min} = N\Delta$. The logarithmic interval $\Delta \equiv |\Delta \ln x| \equiv |\Delta \ln y|$ uniformly discretizes $\ln x$ and later also $\ln y$, i.e., $\ln y_n \equiv \ln y_{\min} + n\Delta$ and $\ln y_{\max}/y_{\min} = N\Delta$.

Define a symmetrized sum

$$\sideset{}{'}\sum_n a_n \equiv \sum_{m=-\lfloor N/2 \rfloor}^{\lfloor N/2 \rfloor} w_n a_n \tag{3}$$

with $w_n = 1$ except that $w_{-N/2} = w_{N/2} = 1/2$ if N is even. Using this and the fact that f_m and $f(x_n)$ are periodic over $m, n \in \mathbb{Z}_N$, let's rewrite the usual discrete Fourier transform

$$f(x_n) = \frac{1}{N}\sum_{m=0}^{N-1} f_m \exp\left(\frac{i2\pi mn}{N}\right) = \frac{1}{N}\sideset{}{'}\sum_m f_m \exp\left(\frac{i2\pi mn}{N}\right) = \frac{1}{N}\sideset{}{'}\sum_m f_m \exp\left[\frac{i2\pi m \ln(x_n/x_{\min})}{N\Delta}\right] \tag{4}$$

$$f_m = \sum_{n=0}^{N-1} f(x_n) \exp\left(-\frac{i2\pi mn}{N}\right) = \sideset{}{'}\sum_n f(x_n) \exp\left(-\frac{i2\pi mn}{N}\right) \tag{5}$$

For smooth $f(x)$, a good approximation is the truncated Fourier series with f_m as coefficients

$$f(x) \approx \frac{1}{N}\sideset{}{'}\sum_m f_m \exp\left[\frac{i2\pi m \ln(x/x_{\min})}{N\Delta}\right] \tag{6}$$

always real thanks to the symmetrized sum.

To evaluate Eq. (2) we can transform each Fourier mode

$$\int_0^\infty \exp\left[\frac{i2\pi m \ln(x/x_{\min})}{N\Delta}\right](xy)^q K(xy)\,\frac{\mathrm{d}x}{x} \tag{7}$$

$$= \int_0^\infty \exp\left\{\frac{i2\pi m}{N\Delta}\left[\ln(xy) - \ln\left(\frac{y}{y_{\min}}\right) + \ln\left(\frac{y_{\max}}{y_{\min}}\right) - \ln(x_{\min}y_{\max})\right]\right\}(xy)^q K(xy)\,\frac{\mathrm{d}x}{x} \tag{8}$$

$$= \exp\left\{-\frac{i2\pi m}{N\Delta}\left[\ln\left(\frac{y}{y_{\min}}\right) + \ln(x_{\min}y_{\max})\right]\right\}\int_0^\infty t^{q-1+i\frac{2\pi m}{N\Delta}} K(t)\,\mathrm{d}t \tag{9}$$

Finally we just need to calculate analytically the Fourier transform of the kernel including the tilt factor, as a Mellin transform

$$U_K(z) \equiv \int_0^\infty t^{z-1} K(t)\, \mathrm{d}t \tag{10}$$

which satisfies $U_K^*(z) = U_K(z^*)$, and derive

$$g(y) \approx \frac{1}{N} {\sum_m}' g_m \exp\left[-\frac{i2\pi m \ln(y/y_{\min})}{N\Delta}\right] \tag{11}$$

$$g(y_n) \approx \frac{1}{N} {\sum_m}' g_m \exp\left[-\frac{i2\pi m \ln(y_n/y_{\min})}{N\Delta}\right] = \frac{1}{N} \sum_{m=0}^{N-1} g_m \exp\left(-\frac{i2\pi mn}{N}\right) \tag{12}$$

where

$$g_m = f_m u_m \tag{13}$$

$$u_m = \exp\left[-\frac{i2\pi m \ln(x_{\min}y_{\max})}{N\Delta}\right] U_K\left(q + i\frac{2\pi m}{N\Delta}\right) \qquad -\lfloor N/2 \rfloor \le m \le \lfloor N/2 \rfloor \tag{14}$$

We should make u_m periodic over $m \in \mathbb{Z}_N$, however $u_{-N/2}$ and $u_{N/2}$ are not necessarily equal for even N. In practice we can impose

$$g_{\pm N/2} \to \Re(g_{N/2}) \qquad N \in 2\mathbb{Z} \tag{15}$$

which is automatically satisfied if

$$\ln(x_{\min}y_{\max}) = \frac{\Delta}{\pi} \mathrm{Arg} U_K\left(q + i\frac{\pi}{\Delta}\right) + \mathrm{integer} \cdot \Delta \tag{16}$$

where the argument takes its principal value in $(-\pi, \pi]$ and we set the arbitrary integer to 0. Otherwise we can just set $x_{\min}y_{\max} = 1$ for convenience.

Algorithm   Follow the steps in equations (5), (10), (16) (or (15)), (14), (13), and (12) for fast evaluation of Eq. (2). u_m from Eq. (14) should be saved for multiple transformations.

Common Integral Transforms:

Hankel transform pair

$$G(y) = \int_0^\infty F(x) J_\nu(xy)\, x\mathrm{d}x \tag{17}$$

$$f(x) \to x^{2-q} F(x) \tag{18}$$
$$g(y) \to y^q G(y) \tag{19}$$
$$K(t) \to J_\nu(t) \tag{20}$$
$$U_K(z) = 2^{z-1} \frac{\Gamma\left(\frac{\nu+z}{2}\right)}{\Gamma\left(\frac{2+\nu-z}{2}\right)} \tag{21}$$

The pair is symmetric when $q = 1$.

Spherical Bessel transform pair

$$G(y) = \sqrt{\frac{2}{\pi}} \int_0^\infty F(x) j_\nu(xy)\, x^2\mathrm{d}x \tag{22}$$

$$f(x) \to x^{3-q} F(x) \tag{23}$$
$$g(y) \to y^q G(y) \tag{24}$$
$$K(t) \to \sqrt{\frac{2}{\pi}} j_\nu(t) = \frac{J_{\nu+\frac{1}{2}}(t)}{\sqrt{t}} \tag{25}$$
$$U_K(z) = 2^{z-\frac{3}{2}} \frac{\Gamma\left(\frac{\nu+z}{2}\right)}{\Gamma\left(\frac{3+\nu-z}{2}\right)} \tag{26}$$

The pair is symmetric when $q = \frac{3}{2}$.

Fourier sine transform pair

$$G(y) = \sqrt{\frac{2}{\pi}} \int_0^\infty F(x) \sin(xy) \, \mathrm{d}x \tag{27}$$

$$f(x) \to x^{1-q} F(x) \tag{28}$$

$$g(y) \to y^q G(y) \tag{29}$$

$$K(t) \to \sqrt{\frac{2}{\pi}} \sin(t) = \sqrt{t} J_{\frac{1}{2}}(t) \tag{30}$$

$$U_K(z) = \sqrt{\frac{2}{\pi}} \Gamma(z) \sin\left(\frac{\pi z}{2}\right) = 2^{z-\frac{1}{2}} \frac{\Gamma\left(\frac{1+z}{2}\right)}{\Gamma\left(\frac{2-z}{2}\right)} \tag{31}$$

The pair is symmetric when $q = \frac{1}{2}$.

Fourier cosine transform pair

$$G(y) = \sqrt{\frac{2}{\pi}} \int_0^\infty F(x) \cos(xy) \, \mathrm{d}x \tag{32}$$

$$f(x) \to x^{1-q} F(x) \tag{33}$$

$$g(y) \to y^q G(y) \tag{34}$$

$$K(t) \to \sqrt{\frac{2}{\pi}} \cos(t) = \sqrt{t} J_{-\frac{1}{2}}(t) \tag{35}$$

$$U_K(z) = \sqrt{\frac{2}{\pi}} \Gamma(z) \cos\left(\frac{\pi z}{2}\right) = 2^{z-\frac{1}{2}} \frac{\Gamma\left(\frac{z}{2}\right)}{\Gamma\left(\frac{1-z}{2}\right)} \tag{36}$$

The pair is symmetric when $q = \frac{1}{2}$.

Applications

Top-hat smoothing of a radial function   in $\mathbb{R}^d$

$$F^W(R) = \int_0^\infty \frac{k^d F(k)}{2^{d-1} \pi^{\frac{d}{2}} \Gamma\left(\frac{d}{2}\right)} W_\mathrm{T}(kR) \frac{\mathrm{d}k}{k} \tag{37}$$

where

$$W_\mathrm{T}(r) = \begin{cases} 1 & r \leq R \\ 0 & r > R \end{cases} \tag{38}$$

$$W_\mathrm{T}(kR) = \frac{2^{\frac{d}{2}} \Gamma\left(\frac{d}{2} + 1\right) J_{\frac{d}{2}}(kR)}{(kR)^{d/2}} \tag{39}$$

$$x \to k \tag{40}$$

$$y \to R \tag{41}$$

$$f(x) \to \frac{k^{d-q} F(k)}{2^{d-1} \pi^{\frac{d}{2}} \Gamma\left(\frac{d}{2}\right)} \tag{42}$$

$$g(y) \to R^q F^W(R) \tag{43}$$

$$K(t) \to W_\mathrm{T}(t) \tag{44}$$

$$U_K(z) = 2^{z-1} \frac{\Gamma\left(\frac{2+d}{2}\right) \Gamma\left(\frac{z}{2}\right)}{\Gamma\left(\frac{2+d-z}{2}\right)} \tag{45}$$

3

Gaussian smoothing of a radial function   in $\mathbb{R}^d$

$$F^W(R) = \int_0^\infty \frac{k^d F(k)}{2^{d-1}\pi^{\frac{d}{2}}\Gamma\left(\frac{d}{2}\right)} W_{\mathrm{G}}(kR)\, \frac{\mathrm{d}k}{k} \tag{46}$$

where

$$W_{\mathrm{G}}(r) = \frac{1}{(2\pi R^2)^{\frac{d}{2}}} \exp\left(-\frac{r^2}{2R^2}\right) \tag{47}$$

$$W_{\mathrm{G}}(kR) = \exp\left(-\frac{k^2 R^2}{2}\right) \tag{48}$$

$$x \to k \tag{49}$$
$$y \to R \tag{50}$$
$$f(x) \to \frac{k^{d-q} F(k)}{2^{d-1}\pi^{\frac{d}{2}}\Gamma\left(\frac{d}{2}\right)} \tag{51}$$
$$g(y) \to R^q F^W(R) \tag{52}$$
$$K(t) \to W_{\mathrm{G}}(t) \tag{53}$$
$$U_K(z) = 2^{\frac{z}{2}-1}\Gamma\left(\frac{z}{2}\right) \tag{54}$$

Cosmology applications

Power spectrum to correlation function

$$\xi_l(r) = i^l \int_0^\infty \frac{k^3 P_l(k)}{2\pi^2} j_l(kr)\, \frac{\mathrm{d}k}{k} \tag{55}$$

$$x \to k \tag{56}$$
$$y \to r \tag{57}$$
$$f(x) \to \frac{i^l k^{3-q} P_l(k)}{(2\pi)^{\frac{3}{2}}} \tag{58}$$
$$g(y) \to r^q \xi_l(r) \tag{59}$$

with the rest the same as the spherical Bessel transform.

Correlation function to power spectrum   also radial profile to its Fourier transform

$$P_l(k) = (-i)^l \int_0^\infty 4\pi r^3 \xi_l(r) j_l(kr)\, \frac{\mathrm{d}r}{r} \tag{60}$$

$$x \to r \tag{61}$$
$$y \to k \tag{62}$$
$$f(x) \to r^{3-q} \xi_l(r) \tag{63}$$
$$g(y) \to \frac{i^l k^q P_l(k)}{(2\pi)^{\frac{3}{2}}} \tag{64}$$

with the rest the same as the spherical Bessel transform. The 2-pt function conversion pair is symmetric when $q = \frac{3}{2}$.

Variance in a Top-hat window   in $\mathbb{R}^3$

$$\sigma_{\mathrm{T}}^2(R) = \int_0^\infty \frac{k^3 P(k)}{2\pi^2} W_{\mathrm{T}}^2(kR) \frac{\mathrm{d}k}{k} \tag{65}$$

where

$$W_{\mathrm{T}}(t) = \frac{3}{t^3}(\sin t - t\cos t) = \frac{3 j_1(t)}{t} \tag{66}$$

$$x \to k \tag{67}$$
$$y \to R \tag{68}$$
$$f(x) \to \frac{k^{3-q} P(k)}{2\pi^2} \tag{69}$$
$$g(y) \to R^q \sigma_{\mathrm{T}}^2(R) \tag{70}$$
$$K(t) \to W_{\mathrm{T}}^2(t) \tag{71}$$
$$U_K(z) = \frac{9\sqrt{\pi}(z-2)}{4(z-6)} \frac{\Gamma\left(\frac{z-4}{2}\right)}{\Gamma\left(\frac{5-z}{2}\right)} \tag{72}$$

Variance in a Gaussian window   in $\mathbb{R}^3$

$$\sigma_{\mathrm{G}}^2(R) = \int_0^\infty \frac{k^3 P(k)}{2\pi^2} W_{\mathrm{G}}^2(kR) \frac{\mathrm{d}k}{k} \tag{73}$$

where

$$W_{\mathrm{G}}(kR) = \exp\left(-\frac{k^2 R^2}{2}\right) \tag{74}$$

$$x \to k \tag{75}$$
$$y \to R \tag{76}$$
$$f(x) \to \frac{k^{3-q} P(k)}{2\pi^2} \tag{77}$$
$$g(y) \to R^q \sigma_{\mathrm{G}}^2(R) \tag{78}$$
$$K(t) \to W_{\mathrm{G}}^2(t) \tag{79}$$
$$U_K(z) = \frac{1}{2}\Gamma\left(\frac{z}{2}\right) \tag{80}$$

Excursion set   in $\mathbb{R}^3$

$$\delta^W(R) = \int_0^\infty \frac{k^3 \delta(k)}{2\pi^2} W_{\mathrm{T}}(kR) \frac{\mathrm{d}k}{k} \tag{81}$$

same as top-hat smoothing of a radial function given previously.

$$x \to k \tag{82}$$
$$y \to R \tag{83}$$
$$f(x) \to \frac{k^{3-q} \delta(k)}{2\pi^2} \tag{84}$$
$$g(y) \to R^q \delta^W(R) \tag{85}$$
$$K(t) \to W_{\mathrm{T}}(t) \tag{86}$$
$$U_K(z) = 3\sqrt{\pi}2^{z-3} \frac{\Gamma\left(\frac{z}{2}\right)}{\Gamma\left(\frac{5-z}{2}\right)} \tag{87}$$

Note that $\delta(k)$ is random and not smooth.

Test We test our implementation on Hankel transform in the following analytic case

$$e^{-y} = \int_0^\infty (1+x^2)^{\frac{3}{2}} J_0(xy)\, x\mathrm{d}x \tag{88}$$

$$(1+y^2)^{\frac{3}{2}} = \int_0^\infty e^{-y} J_0(xy)\, x\mathrm{d}x \tag{89}$$

Parameters

Length: N Odd N has worse ringing problem, similar to the case without low-ringing condition.

Tilt: q We can reduce ringing by balancing the large and small scale amplitudes with the tilt. The gamma function has simple poles at the non-positive integers, which can be avoided by picking q. However, one should not use a tilt too large, as it tends to shift the focus away and thus reduces the accuracy on the interested scales.

Padding: $f(x)$ is padded either with power-law extrapolations from the end segments beyond the tabulated region, or just with zeros.

Gamma function The reflection and duplication formulae are useful for playing with the gamma functions

$$\frac{\pi}{\sin \pi z} = \Gamma(1-z)\Gamma(z) = (-1)^n \Gamma(1+n-z)\Gamma(z-n) \tag{90}$$

$$\Gamma(z)\Gamma(z+\tfrac{1}{2}) = 2^{1-2z}\sqrt{\pi}\,\Gamma(2z) \tag{91}$$

References

[Ham00] A. J. S. Hamilton. Uncorrelated modes of the non-linear power spectrum. *MNRAS*, 312:257–284, February 2000.

[Tal78] J. D. Talman. Numerical Fourier and Bessel Transforms in Logarithmic Variables. *Journal of Computational Physics*, 29:35–48, October 1978.