ReasonLink: P1 Infrastructure and Baselines

Vayun Gupta (vg2684), Aaron Mano Cherian (amc2535)
COMS 6998: AI-Native Computing | Fall 2026
P1 Milestone | Due October 19, 2026, 11:59 PM ET

Repository: https://github.com/AaronCherian404/ReasonLink All numbers below are reproducible from the repository (raw per-run data in `results/p1/`); `PROGRESS.md` logs every step, decision, and command, and Appendix A lists the steps to reproduce them.

I. Summary and Platform Change

We could not obtain the VCU118 that the Chipyard/FireSim flow needed, so we moved from Chipyard and Gemmini to ESP [1], the open SoC platform that already integrates NVDLA [2] as a third-party accelerator alongside Ariane [3]. The neural accelerator is now NVDLA *nv_small* (int8, 64 MACs); the symbolic accelerator is still SAT-Accel [4]. ESP's full flow is installed on a departmental server, and a VCU118 will be available later through ESP. The research question, the visual-Sudoku workload, the two baselines, and the four ReasonLink mechanisms are unchanged.

For P1 we built every piece of the pipeline that does not need the board, checked each against a reference (Table I), and ran both baselines end to end (Sec. III). The main gap is that SAT-Accel itself cannot run yet; a MiniSat stand-in consumes SAT-Accel's exact memory image instead (Sec. II-E).

TABLE I
Component status (October 16).

Component	Status	Evidence
ESP toolchain on server	Ready	ESP 2026.1.0 pinned; Vivado, ModelSim, RISC-V GCC present
NVDLA compile flow	Working	ESP's loadable reproduced byte for byte
int8 LeNet classifier	Working (emulated)	99.20% MNIST; emulator matches NVDLA reference
Sudoku workload	Working	1,000 puzzles + NVDLA output trace
SAT-Accel host image	Working	C port byte-exact vs. SAT-Accel, 13/13
SAT solving	Stand-in	MiniSat on SAT-Accel's image; SAT-Accel blocked
Serial / double-buffered baselines	Working (host)	End to end, cycle-counted, 1,000 puzzles; RISC-V build
NVDLA, SAT-Accel on ESP SoC	Not started	After P1

II. Setup by Component

A. Repository

All code is in one repository: `workload/` (CNF encoder, dataset, classifier, NVDLA compile script), `handoff/` (SAT-Accel image builder, solver backend, tests), `models/` (re-trained weights), and `results/p1/` (machine-readable outputs). SAT-Accel, MiniSat, and Xilinx's open-source `ap_int` headers are git submodules pinned to fixed commits. Local work runs in WSL Ubuntu 24.04 with a pinned Python environment (`env/setup_wsl.sh`).

B. ESP Platform (server)

The server runs RHEL 8.10 (ESP's primary platform) with 16 cores and 62 GB RAM, and already provides ESP's required tools: Vivado 2023.2, ModelSim DE 2023.2, Xcelium 23.09, Vitis HLS 2023.2, and RISC-V GCC 9.2, so ESP's 1–2 h toolchain build is unnecessary. ESP is pinned to release 2026.1.0 (`a45f2bb`); only the NVDLA software submodule is fetched so far. The server lacks Vitis `v++` and XRT, which matters for SAT-Accel (Sec. II-E).

C. NVDLA Classifier

We use the LeNet [5] that ESP ships for its NVDLA demo, so our classifier is the network ESP already runs on NVDLA.

- *Compiler.* Recompiling ESP's model with the pre-built `nvdla_compiler` reproduces ESP's shipped loadable byte for byte with `--quantizationMode per-filter --informat nchw`; the compiler is deterministic, and no other flag combination matched.
- *int8 emulator.* A Python model of the int8 pipeline (the runtime's input mapping, per-filter weight scales, calibrated requantization) reproduces ESP's published NVDLA output for its test image exactly. It generates the per-cell scores that stand in for NVDLA's output buffer.
- *Weights.* ESP's demo weights reach only 74.5% on MNIST. They were trained with mean-image subtraction and a 1/80 input scale that neither the deploy model nor the NVDLA int8 input path applies. We retrained the same architecture on the input NVDLA actually receives and wrote a new calibration table (Table II). The retrained model compiles with ESP's flags to a 445,736-byte loadable.

TABLE II
LeNet accuracy on the MNIST test set (10,000 images).

Weights	float	int8 (emulated)
ESP demo, under NVDLA preprocessing	74.5%	74.5%
Retrained (ours)	99.17%	99.20%

D. Workload

Sudoku uses the standard encoding with variable $81r + 9c + d$: 729 variables and 11,988 base clauses, identical for every puzzle; predicted givens are added as unit clauses. We generated 1,000 puzzles with unique solutions and 24–40 clues (mean 32.1), in the style of visual Sudoku [6]. Each given cell holds an MNIST *test* image of its digit. The classifier's int8 logits for all puzzles are stored as a binary trace, the input to every interface.

E. SAT Solver

Host conversion. SAT-Accel's host code builds a device memory image from the CNF: paged clause and occurrence stores, 64-byte per-variable metadata, and a decision stack. We ported this conversion to standalone C, since it is exactly the work the serial baseline must time. A golden test compiles SAT-Accel's own unmodified parser next to our port and compares every region byte for byte; all 13 instances match: four Sudoku instances (one of them UNSAT) and nine of SAT-Accel's benchmarks, up to 758 variables and 47,820 clauses.

Solving. SAT-Accel's simulation flow requires Vitis `v++` and XRT, which the server lacks and which need root to install. For P1 a MiniSat [7] backend reads the clauses back out of the SAT-Accel image, as the device's copy-in would, and solves them. A PySAT [8] run serves as the software reference. Later, the real accelerator replaces the backend behind the same interface.

III. Results So Far

Functional pipeline. On all 1,000 puzzles, the C path (trace $\rightarrow$ argmax $\rightarrow$ SAT-Accel image $\rightarrow$ MiniSat) agrees with the PySAT reference on SAT/UNSAT for every puzzle. It returns the identical grid for 992; the other eight have several solutions because of one misread given, and we verified that both grids satisfy every clause. Table III summarizes accuracy.

TABLE III
Visual Sudoku, 1,000 puzzles.

Metric	Value
Given-cell accuracy (int8)	99.26%
Puzzles solved correctly	79.0%
UNSAT from misread givens	19.2%
SAT but wrong	1.8%
Solver work per puzzle (decisions / conflicts)	1.2 / 0.16

Handoff size. Table V gives bytes per puzzle on the native SAT-Accel path. The neural stage produces 1.3 KB of logits that encode 36 givens. SAT-Accel's host flow nonetheless rebuilds a 632 KB image, almost all of it the unchanging base formula, and migrates its full 10.5 MB of allocated buffers on every instance.

Baselines. Both baselines run end to end on all 1,000 puzzles. A host thread performs SAT-Accel's native flow: argmax, image build, copy into separate device buffers, and a doorbell plus completion poll. A device thread decodes its copy and solves it. Every phase is timed with the cycle counter (`rdtsc`; `rdcycle` on RISC-V). The double-buffered baseline uses two buffer sets with explicit ownership states. We run each baseline *faithful* (full buffers cleared and copied, as SAT-Accel's host does) and *lean* (only the bytes in use), so that the serial baseline is not a strawman. All four runs return identical answers that match the PySAT reference. Table IV gives the breakdown.

TABLE IV
Baseline breakdown, median μs per puzzle (host x86, 1,000 puzzles). Share: $T_{\text{HANDOFF}}/(T_{\text{HANDOFF}} + T_{\text{SAT}})$ for serial runs; exposed fraction of wall time for double-buffered runs.

Run	T_{conv}	T_{xfer}	T_{sat}	Share	Wall
Serial, faithful	1112	880	728	73.6%	2809
Serial, lean	696	13	726	50.5%	1450
Double, faithful	1461	1159	764	70.5%	2703
Double, lean	711	16	743	5.1%	801

These pilot numbers support H1 and H2. In the native flow, the handoff is 74% of end-to-end time, yet the argmax that actually consumes the neural output takes under 1 μs; the rest is rebuilding and moving the base formula. Double buffering hides the handoff only when it is shorter than the solve. The faithful handoff (2.6 ms vs. a 0.76 ms solve) stays 70% exposed; the lean one is nearly hidden but still moves 632 KB per puzzle. T_{sync} is below 1 μs with busy polling, whereas SAT-Accel's host polls once per second.

TABLE V
Data per puzzle on the native SAT-Accel path (puzzle 0, 36 givens).

Quantity	Bytes
NVDLA output (int8 logits, 81×16 B)	1,296
SAT-Accel image, bytes in use	632,436
SAT-Accel buffers migrated per instance	10,536,436

Limitations. All times are host x86 cycles; on ESP, conversion runs on Ariane and transfers use DMA over the NoC, so absolute values and ratios will change. The same harness cross-compiles to a static RISC-V binary for that purpose. Solver time in P1 is MiniSat CPU time, not SAT-Accel cycles. NVDLA has not yet executed on hardware: the loadable is compiled, and its outputs are emulated. NVDLA's real output layout in memory is still to be confirmed on ESP. Sudoku with $\geq$24 clues is nearly propagation-only, so the H3 crossover will need harder instances.

IV. Next Steps

Target	Task
Nov 2 (P2)	Run SAT-Accel functionally (its HLS kernels as threads, or XRT on a machine with access); first ESP SoC with Ariane and NVDLA in simulation, running the RISC-V baselines; ReasonLink prototype with literal stream and on-chip FIFO, compared against Table IV.
After P2	Delta transfers and overlap; SAT-Accel on ESP; VCU118 runs when the board is available.

Team contributions. [Who did what for P1.]

APPENDIX A
REPRODUCTION STEPS

Every step taken for P1, in order. Commands run from the repository root unless noted. Steps A1–A4 and C1–C2 need a machine with the ESP platform (our server); B1–B4 run on any Linux or WSL machine.

A. ESP server: one-time setup

A1. Inventory (OS, CAD tools, licenses, RISC-V toolchain):

```
bash env/server_probe.sh
```

A2. ESP, pinned, with only the NVDLA software:

```
git clone https://github.com/sld-columbia/esp.git ~/esp
cd ~/esp && git checkout 2026.1.0
git submodule update --init \
    accelerators/third-party/NV_NVDLA/sw
```

A3. This repository (the server receives code through git):

```
git clone https://github.com/AaronCherian404/\
ReasonLink.git ~/ReasonLink
cd ~/ReasonLink
git submodule update --init third_party/minisat
```

A4. Keep it current before each server step: `git pull`.

B. Local: workload, image, baselines

B1. Environment (venv at `~/venvs/reasonlink`):

```
bash env/setup_wsl.sh
source ~/venvs/reasonlink/bin/activate
```

B2. Classifier and workload (Stage 1):

```
bash workload/fetch_esp_lenet.sh
python workload/nvdla_lenet.py --model esp --check
python workload/train_lenet.py
python workload/dataset.py --num 1000 --seed 0
python workload/reference_solve.py
```

B3. SAT-Accel image and solver (Stage 2):

```
cd handoff && make && make golden && make solvecheck
```

B4. Baselines (Stage 3):

```
cd baselines && make run
```

C. ESP server: builds

C1. NVDLA loadables. The script recompiles ESP's demo network and checks that it matches ESP's shipped loadable (md5 `9831533f`). It then compiles our classifier to `build/nvdla/rl_lenet.nvdla` (md5 `eb4c0813`).

```
ESP_ROOT=~/esp bash workload/nvdla_compile.sh
```

Equivalent manual invocation (as run on the server, inside a directory holding the three model files):

```
NVC=~/esp/accelerators/third-party/NV_NVDLA/\
sw/prebuilt/x86-ubuntu
LD_LIBRARY_PATH=$NVC $NVC/nvdla_compiler \
  --prototxt lenet_mnist.prototxt \
  --caffemodel rl_lenet.caffemodel \
  --calibtable rl_lenet.json \
  --cprecision int8 --configtarget nv_small \
  --quantizationMode per-filter --informat nchw
```

The flags were found by recompiling ESP's model with per-kernel quantization (the default) under each `--informat` (nchw, ncxhwx, nhwc), then with per-filter under nchw and nhwc; only per-filter with nchw reproduces ESP's loadable. Inputs must be in the working directory and passed by bare file name, because `--calibtable` with an absolute path fails.

C2. RISC-V baselines for Ariane (static Linux binary; checked under QEMU locally and built on the server with ESP's RISC-V GCC 9.2; `make riscv` supplies a declarations-only `zlib.h`, which MiniSat's headers include but that toolchain lacks):

```
cd baselines && make riscv
file build/riscv64/rl_baselines
```

REFERENCES

[1] P. Mantovani, D. Giri, G. Di Guglielmo, L. Piccolboni, J. Zuckerman, E. G. Cota, M. Petracca, C. Pilato, and L. P. Carloni, "Agile SoC development with open ESP," in *Proceedings of the 39th International Conference on Computer-Aided Design (ICCAD)*, 2020. [Online]. Available: https://www.esp.cs.columbia.edu

[2] NVIDIA, "NVDLA: NVIDIA deep learning accelerator," http://nvdla.org, 2017.

[3] D. Giri, K.-L. Chiu, G. Eichler, P. Mantovani, N. Chandramoorthy, and L. P. Carloni, "Ariane + NVDLA: Seamless third-party IP integration with ESP," in *Fourth Workshop on Computer Architecture Research with RISC-V (CARRV)*, 2020.

[4] M. Lo, M.-C. F. Chang, and J. Cong, "SAT-Accel: A modern SAT solver on a FPGA," in *Proceedings of the 2025 ACM/SIGDA International Symposium on Field Programmable Gate Arrays*, 2025, pp. 234–246. [Online]. Available: https://github.com/milo168/FPGA25_SAT_Accel

[5] Y. LeCun, L. Bottou, Y. Bengio, and P. Haffner, "Gradient-based learning applied to document recognition," *Proceedings of the IEEE*, vol. 86, no. 11, pp. 2278–2324, 1998.

[6] P.-W. Wang, P. L. Donti, B. Wilder, and J. Z. Kolter, "SATNet: Bridging deep learning and logical reasoning using a differentiable satisfiability solver," in *Proceedings of the 36th International Conference on Machine Learning (ICML)*, 2019.

[7] N. Eén and N. Sörensson, "An extensible SAT-solver," in *Theory and Applications of Satisfiability Testing (SAT)*, ser. LNCS, vol. 2919, 2003, pp. 502–518.

[8] A. Ignatiev, A. Morgado, and J. Marques-Silva, "PySAT: A Python toolkit for prototyping with SAT oracles," in *Theory and Applications of Satisfiability Testing (SAT)*, 2018, pp. 428–437.