

Introduction to Electronic Design Automation

Homework 2

(Problems 6-8)

Student: 吳亞倫
ID: B13901011
Department: 電機工程學系

6 Two-level Logic Minimization

6. (a)

Use variable order $abcde$.

$$G = abce + abde + ab\bar{c}e + \bar{a}b\bar{c}e + \bar{a}\bar{b}\bar{c}\bar{e} + \bar{a}\bar{c}\bar{d}e + bc\bar{d}e + cd\bar{e}$$

$$D = \bar{a}b\bar{d}e + abcd\bar{e} + ac\bar{e}$$

Expanding them into minterms:

$$G = \{0, 1, 2, 4, 9, 11, 12, 13, 20, 25, 27, 28, 29, 31\}$$

$$D = \{9, 13, 20, 22, 28, 29, 30\}$$

Thus, we have the minterms of onset F as:

$$F = G - D = \{0, 1, 2, 4, 11, 12, 25, 27, 31\}$$

Therefore,

$$F \cup D = \{0, 1, 2, 4, 9, 11, 12, 13, 20, 22, 25, 27, 28, 29, 30, 31\}$$

$$\begin{aligned} R &= \{0, 1, \dots, 31\} - (F \cup D) \\ &= \{3, 5, 6, 7, 8, 10, 14, 15, 16, 17, 18, 19, 21, 23, 24, 26\} \end{aligned}$$

Writing them as product terms:

$$\begin{aligned} R &= \bar{a}\bar{b}\bar{c}de + \bar{a}\bar{b}c\bar{d}e + \bar{a}\bar{b}cd\bar{e} + \bar{a}\bar{b}cde + \bar{a}b\bar{c}\bar{d}\bar{e} + \bar{a}b\bar{c}d\bar{e} \\ &\quad + \bar{a}b\bar{c}d\bar{e} + \bar{a}b\bar{c}de + \bar{a}b\bar{c}\bar{d}e + \bar{a}b\bar{c}de + \bar{a}b\bar{c}\bar{d}\bar{e} + \bar{a}b\bar{c}d\bar{e} \\ &\quad + \bar{a}b\bar{c}de + \bar{a}b\bar{c}de + \bar{a}b\bar{c}\bar{d}\bar{e} + \bar{a}b\bar{c}d\bar{e} \end{aligned}$$

6. (b)

First, we apply the Quine–McCluskey tabular method on $F \cup D$ to generate all prime implicants.

Round 1	Round 2	Round 3
$\bar{a}\bar{b}\bar{c}\bar{d}\bar{e} \checkmark$	$\bar{a}\bar{b}\bar{c}\bar{d}$ $\bar{a}\bar{b}\bar{c}\bar{e}$ $\bar{a}\bar{b}\bar{d}\bar{e}$	
$\bar{a}\bar{b}\bar{c}d\bar{e} \checkmark$ $\bar{a}\bar{b}c\bar{d}\bar{e} \checkmark$ $\bar{a}b\bar{c}\bar{d}\bar{e} \checkmark$	$\bar{a}\bar{c}\bar{d}\bar{e}$ $\bar{b}c\bar{d}\bar{e} \checkmark$ $\bar{a}c\bar{d}\bar{e} \checkmark$	
$\bar{a}\bar{b}\bar{c}d\bar{e} \checkmark$ $\bar{a}b\bar{c}\bar{d}\bar{e} \checkmark$ $a\bar{b}\bar{c}\bar{d}\bar{e} \checkmark$	$\bar{a}\bar{b}\bar{c}e \checkmark$ $\bar{a}bde \checkmark$ $\bar{b}\bar{c}\bar{d}e \checkmark$ $\bar{a}bcd \checkmark$ $bc\bar{d}\bar{e} \checkmark$ $\bar{a}b\bar{c}e \checkmark$ $ac\bar{d}\bar{e} \checkmark$	$c\bar{d}\bar{e}$ $b\bar{d}e$ $b\bar{c}e$ bcd $ac\bar{e}$
$\bar{a}\bar{b}\bar{c}de \checkmark$ $\bar{a}b\bar{c}d\bar{e} \checkmark$ $a\bar{b}\bar{c}d\bar{e} \checkmark$ $ab\bar{c}\bar{d}\bar{e} \checkmark$ $abcd\bar{e} \checkmark$	$b\bar{c}de \checkmark$ $bc\bar{d}e \checkmark$ $ac\bar{e} \checkmark$ $ab\bar{c}e \checkmark$ $ab\bar{d}e \checkmark$ $abcd \checkmark$ $abc\bar{e} \checkmark$	abe abc
$ab\bar{c}de \checkmark$ $abc\bar{d}e \checkmark$ $abcd\bar{e} \checkmark$	$abde \checkmark$ $abce \checkmark$ $abcd \checkmark$	
$abcde \checkmark$		

Table 1: Quine–McCluskey tabular method for generating prime implicants

Thus, the prime implicants are

$$\{\bar{a}\bar{b}\bar{c}\bar{d}, \bar{a}\bar{b}\bar{c}\bar{e}, \bar{a}\bar{b}\bar{d}\bar{e}, \bar{a}\bar{c}\bar{d}\bar{e}, c\bar{d}\bar{e}, b\bar{d}e, b\bar{c}e, bcd, ac\bar{e}, abe, abc\}.$$

Next, we use the Column covering of Boolean matrix to find the essential prime implicants. The Boolean matrix is as follows:

	$\bar{a}\bar{b}\bar{c}\bar{d}$	$\bar{a}\bar{b}\bar{c}\bar{e}$	$\bar{a}\bar{b}\bar{d}\bar{e}$	$\bar{a}\bar{c}\bar{d}\bar{e}$	$c\bar{d}\bar{e}$	$b\bar{d}e$	$b\bar{c}e$	bcd	$ac\bar{e}$	abe	abc
$m_0 = \bar{a}\bar{b}\bar{c}\bar{d}\bar{e}$	1	1	1	0	0	0	0	0	0	0	0
$m_1 = \bar{a}\bar{b}\bar{c}d\bar{e}$	1	0	0	1	0	0	0	0	0	0	0
$m_2 = \bar{a}\bar{b}c\bar{d}\bar{e}$	0	1	0	0	0	0	0	0	0	0	0
$m_4 = \bar{a}\bar{b}cd\bar{e}$	0	0	1	0	1	0	0	0	0	0	0
$m_{11} = \bar{a}b\bar{c}d\bar{e}$	0	0	0	0	0	0	1	0	0	0	0
$m_{12} = \bar{a}bcd\bar{e}$	0	0	0	0	1	0	0	1	0	0	0
$m_{25} = ab\bar{c}\bar{d}\bar{e}$	0	0	0	0	0	1	1	0	0	1	0
$m_{27} = ab\bar{c}d\bar{e}$	0	0	0	0	0	0	1	0	0	1	0
$m_{31} = abcde$	0	0	0	0	0	0	0	0	0	1	1

Table 2: Boolean matrix

6. (c)

Rows m_2 and m_{11} each have only one 1, so $\bar{a}\bar{b}\bar{c}\bar{e}$ and $b\bar{c}e$ are essential prime implicants. So we remove the rows m_2, m_{11} and the columns of $\bar{a}\bar{b}\bar{c}\bar{e}$ and $b\bar{c}e$. We also remove the rows that have 1 in the removed columns, which are m_0, m_{25}, m_{27} . After removing these rows, the columns $a\bar{c}\bar{e}$ and $b\bar{d}e$ contain only zeros, so we remove them as well. The resulting Boolean matrix is as follows:

	$\bar{a}\bar{b}\bar{c}\bar{d}$	$\bar{a}\bar{b}\bar{d}\bar{e}$	$\bar{a}\bar{c}\bar{d}e$	$c\bar{d}\bar{e}$	$b\bar{c}\bar{d}$	abe	abc
$m_1 = \bar{a}\bar{b}\bar{c}\bar{d}e$	1	0	1	0	0	0	0
$m_4 = \bar{a}\bar{b}\bar{c}\bar{d}\bar{e}$	0	1	0	1	0	0	0
$m_{12} = \bar{a}b\bar{c}\bar{d}\bar{e}$	0	0	0	1	1	0	0
$m_{31} = abcde$	0	0	0	0	0	1	1

Table 3: Reduced Boolean matrix

6. (d)

Column $c\bar{d}\bar{e}$ covers rows m_4 and m_{12} . It dominates both columns $\bar{a}\bar{b}\bar{d}\bar{e}$ and $b\bar{c}\bar{d}$, so we remove these two dominated columns. The resulting Boolean matrix is as follows:

	$\bar{a}\bar{b}\bar{c}\bar{d}$	$\bar{a}\bar{c}\bar{d}e$	$c\bar{d}\bar{e}$	abe	abc
$m_1 = \bar{a}\bar{b}\bar{c}\bar{d}e$	1	1	0	0	0
$m_4 = \bar{a}\bar{b}\bar{c}\bar{d}\bar{e}$	0	0	1	0	0
$m_{12} = \bar{a}b\bar{c}\bar{d}\bar{e}$	0	0	1	0	0
$m_{31} = abcde$	0	0	0	1	1

Table 4: Reduced Boolean matrix

Since rows m_4 and m_{12} have only one 1, the prime implicant $c\bar{d}\bar{e}$ is an induced essential prime implicant. Therefore, we select it and remove rows m_4 and m_{12} .

	$\bar{a}\bar{b}\bar{c}\bar{d}$	$\bar{a}\bar{c}\bar{d}e$	abe	abc
$m_1 = \bar{a}\bar{b}\bar{c}\bar{d}e$	1	1	0	0
$m_{31} = abcde$	0	0	1	1

Table 5: Reduced Boolean matrix

6. (e)

After the reductions in (d), there is no cyclic core to solve, since the remaining matrix is decomposed into two independent single-row choices:

$$m_1 : \{\bar{a}\bar{b}\bar{c}\bar{d}, \bar{a}\bar{c}\bar{d}e\}$$

$$m_{31} : \{abe, abc\}$$

Thus, the independent set heuristic is not applicable. We only need to choose one prime implicant from each set. For example, we choose

$$\bar{a}\bar{b}\bar{c}\bar{d} \quad \text{and} \quad abe.$$

Therefore, the selected prime implicants are

$$\bar{a}\bar{b}\bar{c}\bar{e}, \quad b\bar{c}e, \quad c\bar{d}\bar{e}, \quad \bar{a}\bar{b}\bar{c}\bar{d}, \quad abe.$$

6. (f)

There are four minimum covers with 5 prime implicants:

$$G_1^* = \bar{a}\bar{b}\bar{c}\bar{e} + b\bar{c}e + c\bar{d}\bar{e} + \bar{a}\bar{b}\bar{c}\bar{d} + abe.$$

$$G_2^* = \bar{a}\bar{b}\bar{c}\bar{e} + b\bar{c}e + c\bar{d}\bar{e} + \bar{a}\bar{c}\bar{d}e + abe.$$

$$G_3^* = \bar{a}\bar{b}\bar{c}\bar{e} + b\bar{c}e + c\bar{d}\bar{e} + \bar{a}\bar{b}\bar{c}\bar{d} + abc.$$

$$G_4^* = \bar{a}\bar{b}\bar{c}\bar{e} + b\bar{c}e + c\bar{d}\bar{e} + \bar{a}\bar{c}\bar{d}e + abc.$$

7 Static Timing Analysis**7. (a)**

In this part, we construct the circuit as a DAG, where each node $v \in V$ represents a gate and each edge $e \in E \subseteq V \times V$ represents a connection between gates. Let $R(v)$ denote the required time at the input of node v , $A(v)$ denote the arrival time at the output of node v , and $d_{u,v}$ denotes the delay from node u 's output to node v 's output. Also, we define the slack of node v as

$$S(v) = R(v) - A(v).$$

Suppose there is a node v such that

$$S(v) = R(v) - A(v) \leq c$$

We want to show that there exists a path satisfying every node on the path has slack at most c from some primary input to v and from v to some primary output.

1. From some primary input to v

First, if v is a primary input, then we are done. Otherwise, since

$$A(v) = \max_{u:(u,v) \in E} (A(u) + d_{u,v})$$

there exist a node u such that there is an edge from u to v and

$$A(v) = A(u) + d_{u,v}.$$

And since

$$R(u) = \min_{w:(u,w) \in E} (R(w) - d_{u,w}) \leq R(v) - d_{u,v},$$

we have

$$S(u) = R(u) - A(u) \leq R(v) - d_{u,v} - A(u) = R(v) - A(v) = S(v) \leq c.$$

Thus, we can apply the same argument on u and repeat this process until we reach a primary input.

2. From v to some primary output

First, if v is a primary output, then we are done. Otherwise, since

$$R(v) = \min_{w:(v,w) \in E} (R(w) - d_{v,w})$$

there exist a node w such that there is an edge from v to w and

$$R(v) = R(w) - d_{v,w}.$$

And since

$$A(w) = \max_{x:(x,w) \in E} (A(x) + d_{x,w}) \geq A(v) + d_{v,w},$$

we have

$$S(w) = R(w) - A(w) \leq R(v) + d_{v,w} - A(v) - d_{v,w} = R(v) - A(v) = S(v) \leq c.$$

Thus, we can apply the same argument on w and repeat this process until we reach a primary output.

Hence, there exists a path from some primary input to v and from v to some primary output such that the slack of each node on these paths is at most c .

7. (b)

The equivalence DAG of the given circuit is as Figure 1 below. The delay of each gate is labeled on the corresponding node. Arrival time, required time and slack of each node are labeled on the corresponding edge in the format of (a, r, s) , where a is the arrival time, r is the required time and s is the slack. The critical path is highlighted in red.




Figure 1: static timing analysis result

8 Technology Mapping

In this problem, I wrote two versions of the program. The first one is the basic DAGON mapping algorithm. The second one is an improved version, where I allow adding a pair of inverters for each wire in the subject graph and adding a pattern of a wire that matches two inverters with zero cost.

The node numbering I used in my input file is shown in Figure 2.




Figure 2: Node numbering used in `input.txt`

First, for the basic version without improvement, the result is:

Node	Minimum cost	Selected cell
8	2	nand2
9	1	inv
10	5	nand2
11	2	nand2
12	1	inv
13	5	nand2
14	12	nand2
15	2	nand2
16	3	inv
17	15	nand3

Table 6: Optimal cost and selected cell of each subject node

Thus, the final cover without improvement is obtained by tracing back from output node 17:

$\{8 : \text{nand2}, 9 : \text{inv}, 10 : \text{nand2}, 11 : \text{nand2}, 12 : \text{inv}, 13 : \text{nand2}, 14 : \text{nand2}, 17 : \text{nand3}\}$.

The `nand3` at node 17 covers nodes 15, 16, and 17 together. Therefore, the minimum total area is

$$2 + 1 + 2 + 2 + 1 + 2 + 2 + 3 = 15.$$

Next, for the improved version, the output on original nodes is:

Node	Minimum cost	Selected cell
8	2	nand2
9	1	inv
10	5	nand2
11	2	nand2
12	1	inv
13	5	nand2
14	10	nand2
15	2	nand2
16	3	inv
17	12	oai21

Table 7: Improved result on original subject nodes

The minimum total area becomes 12. This is smaller than 15 because the inserted inverter pairs create extra matching choices. In particular, node 17 can be matched by `oai21` in the improved graph, so the final cost is reduced.

However, if we only apply the original DAGON algorithm directly on the given subject graph, the answer is still 15.

The c++ code of both versions and the input/output files are included in the appendix.

Appendix: `dragon.cpp`

cpp

```

1 #include <bits/stdc++.h>
2 using namespace std;
3 #define ll long long
4 #define pb push_back
5 #define endl '\n'
6 #define AI(x) begin(x),end(x)
7
8
9 const int INF = 1e9;
10
11 enum class GateType {
12     PI,
13     INV,
14     NAND,
15     NOR,
16 };
17
18 string toUpper(string s) {
19     for (char &c : s) c = toupper(c);
20     return s;
21 }
22
23 GateType s2gate_type(string s) {
24     s = toUpper(s);
25
26     if (s == "PI" || s == "IN") return GateType::PI;
27     if (s == "INV") return GateType::INV;
28     if (s == "NAND") return GateType::NAND;
29     if (s == "NOR") return GateType::NOR;
30
31     cerr << "Unknown gate type: " << s << endl;
32     exit(1);
33 }
34
35 bool isCommutative(GateType t) {
36     return t == GateType::NAND || t == GateType::NOR;
37 }
38
39 struct node {
40     int id;

```

```

41 GateType type;
42 vector<int> fanin;
43 vector<int> fanout;
44
45 node() {}
46 node(int i, GateType g) : id(i), type(g) {}
47 };
48
49 vector<int> topological_sort(vector<node>& g) {
50     int n = g.size();
51     vector<int> indeg(n), order;
52     queue<int> q;
53
54     for (int i = 0; i < n; i++) {
55         indeg[i] = g[i].fanin.size();
56         if (indeg[i] == 0) q.push(i);
57     }
58
59     while (!q.empty()) {
60         int u = q.front();
61         q.pop();
62
63         order.pb(u);
64
65         for (int v : g[u].fanout) {
66             indeg[v]--;
67             if (indeg[v] == 0) q.push(v);
68         }
69     }
70
71     return order;
72 }
73
74 // 回傳 pattern subtree match 到 subject subtree 後, boundary dp cost 總和
75 // 若不能 match, 回傳 INF
76 int matchCost(int sid, int pid,
77               vector<node>& sg,
78               vector<node>& pg,
79               vector<int>& dp) {
80
81     node& s = sg[sid];
82     node& p = pg[pid];
83
84     if (p.type == GateType::PI) {
85         return dp[sid];
86     }
87
88     if (s.type != p.type) return INF;
89     if (s.fanin.size() != p.fanin.size()) return INF;
90
91     int n = s.fanin.size();
92
93     vector<int> idx(n);
94     iota(idx.begin(), idx.end(), 0);
95
96     int best = INF;
97
98     do {
99         int total = 0;
100         bool ok = true;
101
102         for (int i = 0; i < n; i++) {
103             int s_child = s.fanin[idx[i]];
104             int p_child = p.fanin[i];
105
106             int sub = matchCost(s_child, p_child, sg, pg, dp);
107
108             if (sub >= INF) {
109                 ok = false;
110                 break;
111             }
112
113             total += sub;
114         }
115
116         if (ok) best = min(best, total);
117     } while (isCommutative(s.type) &&
118             next_permutation(idx.begin(), idx.end()));
119
120     return best;
121 }
122 }
123
124 int32_t main() {
125     ios::sync_with_stdio(0); cin.tie(0); cout.tie(0);
126     int ns, ms;
127     cin >> ns >> ms;
128
129     vector<node> sg(ns);
130

```



```

131     for (int i = 0; i < ns; i++) {
132         string t;
133         cin >> t;
134         sg[i] = node(i, s2gate_type(t));
135     }
136
137     for (int i = 0; i < ms; i++) {
138         int a, b;
139         cin >> a >> b;
140
141         sg[a].fanout.pb(b);
142         sg[b].fanin.pb(a);
143     }
144
145     vector<int> subject_order = topological_sort(sg);
146
147     int p;
148     cin >> p;
149
150     vector<vector<node>> patterns(p);
151     vector<int> cost(p);
152     vector<string> name(p);
153     vector<int> root(p);
154
155     for (int i = 0; i < p; i++) {
156         cin >> name[i] >> cost[i];
157
158         int n, m, r;
159         cin >> n >> m >> r;
160
161         root[i] = r;
162         patterns[i].resize(n);
163
164         for (int j = 0; j < n; j++) {
165             string t;
166             cin >> t;
167             patterns[i][j] = node(j, s2gate_type(t));
168         }
169
170         for (int j = 0; j < m; j++) {
171             int a, b;
172             cin >> a >> b;
173
174             patterns[i][a].fanout.pb(b);
175             patterns[i][b].fanin.pb(a);
176         }
177     }
178
179     vector<int> dp(ns, INF);
180     vector<int> choose(ns, -1);
181
182     for (int v : subject_order) {
183         if (sg[v].type == GateType::PI) {
184             dp[v] = 0;
185             continue;
186         }
187
188         for (int i = 0; i < p; i++) {
189             int boundary_cost = matchCost(v, root[i], sg, patterns[i], dp);
190
191             if (boundary_cost >= INF) continue;
192
193             int total_cost = cost[i] + boundary_cost;
194
195             if (total_cost < dp[v]) {
196                 dp[v] = total_cost;
197                 choose[v] = i;
198             }
199         }
200     }
201
202     // 預設所有 fanout empty 的 node 都是 output
203     int ans = 0;
204
205     for (int i = 0; i < ns; i++) {
206         if (sg[i].fanout.empty()) {
207             ans += dp[i];
208         }
209     }
210
211     cout << "Minimum total cost = " << ans << endl;
212
213     for (int i = 0; i < ns; i++) {
214         cout << "node " << i << ": ";
215
216         if (sg[i].fanin.empty()) {
217             cout << "PI, cost = 0" << endl;
218         } else {
219             cout << "cost = " << dp[i];
220

```

```

221         if (choose[i] != -1) {
222             cout << ", cell = " << name[choose[i]];
223         } else {
224             cout << ", cell = NONE";
225         }
226
227         cout << endl;
228     }
229 }
230
231 return 0;
232 }
233

```

Appendix: dagon_improve.cpp

cpp

```

1 // dagon_improve.cpp
2 #include <bits/stdc++.h>
3 using namespace std;
4
5 #define ll long long
6 #define pb push_back
7 #define endl '\n'
8
9 const ll INF = (ll)4e18;
10
11 enum class GateType {
12     PI,
13     INV,
14     NAND,
15     NOR,
16 };
17
18 string toUpper(string s) {
19     for (char &c : s) c = toupper(c);
20     return s;
21 }
22
23 GateType s2gate_type(string s) {
24     s = toUpper(s);
25
26     if (s == "PI" || s == "IN") return GateType::PI;
27     if (s == "INV") return GateType::INV;
28     if (s == "NAND") return GateType::NAND;
29     if (s == "NOR") return GateType::NOR;
30
31     cerr << "Unknown gate type: " << s << endl;
32     exit(1);
33 }
34
35 string gate2str(GateType t) {
36     if (t == GateType::PI) return "PI";
37     if (t == GateType::INV) return "INV";
38     if (t == GateType::NAND) return "NAND";
39     if (t == GateType::NOR) return "NOR";
40     return "?";
41 }
42
43 bool isCommutative(GateType t) {
44     return t == GateType::NAND || t == GateType::NOR;
45 }
46
47 struct Node {
48     int id;
49     GateType type;
50     vector<int> fanin;
51     vector<int> fanout;
52
53     Node() {}
54     Node(int i, GateType g) : id(i), type(g) {}
55 };
56
57 struct Pattern {
58     string name;
59     ll cost;
60     int root;
61     vector<Node> g;
62 };
63
64 void addEdge(vector<Node> &g, int u, int v) {
65     g[u].fanout.pb(v);
66     g[v].fanin.pb(u);
67 }
68
69 vector<int> topological_sort(vector<Node> &g) {
70     int n = (int)g.size();
71     vector<int> indeg(n), order;
72     queue<int> q;

```

```

73
74     for (int i = 0; i < n; i++) {
75         indeg[i] = (int)g[i].fanin.size();
76         if (indeg[i] == 0) q.push(i);
77     }
78
79     while (!q.empty()) {
80         int u = q.front();
81         q.pop();
82
83         order.pb(u);
84
85         for (int v : g[u].fanout) {
86             if (--indeg[v] == 0) q.push(v);
87         }
88     }
89
90     if ((int)order.size() != n) {
91         cerr << "Error: graph is not a DAG." << endl;
92         exit(1);
93     }
94
95     return order;
96 }
97
98 // 對 subject graph 每條原始 edge u -> v 插入兩個 INV :
99 // u -> inv1 -> inv2 -> v
100 void insertInverterPairs(vector<Node> &sg,
101                          const vector<pair<int,int>> &edges,
102                          vector<char> &isInserted) {
103     for (auto &x : sg) {
104         x.fanin.clear();
105         x.fanout.clear();
106     }
107
108     for (auto [u, v] : edges) {
109         int inv1 = (int)sg.size();
110         sg.pb(Node(inv1, GateType::INV));
111         isInserted.pb(true);
112
113         int inv2 = (int)sg.size();
114         sg.pb(Node(inv2, GateType::INV));
115         isInserted.pb(true);
116
117         addEdge(sg, u, inv1);
118         addEdge(sg, inv1, inv2);
119         addEdge(sg, inv2, v);
120     }
121 }
122
123 // 回傳 pattern subtree match 到 subject subtree 後的 boundary dp cost 總和。
124 // 若不能 match, 回傳 INF。
125 ll matchCost(int sid, int pid,
126              vector<Node> &sg,
127              vector<Node> &pg,
128              vector<ll> &dp,
129              vector<char> &isInserted) {
130
131     Node &s = sg[sid];
132     Node &pnode = pg[pid];
133
134     // pattern 的 PI 是 boundary, 可以停在任何 subject node
135     if (pnode.type == GateType::PI) {
136         return dp[sid];
137     }
138
139     ll bestSkip = INF;
140
141     // 嘗試跳過 virtual INV pair:
142     // u -> inv1 -> inv2
143     // sid = inv2 時, 可以直接嘗試 match u
144     if (isInserted[sid] &&
145         s.type == GateType::INV &&
146         s.fanin.size() == 1) {
147
148         int inv1 = s.fanin[0];
149
150         if (isInserted[inv1] &&
151             sg[inv1].type == GateType::INV &&
152             sg[inv1].fanin.size() == 1) {
153
154             int u = sg[inv1].fanin[0];
155
156             bestSkip = matchCost(u, pid, sg, pg, dp, isInserted);
157         }
158     }
159
160     if (s.type != pnode.type) return bestSkip;
161     if (s.fanin.size() != pnode.fanin.size()) return bestSkip;
162

```

```

163     int n = (int)s.fanin.size();
164
165     vector<int> idx(n);
166     iota(idx.begin(), idx.end(), 0);
167
168     ll best = INF;
169
170     do {
171         ll total = 0;
172         bool ok = true;
173
174         for (int i = 0; i < n; i++) {
175             int s_child = s.fanin[idx[i]];
176             int p_child = pnode.fanin[i];
177
178             ll sub = matchCost(s_child, p_child, sg, pg, dp, isInserted);
179
180             if (sub >= INF) {
181                 ok = false;
182                 break;
183             }
184
185             total += sub;
186
187             if (total >= INF) {
188                 ok = false;
189                 break;
190             }
191         }
192
193         if (ok) best = min(best, total);
194     } while (isCommutative(s.type) &&
195             next_permutation(idx.begin(), idx.end()));
196
197     return min(best, bestSkip);
198 }
199
200 int32_t main() {
201     ios::sync_with_stdio(0); cin.tie(0); cout.tie(0);
202     int ns, ms;
203     cin >> ns >> ms;
204
205     vector<Node> sg(ns);
206
207     for (int i = 0; i < ns; i++) {
208         string t;
209         cin >> t;
210         sg[i] = Node(i, s2gate_type(t));
211     }
212
213     vector<pair<int,int>> original_edges;
214
215     for (int i = 0; i < ms; i++) {
216         int a, b;
217         cin >> a >> b;
218         original_edges.pb({a, b});
219         addEdge(sg, a, b);
220     }
221
222     // 記錄原始 output, 因為後面會清除並重建 edge
223     vector<int> original_outputs;
224     for (int i = 0; i < ns; i++) {
225         if (sg[i].fanout.empty()) original_outputs.pb(i);
226     }
227
228     // improve DAGON: 每條 wire 插入兩個 INV
229     vector<char> isInserted(ns, false);
230     insertInverterPairs(sg, original_edges, isInserted);
231
232     int p;
233     cin >> p;
234
235     vector<Pattern> patterns;
236
237     for (int i = 0; i < p; i++) {
238         Pattern pat;
239         cin >> pat.name >> pat.cost;
240
241         int n, m, r;
242         cin >> n >> m >> r;
243
244         pat.root = r;
245         pat.g.resize(n);
246
247         for (int j = 0; j < n; j++) {
248             string t;
249             cin >> t;
250             pat.g[j] = Node(j, s2gate_type(t));
251         }
252     }

```

```

253     for (int j = 0; j < m; j++) {
254         int a, b;
255         cin >> a >> b;
256         addEdge(pat.g, a, b);
257     }
258
259     patterns.pb(pat);
260 }
261
262 vector<int> order = topological_sort(sg);
263
264 int nsg = (int)sg.size();
265 vector<ll> dp(nsg, INF);
266 vector<int> choose(nsg, -1);
267
268 for (int v : order) {
269     if (sg[v].type == GateType::PI) {
270         dp[v] = 0;
271         continue;
272     }
273
274     for (int i = 0; i < (int)patterns.size(); i++) {
275         ll boundary_cost = matchCost(v, patterns[i].root, sg, patterns[i].g, dp, isInserted);
276
277         if (boundary_cost >= INF) continue;
278
279         ll total_cost = patterns[i].cost + boundary_cost;
280
281         if (total_cost < dp[v]) {
282             dp[v] = total_cost;
283             choose[v] = i;
284         }
285     }
286 }
287
288 ll ans = 0;
289 for (int out : original_outputs) {
290     ans += dp[out];
291 }
292
293 cout << "Minimum total cost = " << ans << endl;
294
295 cout << endl;
296 cout << "[Original nodes]" << endl;
297 for (int i = 0; i < ns; i++) {
298     cout << "node " << i << " (" << gate2str(sg[i].type) << "): ";
299
300     if (sg[i].type == GateType::PI) {
301         cout << "PI, cost = 0";
302     } else {
303         cout << "cost = " << dp[i];
304
305         if (choose[i] != -1) {
306             cout << ", cell = " << patterns[choose[i]].name;
307         } else {
308             cout << ", cell = NONE";
309         }
310     }
311 }
312
313 bool is_output = false;
314 for (int out : original_outputs) {
315     if (out == i) is_output = true;
316 }
317 if (is_output) cout << " [OUTPUT]";
318
319 cout << endl;
320 }
321
322 cout << endl;
323 cout << "[Inserted inverter-pair nodes]" << endl;
324
325 for (int i = ns; i < nsg; i++) {
326     cout << "node " << i << " (" << gate2str(sg[i].type) << "): ";
327     cout << "cost = " << dp[i];
328
329     if (choose[i] != -1) {
330         cout << ", cell = " << patterns[choose[i]].name;
331     } else {
332         cout << ", cell = NONE";
333     }
334
335     cout << endl;
336 }
337
338 return 0;
339 }
340

```

Appendix: input.txt

txt

```

1 18 17
2 PI PI PI PI PI PI PI PI NAND INV NAND INV NAND NAND INV NAND
3 0 8
4 1 8
5 2 9
6 8 10
7 9 10
8 3 11
9 4 11
10 5 12
11 11 13
12 12 13
13 10 14
14 13 14
15 6 15
16 7 15
17 15 16
18 14 17
19 16 17
20 10
21 inv 1
22 2 1 1
23 PI INV
24 0 1
25 buf 0
26 3 2 2
27 PI INV INV
28 0 1
29 1 2
30 nand2 2
31 3 2 2
32 PI PI NAND
33 0 2
34 1 2
35 and2 3
36 4 3 3
37 PI PI NAND INV
38 0 2
39 1 2
40 2 3
41 nand3 3
42 6 5 5
43 PI PI PI NAND INV NAND
44 0 3
45 1 3
46 3 4
47 4 5
48 2 5
49 or2 4
50 5 4 4
51 PI PI INV INV NAND
52 0 2
53 1 3
54 2 4
55 3 4
56 aoi21 3
57 7 6 6
58 PI PI PI NAND INV NAND INV
59 0 3
60 1 3
61 2 4
62 3 5
63 4 5
64 5 6
65 oai21 3
66 7 6 6
67 PI PI PI INV INV NAND NAND
68 0 3
69 1 4
70 3 5
71 4 5
72 5 6
73 2 6
74 aoi22 4
75 8 7 7
76 PI PI PI PI NAND NAND NAND INV
77 0 4
78 1 4
79 2 5
80 3 5
81 4 6
82 5 6
83 6 7
84 nand4 4
85 9 8 8
86 PI PI PI PI NAND INV NAND INV NAND
87 0 4
88 1 4
89 4 5
90 5 6
91 2 6
92 6 7
93 7 8
94 3 8

```

Appendix: output.txt

txt

```

1 Minimum total cost = 15
2 node 0: PI, cost = 0

```

```

3 node 1: PI, cost = 0
4 node 2: PI, cost = 0
5 node 3: PI, cost = 0
6 node 4: PI, cost = 0
7 node 5: PI, cost = 0
8 node 6: PI, cost = 0
9 node 7: PI, cost = 0
10 node 8: cost = 2, cell = nand2
11 node 9: cost = 1, cell = inv
12 node 10: cost = 5, cell = nand2
13 node 11: cost = 2, cell = nand2
14 node 12: cost = 1, cell = inv
15 node 13: cost = 5, cell = nand2
16 node 14: cost = 12, cell = nand2
17 node 15: cost = 2, cell = nand2
18 node 16: cost = 3, cell = inv
19 node 17: cost = 15, cell = nand3
20

```

Appendix: output_improve.txt

txt

```

1 Minimum total cost = 12
2
3 [Original nodes]
4 node 0 (PI): PI, cost = 0
5 node 1 (PI): PI, cost = 0
6 node 2 (PI): PI, cost = 0
7 node 3 (PI): PI, cost = 0
8 node 4 (PI): PI, cost = 0
9 node 5 (PI): PI, cost = 0
10 node 6 (PI): PI, cost = 0
11 node 7 (PI): PI, cost = 0
12 node 8 (NAND): cost = 2, cell = nand2
13 node 9 (INV): cost = 1, cell = inv
14 node 10 (NAND): cost = 5, cell = nand2
15 node 11 (NAND): cost = 2, cell = nand2
16 node 12 (INV): cost = 1, cell = inv
17 node 13 (NAND): cost = 5, cell = nand2
18 node 14 (NAND): cost = 10, cell = nand2
19 node 15 (NAND): cost = 2, cell = nand2
20 node 16 (INV): cost = 3, cell = inv
21 node 17 (NAND): cost = 12, cell = oai21 [OUTPUT]
22
23 [Inserted inverter-pair nodes]
24 node 18 (INV): cost = 1, cell = inv
25 node 19 (INV): cost = 0, cell = buf
26 node 20 (INV): cost = 1, cell = inv
27 node 21 (INV): cost = 0, cell = buf
28 node 22 (INV): cost = 1, cell = inv
29 node 23 (INV): cost = 0, cell = buf
30 node 24 (INV): cost = 3, cell = inv
31 node 25 (INV): cost = 2, cell = buf
32 node 26 (INV): cost = 0, cell = buf
33 node 27 (INV): cost = 1, cell = inv
34 node 28 (INV): cost = 1, cell = inv
35 node 29 (INV): cost = 0, cell = buf
36 node 30 (INV): cost = 1, cell = inv
37 node 31 (INV): cost = 0, cell = buf
38 node 32 (INV): cost = 1, cell = inv
39 node 33 (INV): cost = 0, cell = buf
40 node 34 (INV): cost = 3, cell = inv
41 node 35 (INV): cost = 2, cell = buf
42 node 36 (INV): cost = 0, cell = buf
43 node 37 (INV): cost = 1, cell = inv
44 node 38 (INV): cost = 3, cell = aoi21
45 node 39 (INV): cost = 4, cell = inv
46 node 40 (INV): cost = 3, cell = aoi21
47 node 41 (INV): cost = 4, cell = inv
48 node 42 (INV): cost = 1, cell = inv
49 node 43 (INV): cost = 0, cell = buf
50 node 44 (INV): cost = 1, cell = inv
51 node 45 (INV): cost = 0, cell = buf
52 node 46 (INV): cost = 3, cell = inv
53 node 47 (INV): cost = 2, cell = buf
54 node 48 (INV): cost = 9, cell = aoi21
55 node 49 (INV): cost = 10, cell = inv
56 node 50 (INV): cost = 2, cell = buf
57 node 51 (INV): cost = 3, cell = inv
58

```