CDP & LLDP Questions

8 questions | Original English questions and source answers

Question 1

Refer to the exhibit. Which command provides this output?

```
Capability Codes: R - Router, T - Trans Bridge, B - Source Route Bridge
 S - Switch, H - Host, I - IGMP, r - Repeater, P - Phone,
 D - Remote, C - CVTA, M - Two-port Mac Relay
Device ID  Local Intrfce  Holdtme  Capability  Platform  Port ID
10.1.1.2   Gig 37/3       176      R I         CPT 600   Gig 36/41
10.1.1.2   Gig 37/1       174      R I         CPT 600   Gig 36/43
10.1.1.2   Gig 36/41      134      R I         CPT 600   Gig 37/3
10.1.1.2   Gig 36/43      134      R I         CPT 600   Gig 37/1
10.1.1.2   Ten 3/2        132      R I         CPT 600   Ten 4/2
10.1.1.2   Ten 4/2        174      R I         CPT 600   Ten 3/2
```

Options

A. show ip route

B. show ip interface

C. show interface

D. show cdp neighbor

Answer

D. show cdp neighbor

Source: CCNA 200-301 Questions.html | Question 1

Question 2

An engineer needs to configure LLDP to send the port description time length value (TLV). What command sequence must be implemented?

Options

A. switch#lldp port-description

B. switch(config)#lldp port-description

C. switch(config)#interface gi1/0/1
switch(config-if)#lldp port-description

D. switch#interface gi1/0/1
switch(config-if)#lldp port-description

Answer

B. switch(config)#lldp port-description

Source explanation

Use the switch(config)#lldp port-description option to specify the port description TLV messages.

Source: CCNA 200-301 Questions.html | Question 2

Question 3

A network engineer must create a diagram of a multivendor network. Which command must be configured on the Cisco devices so that the topology of the network can be mapped?

Options

A. `Device(Config)#lldp run`

B. `Device(Config)#cdp run`

C. `Device(Config-if)#cdp enable`

D. `Device(Config)#flow-sampler-map topology`

Answer

A. Device(Config)#lldp run

Source: CCNA 200-301 Questions.html | Question 3

Question 4

In a CDP environment, what happens when the CDP interface on an adjacent device is configured without an IP address?

Options

A. CDP operates normally, but it cannot provide any information for that neighbor.

B. CDP operates normally, but it cannot provide IP address information for that neighbor.

C. CDP uses the IP address of another interface for that neighbor.

D. CDP becomes inoperable on that neighbor.

Answer

C. CDP uses the IP address of another interface for that neighbor.

Source explanation

If a neighbor has no IP address on an interface enabled with Cisco Discovery Protocol, the IP address of another interface will be updated as IP address for the non-IP address interface.

Reference: https://www.cisco.com/c/en/us/td/docs/ios-xml/ios/cdp/configuration/15-mt/cdp-15-mt-book/nm-cdp-discover.html

Source: CCNA 200-301 Questions.html | Question 4

Question 5

How can the Cisco Discovery Protocol be used?

Options

A. to allow a switch to discover the devices that are connected to its ports

B. to determine the hardware platform of the device

C. to determine the IP addresses of connected Cisco devices

D. all of the above

Answer

D. all of the above

Source: CCNA 200-301 Questions.html | Question 5

Question 6

Which command is used to specify the delay time in seconds for LLDP to initialize on any interface?

Options

A. lldp timer

B. lldp holdtime

C. lldp reinit

D. lldp tlv-select

Answer

C. lldp reinit

Source explanation

+ lldp holdtime seconds: Specify the amount of time a receiving device should hold the information from your device before discarding it
+ lldp reinit delay: Specify the delay time in seconds for LLDP to initialize on an interface
+ lldp timer rate: Set the sending frequency of LLDP updates in seconds

Reference: https://www.cisco.com/c/en/us/td/docs/switches/lan/catalyst3560/software/release/12-2_55_se/configuration/guide/3560_scg/swlldp.html

Source: CCNA 200-301 Questions.html | Question 6

Question 7

Which command should you enter to configure an LLDP delay time of 5 seconds?

Options

A. lldp reinit 5

B. lldp reinit 5000

C. lldp holdtime 5

D. lldp timer 5000

Answer

A. lldp reinit 5

Source explanation

+ lldp holdtime seconds: Specify the amount of time a receiving device should hold the information from your device before discarding it
+ lldp reinit delay: Specify the delay time in seconds for LLDP to initialize on an interface
+ lldp timer rate: Set the sending frequency of LLDP updates in seconds

Reference: https://www.cisco.com/c/en/us/td/docs/switches/lan/catalyst3560/software/release/12-2_55_se/configuration/guide/3560_scg/swlldp.html

Source: CCNA 200-301 Questions.html | Question 7

Question 8

Which command is used to enable LLDP globally on a Cisco IOS ISR?

Options

A. lldp run

B. lldp enable

C. lldp transmit

D. cdp run

E. cdp enable

Answer

A. lldp run

Source explanation

Link Layer Discovery Protocol (LLDP) is a industry standard protocol that allows devices to advertise, and discover connected devices, and there capabilities (same as CDP of Cisco). To enable it on Cisco devices, we have to use this command under global configuration mode:

Switch(config)# lldp run

Source: CCNA 200-301 Questions.html | Question 8