NTP Questions

3 questions | Original English questions and source answers

Question 1

Which command should you enter to configure a device as an NTP server?

Options

A. ntp server

B. ntp master

C. ntp authenticate

D. ntp peer

Answer

B. ntp master

Source explanation

To configure a Cisco device as an Authoritative NTP Server, use the ntp master [stratum] command.
To configure a Cisco device as a NTP client, use the command ntp server <IP address>. For example: Router(config)#ntp server 192.168.1.1. This command will instruct the router to query 192.168.1.1 for the time.

Source: CCNA Training » NTP Quiz.pdf | Question 1

Question 2

Which two tasks must be performed to configure NTP to a trusted server in client mode on a single network device? (Choose two)

Options

A. Disable NTP broadcasts

B. Enable NTP authentication

C. Set the NTP server private key

D. Specify the IP address of the NTP server

E. Verify the time zone

Answer

B. Enable NTP authentication

D. Specify the IP address of the NTP server

Source explanation

To configure authentication, perform this task in privileged mode:
Step 1: Configure an authentication key pair for NTP and specify whether the key will be trusted or untrusted.
Step 2: Set the IP address of the NTP server and the public key.
Step 3: Enable NTP client mode.
Step 4: Enable NTP authentication.
Step 5: Verify the NTP configuration.
Reference: https://www.cisco.com/c/en/us/td/docs/switches/lan/catalyst4000/8-2glx/configuration/guide/ntp.html
Note: answer 'Enable NTP authentication' trusted NTP server may or may not require a secret key so it is not a “must” in this question.

Source: CCNA Training » NTP Quiz.pdf | Question 2

Question 3

Which two pieces of information can you determine from the output of the show ntp status command? (Choose two)

Options

A. whether the NTP peer is statically configured

B. whether the clock is synchronized

C. the NTP version number of the peer

D. the IP address of the peer to which the clock is synchronized

E. the configured NTP servers

Answer

B. whether the clock is synchronized

D. the IP address of the peer to which the clock is synchronized

Source explanation

Below is the output of the “show ntp status” command. From this output we learn that R1 has a stratum of 10 and it is getting clock from 10.1.2.1.
R1#show ntp status
Clock is synchronized, stratum 10, reference is 10.1.2.1
nominal freq is 250.0000 Hz, actual freq is 249.9987 Hz, precision is 2**18
reference time is D5E492E9.98ACB4CF (13:00:25.596 CST Wed Sep 18 2013)
clock offset is 15.4356 msec, root delay is 52.17 msec
root dispersion is 67.61 msec, peer dispersion is 28.12 msec

Source: CCNA Training » NTP Quiz.pdf | Question 3