

GRIFOLS Diagnostic Grifols, S.A.	Reference:	REGD-0000806	Version:	4.0, CURRENT
	Status:	Effective	Effective Date:	17-Jun-2011
Title:	SM DG57-DG517. PCA robot 4 axis control current limits adjustment.			Page 2 of 4

DG-57 / DG-517 Service Manual

PCA ROBOT 4 AXIS CONTROL CURRENT LIMITS ADJUSTMENT

Procedure description
This procedure describes how adjust the electronics values of PCA Robot-4 Axis Control. <i>Note: Document REGD-0000806_v4 replaces document REGD-0000806_v3.</i>

GRIFOLS Diagnostic Grifols, S.A.	Reference:	REGD-0000806	Version:	4.0, CURRENT
	Status:	Effective	Effective Date:	17-Jun-2011
Title:	SM DG57-DG517. PCA robot 4 axis control current limits adjustment.			Page 3 of 4

EQUIPMENT

1. Multimeter.




NOTE:

Ground in all measurements is in TP6 (see Picture 1).

SET UP

1. Turn instrument off
2. Open the rear panel
3. Turn instrument on



CAUTION!

Short-circuit between any powered part and ground, may damage the instrument.

PROCEDURE

Process	Expected Results
Adjusting Probe axis current limit 1 Measure the voltage in TP14 with the multimeter. (see Picture 1) 2 If required, adjust P1 until the measured value reaches expected result. (see Picture 1)	$240 \pm 20 \text{ mV}$ $240 \pm 20 \text{ mV}$
Picture 1	

GRIFOLS Diagnostic Grifols, S.A.	Reference:	REGD-0000806	Version:	4.0, CURRENT
	Status:	Effective	Effective Date:	17-Jun-2011
Title:	SM DG57-DG517. PCA robot 4 axis control current limits adjustment.			Page 4 of 4

Process	Expected Results
Adjusting Gripper axis current limit 3 Measure the voltage in TP21 with the multimeter (see Picture 1). 4 If required, adjust P2 (see Picture 1) until the measured value reaches expected result.	240 ± 20 mV 240 ± 20 mV
Adjusting X axis current limit 5 Measure the voltage in TP35 (see Picture 1) with the multimeter. 6 If required, adjust P4 (see Picture 1) until the measured value reaches expected result.	600 ± 20 mV 600 ± 20 mV
Adjusting Y axis current limit 7 Measure the voltage in TP28 (see Picture 1) with the multimeter. 8 If required, adjust P3 (see Picture 1) until the measured value reaches expected result.	600 ± 20 mV 600 ± 20 mV

DOCUMENT CHANGE HISTORY

Document change history			
Version	Date	Change	Rationale
3.0	2005/05/09	Document REGD-0000806_v3 replaces document 57034V0M001.	Document reference changed.
3.0	2005/05/09	Process corrected.	Potentiometer and Test Point for X and Y current limits were exchanged.
4.0	See document header.	Added previous version 'data', 'change' and 'rationale' inside document change history section.	Update change history for previous document history modification.
4.0	See document header.	Document REGD-0000806_v4 replaces document REGD-0000806_v3.	Document version changed.
4.0	See document header.	Document title.	Commercial reference substituted by project reference.
4.0	See document header.	Document header.	Increase information to easy document search.