

myCobot 280 URDF Joint Specifications

```
<joint name="link1_to_link2" type="revolute">
  <axis xyz="0 0 1"/>
  <limit effort="56.0" lower="-2.879793" upper="2.879793" velocity="2.792527"/>
  <parent link="link1"/>
  <child link="link2"/>
  <origin rpy="0 0 1.5707963267948966" xyz="0 0 0.13156"/>
  <dynamics damping="0.0" friction="0.0"/>
--
<joint name="link2_to_link3" type="revolute">
  <axis xyz="0 0 1"/>
  <limit effort="56.0" lower="-2.879793" upper="2.879793" velocity="2.792527"/>
  <parent link="link2"/>
  <child link="link3"/>
  <origin rpy="0 1.5707963267948966 -1.5707963267948966" xyz="0 0 -0.001"/>
  <dynamics damping="0.0" friction="0.0"/>
--
<joint name="link3_to_link4" type="revolute">
  <axis xyz="0 0 1"/>
  <limit effort="56.0" lower="-2.879793" upper="2.879793" velocity="2.792527"/>
  <parent link="link3"/>
  <child link="link4"/>
  <origin rpy="0 0 0" xyz="-0.1104 0 0"/>
  <dynamics damping="0.0" friction="0.0"/>
--
<joint name="link4_to_link5" type="revolute">
  <axis xyz="0 0 1"/>
  <limit effort="56.0" lower="-2.879793" upper="2.879793" velocity="2.792527"/>
  <parent link="link4"/>
  <child link="link5"/>
  <origin rpy="0 0 -1.5707963267948966" xyz="-0.096 0 0.06062"/>
  <dynamics damping="0.0" friction="0.0"/>
--
<joint name="link5_to_link6" type="revolute">
  <axis xyz="0 0 1"/>
  <limit effort="56.0" lower="-2.879793" upper="2.879793" velocity="2.792527"/>
  <parent link="link5"/>
  <child link="link6"/>
  <origin rpy="1.5707963267948966 -1.5707963267948966 0" xyz="0 -0.07318 0"/>
  <dynamics damping="0.0" friction="0.0"/>
--
<joint name="link6_to_link6_flange" type="revolute">
  <axis xyz="0 0 1"/>
  <limit effort="56.0" lower="-3.05" upper="3.05" velocity="2.792527"/>
  <parent link="link6"/>
  <child link="link6_flange"/>
  <origin rpy="-1.5707963267948966 0 0" xyz="0 0.0456 0"/>
  <dynamics damping="0.0" friction="0.0"/>
--
<joint name="link6_flange_to_gripper_base" type="fixed">
  <parent link="link6_flange"/>
  <child link="gripper_base"/>
  <origin rpy="1.579 0 0" xyz="0 0 0.034"/>
</joint>
<link name="gripper_left1">
  <inertial>
--
<joint name="link1_to_link2">
  <command_interface name="position">
    <param name="min">-2.879793</param>
    <param name="max">2.879793</param>
  </command_interface>
  <state_interface name="position"/>
</joint>
<joint name="link2_to_link3">
  <command_interface name="position">
    <param name="min">-2.879793</param>
    <param name="max">2.879793</param>
  </command_interface>
```

myCobot 280 URDF Joint Specifications

```
<state_interface name="position"/>
</joint>
<joint name="link3_to_link4">
  <command_interface name="position">
    <param name="min">-2.879793</param>
    <param name="max">2.879793</param>
  </command_interface>
  <state_interface name="position"/>
</joint>
<joint name="link4_to_link5">
  <command_interface name="position">
    <param name="min">-2.879793</param>
    <param name="max">2.879793</param>
  </command_interface>
  <state_interface name="position"/>
</joint>
<joint name="link5_to_link6">
  <command_interface name="position">
    <param name="min">-2.879793</param>
    <param name="max">2.879793</param>
  </command_interface>
  <state_interface name="position"/>
</joint>
<joint name="link6_to_link6_flange">
  <command_interface name="position">
    <param name="min">-3.05</param>
    <param name="max">3.05</param>
  </command_interface>
  <state_interface name="position"/>
</joint>
```