

PhysicsDiff-PCB: Physics Guided Conditional Diffusion for Crosstalk Aware PCB Layout Generation

Fast inverse synthesis of electrically compliant high-speed PCB trace layouts using physics-aware generative AI

Abishek Jayathilaka* · Ushan Kamesh* · Chanaka Madhuranga* · Sulitha Nulaksha* · Ramishka Thennakoon*

Department of Electrical and Information Engineering, Faculty of Engineering, University of Ruhuna

1 Motivation & Problem

At data rates exceeding 10 Gbps, **characteristic impedance (Z_0)** and **near-end crosstalk (NEXT)** become first-order signal-integrity constraints, requiring precise control of PCB trace geometry.

The core challenge: Inverse design synthesising a geometrically valid copper layout that satisfies target electrical specifications, without iterative field-solver feedback. Traditional design instead relies on manual geometry edits closed through repeated field-solver checks slow and computationally expensive.

Existing approaches fall short:

EDA tools enforce design rules reactively, not generatively

ML surrogates predict electrical response from geometry (forward-only) they don't generate layouts Optimisation and diffusion methods generate single or unconstrained layouts, without in-loop electromagnetic feedback

Our goal:

Generate diverse, structurally valid PCB layouts directly from electromagnetic specifications, while maintaining electrical compliance.

2 Proposed Approach

PhysicsDiff-PCB combines: Conditional DDPM, Cross-Attention Conditioning, a Physics Surrogate, and Fabrication-Aware Losses. A conditional U-Net receives an 8-dimensional electromagnetic specification vector and generates a 128×128 binary copper-mask layout via DDIM sampling - learning a direct mapping from electromagnetic specification to copper mask layout.

Physics proxies used for training supervision

Characteristic Impedance

$$Z_0 = [87 / \sqrt{(\epsilon_r + 1.41)}] \cdot \ln[5.98h / (0.8w + t)]$$

The Wadell microstrip approximation used to estimate the characteristic impedance (Z_0) of a microstrip trace based on substrate permittivity (ϵ_r), trace width (w), thickness (t), and height (h).

Near-End Crosstalk

$$V_{NEXT} = e^{(-1.6 \cdot s/h)} \cdot (L/20) \cdot (\epsilon_r/4.5) \cdot (0.35/w)$$


A coupled-line proxy model estimating near-end crosstalk voltage (V_{NEXT}) as a function of trace separation (s), trace length (L), substrate permittivity (ϵ_r), and trace width (w).

Composite training objective


$$L_{total} = L_{diff} + L_{mask} + L_{physics} + L_{smooth}$$

- Diffusion loss → accurate denoising
- Dice + Focal loss → trace-mask quality and boundary sharpness
- Huber physics losses → impedance and crosstalk compliance
- Total variation → smooth, continuous, fabricable traces

3 System Architecture



Conditional DDPM U-Net predicts noise $\epsilon_\theta(x_t, t, c)$ from an 8-D electromagnetic specification vector, with cross-attention conditioning at the U-Net bottleneck. A frozen PhysicsPredictor (PhysicsSurrogateV2) supplies differentiable impedance ($\hat{Z}_0$) and crosstalk ($\hat{V}_{NEXT}$) feedback via Huber losses during training — without invoking a full-wave solver. At inference, DDIM ($S = 50, \eta = 0$) generates electrically compliant copper masks in 50 steps.



Left: compliant sample, satisfying surrogate-predicted impedance and crosstalk limits. Right: non-compliant sample visually trace-like but fails the compliance check, confirming visual quality alone doesn't guarantee electrical validity.

4 Results: Electrical Accuracy & Conditioning

Metric	PhysicsDiff	CGAN	VAE	Uncond. DDPM	Cond. DDPM
IoU ↑	0.612	0.737	0.815	0.347	0.087
Dice ↑	0.754	0.833	0.905	0.486	0.159
SSIM ↑	0.718	-	-	0.458	0.456
Z_0 Err. (Ω) ↓	5.21	23.44	17.83	5.01	22.76
NEXT Err. (V) ↓	0.183	0.776	0.744	0.804	0.725
Compliance ↑	0.578	0.270	0.344	1.000	0.259
Cond. Responsiveness	0.312	0.001	0.112	-	0.074
Structural Gap ↓	0.083	0.007	0.008	1.214	0.587
Diversity ↑	0.041	0.0003	0.175	0.057	0.055

PhysicsDiff-PCB achieves the lowest NEXT error (0.183V) and highest conditioning responsiveness (0.312).

PhysicsVAE tops IoU/Dice via its reconstruction objective, but weaker electrical accuracy confirms geometric similarity alone doesn't guarantee compliance.

5 Independent Validation with Full-Wave FDTD

Representative generated layouts were independently simulated in openEMS (full-wave FDTD, no frozen PhysicsPredictor) to validate beyond the surrogate.

Metric	Target	PhysicsPredictor	openEMS FDTD
Z_0 (Ω)	112.38	116.52	112.36
V_{NEXT}	0.1596	0.2006	0.2663

The impedance estimate agrees closely with the independent FDTD result, confirming the generated geometry's overall electromagnetic behaviour is physically realistic. A larger discrepancy is observed for near-end crosstalk, reflecting the greater complexity of coupled electromagnetic interactions relative to the analytical proxy used during training.

6 Limitations & Conclusion

Limitations:

- Analytical proxy labels are valid primarily under quasi-static assumptions and may underestimate higher-frequency effects
- FDTD validation is representative rather than large-scale
- Experimental hardware measurements remain future work

Conclusion:

PhysicsDiff-PCB demonstrates that conditional diffusion models can be guided by differentiable, physics-aware surrogate feedback to generate diverse, specification-conditioned PCB layouts — achieving the lowest crosstalk error and strongest conditioning responsiveness among tested generative approaches, with physical plausibility confirmed independently via full-wave FDTD simulation.

This establishes physics-guided generative AI as a viable path toward automated, EMI-aware high-speed PCB layout synthesis.

