

AudioPowerSupply

Reference	Qty	Value			Footprint
		15V-0-15V	21V-0-21V	48V Single	
C1,C2	2	1000uF 63V	1000uF 63V	220uF 100V	D16.0mm_P7.50mm
C3,C4	2	10uF 50V	10uF 50V	10uF 50V	D5.0mm_P2.50mm
C5	2	470nF	470nF	10uF 63V	L7.2mm_W3.0mm_P5.00mm
C6	2	470nF	470nF	omit	L7.2mm_W3.0mm_P5.00mm
C7,C8	2	470uF >30V	220uF >42V	omit	D10.0mm_P5.00mm
C9	1	10nF	10nF	10nF	L7.2mm_W3.0mm_P5.00mm
C10,C11,C12	3	100nF	100nF	100nF	L7.2mm_W3.0mm_P5.00mm
D1,D2,D3,D4	4	1N4002 / SB40	1N4004	1N4004	DO-41
D5,D6	2	1N4002	ZY24(24V/2W Zener)	ZY24(24V/2W Zener)	DO-41
D7	1	1N4002	1N4002	1N4002	DO-41
D8	1	1N4148	1N4148	1N4148	DO-35
J1,J4,J5,J6,J7	5	Conn_01x03_Pin	Conn_01x03_Pin	Conn_01x03_Pin	TerminalBlock 1x03 P3.50mm
J2	1	Conn_01x02_Pin	Conn_01x02_Pin	Conn_01x02_Pin	Molex KK-254 1x02 P2.54mm
J3	1	Conn_01x03_Pin	Conn_01x03_Pin	Conn_01x03_Pin	Molex KK-254 1x03 P2.54mm
L1	1	(10uH)	(10uH)	omit	L9.5mm_D4.0mm_P12.70mm
LED1	1	LED	LED	LED	(Off board)
PTC1	1	(XF050 500mA)	XF050 500mA	XF050 170mA	D9mm_W3.3mm_P5mm
Q1	1	(BC337)	omit	omit	TO-92
Q2	1	BC327	BC327	BC327	TO-92
R1	1	2R2 2.5W	2R2 2.5W	2R2 2.5W	L11.9mm_D4.5mm_P15.24mm
R2	1	3K3 1W	5K6 1W	9K1 1W	L11.9mm_D4.5mm_P15.24mm
R3	1	(6R2)	omit	omit	L6.3mm_D2.5mm_P10.16mm
R4	1	(12R)	omit	omit	L6.3mm_D2.5mm_P10.16mm
R5	1	2K7	8K2	9K1	L6.3mm_D2.5mm_P10.16mm
R6	1	omit	3K3	6K2	L6.3mm_D2.5mm_P10.16mm
R7	1	120R	120R	120R	L6.3mm_D2.5mm_P10.16mm
R8	1	56K	56K	56K	L6.3mm_D2.5mm_P10.16mm
R9,R10	2	100K	100K	omit	L6.3mm_D2.5mm_P10.16mm
R11,R12	2	47R	47R	omit	L6.3mm_D2.5mm_P10.16mm
R13	1	(22R)	(22R)	omit	L6.3mm_D2.5mm_P10.16mm
R14	1	1K	1K	1K	L6.3mm_D2.5mm_P10.16mm
R15	1	Linked out	2R2 2.5W	10R 2.5W	L11.9mm_D4.5mm_P15.24mm
R16	1	Linked out	10R	10R	L6.3mm_D2.5mm_P10.16mm
RV1	1	omit	10K	5K	Piher_PT-10-V05_Vertical
RV2	1	100K	100K	omit	Piher_PT-10-V05_Vertical
U1	1	LM317_TO-220	LM317_TO-220	LM317_TO-220	TO-220
U2	1	NE5532/LM1458	NE5532	omit	DIP-8
Transformer	1	28V / 140mA (5VA) or 25V / 15VA	18-0-18(26V) / 15VA	24-0-24(48V) / 15VA	(Off board)
Heatsink		>18K/W+	>21K/W	>21K/W	TO-220 twisted vane

Either user PTC1 or Q1/R3/R4

L1/R13 normally linked out

Note that newer NE5532s (like LM1458) only support 18V-0-18V