TENNANT CREEK MINE

TCMG-STD-FL-001
Rev 2.0
12 Mar 2026

Functional Location Codes

Gold Processing Plant | FL Code Standard

1. Purpose

FL codes define where assets physically and functionally exist within the plant. They answer: **"Where in the plant does this equipment belong?"** Used for asset hierarchy, maintenance planning, work history, PM alignment, and D365 integration.

2. FL Code Format

```
TCMG-PP-[AREA]-[SUBAREA]-[SYSTEM]
```

Segment	Meaning
TCMG	Tennant Creek Gold Mine
PP	Processing Plant
AREA	Major plant area (6 approved codes)
SUBAREA	Functional sub area within the area
SYSTEM	Parent Asset / System (lowest FL level)

```
TCMG
  └─ PP (Processing Plant)
    └─ COM (Comminution / Process)
      └─ GRIND (Grinding)
        └─ BM01 (Primary Ball Mill) ← FL stops here
          └─ BM01-MTR01 (inherits parent FL)
```

3. Area Codes (6 Approved)

Code	Area	Sub Area Codes
SITE	Site Infrastructure	INFRA
UTL	Utilities & Power	COMP, ELEC, REAG, WTR
COM	Comminution / Process	FEED, GRIND, CLASS
GR	Gold Recovery	CIP, ELUT, GOLD, GRAV, REGEN
TAIL	Tailings	FILT, THK
SUP	Support Services	MOBILE

4. Sub Area Codes & Live Examples

Area	Code	Sub Area	Example FL
COM	FEED	Feed / Reclaim	TCMG-PP-COM-FEED-RCFD01
COM	GRIND	Grinding	TCMG-PP-COM-GRIND-BM01
COM	CLASS	Classification	TCMG-PP-COM-CLASS-CYC01
GR	CIP	CIP / Leaching	TCMG-PP-GR-CIP-LCH01
GR	ELUT	Elution	TCMG-PP-GR-ELUT-ELU01
GR	GOLD	Gold Room	TCMG-PP-GR-GOLD-EW01
GR	GRAV	Gravity Circuit	TCMG-PP-GR-GRAV-KNL01
GR	REGEN	Carbon Regeneration	TCMG-PP-GR-REGEN-KLN01
TAIL	FILT	Filtering	TCMG-PP-TAIL-FILT-FP01
TAIL	THK	Thickening	TCMG-PP-TAIL-THK-THK01
UTL	COMP	Compressed Air	TCMG-PP-UTL-COMP-COMP01
UTL	ELEC	Electrical / Controls	TCMG-PP-UTL-ELEC-GEN01
UTL	REAG	Reagents	TCMG-PP-UTL-REAG-LIME01
UTL	WTR	Water	TCMG-PP-UTL-WTR-RO01
SITE	INFRA	Site Infrastructure	TCMG-PP-SITE-INFRA-BLDG01
SUP	MOBILE	Mobile Equipment	TCMG-PP-SUP-MOBILE-MOB01

5. Rules & Constraints

#	Rule
1	FLs stop at System Level. Assets and components do NOT receive their own FL codes
2	Equipment and components inherit the FL of their parent system
3	Hierarchy must be followed exactly. No levels skipped, no shortcuts
4	FL codes are immutable once assigned. Never renamed, reused, or changed
5	Each FL is unique across the entire site. No duplicates permitted
6	Duty/Standby and identical grouped assets share one Parent FL

6. Inheritance Examples (Live Data)

Assets and components do NOT receive new FL codes. They inherit the FL code of their parent System.

Functional Location	System	Inheriting Assets
TCMG-PP-COM-GRIND-BM01	BM01 Primary Ball Mill	BM01-MTR01, BM01-GBX01, BM01-BRG01
TCMG-PP-COM-CLASS-CYC01	CYC01 Primary Cyclones	CYC01-PMP01, CYC01-FDR01
TCMG-PP-GR-CIP-LCH01	LCH01 Leach Tanks	LCH01-AGT01, LCH01-PMP01
TCMG-PP-GR-GRAV-KNL01	KNL01 Knelson Concentrator	KNL01-PMP01, KNL01-PNL01
TCMG-PP-TAIL-THK-THK01	THK01 Tails Thickener	THK01-DRV01, THK01-PMP01
TCMG-PP-UTL-ELEC-GEN01	GEN01 Generation	PGEN01, PGEN02, PGEN03

7. When New FLs Can Be Created

Allowed

- A new system boundary is introduced
- A new process line or major modification is installed
- Approved changes to P&IDs define a new system

Not Allowed

- Component replacement
- Equipment upgrades
- Temporary equipment
- Maintenance workarounds

8. Relationship to Asset & Parts Numbering

FL Codes	Asset Numbers	Parts Numbers
Define WHERE an asset sits in the plant	Define WHAT the equipment is	Define what is STOCKED in stores

FL → Asset → Component → Part (all three systems are independent but linked)