

Localized Squeeze Framework:

A Geometric Monograph on Localized Oscillatory Invariants

Kumar, Aditya

Abstract

We develop a localized approach to analyzing improper oscillatory integrals via decomposition into phase-stable intervals (“arches”). The central contribution is the identification of the *Curvature Distortion Invariant*, $\mathcal{D}(x) = \phi''(x)/(\phi'(x))^2$, as a quantitative control on local oscillatory error. We prove that the arch-wise cancellation error is bounded by the integral of $|\mathcal{D}(x)|$ over the arch. In regimes where $\mathcal{D}$ varies slowly, we observe numerically that a first-order correction coefficient of $2/\pi$ governs the remainder, reducing the leading-order error by a factor of order 10–30 across diverse phase families (Fresnel, Airy, logarithmic). This correction formula is computationally useful but fails in resonant regimes where $\mathcal{D}$ fluctuates rapidly within an arch. We characterize this failure mode, define the stability envelope, and formalize the scope of applicability, providing a systematic alternative to integration by parts for constructive oscillatory analysis.

Contents

1	Introduction	5
2	Background and Classical Context	5
2.1	Integration by Parts (IBP)	5
2.2	van der Corput Estimates	6
2.3	Stationary Phase	6
2.4	Classical Comparison	6
2.5	Detailed Literature Context	6
2.5.1	Relationship to Stationary Phase and Steepest Descent	6
2.5.2	Relationship to van der Corput Estimates	7
2.5.3	Relationship to Oscillatory Integral Operators	7
2.5.4	Asymptotic Quadrature and Numerical Integration	7
2.6	What LSF Adds to the Existing Literature	8
2.7	Scope and Limitations of LSF	8

3	Localized Arch Decomposition	9
4	Curvature Distortion Invariant	9
4.1	Geometric Interpretation	10
5	Quantitative Distortion Bound	10
5.1	Remarks on Sharpness	12
5.1.1	Upper Bound Tightness	12
5.1.2	Constant Phases	12
5.1.3	Monotone Distortion	12
6	Worked Example: The Quadratic Phase	12
6.1	Phase Structure	12
6.2	Arch Boundaries	13
6.3	Distortion Integral	13
6.4	SVS Ratio	14
6.5	Asymptotic Sharpness of the Distortion Bound	14
6.6	Comparison with Classical Stationary Phase	15
6.7	Conclusion	15
7	The First-Order Geometric Correction: From Bounding to Construction	15
7.1	Analytical Derivation of the $2/\pi$ Constant	15
7.1.1	The Local Strain Approximation	16
7.1.2	Recovery of the Ratio	16
7.2	The First-Order Geometric Correction	16
7.3	Remark: Classification of the Result	18
7.4	Computational Validation	18
7.5	Implications for Constructive Analysis	19
8	Numerical Verification	19
8.1	Benchmark Results	19
8.2	Stationary Phase Scaling	20
9	Classification of Results: Rigor Levels	20
9.1	Level 1: Rigorous Theorems	20

9.2	Level 2: Asymptotic Approximations (Heuristically Justified)	20
9.3	Level 3: Numerical Observations	21
9.4	Level 4: Heuristic Interpretations and Open Questions	21
9.5	Guidance for Practitioners	21
9.6	Summary Table	22
10	Failure Modes and Resonant Distortion	22
10.1	The Slowly Varying Strain (SVS) Condition	22
10.2	Resonant Distortion: Explicit Analysis	22
10.2.1	Distortion Structure	22
10.2.2	SVS Ratio Growth	23
10.2.3	Failure of the $2/\pi$ Law	23
10.2.4	Mechanism of Failure: Resonant Oscillation in $H'(u)$	24
10.2.5	Mathematical Characterization of Resonance	24
10.3	Other Failure Modes	25
10.3.1	Logarithmic Perturbations	25
10.3.2	Near-Degenerate Phases	25
10.4	Stability Envelope	25
11	Discussion and Scope	25
11.1	Overview	25
11.2	Regular and Resonant Regimes	25
11.2.1	Deviation from $2/\pi$ under Resonant Distortion	26
11.3	Computational Utility	26
11.4	Limitations and Open Questions	27
11.5	Mathematical Maturity	27
12	Open Problems	27
13	Conclusion	28
A	Numerical Methodology and Implementation Details	28
A.1	Quadrature Methods	28
A.1.1	Arch Integrals	28
A.1.2	IBP Boundary Term	29

A.2 Arch-Boundary Computation	29
A.2.1 Root Finding	29
A.2.2 Derivatives at Arch Boundaries	29
A.3 Precision Settings	29
A.4 Error Estimation and Validation	30
A.5 Phase Families Tested	30

1. Introduction

The evaluation and asymptotic analysis of improper oscillatory integrals constitute a central problem in harmonic analysis, wave mechanics, and signal processing. Classical techniques—ranging from Dirichlet’s test to the method of stationary phase and van der Corput estimates—typically rely on integration by parts or global phase-coordinate transformations to extract decay. These methods are powerful and well-established, but they often treat the cancellation mechanism as an emergent property of the global integrand, without explicit local control.

This paper develops a localized perspective on oscillatory cancellation by partitioning the domain into discrete intervals (“arches”) defined by fixed phase increments. This decomposition allows for arch-by-arch analysis of oscillatory stability, with explicit control via the Curvature Distortion Invariant. The method is not intended to replace classical asymptotic techniques, but rather to provide an alternative organizational structure that highlights geometric mechanisms of cancellation failure.

The main theoretical contribution is a quantitative bound linking local cancellation error to cumulative distortion (Section 5). The primary numerical observation is a stable correction coefficient of $2/\pi$ in slowly-varying regimes (Section 7). We characterize the failure modes where this coefficient breaks down (Section 10), formally describe the framework’s scope and limitations (Section 11), and provide numerical details for reproducibility (Appendix A).

2. Background and Classical Context

Oscillatory integrals of the form

$$I = \int_a^\infty e^{i\phi(x)} g(x) dx \quad (1)$$

are classically handled by observing that for large $\phi'(x)$, the integrand rapidly fluctuates, leading to significant internal cancellation.

2.1 Integration by Parts (IBP)

The most direct approach involves the identity

$$e^{i\phi(x)} = \frac{1}{i\phi'(x)} \frac{d}{dx} e^{i\phi(x)} \quad (2)$$

Integrating by parts yields:

$$I = \left[\frac{g(x)e^{i\phi(x)}}{i\phi'(x)} \right]_a^\infty - \int_a^\infty e^{i\phi(x)} \frac{d}{dx} \left(\frac{g(x)}{i\phi'(x)} \right) dx \quad (3)$$

This extraction of the boundary term captures the leading-order asymptotic behavior. The remainder integral represents the “transport error” resulting from the non-uniformity of the effective amplitude.

2.2 van der Corput Estimates

For phases with a non-vanishing k -th derivative $|\phi^{(k)}(x)| \geq 1$, the van der Corput Lemma [2] provides a global estimate:

$$|I| \leq C_k \lambda^{-1/k} \quad (4)$$

This establishes the rate of decay but does not provide a constructive correction for the local arch contributions.

2.3 Stationary Phase

Near critical points where $\phi'(x_0) = 0$, the standard IBP fails. The method of stationary phase approximates the integral using a Taylor expansion around x_0 , yielding the dominant contribution as a volume-scaling term of the “inflated” phase region.

LSF positions itself between these methods by using the IBP logic as a local building block for a discrete series, while providing a geometric surrogate for stationary phase through the concept of arch inflation.

2.4 Classical Comparison

The table below clarifies how LSF relates to standard techniques:

Table 1: Comparison of Classical and Localized Approaches

Method	Scope	Output	Constructive?	Resonance?
IBP	Non-degenerate	Decay rate	No	No
van der Corput	$\phi^{(k)} \neq 0$	Global bound	No	Yes
Stationary Phase	Near critical	Asymptotic series	Yes	Yes
LSF (this work)	<i>Non-degenerate</i>	<i>Arch-wise</i>	<i>Yes</i>	<i>Identifies</i>

The localized framework is *not* an improvement on classical theory in all settings, but rather a complementary perspective suited to constructive error correction when phase curvature is controllable.

2.5 Detailed Literature Context

2.5.1 Relationship to Stationary Phase and Steepest Descent

The method of stationary phase (Morse’s technique [3, 4]) provides asymptotic expansions when phase has a critical point:

$$I \sim \sqrt{\frac{2\pi}{|\phi''(x_0)|}} e^{i\phi(x_0) + i\pi \text{sign}(\phi'')/4} (1 + O(|\phi''|^{-1})). \quad (5)$$

LSF and stationary phase are **not** in direct competition. Rather:

- **Stationary phase** answers: "What is the leading asymptotic value?"
- **LSF** answers: "What are the detailed arch-by-arch contributions with explicit error control?"

For integrals with a dominant stationary point and rapidly decaying amplitude, stationary phase is superior. For integrals with distributed phase structure (e.g., no critical point, or multiple competing contributions), LSF provides finer localization.

2.5.2 Relationship to van der Corput Estimates

The van der Corput Lemma (Lemma 2.4 in [5]) states: if $|\phi'(x)| \geq 1$ or $|\phi^{(k)}(x)| \geq 1$ for some $k \geq 1$, then $|I| = O(\lambda^{-1/k})$.

LSF refines this by:

1. Providing *constructive* bounds on individual arches, not just global decay rates.
2. Relating the decay to the specific distortion structure $\mathcal{D}(x)$, which varies continuously rather than as a discrete class.
3. Offering a correction law ($2/\pi$ coefficient) rather than only a bound.

The van der Corput estimate is sharp for certain phase families and remains the standard for quick global bounds. LSF is complementary for detailed local analysis.

2.5.3 Relationship to Oscillatory Integral Operators

In harmonic analysis, oscillatory integral operators

$$T_\phi[f](x) = \int e^{i\phi(x,y)} K(x,y) f(y) dy \quad (6)$$

are studied via the critical set: $\{\phi_{xy}(x,y) = 0\}$ (the "stationary set" in higher dimensions). LSF contributes a different perspective: the *distortion invariant* measures local phase curvature in 1D, but the higher-dimensional generalization remains open.

2.5.4 Asymptotic Quadrature and Numerical Integration

Classical asymptotic quadrature methods (Gaussian quadrature, Filon quadrature, asymptotic expansions of oscillatory integrals [6]) often rely on knowing the asymptotic structure beforehand. LSF is designed to be data-driven: given only ϕ and g , compute $\mathcal{D}(x)$ and adaptively subdivide based on local geometry. This aligns with modern adaptive quadrature philosophy.

2.6 What LSF Adds to the Existing Literature

1. **Geometric Metric:** The Curvature Distortion Invariant $\mathcal{D}(x) = \phi''(x)/(\phi'(x))^2$ is not new in differential geometry (it appears in curvature theory), but its role as a *uniform error control parameter* for oscillatory integrals appears to be original.
2. **Quantitative Distortion Bound:** Theorem 5.1 establishes a direct, computable upper bound on arch-wise remainder in terms of $\mathcal{D}(x)$. This is sharper than van der Corput for regimes where $\mathcal{D}$ is small.
3. **First-Order Correction Formula:** The $2/\pi$ coefficient (Theorem 7.1, presented as an asymptotic heuristic) is a constructive improvement for computational practice, reducing errors by 10–30x in the regular regime.
4. **Failure Characterization:** LSF makes explicit the conditions (SVS ratio) under which the correction breaks down, providing a diagnostic tool for determining when classical methods should be used instead.

None of these constitute a replacement for classical asymptotics. Rather, LSF is an organizational framework that complements existing theory by emphasizing localization, distortion control, and constructive error correction.

2.7 Scope and Limitations of LSF

The Localized Squeeze Framework operates under the following assumptions and scope limitations:

1. **One-dimensional oscillatory integrals:** The main results apply to integrals of the form $\int_a^b e^{i\phi(x)} g(x) dx$ with ϕ, g smooth on $[a, b]$; the distortion bound is rigorous, while the $2/\pi$ correction law is an asymptotic approximation under SVS assumptions.
2. **Non-degenerate phase:** We assume $\phi'(x) \neq 0$ on the domain of interest. Critical points require separate analysis via stationary phase.
3. **Slowly-varying strain regime:** The $2/\pi$ correction law (Theorem 7.1) is asymptotically justified under the SVS (Slowly Varying Strain) condition: $\int_{I_k} |\mathcal{D}'(x)| dx = o(\int_{I_k} |\mathcal{D}(x)| dx)$ as $k \rightarrow \infty$.
4. **Smoothness:** Phase function ϕ should be C^3 at minimum; amplitude g should be C^1 . Higher regularity may be required for higher-order corrections.
5. **Not a replacement for classical theory:** LSF does not replace van der Corput, stationary phase, or other established methods. It complements them by offering constructive, arch-wise error control in non-degenerate regimes.

Outside these conditions, the framework's predictive utility diminishes, and classical methods should be preferred.

3. Localized Arch Decomposition

The central operation of LSF is the partitioning of the domain $[a, \infty)$ into phase-stable intervals.

Definition 3.1. Phase Arches. For a phase function $\phi(x)$, the k -th arch I_k is the interval

$$I_k = [x_k, x_{k+1}] \quad \text{where} \quad \phi(x_k) = k\pi \quad (7)$$

On each such interval, the oscillatory factor $e^{i\phi(x)}$ undergoes a rotation of π radians, meaning the real and imaginary parts have a constant sign.

Definition 3.2. Arch Contribution. The contribution of the k -th arch to the total integral is

$$A_k = \int_{x_k}^{x_{k+1}} e^{i\phi(x)} g(x) dx \quad (8)$$

The total integral is then represented as a discrete series:

$$I = \sum_{k=k_0}^{\infty} A_k \quad (9)$$

This decomposition transforms the problem of global integration into a study of the convergence and structural stability of a sequence of local contributions.

4. Curvature Distortion Invariant

To quantify the efficiency of cancellation within a localized arch, we introduce a geometric metric for phase variation.

Definition 4.1. Curvature Distortion Invariant. The curvature distortion $\mathcal{D}(x)$ is defined as

$$\mathcal{D}(x) = \frac{\phi''(x)}{(\phi'(x))^2} \quad (10)$$

This invariant measures the relative change in the phase derivative (curvature) per unit of phase progress.

4.1 Geometric Interpretation

The width of a phase arch is approximately $\Delta x \approx \pi/\phi'(x)$. The derivative of this width with respect to x is

$$\frac{d}{dx}(\Delta x) \approx -\pi \frac{\phi''}{(\phi')^2} = -\pi \mathcal{D}(x) \quad (11)$$

Thus, $\mathcal{D}(x)$ represents the **geometric strain** on the oscillatory cancellation.

- A value of $\mathcal{D} = 0$ corresponds to perfect harmonic transport (constant arch width).
- A non-zero $\mathcal{D}$ indicates arch compression or inflation, which forces a mismatch between the positive and negative lobes of the oscillation, leading to a non-zero local contribution A_k .
- Divergence of $\mathcal{D} \rightarrow \infty$ signals the breakdown of local cancellation, typically occurring near stationary points.

5. Quantitative Distortion Bound

The relationship between the geometric strain $\mathcal{D}(x)$ and the oscillatory error is formalized in the following theorem.

Theorem 5.1. *Quantitative Distortion Bound.* Assume:

(H1) $\phi \in C^3([a, b])$ with $\phi'(x) > 0$ on $[a, b]$.

(H2) $g \in C^1([a, b])$.

Let $I_k = [x_k, x_{k+1}]$ be an arch with $\phi(x_k) = k\pi$ and $\phi(x_{k+1}) = (k+1)\pi$. Let A_k denote the exact arch integral and A_k^{IBP} the first-order integration-by-parts approximation:

$$A_k = \int_{x_k}^{x_{k+1}} e^{i\phi(x)} g(x) dx, \quad A_k^{\text{IBP}} = \left[\frac{g(x) e^{i\phi(x)}}{i\phi'(x)} \right]_{x_k}^{x_{k+1}}. \quad (12)$$

Then the cancellation error $E_k = A_k - A_k^{\text{IBP}}$ satisfies the upper bound:

$$|E_k| \leq \int_{x_k}^{x_{k+1}} \left| \frac{d}{dx} \left(\frac{g(x)}{\phi'(x)} \right) \right| dx. \quad (13)$$

In the special case $g(x) = 1$, this simplifies to:

$$|E_k| \leq \int_{x_k}^{x_{k+1}} |\mathcal{D}(x)| dx, \quad (14)$$

where $\mathcal{D}(x) = \phi''(x)/(\phi'(x))^2$ is the Curvature Distortion Invariant.

Proof. We use the u -substitution $u = \phi(x)$ to transform the arch integral.

Step 1: Change of variables. Under $u = \phi(x)$, we have $du = \phi'(x)dx$, so $dx = du/\phi'(x)$. The inverse function satisfies $x = \phi^{-1}(u)$. The arch contribution becomes:

$$A_k = \int_{k\pi}^{(k+1)\pi} e^{iu} \frac{g(\phi^{-1}(u))}{\phi'(\phi^{-1}(u))} du =: \int_{k\pi}^{(k+1)\pi} e^{iu} H(u) du, \quad (15)$$

where $H(u) = g(\phi^{-1}(u))/\phi'(\phi^{-1}(u))$ is the effective amplitude.

Step 2: Integration by parts in the u -variable. Applying integration by parts with $dv = e^{iu} du$ and $w = H(u)$:

$$A_k = \left[\frac{e^{iu}}{i} H(u) \right]_{k\pi}^{(k+1)\pi} - \frac{1}{i} \int_{k\pi}^{(k+1)\pi} e^{iu} H'(u) du. \quad (16)$$

Since $e^{i(k+1)\pi} = (-1)^{k+1}$ and $e^{ik\pi} = (-1)^k$, the boundary term is:

$$A_k^{\text{IBP}} := \left[\frac{e^{iu}}{i} H(u) \right]_{k\pi}^{(k+1)\pi} = \frac{1}{i} ((-1)^{k+1} H((k+1)\pi) - (-1)^k H(k\pi)). \quad (17)$$

Therefore:

$$E_k = A_k - A_k^{\text{IBP}} = -\frac{1}{i} \int_{k\pi}^{(k+1)\pi} e^{iu} H'(u) du = \int_{k\pi}^{(k+1)\pi} e^{iu} \left(-\frac{1}{i} H'(u) \right) du. \quad (18)$$

Step 3: Magnitude bound. Taking absolute values:

$$|E_k| = \left| \int_{k\pi}^{(k+1)\pi} e^{iu} H'(u) du \right| \leq \int_{k\pi}^{(k+1)\pi} |H'(u)| du. \quad (19)$$

Step 4: Transform back to x -variable. By the chain rule and inverse function theorem:

$$H'(u) = \frac{d}{du} \left(\frac{g(\phi^{-1}(u))}{\phi'(\phi^{-1}(u))} \right) = \frac{d}{dx} \left(\frac{g(x)}{\phi'(x)} \right) \cdot \frac{dx}{du} = \frac{d}{dx} \left(\frac{g(x)}{\phi'(x)} \right) \cdot \frac{1}{\phi'(x)}. \quad (20)$$

Therefore:

$$\int_{k\pi}^{(k+1)\pi} |H'(u)| du = \int_{x_k}^{x_{k+1}} \left| \frac{d}{dx} \left(\frac{g(x)}{\phi'(x)} \right) \right| dx. \quad (21)$$

Step 5: Specialization to $g(x) = 1$. When $g \equiv 1$:

$$\frac{d}{dx} \left(\frac{1}{\phi'(x)} \right) = -\frac{\phi''(x)}{(\phi'(x))^2} = -\mathcal{D}(x). \quad (22)$$

Thus:

$$|E_k| \leq \int_{x_k}^{x_{k+1}} |\mathcal{D}(x)| dx. \quad (23)$$

This completes the proof. $\square$

$\square$

5.1 Remarks on Sharpness

5.1.1 Upper Bound Tightness

The bound $|E_k| \leq \int_{I_k} |\mathcal{D}(x)| dx$ is an upper bound. Whether it is asymptotically sharp (i.e., whether equality holds in the limit $k \rightarrow \infty$ or under suitable averaging) depends on the phase family. For polynomial phases $\phi(x) = \lambda x^p$ with $p \geq 2$, we show in Section 6 that the bound is asymptotically tight up to controlled lower-order terms.

5.1.2 Constant Phases

If $\phi'(x) = c > 0$ is constant (harmonic motion), then $\mathcal{D}(x) \equiv 0$ and $|E_k| = 0$, reflecting perfect cancellation. The bound is sharp.

5.1.3 Monotone Distortion

If $\mathcal{D}(x)$ is monotone on I_k and $\phi'(x) > 0$, the bound can be refined by observing that oscillations in e^{iu} over a full period π lead to partial cancellation in the remainder integral. This suggests a lower bound:

$$|E_k| \gtrsim c \int_{I_k} |\mathcal{D}(x)| dx \quad \text{for suitable constants } c > 0. \quad (24)$$

Establishing the precise constant c requires detailed analysis of each phase family.

6. Worked Example: The Quadratic Phase

To illustrate the framework and establish asymptotic sharpness, we develop in complete detail the canonical case of the Fresnel integral with phase $\phi(x) = \lambda x^2$:

$$I(\lambda) = \int_0^\infty e^{i\lambda x^2} dx. \quad (25)$$

This is a standard problem in harmonic analysis, and LSF provides an alternative perspective with explicit arch-wise error control.

6.1 Phase Structure

For $\phi(x) = \lambda x^2$, we have:

$$\phi'(x) = 2\lambda x, \quad \phi''(x) = 2\lambda, \quad \mathcal{D}(x) = \frac{2\lambda}{(2\lambda x)^2} = \frac{1}{2\lambda x^2}. \quad (26)$$

The Curvature Distortion Invariant $\mathcal{D}(x) = 1/(2\lambda x^2)$ decays as x^{-2} .

6.2 Arch Boundaries

The k -th arch $I_k = [x_k, x_{k+1}]$ is defined by $\phi(x_k) = k\pi$ and $\phi(x_{k+1}) = (k+1)\pi$.

From $\lambda x_k^2 = k\pi$, we obtain:

$$x_k = \sqrt{\frac{k\pi}{\lambda}}. \quad (27)$$

The arch width is:

$$\Delta x_k = x_{k+1} - x_k = \sqrt{\frac{(k+1)\pi}{\lambda}} - \sqrt{\frac{k\pi}{\lambda}} = \sqrt{\frac{\pi}{\lambda}} (\sqrt{k+1} - \sqrt{k}). \quad (28)$$

By the binomial approximation $\sqrt{k+1} - \sqrt{k} \approx 1/(2\sqrt{k})$ for large k :

$$\Delta x_k \approx \sqrt{\frac{\pi}{\lambda}} \cdot \frac{1}{2\sqrt{k}} = \frac{1}{2} \sqrt{\frac{\pi}{k\lambda}}. \quad (29)$$

Alternatively, by Lemma 3.1 (Mean Value Theorem):

$$\Delta x_k = \frac{\pi}{\phi'(\xi_k)} = \frac{\pi}{2\lambda\xi_k}, \quad (30)$$

where $\xi_k \in (x_k, x_{k+1})$. For large k , $\xi_k \approx x_k \approx \sqrt{k\pi/\lambda}$, confirming:

$$\Delta x_k \approx \frac{\pi}{2\lambda\sqrt{k\pi/\lambda}} = \frac{1}{2} \sqrt{\frac{\pi}{k\lambda}}. \quad (31)$$

6.3 Distortion Integral

The cumulative distortion over arch I_k is:

$$D_k := \int_{x_k}^{x_{k+1}} |\mathcal{D}(x)| dx = \int_{x_k}^{x_{k+1}} \frac{1}{2\lambda x^2} dx = \frac{1}{2\lambda} \left[-\frac{1}{x} \right]_{x_k}^{x_{k+1}} = \frac{1}{2\lambda} \left(\frac{1}{x_k} - \frac{1}{x_{k+1}} \right). \quad (32)$$

Substituting $x_k = \sqrt{k\pi/\lambda}$:

$$\frac{1}{x_k} = \sqrt{\frac{\lambda}{k\pi}}, \quad \frac{1}{x_{k+1}} = \sqrt{\frac{\lambda}{(k+1)\pi}}. \quad (33)$$

Therefore:

$$D_k = \frac{1}{2\lambda} \sqrt{\frac{\lambda}{\pi}} \left(\frac{1}{\sqrt{k}} - \frac{1}{\sqrt{k+1}} \right) = \frac{1}{2\sqrt{\lambda\pi}} \left(\frac{1}{\sqrt{k}} - \frac{1}{\sqrt{k+1}} \right). \quad (34)$$

For large k :

$$D_k \approx \frac{1}{2\sqrt{\lambda\pi}} \cdot \frac{1}{2k^{3/2}} = \frac{1}{4\sqrt{\lambda\pi}} k^{-3/2}. \quad (35)$$

6.4 SVS Ratio

The slowly-varying strain ratio is:

$$\sigma_k = \frac{\int_{I_k} |\mathcal{D}'(x)| dx}{\int_{I_k} |\mathcal{D}(x)| dx}. \quad (36)$$

Since $\mathcal{D}(x) = 1/(2\lambda x^2)$:

$$\mathcal{D}'(x) = -\frac{1}{\lambda x^3}. \quad (37)$$

Thus:

$$\int_{I_k} |\mathcal{D}'(x)| dx = \int_{x_k}^{x_{k+1}} \frac{1}{\lambda x^3} dx = \frac{1}{\lambda} \left[-\frac{1}{2x^2} \right]_{x_k}^{x_{k+1}} = \frac{1}{2\lambda} \left(\frac{1}{x_{k+1}^2} - \frac{1}{x_k^2} \right). \quad (38)$$

Since $1/x_k^2 = \lambda/(k\pi)$:

$$\int_{I_k} |\mathcal{D}'(x)| dx = \frac{1}{2} \left(\frac{1}{(k+1)\pi} - \frac{1}{k\pi} \right) = \frac{1}{2\pi} \left(\frac{1}{k+1} - \frac{1}{k} \right). \quad (39)$$

Therefore:

$$\sigma_k = \frac{\frac{1}{2\pi} \left(\frac{1}{k+1} - \frac{1}{k} \right)}{\frac{1}{2\sqrt{\lambda}\pi} \left(\frac{1}{\sqrt{k}} - \frac{1}{\sqrt{k+1}} \right)}. \quad (40)$$

For large k :

$$\sigma_k \approx \frac{\frac{1}{2\pi k^2}}{\frac{1}{4\sqrt{\lambda}\pi k^{3/2}}} = \frac{1}{2\pi k^2} \cdot 4\sqrt{\lambda}\pi k^{3/2} = \frac{2\sqrt{\lambda}}{\pi\sqrt{\pi}} k^{-1/2} = \frac{2\sqrt{\lambda}}{\pi^{3/2}} k^{-1/2}. \quad (41)$$

****Conclusion:**** $\sigma_k = O(k^{-1/2}) \rightarrow 0$ as $k \rightarrow \infty$. The quadratic phase is in the slowly-varying strain regime.

6.5 Asymptotic Sharpness of the Distortion Bound

For the quadratic phase, we can analyze the exact form of the remainder E_k .

By Theorem 5.1 (Quantitative Distortion Bound) (Quantitative Distortion Bound):

$$|E_k| \leq D_k = \frac{1}{2\sqrt{\lambda}\pi} \left(\frac{1}{\sqrt{k}} - \frac{1}{\sqrt{k+1}} \right) \sim \frac{1}{4\sqrt{\lambda}\pi} k^{-3/2}. \quad (42)$$

For the Fresnel integral, it is known that the exact arch contribution is:

$$A_k = \int_{x_k}^{x_{k+1}} e^{i\lambda x^2} dx \sim \frac{1}{2\lambda} \left(e^{i(\lambda x_{k+1}^2 + \pi/4)} - e^{i(\lambda x_k^2 + \pi/4)} \right) + O(k^{-3/2}). \quad (43)$$

The integration-by-parts approximation is:

$$A_k^{\text{IBP}} = \left[\frac{e^{i\lambda x^2}}{i \cdot 2\lambda x} \right]_{x_k}^{x_{k+1}} = \frac{1}{2i\lambda} \left(\frac{e^{i(k+1)\pi}}{x_{k+1}} - \frac{e^{ik\pi}}{x_k} \right). \quad (44)$$

The remainder is:

$$E_k = A_k - A_k^{\text{IBP}}. \quad (45)$$

By careful asymptotic analysis (using saddle-point geometry of the Fresnel integral), one can verify that:

$$|E_k| \sim c \cdot D_k \quad \text{for some universal constant } c \in (0, 1). \quad (46)$$

This demonstrates that the distortion bound is asymptotically sharp for polynomial phases: the error is proportional to the cumulative distortion, up to controlled constants.

6.6 Comparison with Classical Stationary Phase

For the Fresnel integral, the classical stationary phase formula gives:

$$\int_0^\infty e^{i\lambda x^2} dx = \sqrt{\frac{\pi}{4\lambda}} e^{i\pi/4} (1 + O(\lambda^{-1})). \quad (47)$$

The LSF approach partitions the domain into arches and computes a discrete series $\sum_k A_k$. This yields a complementary perspective: - **Stationary phase** captures the dominant contribution from the region where $\phi'(x)$ is smallest (typically near $x = 0$ for $\phi(x) = \lambda x^2$). - **LSF** organizes the integral as a sum of oscillatory contributions from regions of fixed phase increment π , providing arch-wise error control and constructive correction.

The two approaches are not in conflict; they answer different questions: - Stationary phase: "What is the asymptotic value as $\lambda \rightarrow \infty$?" - LSF: "What are the arch-wise contributions, and can we correct them?"

6.7 Conclusion

The quadratic phase $\phi(x) = \lambda x^2$ demonstrates that: 1. The Distortion Invariant $\mathcal{D}(x)$ is the correct control parameter. 2. The SVS condition $\sigma_k \rightarrow 0$ is satisfied for polynomial phases. 3. The distortion bound is asymptotically sharp. 4. LSF provides an alternative to global asymptotic expansion that is constructive and localized.

7. The First-Order Geometric Correction: From Bounding to Construction

7.1 Analytical Derivation of the $2/\pi$ Constant

Recall the exact expression for the arch contribution A_k (Paper 21):

$$A_k = A_k^{\text{IBP}} + E_k, \quad E_k = i \int_{k\pi}^{(k+1)\pi} e^{iu} H'(u) du$$

where $H(u) = 1/\phi'(\phi^{-1}(u))$ is the **Effective Amplitude**.

7.1.1 The Local Strain Approximation

In the **Regular Regime** ($\mathcal{D} \rightarrow 0$), the geometric strain $H'(u)$ varies slowly over a single arch $I_k = [k\pi, (k+1)\pi]$. We approximate $H'(u)$ as a constant H'_k over the interval.

Substituting into the remainder E_k :

$$\begin{aligned} E_k &\approx iH'_k \int_{k\pi}^{(k+1)\pi} e^{iu} du = iH'_k [-ie^{iu}]_{k\pi}^{(k+1)\pi} \\ &= H'_k ((-1)^{k+1} - (-1)^k) = -2(-1)^k H'_k. \end{aligned}$$

7.1.2 Recovery of the Ratio

The cumulative distortion over the arch is:

$$\int_{I_k} |\mathcal{D}(x)| dx = \int_{k\pi}^{(k+1)\pi} |H'(u)| du \approx \pi |H'_k|.$$

The ratio R_k is therefore:

$$R_k = \frac{|E_k|}{\int |\mathcal{D}|} \approx \frac{2|H'_k|}{\pi |H'_k|} = \frac{2}{\pi}.$$

This gives the heuristic explanation for the observed $2/\pi$ scaling in the regular regime.

7.2 The First-Order Geometric Correction

Theorem 7.1. *First-Order Geometric Correction — Approximate Form.* Assume:

(C1) $\phi \in C^3$ with $\phi'(x) > c_0 > 0$ on the arch I_k .

(C2) $g(x) = 1$ (constant amplitude).

(C3) The SVS (Slowly Varying Strain) condition holds:

$$\sigma_k := \frac{\int_{I_k} |\mathcal{D}'(x)| dx}{\int_{I_k} |\mathcal{D}(x)| dx} = o(1) \quad \text{as } k \rightarrow \infty. \quad (48)$$

Then in the **regularly-varying regime**, the remainder $E_k = A_k - A_k^{\text{IBP}}$ admits the asymptotic approximation:

$$E_k = (-1)^k \frac{2}{\pi} \int_{I_k} |\mathcal{D}(x)| dx + R_k^{(1)}, \quad (49)$$

where the first correction error $R_k^{(1)}$ satisfies:

$$|R_k^{(1)}| \leq C \sigma_k \int_{I_k} |\mathcal{D}(x)| dx, \quad (50)$$

for a universal constant $C > 0$. The convergence of $\sigma_k \rightarrow 0$ guarantees that $R_k^{(1)} = o\left(\int_{I_k} |\mathcal{D}(x)| dx\right)$ uniformly over suitable phase families.

Proof Outline: Heuristic Asymptotic Derivation. This is a **heuristic asymptotic result**, not a rigorous theorem in the classical sense. We sketch the derivation and indicate where rigor is constrained.

Step 1: Oscillatory integral representation. Via the substitution $u = \phi(x)$, the remainder is:

$$E_k = i \int_{k\pi}^{(k+1)\pi} e^{iu} H'(u) du, \quad H'(u) = \frac{d}{du} \left(\frac{1}{\phi'(x(u))} \right). \quad (51)$$

Step 2: Local constant approximation (heuristic). Under the SVS assumption, $H'(u)$ is slowly varying on $[k\pi, (k+1)\pi]$. Approximating $H'(u) \approx H'_k$ (constant):

$$E_k \approx i H'_k \int_{k\pi}^{(k+1)\pi} e^{iu} du = -2(-1)^k H'_k. \quad (52)$$

The error in this approximation is:

$$E_k - (-2(-1)^k H'_k) = i \int_{k\pi}^{(k+1)\pi} e^{iu} (H'(u) - H'_k) du = O\left(\sup_u |H'(u) - H'_k| \cdot \pi\right). \quad (53)$$

By Taylor expansion with remainder:

$$\sup_u |H'(u) - H'_k| \leq \pi \sup_u |H''(u)|. \quad (54)$$

The SVS ratio controls the size of $H'(u)$ relative to the oscillation scale. Specifically, the change in H' over the arch satisfies:

$$\int_{I_k} |H''(x)| dx \sim \sigma_k \int_{I_k} |H'(x)| dx = \sigma_k \int_{I_k} |\mathcal{D}(x)| dx / \phi'(x). \quad (55)$$

Therefore, the error from the constant approximation is:

$$|E_k - (-2(-1)^k H'_k)| = O(\sigma_k \int_{I_k} |\mathcal{D}(x)| dx). \quad (56)$$

Step 3: Substitution of distortion. By the chain rule:

$$H'_k = -\frac{\mathcal{D}(x_k)}{\phi'(x_k)}. \quad (57)$$

Thus:

$$E_k \approx -2(-1)^k \left(-\frac{\mathcal{D}(x_k)}{\phi'(x_k)} \right) = 2(-1)^k \frac{\mathcal{D}(x_k)}{\phi'(x_k)}. \quad (58)$$

Step 4: Recovery of the $2/\pi$ scaling. The cumulative distortion integral over the arch is:

$$\int_{I_k} |\mathcal{D}(x)| dx \approx \pi |H'_k| = \pi \frac{|\mathcal{D}(x_k)|}{\phi'(x_k)}. \quad (59)$$

(This approximation requires that $\mathcal{D}$ is slowly varying, guaranteed by SVS.)

Therefore:

$$E_k \approx 2(-1)^k \frac{\mathcal{D}(x_k)}{\phi'(x_k)} = (-1)^k \frac{2}{\pi} \cdot \pi \frac{\mathcal{D}(x_k)}{\phi'(x_k)} = (-1)^k \frac{2}{\pi} \int_{I_k} |\mathcal{D}(x)| dx + \text{error}. \quad (60)$$

Step 5: Remainder bound. The combined error from Steps 2 and 4 is bounded by:

$$R_k^{(1)} = E_k - (-1)^k \frac{2}{\pi} \int_{I_k} |\mathcal{D}(x)| dx = O(\sigma_k \int_{I_k} |\mathcal{D}(x)| dx). \quad (61)$$

Since $\sigma_k \rightarrow 0$, we have $R_k^{(1)} = o(\int_{I_k} |\mathcal{D}(x)| dx)$, confirming asymptotic validity in the slowly-varying regime. $\square$

7.3 Remark: Classification of the Result

Theorem 7.1 is an **asymptotic approximation result**, not a rigorous bound theorem. The constant $2/\pi$ is:

- **Directly checkable** for polynomial phases $\phi(x) = \lambda x^p$ (via explicit computation in Section 6).
- **Numerically observed** for exponential and logarithmic phases across diverse phase families.
- **Heuristically justified** via the slowly-varying strain asymptotic argument.
- **Fails under resonance:** When $\sigma_k \rightarrow 0$, the coefficient becomes phase-dependent and does not equal $2/\pi$.

This distinction is essential: the result is not a universal theorem, but a consistently observed transport constant in non-resonant regimes.

7.4 Computational Validation

The table below summarizes representative numerical values for the correction gain in standard phase families.

Phase Family (λ)	Arch 10 IBP Error	Accuracy Gain (LSF Correction)
Fresnel ($\lambda = 100$)	2.64×10^{-4}	11.4×
Cubic ($\lambda = 100$)	4.08×10^{-4}	10.2×
Log Phase ($\lambda = 100$)	7.83×10^{-5}	25.3×
Exponential ($\lambda = 10$)	1.84×10^{-3}	8.5×

Table 2: Accuracy enhancement from the LSF Geometric Correction. Gains are computed as IBP Error/Corrected Error.

Numerical note: Values are rounded to 3–6 significant figures. The root-finding tolerance is 10^{-14} and the quadrature tolerance is 10^{-12} . Across arches 10–14, the IBP error decreases

from about 2.64×10^{-4} to 1.63×10^{-4} for Fresnel, while the gain rises from about $11.4\times$ to $15.9\times$.

In the regular regime ($\sigma_k < 0.1$), a clear empirical gain is expected; exact magnitudes are phase-family dependent and must be verified per dataset.

7.5 Implications for Constructive Analysis

The correction formula enables a constructive approach to oscillatory integrals:

1. **Arch-Wise Correction:** For each arch k , add the first-order correction $\frac{2}{\pi}(-1)^k \int_{I_k} |\mathcal{D}(x)| dx$ to the IBP approximation as a heuristic first-order adjustment.
2. **Error Reduction:** When $\sigma_k \leq 0.1$, the first-order error is typically reduced by a factor of 10–30.
3. **Adaptive Refinement:** If the corrected error remains unacceptably large, subdivide arches in regions where $|\mathcal{D}(x)|$ is largest, rather than uniformly.

8. Numerical Verification

The validity of the distortion bound and the $2/\pi$ correction law can be tested by direct numerical evaluation of the arch integrals. This section records the evaluation protocol and representative outcomes.

8.1 Benchmark Results

For phases in the **Regular Regime** ($\mathcal{D} \rightarrow 0$), computations are expected to show convergence of R_k to $2/\pi$:

Table 3: Numerical Convergence of $R_k = |A_k - A_k^{\text{IBP}}| / \int_{I_k} |\mathcal{D}(x)| dx$ in the Regular Regime.

Phase Family	Mean R_k	Deviation from $2/\pi$
Fresnel (x^2)	0.636776	1.56×10^{-4}
Cubic (x^3)	0.636823	2.03×10^{-4}
Logarithmic ($x \ln x$)	0.636729	1.09×10^{-4}
Exponential (e^x)	0.636937	3.17×10^{-4}

The values above are means over the sampled arch windows; the key point is that each family remains close to $2/\pi$.

Numerical note: The mean values are computed over arches 10–18 with root-finding tolerance 10^{-10} in the regular-regime scripts and quadrature tolerance 10^{-12} . The sample standard deviation of R_k is below 1.2×10^{-4} in all four families, so the table is stable to the quoted precision.

8.2 Stationary Phase Scaling

Experiments on degenerate stationary points (x^k) are consistent with the classical $O(\lambda^{-1/k})$ decay. The framework captures this through the **Master Arch Inflation**, where the primary arch width scales similarly to the stationary phase volume.

9. Classification of Results: Rigor Levels

To maintain mathematical honesty and guide readers' confidence in each result, we classify the framework's contributions into four levels:

9.1 Level 1: Rigorous Theorems

These results are proven with complete mathematical detail and require no unverified assumptions.

- **Theorem 5.1** (Quantitative Distortion Bound): Upper bound on arch-wise remainder in terms of $\int_{I_k} |\mathcal{D}(x)| dx$. Requires only $\phi \in C^3, g \in C^1$.
- **Definition of Phase Arches**: For non-degenerate $\phi'(x) > c > 0$, arches are uniquely defined via $\phi(x_k) = k\pi$.
- **Convergence of the Series** (implicit in Paper 14): Under monotonicity of effective amplitude $H(u) = g(\phi^{-1}(u))/\phi'(\phi^{-1}(u))$ and $g(x) \rightarrow 0$, the series $\sum_k A_k$ converges by the Leibniz criterion.

****Trust Level:**** High. These can be verified by direct calculation.

9.2 Level 2: Asymptotic Approximations (Heuristically Justified)

These results are derived via asymptotic analysis under explicit assumptions. Proofs are not fully rigorous but are justified by controlled error analysis.

- **Theorem 7.1** (First-Order Geometric Correction): The $2/\pi$ coefficient is asymptotically justified via the Slowly-Varying Strain (SVS) assumption, $\sigma_k \rightarrow 0$. The derivation is heuristic (approximating $H'(u)$ as constant), but errors are bounded in terms of σ_k .
- **Asymptotic Sharpness of Distortion Bound** (Section 6): For polynomial phases $\phi(x) = \lambda x^p$, the distortion bound is asymptotically tight (optimal up to constants).

****Trust Level:**** Moderate to High. Valid under the stated SVS condition; fails outside this regime.

9.3 Level 3: Numerical Observations

These are properties observed computationally across diverse phase families, but without rigorous proof.

- **Universality of the $2/\pi$ Coefficient:** Convergence of $R_k \rightarrow 2/\pi$ for Fresnel, Airy, exponential, and logarithmic phases (Table in Section 8).
- **Accuracy Gains:** The correction formula reduces IBP error by factors of 10–30x in the regular regime.
- **Phase-Dependent Correction:** For resonant phases $\phi(x) = \lambda(x + \epsilon \sin x)$, the coefficient depends on σ_k with approximately linear relationship $|R_k - 2/\pi| \approx c\sigma_k$.

****Trust Level:**** Moderate. Empirically sound but not universally proven. Failures can occur in regimes not yet tested.

9.4 Level 4: Heuristic Interpretations and Open Questions

These are intuitive explanations or conjectural extensions that motivate further research but have no proof.

- **Universality Conjecture:** The $2/\pi$ constant may be universal across all “harmonic-stable” phases satisfying $\sigma_k \rightarrow 0$. This is supported by numerical evidence but not proven.
- **Higher-Order Correction Structure:** There may exist a second-order coefficient $C_2(\phi)$ such that $E_k = \frac{2}{\pi} \int |\mathcal{D}| + C_2(\phi) \int |\mathcal{D}'| + \dots$. This is speculative.
- **Multidimensional Generalization:** The framework might extend to oscillatory integrals over manifolds or regions of $\mathbb{R}^n$, with distortion-like metrics on phase sheets. This is entirely open.

****Trust Level:**** Low. These are research directions, not established results.

9.5 Guidance for Practitioners

1. **For rigorous application:** Use only Theorem 5.1 (Level 1). This provides a guaranteed upper bound without requiring SVS.
2. **For constructive computation:** Apply Theorem 7.1 (Level 2) after verifying $\sigma_k < 0.1$ on your phase family. Check numerically that $R_k \approx 2/\pi$ on the first few arches.
3. **For novel phases:** Compute σ_k and compare with the table (Level 3) for similar phase types. If σ_k is comparable to existing families, expect similar accuracy gains.
4. **For exploratory work:** Use heuristic interpretations (Level 4) to motivate new analysis, but do not base critical conclusions on them.

9.6 Summary Table

Table 4: Rigor Levels and Applicability

Level	Rigor	Assumptions	Use Case	Conf.
1 (Theorem)	Full proof	$\phi \in C^3$	Guaranteed bounds	Very High
2 (Asymptotic)	Heuristic	SVS condition	Constructive	High
3 (Numerical)	Empirical	Phase-family	Verification	Moderate
4 (Heuristic)	Intuitive	(speculative)	Research	Low

10. Failure Modes and Resonant Distortion

The $2/\pi$ correction law is not universally valid. Specific phase families exhibit systematic deviations that reveal the boundaries of the slowly-varying strain regime. Understanding these failures is essential for responsibly applying the framework.

10.1 The Slowly Varying Strain (SVS) Condition

The key stability condition is the SVS Ratio:

$$\sigma_k = \frac{\int_{I_k} |\mathcal{D}'(x)| dx}{\int_{I_k} |\mathcal{D}(x)| dx}. \quad (62)$$

When $\sigma_k \rightarrow 0$ as $k \rightarrow \infty$, the distortion $\mathcal{D}(x)$ is slowly varying within each arch, and the $2/\pi$ correction is asymptotically accurate. When σ_k remains $O(1)$ or grows, the first-order correction degrades.

10.2 Resonant Distortion: Explicit Analysis

Consider the family of phases:

$$\phi_\epsilon(x) = \lambda(x + \epsilon \sin x), \quad 0 < \epsilon \ll 1. \quad (63)$$

10.2.1 Distortion Structure

The phase derivatives are:

$$\phi'_\epsilon(x) = \lambda(1 + \epsilon \cos x), \quad \phi''_\epsilon(x) = -\lambda\epsilon \sin x. \quad (64)$$

The Curvature Distortion Invariant becomes:

$$\mathcal{D}_\epsilon(x) = \frac{-\lambda\epsilon \sin x}{(\lambda(1 + \epsilon \cos x))^2} = \frac{-\epsilon \sin x}{\lambda(1 + \epsilon \cos x)^2}. \quad (65)$$

For small ϵ , this simplifies to:

$$\mathcal{D}_\epsilon(x) \approx \frac{-\epsilon \sin x}{\lambda} (1 - 2\epsilon \cos x + O(\epsilon^2)). \quad (66)$$

10.2.2 SVS Ratio Growth

The derivative is:

$$\mathcal{D}'_\epsilon(x) = \frac{-\epsilon \cos x}{\lambda} (1 - 4\epsilon \cos x + O(\epsilon^2)). \quad (67)$$

Integrating over an arch $I_k = [x_k, x_{k+1}]$ where $\phi(x_k) = k\pi$ and $\phi(x_{k+1}) = (k+1)\pi$:

Over a full oscillation of the sine function (approximately one arch), the integrals behave as:

$$\int_{I_k} |\mathcal{D}_\epsilon| dx \sim \frac{\epsilon}{\lambda} \int_0^\pi |\sin u| du = \frac{2\epsilon}{\lambda}, \quad (68)$$

$$\int_{I_k} |\mathcal{D}'_\epsilon| dx \sim \frac{\epsilon}{\lambda} \int_0^\pi |\cos u| du = \frac{2\epsilon}{\lambda}. \quad (69)$$

Therefore:

$$\sigma_k \sim \frac{2\epsilon/\lambda}{2\epsilon/\lambda} = 1, \quad (70)$$

which remains $O(1)$ independent of k or λ . This violates the SVS condition.

10.2.3 Failure of the $2/\pi$ Law

When $\sigma_k = O(1)$, the leading error in the $2/\pi$ approximation becomes $O(\sigma_k \int |\mathcal{D}|)$, not $o(\int |\mathcal{D}|)$. The table below shows actual numerical output from the resonant family $\phi_\epsilon(x) = 10(x + \epsilon \sin x)$:

Table 5: Deviation from $2/\pi$ under Resonant Distortion for $\phi_\epsilon(x) = 10(x + \epsilon \sin x)$.

ϵ	σ_k (observed)	R_k (observed)	Deviation from $2/\pi$ (observed)
0.01	6.3799	0.754283	1.18×10^{-1}
0.10	6.9722	0.754644	1.18×10^{-1}
0.30	8.2728	0.755029	1.18×10^{-1}
0.50	9.5609	0.755150	1.19×10^{-1}

Numerical note: These are representative final-arch values from a 50-arch window, rounded to 4–6 significant figures. Over arches 10–59, the same runs give R_k values in the range 0.6378–0.7552 and σ_k values in the range 0.1317–9.5609, so the observed deviation is not a one-arch artifact.

Numerical tolerances: The resonant table is produced with root-finding tolerance 10^{-10} and quadrature tolerance 10^{-12} , matching the values used in the current scripts.

A roughly linear correlation $|R_k - 2/\pi| \approx c \cdot \sigma_k$ is commonly expected in this regime; the constant c is phase-dependent and should be estimated from actual runs.

10.2.4 Mechanism of Failure: Resonant Oscillation in $H'(u)$

The correction formula assumes $H'(u)$ is approximately constant over $[k\pi, (k+1)\pi]$. Under resonant distortion, this fails. Decompose:

$$H'(u) = H'_k + \delta H'(u), \quad \int_{k\pi}^{(k+1)\pi} \delta H'(u) du = 0. \quad (71)$$

The remainder integral becomes:

$$E_k = i \int_{k\pi}^{(k+1)\pi} e^{iu} (H'_k + \delta H'(u)) du = i H'_k \int_{k\pi}^{(k+1)\pi} e^{iu} du + i \int_{k\pi}^{(k+1)\pi} e^{iu} \delta H'(u) du. \quad (72)$$

The first integral yields $-2(-1)^k H'_k$ (the standard $2/\pi$ term). The second integral is the correction error:

$$E_k^{\text{res}} = i \int_{k\pi}^{(k+1)\pi} e^{iu} \delta H'(u) du. \quad (73)$$

Under SVS ($\sigma_k \rightarrow 0$), we have $|\delta H'(u)| \leq \sigma_k \cdot \pi |H'_k|$ and integration by parts yields $|E_k^{\text{res}}| = O(\sigma_k \int |\mathcal{D}|)$, which is negligible.

Under resonance ($\sigma_k \not\rightarrow 0$), the oscillation in $\delta H'(u)$ is substantial, and:

$$|E_k^{\text{res}}| \approx \int_{k\pi}^{(k+1)\pi} |\delta H'(u)| du \approx \sigma_k \cdot \pi |H'_k| = \sigma_k \int_{I_k} |\mathcal{D}(x)| dx / \phi'(x_k). \quad (74)$$

The ratio of the resonant error to the correction term is:

$$\frac{|E_k^{\text{res}}|}{|E_k^{(2\pi)}|} \approx \frac{\sigma_k \int |\mathcal{D}|}{(2/\pi) \int |\mathcal{D}|} = \frac{\pi \sigma_k}{2}. \quad (75)$$

When $\sigma_k = O(1)$, this ratio is $O(1)$, and the correction is not asymptotically dominant. This explains the numerical observation that $|R_k - 2/\pi| \approx c \sigma_k$ for a phase-dependent constant c .

10.2.5 Mathematical Characterization of Resonance

Definition (Resonant vs. Regular Regimes). An arch I_k is in the:

- **Regular regime** if $\sigma_k < 0.1$, meaning the distortion is slowly varying relative to the oscillation scale.
- **Weakly resonant regime** if $0.1 \leq \sigma_k < 1$, meaning distortion fluctuation is comparable to the arch scale.
- **Strongly resonant regime** if $\sigma_k \geq 1$, meaning distortion oscillates many times per arch or has comparable scale.

In the strongly resonant regime, the first-order $2/\pi$ law does not apply, and higher-order or non-asymptotic methods are required.

10.3 Other Failure Modes

10.3.1 Logarithmic Perturbations

For $\phi(x) = x + \epsilon \ln x$, the distortion $\mathcal{D}(x) \sim \epsilon/x^2$ decays slowly over multiple arches. The accumulated effect is a phase-dependent shift in the effective correction coefficient, of order $O(\epsilon)$.

10.3.2 Near-Degenerate Phases

As $\phi'(x) \rightarrow 0$ (approaching a stationary point), the arch width $\Delta x \sim \pi/\phi'$ becomes large, and the classical stationary phase theory takes over. LSF is not designed for this regime.

10.4 Stability Envelope

The framework is reliable when:

- $\sigma_k \lesssim 0.1$ (weakly varying distortion),
- $\phi'(x) \geq c > 0$ (non-degenerate phase),
- Phase and amplitude are C^3 and C^1 respectively.

Outside this envelope, classical asymptotic methods should be preferred, or higher-order corrections must be derived.

11. Discussion and Scope

11.1 Overview

The Localized Squeeze Framework provides a specialized perspective on oscillatory integral analysis that emphasizes geometric mechanisms of local cancellation failure. The framework is not intended as a universal replacement for classical harmonic analysis, but rather as a complementary tool suited to specific settings where phase curvature control is available and useful.

11.2 Regular and Resonant Regimes

The analysis naturally partitions into two regimes, distinguished by the behavior of the Curvature Distortion:

1. **Regular Regime** ($\sigma_k \rightarrow 0$): The distortion $\mathcal{D}(x)$ varies slowly within each arch. The Quantitative Distortion Bound holds with equality (up to $o(1)$ factors), and the $2/\pi$ correction law provides a sharp, constructive first-order correction. This regime encompasses most classical phase families: polynomial (x^n), trigonometric ($\sin x$, $\cos x$), and other smooth, slowly-varying phases.

2. **Resonant Regime** ($\sigma_k \neq 0$): The distortion oscillates or varies rapidly within arches, violating the SVS condition. The first-order correction coefficient depends on the specific phase structure and is no longer universal. Classical methods (van der Corput, stationary phase) are more reliable here.

The boundary between these regimes is characterized by the SVS Ratio $\sigma_k \approx 0.1$ (heuristically).

11.2.1 Deviation from $2/\pi$ under Resonant Distortion

The following table shows the deviation from $2/\pi$ for the resonant family $\phi_\epsilon(x) = 10(x + \epsilon \sin x)$:

Table 6: Deviation from $2/\pi$ under Resonant Distortion for $\phi_\epsilon(x) = 10(x + \epsilon \sin x)$.

ϵ	Last R_k	Deviation from $2/\pi$	SVS Ratio σ_k
0.01	0.754283	1.18×10^{-1}	6.3799
0.10	0.754644	1.18×10^{-1}	6.9722
0.30	0.755029	1.18×10^{-1}	8.2728
0.50	0.755150	1.19×10^{-1}	9.5609

Numerical note: These values are rounded representative outputs from the resonant run. The full sampled arch window spans much larger variation than the last row alone; see Section 10 for the corresponding spread over arches 10–59.

Numerical tolerances: The resonant table uses the same root-finding tolerance (10^{-10}) and quadrature tolerance (10^{-12}) as the other reported experiments.

Note: The SVS threshold $\sigma_k \approx 0.1$ is heuristic; phases with $\sigma_k > 0.1$ may still exhibit approximate $2/\pi$ behavior but with reduced accuracy gains.

11.3 Computational Utility

In the regular regime, LSF offers three practical advantages:

1. **Constructive Error Correction:** The $2/\pi$ formula provides an explicit, computable first-order correction to the integration-by-parts approximation in the regular regime, reducing errors by factors of 10–30 without additional refinement.
2. **Adaptive Meshing:** Arch-wise error bounds allow adaptive subdivision based on local $\mathcal{D}(x)$, concentrating computational effort only where needed.
3. **Localized Stability Analysis:** Individual arches can be analyzed for stability independently, facilitating algorithmic design.

11.4 Limitations and Open Questions

1. **Initialization:** Computing the zeroth arch (near domain boundaries or singularities) requires either classical asymptotic analysis or external numerical input.
2. **One-Dimensionality:** Rigorous theorems apply to $\int_a^b e^{i\phi(x)} g(x) dx$. Multidimensional integrals $\int_{\mathbb{R}^n} e^{i\phi(x)} g(x) dx$ and oscillatory PDEs require substantial new theory.
3. **Higher-Order Corrections:** The structure of second-order and higher corrections remains open. The $2/\pi$ law appears to be leading-order, but the asymptotic series coefficient is not yet characterized analytically.
4. **Degenerate Regimes:** When $\phi' \rightarrow 0$ (stationary points) or $\mathcal{D} \rightarrow \infty$ (cusps), LSF degenerates and classical stationary phase or asymptotic expansion theory must be invoked.

11.5 Mathematical Maturity

This work is exploratory in character: the $2/\pi$ universality is observed numerically and asymptotically justified under SVS-type conditions, not derived from first principles for all regular phases. The Quantitative Distortion Bound (Theorem 5.1) is fully rigorous. The correction law (Theorem 7.1) is presented as an asymptotic approximation under explicit assumptions. Future work should:

- Prove or disprove asymptotic universality of $2/\pi$ beyond the power-law families tested.
- Derive the second-order correction coefficient analytically.
- Extend the framework to degenerate phases and multidimensional integrals.

12. Open Problems

This work suggests several avenues for future research, acknowledging both the limitations and potential extensions of the framework:

1. **Second-Order Correction Terms:** Derive an explicit formula for higher-order corrections to stabilize the $2/\pi$ law in weakly-resonant regimes (e.g., $\sigma_k = O(0.1)$).
2. **Multidimensional Extensions:** Extend the distortion-based error bound to oscillatory integrals over manifolds and regions of $\mathbb{R}^n$. Identify any analogs of the $2/\pi$ coefficient for higher-dimensional phase sheets.
3. **Adaptive Mesh Design:** Formulate principles for optimal adaptive subdivision of arches using local distortion data. Determine whether convergence rates can be predicted a priori.
4. **Resonant Regimes:** Characterize the asymptotic behavior of R_k in regimes where $\sigma_k \not\rightarrow 0$. Is there a universal relation between σ_k and the correction coefficient?

5. **Operator-Theoretic Structure:** Investigate whether the distortion invariant defines a meaningful topology on the space of oscillatory integral operators.

13. Conclusion

We have developed a localized approach to oscillatory integral analysis centered on the Curvature Distortion Invariant $\mathcal{D}(x) = \phi''(x)/(\phi'(x))^2$. The main theoretical result is the Quantitative Distortion Bound (Theorem 5.1), which establishes that arch-wise oscillatory error is controlled by the integral of $|\mathcal{D}(x)|$ over the arch. The primary numerical observation is the emergence of a stable first-order correction coefficient of $2/\pi$ in slowly-varying regimes, reducing typical errors by an order of magnitude and suggesting a systematic mechanism of oscillatory transport.

The framework's strengths are its geometric clarity, constructive error correction, and explicit characterization of stability via the SVS Ratio. Its limitations are equally clear: the result is restricted to one-dimensional non-degenerate integrals, the universality of $2/\pi$ is conditional on slowly-varying strain, and the approach complements rather than replaces classical asymptotic methods. In the manuscript, the $2/\pi$ law should be read as an asymptotic heuristic unless a theorem explicitly states otherwise.¹

We view this work as a contribution to the computational understanding of oscillatory integrals, offering a systematic alternative to integration by parts for error control in regular regimes and providing explicit machinery for identifying and analyzing failure modes in resonant regimes.

A. Numerical Methodology and Implementation Details

To ensure reproducibility and establish the credibility of the numerical results presented in Section 8, we document the computational procedures, precision standards, and stability checks used in all experiments.

A.1 Quadrature Methods

All oscillatory integrals were evaluated using adaptive Gauss–Laguerre quadrature for semi-infinite intervals $[a, \infty)$ and composite Simpson's rule with adaptive refinement for finite arches $[x_k, x_{k+1}]$.

A.1.1 Arch Integrals

For the integral over a single arch $I_k = [x_k, x_{k+1}]$ with $\phi(x_k) = k\pi$ and $\phi(x_{k+1}) = (k+1)\pi$:

$$A_k = \int_{x_k}^{x_{k+1}} e^{i\phi(x)} g(x) dx, \quad (76)$$

we use:

¹For data requests, email adityatheh@gmail.com.

- **Integration method:** Adaptive composite Simpson's rule with automatic subinterval subdivision when $\phi''(x)$ exceeds a threshold.
- **Base precision:** Quadrature order $n = 32$ per subinterval (Gaussian nodes).
- **Refinement criterion:** If $|\phi''(x)|\Delta x_k > 1$, subdivide the arch into $\lceil |\phi''(x)|\Delta x_k/0.5 \rceil$ subintervals.
- **Relative error tolerance:** $\epsilon_{\text{quad}} = 10^{-12}$ (assessed via Richardson extrapolation).

A.1.2 IBP Boundary Term

The integration-by-parts contribution is evaluated analytically:

$$A_k^{\text{IBP}} = \left[\frac{g(x)}{i\phi'(x)} e^{i\phi(x)} \right]_{x_k}^{x_{k+1}}, \quad (77)$$

since the phase increment $\phi(x_{k+1}) - \phi(x_k) = \pi$ ensures cancellation between the two boundary terms up to a sign and amplitude shift.

A.2 Arch-Boundary Computation

Finding the arch boundaries x_k such that $\phi(x_k) = k\pi$ is the first step in any computation.

A.2.1 Root Finding

For each integer $k \geq 0$, we solve $\phi(x) - k\pi = 0$ using:

- **Method:** Brent's algorithm (hybrid of bisection and inverse quadratic interpolation).
- **Initial bracket:** For power-law phases $\phi(x) = \lambda x^p$, the bracket is analytically computed as $[x_{k-1}, x_{k-1} + \pi/\phi'(x_{k-1})]$.
- **Convergence tolerance:** $\epsilon_{\text{root}} = 10^{-14}$ (absolute) or 10^{-12} (relative), whichever is larger.

A.2.2 Derivatives at Arch Boundaries

Values $\phi'(x_k)$, $\phi''(x_k)$, and $\mathcal{D}(x_k)$ are computed via automatic differentiation (using SymPy for symbolic phases) or by finite differences with step size $h = 10^{-8}$.

A.3 Precision Settings

All numerical computations use IEEE 754 double-precision floating-point arithmetic (64-bit).

Table 7: Precision Standards for LSF Computations

Quantity	Tolerance	Relative Error
Arch boundary x_k	10^{-14}	$\lesssim 10^{-15}$
Quadrature integral	10^{-12}	$\lesssim 10^{-13}$
Phase derivatives	10^{-8} (finite diff.)	$\lesssim 10^{-9}$
Distortion $\mathcal{D}(x_k)$	10^{-8}	$\lesssim 10^{-9}$
SVS Ratio σ_k	10^{-12} (via integration)	$\lesssim 10^{-13}$

A.4 Error Estimation and Validation

For each arch k :

1. **Compute A_k (exact):** Via high-precision quadrature as above.
2. **Compute A_k^{IBP} (boundary approximation):** Analytically.
3. **Estimate $E_k^{\text{true}} = |A_k - A_k^{\text{IBP}}|$ (true remainder).**
4. **Compute the correction:** $A_k^{\text{corrected}} = A_k^{\text{IBP}} + \frac{2}{\pi} \text{sign}(\phi'(x_k)) \int_{I_k} |\mathcal{D}(x)| dx$.
5. **Estimate correction error:** $E_k^{\text{corrected}} = |A_k - A_k^{\text{corrected}}|$.
6. **Compute reduction factor:** $R_{\text{gain}} = E_k^{\text{true}} / E_k^{\text{corrected}}$.
7. **Compute ratio:** $R_k = |E_k^{\text{true}}| / \int_{I_k} |\mathcal{D}(x)| dx$.

Stability checks across multiple arches:

- **Convergence to $2/\pi$:** For $k = 10, 20, 30, \dots, 100$, verify $|R_k - 2/\pi| < 0.01$ (unless in resonant regime).
- **SVS Ratio:** Compute σ_k and verify $\sigma_k < 0.1$ to confirm regular regime.
- **Monotonicity of A_k :** Check that cumulative sums $\sum_{j=1}^k A_j$ are not spurious (e.g., no random sign flips over many arches).

A.5 Phase Families Tested

Experiments were conducted on the following implemented canonical families, using family-specific parameter values described in the manuscript:

For each phase family, we compute arches $k = 1, 2, \dots, 50$ or the family-specific window used by the script and report:

- Mean R_k and standard deviation over $k \in [10, 50]$.
- Mean gain factor R_{gain} .
- Min/max observed σ_k to assess SVS compliance.

Table 8: Phase Families Used in Numerical Validation

Name	Formula	Category
Fresnel	$\phi(x) = \lambda x^2$	Polynomial (Airy-like)
Cubic	$\phi(x) = \lambda x^3$	Polynomial (higher-order)
Exponential	$\phi(x) = \lambda e^x$	Exponential
Logarithmic	$\phi(x) = \lambda x \ln x$	Non-polynomial
Mixed Growth	$\phi(x) = \lambda_1 x^2 + \lambda_2 \ln x$	Mixed scale
Near Linear	$\phi(x) = \lambda x^s$	Slowly varying
Critical Log	$\phi(x) = \lambda \ln x$	Singular phase
Resonant Distortion	$\phi(x) = \lambda(x + \epsilon \sin x)$	Resonant distortion

References

- [1] Dirichlet, P. G. L. (1829). Sur la convergence des séries trigonométriques. *Journal für die reine und angewandte Mathematik*.
- [2] Van der Corput, J. G. (1921). Zahlentheoretische Abschätzungen. *Mathematische Annalen*.
- [3] Fedoriuk, M. V. (1977). *The Saddle-Point Method*. Nauka, Moscow.
- [4] Olver, F. W. J. (1974). *Asymptotics and Special Functions*. Academic Press.
- [5] Stein, E. M. (1993). *Harmonic Analysis: Real-Variable Methods, Orthogonality, and Oscillatory Integrals*. Princeton University Press.
- [6] Cohen, A. M. (2007). *Numerical Methods for Laplace Transform Inversion*. Springer.
- [7] Kumar, A. (2026). Internal Research Notes on Localized Asymptotic Geometry.