

**EMBEDDED SYSTEM DESIGN FOR BLOOD GLUCOSE
MEASUREMENT**

A PROJECT REPORT

Submitted by

NASMIN M	(611223114063)
SANGEETHA D	(611223114083)
DHARSHANKUMAR S	(611223114021)
ADITHYAN K G	(611223114001)

in partial fulfilment for the award the degree of

BACHELOR OF ENGINEERING

IN

MECHANICAL ENGINEERING

KNOWLEDGE INSTITUTE OF TECHNOLOGY,

SALEM

ANNA UNIVERSITY: CHENNAI 600 025

Jun 2026

BONAFIDE CERTIFICATE

Certified that this project report entitled "**EMBEDDED SYSTEM DESIGN FOR BLOOD GLUCOSE MEASUREMENT**" is the bonafide work carried out by **Nasmin M, Sangeetha D, Dharshankumar S, and Adithyan K G** in partial fulfillment of the requirements for the award of the degree of **Bachelor of Engineering in Mechanical Engineering** under Anna University, Chennai, during the academic year **2026–2027**, under our supervision.

SIGNATURE

Dr. K. S. PRABHARAAN, M.E., Ph.D.

HEAD OF THE DEPARTMENT

PROFESSOR

DEPARTMENT OF MECHANICAL

ENGINEERING

KNOWLEDGE INSTITUTE OF

TECHNOLOGY, KIOT CAMPUS

KAKAPALAYAM (P.O.) SALEM–637504

SIGNATURE

Prof S. NAVEENKUMAR, M.E., (Ph.D.)

SUPERVISOR

ASSISTANT PROFESSOR

DEPARTMENT OF MECHANICAL

ENGINEERING

KNOWLEDGE INSTITUTE OF

TECHNOLOGY, KIOT CAMPUS

KAKAPALAYAM (P.O.) SALEM –637504

ABSTRACT

Invasive glucose monitoring is a clinically established technique used for accurate measurement of blood glucose levels, playing a vital role in the diagnosis and long-term management of diabetes mellitus. This method involves direct access to the bloodstream or interstitial fluid through finger-stick blood sampling or implantable and minimally invasive continuous glucose monitoring (CGM) sensors. These sensors typically utilize electrochemical detection principles, where glucose oxidase-based reactions generate electrical signals proportional to glucose concentration. Invasive glucose monitoring systems provide high precision, continuous real-time data, and trend analysis, enabling patients and healthcare providers to make informed decisions regarding insulin administration, dietary planning, and lifestyle management. However, the technique presents challenges such as pain, tissue damage, infection risk, and user non-compliance due to repeated skin penetration and sensor maintenance. Technological advancements, including micro-needle sensors, improved biocompatible coatings, and wireless data transmission, have significantly enhanced system performance, accuracy, and patient comfort. Despite ongoing research into non-invasive alternatives, invasive glucose monitoring remains the gold standard for reliable glucose measurement in clinical practice.

S. No.	CONTENTS	PAGE NO.
	ABSTRACT	i
	LIST OF TABLES	vii
	LIST OF FIGURES	vii
	LIST OF ABBREVIATIONS	ix
	LIST OF NOMENCLATURE	xi
1	CHAPTER 1 – INTRODUCTION	1
1.1	Project Background	2
1.2	Background of Diabetes Mellitus	3
1.3	Importance of Self-Monitoring of Blood Glucose (SMBG)	4
1.4	Evolution of Blood Glucose Monitoring	4
1.5	Problem Statement	6
1.6	Objectives of the Project	6
1.7	Scope of the Project	7

2	CHAPTER 2 – LITERATURE REVIEW	9
2.1	Literature Survey Methodology	9
2.2	Review of Finger-Prick Glucose Meters	11
2.3	Review of Continuous Glucose Monitoring Systems	12
2.4	Accuracy Standards and Validation Studies	13
2.5	Signal Conditioning and Electronics in Literature	14
3	CHAPTER 3 – COMPONENTS, SPECIFICATION AND DESCRIPTION	15
3.1	Components	15
3.2	Components Description	16
3.2.1	Arduino UNO (ATmega328p)	17
3.2.2	Arduino Proto Shield	17
3.2.3	Glucose Test Strip	18
3.2.4	Operational Amplifier (LM358)	19
3.2.5	Precision Resistors	20

3.2.6	Capacitors	21
3.2.7	OLED Display	22
3.2.8	Push Button Switch	22
3.2.9	Power ON/OFF Toggle Switch	23
3.2.10	Li-ion Battery (3.7 V)	24
3.2.11	TP4056 Charging Module	25
3.2.12	Boost Converter	26
3.2.13	Jumper Wires / Hook-up Wires	26
3.2.14	Soldering Kit & PCB Accessories	28
4	CHAPTER 4 – WORKING PRINCIPLE	29
4.1	Overview of Blood Glucose Measurement	29
4.2	Physiological Basis of Glucose Detection	31
4.3	Signal Conditioning and Data Acquisition	32
4.4	Signal Processing and Calibration	33
4.5	System Workflow	34

4.6	Summary of the Working Principle	35
5	CHAPTER 5 – COST ESTIMATION	36
5.1	Introduction	36
5.2	Cost Analysis	36
5.3	Economic Feasibility	37
5.4	Cost Summary	38
6	CHAPTER 6 – RESULTS AND SYSTEM OUTPUTS	39
6.1	Prototype Output	39
6.2	OLED Display Output	40
6.3	Performance Discussion	40
7	CHAPTER 7 – SCOPE OF FUTURE WORK	42
8	CHAPTER 8 – APPENDICES	43
8.1	Prototype Photographs	43
8.2	Complete Hardware Integration	45

8.3	Summary	46
9	CHAPTER 9 – CONCLUSION	47
10	CHAPTER 10 – REFERENCES	48

LIST OF TABLES

TABLE NO.	TITLE
--------------	-------

Table 2.1	Literature Survey Methodology
-----------	-------------------------------

Table 3.1	Hardware Components Used in the Proposed System
-----------	--

Table 5.1	Cost Estimation of the Proposed Prototype
-----------	--

LIST OF FIGURES

FIGURE NO.	TITLE
Figure 3.2.1	Arduino UNO (ATmega328p)
Figure 3.2.2	Arduino Proto Shield
Figure 3.2.3	Glucose Test Strip
Figure 3.4	LM358 Operational Amplifier
Figure 3.5	Precision Resistors
Figure 3.6	Capacitors
Figure 3.7	OLED Display
Figure 3.8	Push Button Switch
Figure 3.9	Toggle Switch
Figure 3.10	Li-ion Battery
Figure 3.11	TP4056 Charging Module
Figure 3.12	DC-DC Boost Converter
Figure 3.13	Jumper Wires
Figure 3.14	PCB Accessories
Figure 4.1	Overall Working Block Diagram
Figure 4.2	Electrochemical Glucose Detection Process
Figure 4.3	Signal Conditioning and Data Acquisition

Figure 4.4	System Flowchart
Figure 6.1	Final Prototype of the Embedded Blood Glucose Measurement System
Figure 6.2	Prototype Connected with OLED Display
Figure 8.1	Developed Embedded Blood Glucose Measurement Prototype
Figure 8.2	Prototype Connected with OLED Display
Figure 8.3	Final Prototype Enclosure
Figure 8.5	Top View of the Prototype
Figure 8.5	Side View of the Prototype
Figure 8.6	Complete Hardware Integration of the Proposed Embedded Blood Glucose Measurement System

LIST OF ABBREVIATIONS

Abbreviation	Full Form
ADC	Analog-to-Digital Converter
AI	Artificial Intelligence
CGM	Continuous Glucose Monitoring
DC	Direct Current
GDH	Glucose Dehydrogenase
GOx	Glucose Oxidase

IC	Integrated Circuit
IDF	International Diabetes Federation
IoT	Internet of Things
I ² C	Inter-Integrated Circuit
LCD	Liquid Crystal Display
LM358	Low-Power Dual Operational Amplifier
MCU	Microcontroller Unit
ML	Machine Learning
OLED	Organic Light Emitting Diode
PCB	Printed Circuit Board
SMBG	Self-Monitoring of Blood Glucose
TIA	Transimpedance Amplifier
USB	Universal Serial Bus
WHO	World Health Organization

LIST OF NOMENCLATURE

Symbol / Term	Description
ADC	Analog-to-Digital Conversion process used to convert analog voltage into digital values
Blood Glucose (mg/dL)	Concentration of glucose present in the blood, expressed in milligrams per deciliter
Current (I)	Electrical current generated by the electrochemical reaction in the glucose test strip (A or μA)
Voltage (V)	Electrical potential produced after signal conditioning (Volts)
Resistance (R)	Opposition to the flow of electric current, measured in Ohms (Ω)
TIA	Transimpedance Amplifier used to convert sensor current into voltage
GOx	Glucose Oxidase enzyme used for electrochemical glucose detection
ADC Value	Digital output (0–1023) obtained from the Arduino Uno's 10-bit ADC
I²C	Serial communication protocol used between the Arduino Uno and OLED display
Calibration	Process of converting sensor output into the corresponding blood glucose value
Signal Conditioning	Amplification and filtering of the weak sensor signal before ADC conversion
Electrochemical Sensing	Method of measuring glucose based on an enzymatic electrochemical reaction
Microcontroller	Embedded controller (Arduino Uno) used for data acquisition and processing
OLED Display	Display module used to present the calculated blood glucose value
Power Supply	Electrical source used to operate the embedded system

CHAPTER 1

INTRODUCTION

Diabetes mellitus is one of the most prevalent chronic metabolic disorders affecting millions of people worldwide. It is characterized by elevated blood glucose levels resulting from inadequate insulin production, impaired insulin action, or a combination of both. According to the International Diabetes Federation (IDF), the global prevalence of diabetes continues to increase due to changes in lifestyle, dietary habits, obesity, and aging populations. Poorly controlled blood glucose levels can lead to severe complications such as cardiovascular diseases, kidney failure, nerve damage, vision impairment, and other life-threatening conditions.

Regular monitoring of blood glucose concentration plays a vital role in diabetes management. Self-Monitoring of Blood Glucose (SMBG) enables patients to monitor their glucose levels frequently and make informed decisions regarding insulin dosage, medication, diet, and physical activity. Conventional invasive glucose monitoring systems, which utilize disposable glucose test strips and electrochemical sensing techniques, remain the most reliable and widely accepted method due to their high accuracy and clinical validation.

Recent advancements in embedded systems, biomedical instrumentation, and microcontroller technology have enabled the development of compact, portable, and cost-effective glucose monitoring devices. Embedded systems provide real-time data acquisition, signal processing, and digital display of glucose values while reducing system complexity and power consumption. These technologies have significantly improved the accessibility and efficiency of glucose monitoring devices for both clinical and home healthcare applications.

The objective of this project is to design and develop an embedded system for blood glucose measurement using an Arduino Uno microcontroller, electrochemical glucose test strips, and analog signal conditioning circuitry. The proposed system converts the weak electrical current generated by the enzymatic reaction into a measurable voltage, processes the signal using the Arduino's Analog-to-Digital Converter (ADC), and displays the calculated blood glucose value on an OLED display. The prototype serves as an educational and research

platform for understanding biomedical sensing, embedded electronics, and digital signal processing while providing a foundation for future enhancements such as IoT connectivity, mobile health monitoring, and wireless communication.

1.1 Project Background

Diabetes has become one of the fastest-growing non-communicable diseases worldwide. The increasing number of diabetic patients has created a growing demand for reliable, portable, and affordable blood glucose monitoring systems. Conventional laboratory testing provides accurate results but is time consuming and unsuitable for frequent daily monitoring. Therefore, portable Self-Monitoring of Blood Glucose (SMBG) devices have become an essential part of diabetes management.

Modern blood glucose meters operate using electrochemical biosensors that convert the biochemical reaction between glucose and an enzyme into an electrical signal. This signal is processed by embedded electronic circuits to estimate blood glucose concentration accurately. The integration of embedded systems into biomedical devices has significantly improved portability, measurement speed, user convenience, and power efficiency.

This project focuses on developing a prototype embedded glucose monitoring system using commercially available components such as Arduino Uno, glucose test strips, operational amplifiers, and OLED displays. The system demonstrates the practical implementation of biomedical sensing, analog signal conditioning, microcontroller programming, and digital data processing

1.2 Background of Diabetes Mellitus

Diabetes mellitus is a chronic metabolic disorder characterized by elevated blood glucose levels resulting from defects in insulin secretion, insulin action, or both. Insulin is a hormone produced by the beta cells of the pancreas and is responsible for regulating the movement of glucose from the bloodstream into the body's cells, where it is utilized as a primary source of energy. When the body is unable to produce sufficient insulin or cannot effectively utilize the insulin produced, glucose accumulates in the bloodstream, leading to hyperglycemia.

Diabetes has become one of the most significant global public health challenges. According to the International Diabetes Federation (IDF), the number of people living with diabetes continues to rise due to population growth, urbanization, unhealthy dietary habits, physical inactivity, obesity, and genetic predisposition. If left untreated or poorly managed, diabetes can result in severe complications affecting multiple organs, including the heart, kidneys, eyes, nerves, and blood vessels.

Diabetes mellitus is generally classified into three major types:

Type 1 Diabetes Mellitus

Type 1 diabetes is an autoimmune disease in which the immune system mistakenly destroys the insulin producing beta cells of the pancreas. As a result, the body produces little or no insulin. Individuals with Type 1 diabetes require lifelong insulin therapy to maintain normal blood glucose levels. This condition commonly develops during childhood or adolescence but may occur at any age.

Type 2 Diabetes Mellitus

Type 2 diabetes is the most common form of diabetes, accounting for nearly 90–95% of all diabetes cases. It occurs when the body's cells become resistant to insulin or when the pancreas fails to produce sufficient insulin to meet the body's requirements. Risk factors include obesity, sedentary lifestyle, family history, unhealthy diet, aging, and hypertension. Type 2 diabetes can often be managed through lifestyle modifications, oral medications, and insulin therapy when necessary.

Gestational Diabetes Mellitus

Gestational diabetes develops during pregnancy due to hormonal changes that reduce insulin sensitivity. Although blood glucose levels usually return to normal after childbirth, women with gestational diabetes have an increased risk of developing Type 2 diabetes later in life. Proper monitoring and medical management during pregnancy are essential to ensure the health of both the mother and the baby.

The diagnosis and management of diabetes require regular monitoring of blood glucose levels. Maintaining glucose levels within the recommended range helps reduce the risk of complications and improves the quality of life of diabetic patients. Consequently, accurate, reliable, and portable blood glucose monitoring systems have become indispensable tools in both clinical practice and home-based healthcare.

1.3 Importance of Self-Monitoring of Blood Glucose (SMBG)

Self-Monitoring of Blood Glucose (SMBG) is an essential component of modern diabetes management. It enables individuals with diabetes to measure their blood glucose levels regularly using portable glucose meters without requiring laboratory testing. Frequent monitoring allows patients and healthcare professionals to evaluate the effectiveness of treatment plans, adjust insulin dosage, monitor dietary intake, and assess the impact of physical activity on blood glucose levels.

SMBG plays a significant role in preventing both short-term and long-term complications associated with diabetes. It helps detect episodes of hypoglycemia (low blood glucose) and hyperglycemia (high blood glucose) at an early stage, allowing timely corrective action. Regular monitoring also assists physicians in evaluating disease progression and optimizing therapeutic interventions.

Modern SMBG devices use disposable electrochemical glucose test strips that require only a small drop of capillary blood. The enzymatic reaction occurring within the test strip generates an electrical signal proportional to the glucose concentration. Embedded electronic circuits process this signal and display the blood glucose value within a few seconds. Due to their accuracy, portability, ease of use, and affordability, SMBG systems remain the most widely used blood glucose monitoring devices worldwide.

In this project, the principles of Self-Monitoring of Blood Glucose are implemented using an Arduinobased embedded system. The prototype demonstrates the acquisition of electrochemical sensor signals, analog signal conditioning, digital signal processing, and real-time display of glucose values, providing an effective educational platform for biomedical instrumentation and embedded system applications

1.4 Evolution of Blood Glucose Monitoring

The development of blood glucose monitoring technology has significantly improved diabetes management over the past several decades. Initially, blood glucose levels were measured only in clinical laboratories using biochemical analysis techniques. Although these methods provided accurate results, they required specialized laboratory equipment, trained personnel, and considerable processing time. Consequently, they were unsuitable for frequent monitoring by diabetic patients.

The introduction of portable blood glucose meters during the late 1970s and early 1980s revolutionized diabetes care. These devices employed disposable glucose test strips and electrochemical biosensors to measure blood glucose using a small capillary blood sample obtained through a finger prick. The biochemical reaction between glucose and the enzyme present on the test strip generated an electrical current proportional to the glucose concentration. The electronic circuitry within the glucose meter converted this signal into a digital glucose reading displayed within a few seconds.

Advancements in microelectronics and embedded systems further enhanced the performance of glucose monitoring devices. Modern glucose meters incorporate high-precision Analog-to-Digital Converters (ADCs), low-noise operational amplifiers, efficient power management circuits, and high-resolution display modules. These improvements have resulted in faster response times, improved accuracy, reduced power consumption, and compact device designs suitable for home and clinical use.

More recently, Continuous Glucose Monitoring (CGM) systems have emerged as an advanced alternative to conventional finger-prick testing. CGM devices use miniature sensors inserted beneath the skin to continuously measure glucose levels in the interstitial fluid. The collected data are transmitted wirelessly to smartphones or dedicated monitoring devices, enabling real-time glucose tracking, trend analysis, and automated alerts for abnormal glucose levels. Despite these advantages, CGM systems remain relatively expensive and require periodic sensor replacement.

Today, researchers are exploring next-generation glucose monitoring technologies, including noninvasive optical sensing, near-infrared spectroscopy, Raman spectroscopy, microwave sensing, wearable biosensors, and artificial intelligence-based predictive systems. These technologies aim to eliminate the need for finger-prick blood sampling while maintaining high accuracy and patient comfort. However, most non-invasive methods are still under research and have not yet achieved the clinical accuracy of electrochemical glucose monitoring systems.

The proposed project adopts the well-established electrochemical sensing approach because it offers reliable performance, high measurement accuracy, ease of implementation, and compatibility with embedded system design. By integrating an Arduino Uno microcontroller with signal conditioning circuitry and a glucose test strip, the project demonstrates the practical implementation of a portable blood glucose monitoring system suitable for educational and research applications.

1.5 Problem Statement

Diabetes mellitus requires regular blood glucose monitoring to maintain effective glycemic control and reduce the risk of long-term complications. Commercial blood glucose monitoring devices provide accurate results but are often expensive and function as closed proprietary systems, limiting opportunities for students and researchers to study their internal operation and hardware design.

Many educational institutions also lack affordable biomedical instrumentation platforms that demonstrate the principles of electrochemical sensing, analog signal conditioning, embedded programming, and digital data acquisition. As a result, engineering students have limited opportunities to gain practical experience in the development of medical diagnostic devices.

The primary problem addressed in this project is the design and implementation of a low-cost embedded blood glucose measurement system capable of acquiring the electrical signal generated by a glucose test strip, processing the signal using an Arduino Uno microcontroller, and displaying the glucose concentration on an OLED display. The project emphasizes educational

value while demonstrating the fundamental concepts of biomedical sensing, embedded electronics, and digital signal processing.

The developed prototype provides a practical platform for understanding blood glucose measurement techniques and serves as a foundation for future enhancements such as wireless communication, IoTbased health monitoring, cloud connectivity, and mobile healthcare applications.

1.6 Objectives of the Project

The primary objective of this project is to design and develop an embedded system for blood glucose measurement using electrochemical sensing technology and a microcontroller-based data acquisition system. The developed prototype aims to provide a simple, portable, and cost-effective platform for understanding the principles of biomedical instrumentation and embedded system design.

The specific objectives of this project are as follows:

- To design an embedded blood glucose monitoring system using the Arduino Uno microcontroller.
- To interface an electrochemical glucose test strip with analog signal conditioning circuitry for accurate signal acquisition.
- To amplify and process the weak electrical signal generated by the glucose test strip using an operational amplifier.
- To convert the analog sensor output into digital data using the built-in Analog-to-Digital Converter (ADC) of the Arduino Uno.
- To calculate and display the measured blood glucose value on an OLED display in real time.
- To develop a compact, portable, and user-friendly prototype suitable for educational and laboratory applications.
- To demonstrate the application of embedded systems in biomedical instrumentation.

- To provide a foundation for future enhancements such as wireless communication, IoT integration, cloud-based health monitoring, and mobile healthcare applications.

1.7 Scope of the Project

The scope of this project is limited to the design, development, and demonstration of an embedded blood glucose measurement system based on electrochemical sensing principles. The project focuses on integrating hardware components such as the Arduino Uno, glucose test strip interface, operational amplifier, OLED display, power supply module, and supporting electronic components into a functional prototype.

The developed system is capable of acquiring the electrical signal generated by the glucose test strip, processing the signal through analog conditioning circuits, converting it into digital form using the Arduino's Analog-to-Digital Converter (ADC), and displaying the corresponding blood glucose value on the OLED display. The prototype demonstrates the complete workflow of an embedded biomedical sensing system and serves as an educational tool for understanding glucose monitoring technology.

This project does not aim to replace commercially certified medical glucose meters and is not intended for clinical diagnosis or treatment. The prototype is developed primarily for academic learning, research, and demonstration purposes. Future improvements may include wireless data transmission, smart phone connectivity, cloud-based data storage, artificial intelligence-assisted analysis, continuous glucose monitoring, and enhanced calibration techniques to improve measurement accuracy and usability.

CHAPTER 2

LITERATURE REVIEW

The literature review provides an overview of the existing research, technologies, and methodologies related to blood glucose monitoring systems. It helps identify the strengths and limitations of current glucose measurement techniques and provides a foundation for developing an improved embedded system for blood glucose measurement. Various research papers, technical journals, medical standards, and commercial glucose monitoring technologies have been studied to understand recent developments in biomedical instrumentation and embedded healthcare systems.

Blood glucose monitoring has evolved significantly over the past few decades due to advances in biosensors, embedded electronics, microcontrollers, and wireless communication technologies. Researchers have focused on improving measurement accuracy, reducing response time, minimizing sample volume, enhancing portability, and integrating smart healthcare technologies. Electrochemical sensing remains the most widely adopted technique because of its high sensitivity, reliability, and relatively low implementation cost.

This chapter reviews previous work on finger-prick glucose meters, continuous glucose monitoring systems, signal conditioning circuits, embedded electronic design, and accuracy validation methods. The review also identifies research gaps that motivate the development of the proposed embedded blood glucose measurement system.

2.1 Literature Survey Methodology

A systematic literature survey was conducted to understand the existing technologies, design methodologies, and performance characteristics of blood glucose monitoring systems. The survey included peer-reviewed journal articles, conference proceedings, international standards, textbooks, and technical documentation published by recognized organizations such as the International Diabetes Federation (IDF), World Health Organization (WHO), and the International Organization for Standardization (ISO).

The literature survey mainly focused on the following areas:

- Principles of electrochemical glucose sensing
- Finger-prick blood glucose monitoring devices
- Continuous Glucose Monitoring (CGM) systems
- Analog signal conditioning techniques
- Embedded microcontroller-based biomedical devices
- Analog-to-Digital Converter (ADC) implementation
- Calibration and measurement accuracy
- Portable healthcare monitoring systems

The collected information was analyzed to identify commonly used hardware components, sensing principles, signal processing methods, and system architectures. Based on the findings, an embedded blood glucose measurement system was designed using an Arduino Uno microcontroller and electrochemical sensing technology. The literature survey also helped identify current challenges and opportunities for future improvements in portable glucose monitoring systems.

S.No	Literature Source	Focus Area	Purpose of Review
1	Research Journal Articles	Blood glucose sensing technologies	To understand recent developments in glucose monitoring systems
2	IEEE Conference Papers	Embedded system design	To study hardware implementation and signal processing techniques
3	Medical Research Papers	Diabetes diagnosis and	To analyze clinical requirements and measurement accuracy

4	ISO 15197 Standard	Accuracy requirements	To understand international standards for blood glucose meters
5	WHO & IDF Reports	Diabetes statistics	To study the global impact and importance of glucose monitoring
6	Manufacture Datasheets	Electronic components	To select suitable hardware components for the prototype
7	Books & Technical References	Biomedical instrumentation	To understand biosensors and signal conditioning circuits

Table 2.1: Literature Survey Methodology

The literature survey presented in **Table 2.1** summarizes the major sources of information used during the project. Research articles, international standards, medical reports, and technical datasheets were reviewed to understand current blood glucose monitoring technologies, embedded system design, biosensor principles, and performance evaluation methods. The knowledge obtained from these sources was used to develop the proposed embedded blood glucose measurement system.

2.2 Review of Finger-Prick Glucose Meters

Finger-prick glucose meters are among the most widely used medical devices for diabetes management. These devices measure blood glucose concentration using disposable electrochemical glucose test strips and require only a small drop of capillary blood obtained through a finger prick. Their portability, ease of operation, rapid measurement, and reliable performance have made them the standard method for self-monitoring of blood glucose (SMBG).

The working principle of these devices is based on an enzymatic electrochemical reaction. The glucose present in the blood reacts with enzymes such as **Glucose Oxidase (GOx)** or **Glucose Dehydrogenase (GDH)** coated on the test strip. This reaction generates an electrical current proportional to the

glucose concentration. The generated current is converted into a voltage using a transimpedance amplifier and then processed by an Analog-to-Digital Converter (ADC) before being displayed as a blood glucose value.

Modern glucose meters incorporate several advanced features, including:

- Automatic calibration
- Fast measurement (typically 5–10 seconds)
- Small blood sample requirement
- Memory storage for previous readings
- High measurement accuracy
- Battery-powered portable operation

Despite these advantages, finger-prick glucose meters have certain limitations. Repeated finger pricking can cause discomfort and pain, frequent replacement of disposable test strips increases operating costs, and improper handling of the strips may affect measurement accuracy. Nevertheless, electrochemical finger-prick glucose monitoring remains the most accurate and clinically accepted method for routine diabetes management.

2.3 Review of Continuous Glucose Monitoring Systems

Continuous Glucose Monitoring (CGM) systems represent a significant advancement in diabetes management by providing real-time monitoring of glucose levels throughout the day. Unlike conventional Self-Monitoring of Blood Glucose (SMBG) devices, which require finger-prick blood samples, CGM systems use a small sensor inserted beneath the skin to measure glucose concentration in the interstitial fluid. The measured data are continuously transmitted to a receiver, smart phone, or insulin pump through wireless communication.

A typical CGM system consists of three main components: a disposable glucose sensor, a transmitter, and a display device or mobile application. The sensor measures glucose levels at regular intervals, usually every 1 to 5 minutes, allowing patients and healthcare professionals to monitor glucose trends rather than individual readings. This continuous monitoring helps detect episodes of hypoglycemia and hyperglycemia at an early stage, enabling timely medical intervention.

Despite their advantages, CGM systems have certain limitations. The sensors require periodic replacement, increasing the overall cost of treatment. In addition, the glucose concentration measured in the interstitial fluid may differ slightly from the actual blood glucose level, particularly during rapid changes in glucose concentration. Regular calibration may also be required for some CGM devices to maintain measurement accuracy.

Although Continuous Glucose Monitoring systems provide advanced features such as trend analysis, wireless data transmission, and automated alerts, their high cost and increased system complexity make them less suitable for low-cost educational prototypes. Therefore, the present project adopts the electrochemical finger-prick method, which offers high accuracy, simple hardware implementation, and reliable performance while effectively demonstrating the principles of embedded biomedical instrumentation.

2.4 Accuracy Standards and Validation Studies

The accuracy of a blood glucose monitoring system is one of the most critical factors in ensuring reliable diabetes management. Inaccurate glucose measurements may lead to inappropriate medical decisions, increasing the risk of hypoglycemia or hyperglycemia. Therefore, blood glucose meters are evaluated according to internationally accepted performance standards before being approved for clinical use.

The **ISO 15197:2013** standard specifies the accuracy requirements for blood glucose monitoring systems intended for self-testing by diabetic patients. According to this standard, glucose meters must produce results that are sufficiently close to those obtained using certified laboratory reference methods. The standard also defines procedures for evaluating system performance under

different operating conditions, including variations in temperature, humidity, and blood glucose concentration.

In addition to ISO standards, various clinical validation methods are used to assess the performance of blood glucose monitoring systems. These include statistical error analysis, comparison with laboratory measurements, and repeatability testing. Such validation procedures ensure that the device provides consistent and dependable glucose readings during routine operation.

The prototype developed in this project is intended for educational and research purposes. Although it follows the basic principles of electrochemical glucose measurement used in commercial glucose meters, it is not designed for clinical diagnosis or medical treatment. However, the system architecture has been developed with reference to internationally accepted measurement principles, providing a practical understanding of biomedical instrumentation and embedded system design

2.5 Signal Conditioning and Electronics in Literature

Signal conditioning is an essential stage in embedded blood glucose monitoring systems because the electrical signal generated by the glucose test strip is extremely small, typically in the microampere range. This weak signal cannot be processed directly by a microcontroller and therefore requires amplification and filtering before digital conversion.

Several researchers have proposed the use of operational amplifiers as transimpedance amplifiers (TIA) to convert the sensor current into a proportional voltage. Among the commonly used operational amplifiers, the **LM358** is widely preferred due to its low power consumption, single-supply operation, low cost, and ease of implementation in portable biomedical devices. The amplified signal is then passed through filtering circuits to reduce electrical noise and improve measurement stability.

Microcontrollers play a significant role in modern glucose monitoring systems by performing Analog-to Digital Conversion (ADC), signal processing, calibration, and display control. Various microcontrollers such as Arduino Uno, STM32, PIC, and ESP32 have been used in research for biomedical applications. Among these, the **Arduino Uno** is widely adopted for academic and prototype

development because of its simple programming environment, built-in 10-bit ADC, extensive documentation, and compatibility with various sensors and display modules.

Recent studies also highlight the use of compact OLED displays for presenting glucose measurements. Compared to conventional LCDs, OLED displays offer better visibility, lower power consumption, and a compact design, making them suitable for portable medical devices.

Based on the findings from the literature, this project utilizes an **Arduino Uno**, **LM358 operational amplifier**, **electrochemical glucose test strip**, and **OLED display** to develop a simple and reliable embedded blood glucose measurement system. These components provide an effective balance between performance, affordability, and ease of implementation, making them suitable for educational and applications

CHAPTER 3

COMPONENTS, SPECIFICATION AND DESCRIPTION

The successful implementation of an embedded blood glucose measurement system depends on the proper selection and integration of electronic components. Each component performs a specific function in acquiring, processing, and displaying the blood glucose measurement. The overall system consists of a glucose sensing element, signal conditioning circuit, microcontroller, display module, power supply, and supporting electronic components.

The glucose test strip acts as the sensing element by generating a small electrical current through an electrochemical reaction with the blood sample. Since the generated current is extremely small, it is converted into a measurable voltage using an operational amplifier. The processed signal is then converted into digital data by the Arduino Uno microcontroller. Finally, the calculated glucose value is displayed on an OLED screen, providing a simple and user-friendly interface.

The following sections describe the components used in the proposed system along with their specifications and functions.

3.1 Components

The major hardware components used in the development of the embedded blood glucose measurement system are listed in **Table 3.1**.

Table 3.1 Hardware Components Used in the Proposed System

S. No.	Component	Purpose
1	Arduino Uno	Main microcontroller for data processing
2	Arduino Proto Shield	Circuit prototyping and component mounting
3	Glucose Test Strip	Blood glucose sensing element
4	LM358 Operational Amplifier	Signal amplification and current-to-voltage conversion

5	Precision Resistors	Feedback and voltage control
6	Capacitors	Noise filtering and signal stabilization
7	OLED Display	Display of glucose measurement
8	Push Button Switch	System operation and user input
9	Toggle Switch	Main power control
10	Li-ion Battery (3.7 V)	Portable power source
11	TP4056 Charging Module	Battery charging and protection
12	Boost Converter	Converts 3.7 V to 5 V output
13	Jumper Wires	Electrical connections
14	PCB Accessories	Circuit assembly and soldering

3.2 Components Description

This section describes the major hardware components used in the embedded blood glucose measurement system. Each component plays a vital role in sensing, processing, displaying, and powering the system.

The specifications and functions of the selected components are discussed in the following subsections.

3.2.1 Arduino UNO (ATmega328p)



Figure 3.2.1 Arduino UNO (ATmega328p)

The **Arduino Uno** is the main controller used in the proposed embedded blood glucose measurement system. It is based on the **ATmega328P** microcontroller and is responsible for acquiring analog data from the signal conditioning circuit, processing the measured values, and displaying the glucose concentration on the OLED display.

The Arduino Uno contains a built-in **10-bit Analog-to-Digital Converter (ADC)**, which converts the amplified analog voltage into digital values for further processing. Its simple programming environment, low cost, and wide community support make it suitable for educational and prototype development.

3.2.2 Arduino Proto Shield



Figure3.2.2 Arduino Proto Shield

The **Arduino Proto Shield** is an expansion board designed to simplify the development of electronic prototypes. It is mounted directly on top of the

Arduino Uno and provides a convenient platform for connecting electronic components without modifying the main controller board.

In this project, the Proto Shield is used to assemble the signal conditioning circuit, which includes the operational amplifier, resistors, capacitors, and other supporting components. It provides a stable and organized layout, making the circuit easy to construct, test, and troubleshoot.

Function in the Project

- Provides a platform for assembling the analog signal conditioning circuit.
- Simplifies wiring between components.
- Reduces loose connections during testing.
- Improves the overall reliability of the prototype.

3.2.3 Glucose Test Strip



Figure 3.2.3 Glucose Test Strip

The **glucose test strip** is the primary sensing element of the embedded blood glucose measurement system. It contains an enzyme-coated reaction area that reacts with the glucose present in a small blood sample. During this electrochemical reaction, a small electrical current is generated, which is directly proportional to the glucose concentration.

Since the generated current is extremely small, it is first converted into a measurable voltage using the LM358 operational amplifier before being processed by the Arduino Uno. The accuracy of the entire system largely depends on the quality and proper handling of the glucose test strip. Key Specifications

Function in the Project

- Detects the glucose concentration in the blood sample.
- Generates an electrical current proportional to glucose concentration.
- Serves as the primary input sensor for the embedded system.
- Enables rapid and accurate glucose measurement.

3.2.4 Operational Amplifier (LM358)



Figure 3.4: LM358 Operational Amplifier

The **LM358 Operational Amplifier** is used as the signal conditioning circuit in the proposed embedded blood glucose measurement system. The electrical current generated by the glucose test strip is extremely small (in the microampere range) and cannot be measured directly by the Arduino Uno. Therefore, the LM358 converts this small current into a proportional voltage and amplifies it to a level that can be processed by the micro controller. In this project, it is configured as a **Transimpedance Amplifier (TIA)** to improve the accuracy and reliability of glucose measurement.

Function in the Project

- Converts the sensor current into a measurable voltage.
- Amplifies the weak signal generated by the glucose test strip.
- Reduces the effect of electrical noise on the sensor output.
- Supplies a stable analog voltage to the Arduino Uno ADC.

3.2.5 Precision Resistors




Figure 3.5: Precision Resistors

Precision resistors are used in the signal conditioning circuit to control current flow and determine the gain of the operational amplifier. In the transimpedance amplifier configuration, the feedback resistor plays a critical role in converting the sensor current into a proportional voltage. High-precision resistors are selected to improve measurement accuracy and ensure stable circuit performance.

Function in the Project

- Sets the amplifier gain.
- Converts sensor current into voltage.
- Improves measurement accuracy.
- Ensures stable circuit operation.

3.2.6 Capacitors



Figure 3.6: Capacitors

Capacitors are passive electronic components used for filtering and stabilizing the power supply and signal lines. They reduce unwanted electrical noise and voltage fluctuations that may affect the accuracy of the glucose measurement. Proper capacitor selection improves the overall stability and reliability of the embedded system.

Function in the Project

- Filters electrical noise.
- Stabilizes the power supply.
- Improves signal quality.
- Enhances circuit reliability.

3.2.7 OLED Display




Figure 3.7: OLED Display

The **OLED (Organic Light Emitting Diode) Display** is used to display the measured blood glucose value and system status. Compared to conventional LCDs, OLED displays provide higher contrast, lower power consumption, and better visibility under different lighting conditions. The display receives processed data from the Arduino Uno through the I²C communication interface.

Function in the Project

- Displays the blood glucose reading.
- Provides user-friendly output.
- Displays system status during operation.

3.2.8 Push Button Switch



Figure 3.8: Push Button Switch

The push button switch is used to control user operations such as starting or resetting the measurement process. It provides a simple interface for operating the prototype.

Function in the Project

- Starts the measurement process.
- Resets the system when required.

3.2.9 Power ON/OFF Toggle Switch



Figure 3.9: Toggle Switch

The toggle switch is used as the main power control for the embedded system. It allows the user to safely turn the device ON or OFF, helping to conserve battery power when the system is not in use.

Function in the Project

- Controls the main power supply.
- Prevents unnecessary battery discharge.

3.2.10 Li-ion Battery (3.7 V)



Figure 3.10: Li-ion Battery

A rechargeable **3.7 V Lithium-ion battery** is used as the primary power source for the prototype. It provides portable operation and eliminates the need for a continuous external power supply.

Function in the Project

- Supplies power to the complete system.
- Enables portable operation.

3.2.11 TP4056 Charging Module




Figure 3.11: TP4056 Charging Module

The **TP4056 Charging Module** is used to charge and protect the lithium-ion battery. It provides safe charging by preventing overcharging, over-discharging, and short circuits, thereby improving battery life and system safety.

Function in the Project

- Charges the battery safely.
- Protects the battery from damage.
- Extends battery life.

3.2.12 Boost Converter



Figure 3.12: DC-DC Boost Converter

The boost converter increases the battery voltage from **3.7 V** to a regulated **5 V**, which is required by the Arduino Uno and other electronic components. It ensures a stable power supply throughout the system.

Function in the Project

- Converts 3.7 V to 5 V.
- Maintains stable system voltage.

3.2.13 Jumper Wires / Hook-up Wires

Function in the Project

- Permanent component assembly.
- Reliable electrical connections.
- Improves prototype

CHAPTER 4

WORKING PRINCIPLE

The embedded blood glucose measurement system operates based on the electrochemical reaction between glucose present in the blood sample and the enzyme coated on the glucose test strip. The generated electrical signal is processed through signal conditioning circuits, converted into digital data by the Arduino Uno, and finally displayed as the blood glucose concentration on the OLED display. The overall working process is simple, reliable, and suitable for educational prototype development.

The system consists of five major stages:

1. Blood Sample Detection
2. Electrochemical Signal Generation
3. Signal Conditioning
4. Analog-to-Digital Conversion
5. Display of Blood Glucose Value

Each stage is explained in the following sections.

4.1 Overview of Blood Glucose Measurement

The proposed system measures blood glucose using an electrochemical sensing method. A small blood sample is placed on the glucose test strip. The glucose present in the blood reacts with the enzyme coated on the strip, producing a small electrical current proportional to the glucose concentration.

Since this current is extremely small, it is amplified using the LM358 operational amplifier. The amplified voltage is read by the Arduino Uno through

its Analog-to-Digital Converter (ADC). The microcontroller processes the digital data using a calibration equation and calculates the blood glucose concentration.

Finally, the glucose value is displayed on the OLED display within a few seconds.

This sequence enables fast, accurate, and portable blood glucose measurement while demonstrating the practical application of embedded systems in biomedical instrumentation.




Figure 4.1 Overall Working Block Diagram

4.2 Physiological Basis of Glucose Detection

Blood glucose refers to the concentration of glucose present in the bloodstream. Glucose is the primary source of energy for the human body and is transported through the blood to various tissues and organs. In individuals with diabetes mellitus, the body's ability to regulate blood glucose is impaired due to insufficient insulin production or ineffective insulin utilization. Therefore, regular monitoring of blood glucose levels is essential for effective diabetes management.

The proposed system measures blood glucose using an **electrochemical glucose test strip**. When a small drop of blood is applied to the reaction area of the test strip, the glucose present in the blood reacts with the enzyme coated on the strip, typically **Glucose Oxidase (GOx)**. This enzymatic reaction produces a small electrical current that is directly proportional to the glucose concentration in the blood sample.

Since the generated current is very small, it cannot be measured directly by the microcontroller. Therefore, it is converted into a measurable voltage using the LM358 operational amplifier. The processed signal is then digitized by the Arduino Uno and used to calculate the blood glucose concentration, which is displayed on the OLED screen.

This electrochemical sensing technique is widely used in commercial blood glucose meters because it offers high sensitivity, good accuracy, rapid response, and reliable performance.




Figure 4.2 Electrochemical Glucose Detection Process

4.3 Signal Conditioning and Data Acquisition

The electrical current generated by the glucose test strip is extremely small and cannot be measured directly by the Arduino Uno. Therefore, a signal conditioning circuit is used to convert the weak current into a stable voltage suitable for Analog-to-Digital Conversion (ADC).

In the proposed system, the **LM358 operational amplifier** is configured as a transimpedance amplifier (TIA). It converts the sensor current into a proportional voltage while providing the necessary amplification. Passive components such as precision resistors and capacitors are incorporated into the circuit to improve signal stability and reduce electrical noise.

The amplified analog voltage is applied to one of the Arduino Uno's analog input pins. The built-in **10-bit ADC** converts the analog voltage into a digital value ranging from **0 to 1023**. The Arduino processes this digital value using a calibration equation to determine the corresponding blood glucose concentration.

After the calculation is completed, the glucose value is transmitted to the OLED display through the I²C communication interface, allowing the user to view the measurement instantly. This process is completed within a few seconds, providing a fast and reliable glucose reading.



Figure 4.3 Signal Conditioning and Data Acquisition

4.4 Signal Processing and Calibration

After the analog signal is converted into digital form by the Arduino Uno, the microcontroller processes the measured value using a predefined calibration equation. Calibration is performed to establish the relationship between the sensor output voltage and the actual blood glucose concentration. This process improves the accuracy and consistency of the measured results.

The Arduino continuously reads the ADC value, converts it into voltage, and calculates the corresponding glucose concentration. The calculated value is then formatted and displayed on the OLED screen in **mg/dL**, which is the standard unit used for blood glucose measurement.

The calibration equation used in the prototype is based on the characteristics of the signal conditioning circuit and the glucose test strip. During practical implementation, the calibration constants can be adjusted using reference glucose samples to improve measurement accuracy.

4.5 System Workflow

The overall operation of the proposed embedded blood glucose measurement system follows a sequential process, beginning with blood sample application and ending with the display of the glucose concentration. Each stage is designed to ensure accurate signal acquisition, processing, and result presentation.

Initially, the system is powered ON using the toggle switch. A small blood sample is then placed on the glucose test strip. The glucose present in the blood reacts with the enzyme-coated sensing area, producing a small electrical current proportional to the glucose concentration. This weak electrical signal is amplified and conditioned using the LM358 operational amplifier before being supplied to the Arduino Uno.

The Arduino Uno converts the analog signal into digital data using its built-in Analog-to-Digital Converter (ADC). The digital values are processed using the programmed calibration algorithm to calculate the blood glucose concentration. Finally, the calculated glucose value is displayed on the OLED screen, providing the user with a clear and readable




Figure 4.4 System Flowchart

4.6 Summary of the Working Principle

The proposed embedded blood glucose measurement system successfully integrates electrochemical sensing, signal conditioning, microcontroller-based processing, and digital display into a compact prototype. The glucose test strip detects the blood glucose level through an electrochemical reaction, while the LM358 operational amplifier converts and amplifies the resulting electrical signal. The Arduino Uno processes the signal using its built-in ADC and calculates the glucose concentration based on the programmed calibration algorithm. The final blood glucose value is displayed on the OLED screen, enabling quick and convenient monitoring.

The developed prototype demonstrates the practical implementation of biomedical sensing and embedded system technology. Although intended for educational and research purposes, the system follows the same fundamental operating principle used in many commercial blood glucose monitoring devices.

CHAPTER 5

COST ESTIMATION

5.1 Introduction

Cost estimation is an important aspect of prototype development as it provides an overview of the expenditure involved in constructing the embedded blood glucose measurement system. The total cost includes the electronic components, sensing elements, power supply, display module, and supporting accessories required for assembling the prototype. The selected components were chosen based on their availability, reliability, ease of integration, and affordability. Since the project is developed as an educational prototype, commercially available components have been used to minimize the overall development cost while maintaining satisfactory performance.

5.2 Cost Analysis

The overall cost of the proposed prototype is determined by considering the individual cost of the hardware components and supporting accessories. The major cost contributors include the Arduino Uno, glucose sensing element, OLED display, power supply components, and circuit assembly accessories. Careful selection of readily available components helps in reducing the overall development cost without affecting the basic functionality of the prototype.

The use of a rechargeable Li-ion battery along with a TP4056 charging module provides a convenient power solution for the portable prototype. Similarly, the Arduino Proto Shield, resistors, capacitors, jumper wires, and PCB accessories support the practical implementation and testing of the signal conditioning circuit. These components collectively contribute to the complete development of the embedded blood glucose measurement system.

5.3 Economic Feasibility

The proposed system is economically feasible for **academic, laboratory, and research demonstration purposes**. The prototype uses low-cost and easily available electronic components, making it suitable for student-level biomedical instrumentation projects. The modular hardware arrangement also allows individual components to be replaced or upgraded without redesigning the entire system.

The estimated total cost of the prototype is approximately **₹2,020**. The relatively low development cost demonstrates that an embedded blood glucose measurement platform can be developed using commercially available components while providing practical exposure to electrochemical sensing, signal conditioning, embedded processing, and digital display.

5.4 Cost Summary

The total estimated expenditure for the prototype is approximately **₹2,020**. This includes the sensing element, microcontroller, signal-conditioning components, display, power supply, charging circuit, wiring, and PCB-related accessories. The cost estimation provides a clear understanding of the resources

required for prototype development and also serves as a reference for future modifications and improvements.

The prototype can be further enhanced in future by incorporating wireless communication, IoT connectivity, improved calibration, and a customized PCB. Such modifications may increase the overall cost depending on the components and technologies selected.

The estimated cost of the proposed system is presented in **Table 5.1**.

The estimated total cost of the prototype is approximately **₹2,020**, making it suitable for academic projects and laboratory demonstrations. The use of low-cost and readily available electronic components reduces development expenses while ensuring reliable system performance. The prototype can also be further enhanced by integrating advanced communication modules and cloud-based monitoring systems, depending on future requirements.

Table 5.1 Cost Estimation of the Proposed Prototype

S.NO	Component		Price
1	Arduino Uno	1	650
2	Arduino Proto Shield	1	180
3	Glucose Test Strip	1	120
4	LM358 Operational Amplifier	1	20
5	Precision Resistors	5	25
6	Capacitors	4	20
7	OLED Display	1	250
8	Push Button Switch	1	15

9	Toggle Switch	1	30
10	Li-ion Battery (3.7 V)	1	250
11	TP4056 Charging Module	1	50
12	Boost Converter	1	80
13	Jumper Wires	1 Set	100
14	PCB & Soldering Accessories	1 Set	210
	Total Estimated Cost		₹2,020

CHAPTER 6

RESULTS AND SYSTEM OUTPUTS

The developed embedded blood glucose measurement system was successfully designed and implemented using the selected hardware components. The prototype integrates an electrochemical glucose test strip, LM358 operational amplifier, Arduino Uno, OLED display, rechargeable power supply, and supporting electronic circuits to perform blood glucose measurement.

The system was assembled and tested under laboratory conditions to verify the proper operation of each hardware module. During testing, the signal generated by the glucose test strip was successfully amplified by the signal conditioning circuit and converted into digital values by the Arduino Uno. The processed glucose value was displayed correctly on the OLED screen, demonstrating the successful operation of the complete system.

The prototype confirmed that the integration of embedded hardware and electrochemical sensing principles can be effectively used for educational demonstrations of blood glucose measurement systems.

6.1 Prototype Output




Figure 6.1: Final Prototype of the Embedded Blood Glucose Measurement System

The completed prototype consists of all the essential hardware modules integrated into a compact embedded system. The Arduino Uno serves as the central controller, while the LM358 operational amplifier conditions the sensor signal before it is processed by the microcontroller. The OLED display presents the calculated blood glucose value to the user in real time.

The prototype was designed with portability, ease of assembly, and low development cost in mind. All components were securely mounted to ensure stable operation during testing.

6.2 OLED Display Output



Figure 6.2 Prototype Connected with OLED Display

The OLED display provides a clear and readable interface for displaying the measured blood glucose value. After signal processing and calibration, the Arduino transmits the calculated glucose concentration to the display through the I²C communication interface.

The display updates within a few seconds after the measurement process is completed, allowing the user to obtain the glucose reading quickly.

6.3 Performance Discussion

The developed prototype successfully demonstrated the complete workflow of an embedded blood glucose measurement system. The electrochemical signal

generated by the glucose test strip was amplified using the LM358 operational amplifier and accurately processed by the Arduino Uno. The OLED display presented the calculated glucose value in a simple and user-friendly format.

The system performed reliably during repeated laboratory testing and demonstrated stable operation under normal operating conditions. Although the prototype is intended for educational and research purposes, it effectively illustrates the practical application of biomedical sensing, analog signal conditioning, embedded programming, and digital signal processing.

The overall performance of the prototype indicates that the proposed design can serve as a useful platform for understanding the working principles of portable blood glucose monitoring systems

CHAPTER 7

SCOPE OF FUTURE WORK

The proposed embedded blood glucose measurement system successfully demonstrates the basic principles of electrochemical glucose sensing and embedded system design. Although the prototype performs its intended function effectively, several improvements can be incorporated in future versions to enhance its performance, accuracy, and usability.

One possible improvement is the integration of **wireless communication technologies** such as Bluetooth or Wi-Fi. This would enable blood glucose readings to be transmitted directly to a smartphone or computer, allowing users to maintain digital health records and monitor glucose levels remotely.

The system can also be enhanced by incorporating **IoT (Internet of Things)** technology for cloud-based data storage and remote access. This would allow healthcare professionals to monitor patient glucose data from any location and provide timely medical advice.

Another important enhancement is the implementation of **mobile application support**. A dedicated mobile application could display historical glucose readings, generate graphical reports, and provide reminders for regular glucose testing and medication schedules.

The prototype may also be improved by using **high-precision signal conditioning circuits**, advanced microcontrollers, and improved calibration techniques to achieve better measurement accuracy and stability.

In future research, **Artificial Intelligence (AI)** and **Machine Learning (ML)** algorithms can be integrated to analyze glucose trends, predict abnormal glucose levels, and assist in the early detection of diabetic complications.

Finally, the system can be further developed into a compact, portable medical device by designing a custom Printed Circuit Board (PCB), reducing the overall size of the hardware, and improving the enclosure design for everyday use.

CHAPTER 8

APPENDICES

The appendices provide supplementary information related to the design, development, implementation, and testing of the proposed embedded blood glucose measurement system. These materials support the discussions presented in the previous chapters and offer additional technical details that may be useful for understanding the hardware implementation and prototype development. The appendix includes photographs of the developed prototype, hardware integration, circuit implementation, and supporting documentation.

8.1 Prototype Photographs

This section presents photographs of the developed embedded blood glucose measurement prototype. The images illustrate the overall hardware assembly, OLED display integration, enclosure design, and internal circuit arrangement. These photographs provide visual evidence of the successful implementation of the proposed system.



Figure 8.1 Developed Embedded Blood Glucose Measurement Prototype



Insert Figure 8.2 Prototype Connected with OLED Display



Insert Figure 8.3 Final Prototype Enclosure



Figure 8.5 Top View of the Prototype



Figure 8.5 Side View of the Prototype

8.2 Complete Hardware Integration

The complete hardware integration of the proposed embedded blood glucose measurement system is shown below. The system consists of an Arduino Uno microcontroller, LM358 operational amplifier, glucose test strip interface, OLED display, TP4056 charging module, lithium-ion battery, DC-DC boost converter, and supporting electronic components. All hardware modules were interconnected to achieve reliable signal acquisition, processing, and glucose value display.




Figure 8.6 Complete Hardware Integration of the Proposed Embedded Blood Glucose Measurement System

8.3 Summary

The appendices provide additional information that supports the implementation of the proposed embedded blood glucose measurement system. The prototype photographs and hardware integration diagrams demonstrate the successful development of the system and serve as reference material for future enhancement, testing, and research activities.

CHAPTER 9

CONCLUSION

The proposed **Embedded System Design for Blood Glucose Measurement** was successfully designed and developed using an Arduino Uno microcontroller, an electrochemical glucose test strip, an LM358 operational amplifier, and an OLED display. The developed prototype demonstrates the practical implementation of an embedded biomedical system capable of acquiring, processing, and displaying blood glucose measurements based on electrochemical sensing principles.

The system effectively performs signal conditioning, analog-to-digital conversion, and digital signal processing to estimate blood glucose concentration. The integration of low-cost electronic components and embedded programming provides a portable, user-friendly, and economical solution suitable for educational and research purposes. The experimental implementation confirmed the successful operation of the hardware modules and demonstrated the feasibility of the proposed design.

Although the developed prototype is intended primarily for academic demonstration and laboratory applications, it provides a strong foundation for understanding the working principles of commercial blood glucose monitoring systems. The project also highlights the importance of embedded systems in modern biomedical instrumentation and healthcare technology.

Future enhancements such as wireless communication, Internet of Things (IoT) connectivity, cloud-based health monitoring, mobile application support, Artificial Intelligence (AI), and Machine Learning (ML) can further improve the performance, functionality, and usability of the system. Overall, the project successfully achieves its objectives and serves as an effective platform for future research and development in embedded medical devices

CHAPTER 1

REFERENCES

[1] American Diabetes Association, "Standards of Medical Care in Diabetes—2025," *Diabetes Care*, vol. 48, Suppl. 1, pp. S1–S350, 2025.

[2] ISO 15197:2013, *In Vitro Diagnostic Test Systems—Requirements for Blood-Glucose Monitoring Systems for Self-Testing in Managing Diabetes Mellitus*, International Organization for Standardization, Geneva, Switzerland, 2013.

[3] D. A. Skoog, F. J. Holler, and S. R. Crouch, *Principles of Instrumental Analysis*, 7th ed. Boston, MA, USA: Cengage Learning, 2018.

[4] J. G. Webster and J. W. Clark, *Medical Instrumentation: Application and Design*, 5th ed. Hoboken, NJ, USA: John Wiley & Sons, 2018.

[5] A. J. Bard and L. R. Faulkner, *Electrochemical Methods: Fundamentals and Applications*, 2nd ed. New York, NY, USA: Wiley, 2001.

[6] Arduino, *Arduino Uno Rev3 Technical Specifications*. Arduino Documentation.

[7] Texas Instruments, *LM358 Low Power Dual Operational Amplifier Datasheet*, Texas Instruments Inc.

[8] Analog Devices, *Operational Amplifier Applications Handbook*, Analog Devices, Inc.

[9] J. Fraden, *Handbook of Modern Sensors*, 5th ed. Cham, Switzerland: Springer, 2016.

- [10] M. N. O. Sadiku, *Elements of Electromagnetics*, 7th ed. Oxford, U.K.: Oxford University Press, 2018.
- [11] S. C. Dutta Roy, *Biomedical Instrumentation and Measurements*, New Delhi, India: PHI Learning, 2019.
- [12] J. Enderle and J. Bronzino, *Introduction to Biomedical Engineering*, 4th ed. Academic Press, 2021.
- [13] S. Franco, *Design with Operational Amplifiers and Analog Integrated Circuits*, 4th ed. New York, NY, USA: McGraw-Hill, 2015.
- [14] M. H. Rashid, *Power Electronics: Circuits, Devices, and Applications*, 4th ed. Pearson, 2019.
- [15] Adafruit Industries, *SSD1306 OLED Display Guide*, Adafruit Learning System.
- [16] Microchip Technology Inc., *ATmega328P Datasheet*, 2022.
- [17] R. S. Khandpur, *Biomedical Instrumentation: Technology and Applications*, McGraw-Hill Education.
- [18] B. G. Lipták, *Instrument Engineers' Handbook*, 5th ed. CRC Press, 2018.
- [19] J. M. Cooper and C. R. Lowe, *Biosensors: Fundamentals and Applications*, Oxford University Press.
- [20] S. Park et al., "Recent Advances in Continuous Glucose Monitoring Technologies," *Sensors*, vol. 22, no. 8, 2022.
- [21] Y. Zhang et al., "Advances in Electrochemical Biosensors for Glucose Monitoring," *Biosensors*, vol. 13, no. 2, 2023.

[22] A. Heller and B. Feldman, "Electrochemical Glucose Sensors and Their Applications in Diabetes Management," *Chemical Reviews*, vol. 108, no. 7, pp. 2482–2505.