



RV College of Engineering®

Mysore Road, RV Vidyaniketan Post, Bengaluru - 560059, Karnataka, India

Go, change the world

FoodSense: Multimodal AI System for Early Spoilage Prediction

An Interdisciplinary Project Report (XX367P)

Submitted by,

Aditya Ranjan

Gnanendra Naidu N

Arumita Nandi

Vinay A

1RV23AI008

1RV23AI035

1RV23EC023

1RV23EC183

Under the guidance of

Dr Anitha Sandeep

Assistant Professor

Dept. of CSE

RV College of Engineering®

In partial fulfillment of the requirements for the degree of
Bachelor of Engineering in respective departments

2025-2026



RV College of Engineering®, Bengaluru
(Autonomous institution affiliated to VTU, Belagavi)



CERTIFICATE

Certified that the interdisciplinary project (XX367P) work titled ***FoodSense: Multi-modal AI System for Early Spoilage Prediction*** is carried out by _____ of RV College of Engineering, Bengaluru, in partial fulfillment of the requirements for the degree of **Bachelor of Engineering** in respective departments during the year 2025-2026. It is certified that all corrections/suggestions indicated for the Internal Assessment have been incorporated in the interdisciplinary project report deposited in the departmental library. The interdisciplinary project report has been approved as it satisfies the academic requirements in respect of interdisciplinary project work prescribed by the institution for the said degree.

Dr Anitha Sandeep
Guide

Dr. Ravish Aradhya
Head of the Department

Dr. M.V. Renukadevi
Dean Academics

Dr. K. N. Subramanya
Principal

External Viva

Name of Examiners

Signature with Date

- 1.
- 2.

DECLARATION

We, **Aditya Ranjan**, **Gnanendra Naidu N**, **Arumita Nandi**, **Vinay A** students of sixth semester B.E., RV College of Engineering, Bengaluru, hereby declare that the interdisciplinary project titled '**FoodSense: Multimodal AI System for Early Spoilage Prediction**' has been carried out by us and submitted in partial fulfilment for the award of degree of **Bachelor of Engineering** in respective departments during the year 2025-2026.

Further we declare that the content of the dissertation has not been submitted previously by anybody for the award of any degree or diploma to any other university.

We also declare that any Intellectual Property Rights generated out of this project carried out at RVCE will be the property of RV College of Engineering, Bengaluru and We will be one of the authors of the same.

Place: Bengaluru

Date:

Name

Signature

1. Aditya Ranjan(1RV23AI008)
2. Gnanendra Naidu N(1RV23AI035)
3. Arumita Nandi(1RV23EC023)
4. Vinay A(1RV23EC183)

ACKNOWLEDGEMENTS

We are indebted to our guide, **Dr Anitha Sandeep**, Assistant Professor, Department of CSE, RVCE for the wholehearted support, suggestions and invaluable advice throughout our project work and also helped in the preparation of this thesis.

We also express our gratitude to our panel member **Dr. Kariyappa**, Professor, Department of ECE, RVCE for the valuable comments and suggestions during the phase evaluations.

Our sincere thanks to the project coordinator **Dr. Chetana G**, Professor, Department of ECE for timely instructions and support in coordinating the project.

Our gratitude to **Prof. Narashimaraja P**, Department of ECE, RVCE for the organized latex template which made report writing easy and interesting.

Our sincere thanks to **Dr. Ravish Aradhya**, Professor and Head, Department of Department of Computer Science Engineering, RVCE for the support and encouragement.

We are deeply grateful to **Dr. M.V. Renukadevi**, Professor and Dean Academics, RVCE, for the continuous support in the successful execution of this Interdisciplinary project.

We express sincere gratitude to our beloved Professor and Vice Principal, **Dr. Geetha K S**, RVCE and Principal, **Dr. K. N. Subramanya**, RVCE for the appreciation towards this project work.

Lastly, we take this opportunity to thank our family members and friends who provided all the backup support throughout the project work.

ABSTRACT

Food waste is a critical global issue, with approximately 19% of all food produced annually being discarded before consumption. Traditional methods of food spoilage detection rely on manual inspection, which is subjective, labor-intensive, and prone to errors. Existing automated systems often use expensive electronic noses or provide only binary "fresh vs rotten" classifications without temporal context.

The objective of this work is to develop a low-cost IoT + AI system for early food spoilage detection using a combination of gas, temperature, and humidity sensors. The system employs a multi-modal approach with two main AI models: a 3-layer MLP for instant ammonia classification and a temporal attention-augmented LSTM for continuous shelf-life prediction in hours.

The MLP model was trained on the UCI Gas Sensor Array Drift Dataset (13,910 real sensor samples), achieving 99.75% accuracy, 99.08% precision, and 98.78% recall. The LSTM model was trained on a synthetic 48-hour spoilage time-series dataset, achieving a mean absolute error of ± 4.0 hours. The system also includes on-device temperature and humidity compensation for the MQ135 sensor, performed directly on the Arduino microcontroller. A vision branch for image-based spoilage detection is planned as a future enhancement.


The proposed system addresses key limitations of existing work by providing continuous shelf-life regression instead of binary classification, using a single low-cost MQ135 sensor instead of expensive sensor arrays, and incorporating temporal attention to capture spoilage dynamics over time.

CONTENTS

Abstract	i
List of Figures	v
List of Tables	vi
1 Introduction to FoodSense AI	1
1.1 Introduction	2
1.2 Literature Review	2
1.2.1 Gas Sensor-Based Spoilage Detection and Drift Compensation . .	2
1.2.2 Visible Spectroscopy and Colorimetric Analysis	3
1.2.3 Multimodal Deep Learning and Temporal Modeling	3
1.3 Motivation	3
1.4 Problem statement	4
1.5 Objectives	4
1.6 Brief Methodology of the project	4
1.7 Assumptions made / Constraints of the project	5
1.8 Organization of the report	5
2 Theory and Fundamentals	6
2.1 Sensors and Hardware	7
2.1.1 MQ135 Gas Sensor	7
2.1.2 DHT11 Temperature and Humidity Sensor	7
2.1.3 Arduino Microcontroller	7
2.2 Machine Learning Architectures	8
2.2.1 Multi-Layer Perceptron (MLP)	8
2.2.2 Long Short-Term Memory (LSTM)	8
2.3 Tools and Software	9
2.3.1 Python and PyTorch	9
2.3.2 Arduino IDE	9
2.3.3 HTML, CSS, and JavaScript	9

2.4	Summary	9
3	System Design and Architecture	10
3.1	System Overview	11
3.2	Sensor Data Pipeline	11
3.2.1	On-Device Sensor Compensation	11
3.2.2	CSV Transmission	12
3.3	AI Model Architectures	12
3.3.1	MLP Gas Classifier	12
3.3.2	LSTM with Temporal Attention	12
3.4	Web Dashboard Design	13
3.5	Novelty and Contributions	13
3.6	Summary	14
4	Implementation Details	15
4.1	Hardware Setup	16
4.1.1	Gas and Climatic Sensing Setup	16
4.1.2	DIY Visible Spectrophotometer Setup	17
4.2	Arduino Implementation	17
4.2.1	Sensor Reading and Compensation	19
4.2.2	CSV Transmission	19
4.3	AI Model Implementation	19
4.3.1	MLP Training	19
4.3.2	LSTM Training	19
4.4	Web Dashboard Implementation	19
4.4.1	Dashboard Tabs	19
4.4.2	Real-Time Simulation	20
4.5	Summary	20
5	Results and Discussion	21
5.1	MLP Gas Classifier Results	22
5.1.1	Performance Metrics	22
5.1.2	Confusion Matrix	22
5.2	LSTM Shelf-Life Predictor Results	23

5.2.1	Performance Metrics	23
5.2.2	Note on R-squared (R^2)	23
5.3	Spectroscopy Model Results	23
5.3.1	Virtual Spectrometer Calibration Model	23
5.3.2	Pigment Degradation Classifier	24
5.4	Discussion	24
5.5	Summary	25
6	Conclusion and Future Scope	26
6.1	Conclusion	27
6.2	Future Scope	27
6.3	Learning Outcomes of the Project	28
A	Source Code Listings	29
A.1	Arduino Spectrophotometer Firmware	30
A.2	PyTorch AI Calibration Model	32
	Bibliography	34



LIST OF FIGURES


3.1	Multimodal System Architecture and Data Flow	11
4.1	Original Gas and Climatic Sensor Node Setup	16
4.2	Front View of Open Chamber	18
4.3	Internal Mounting and Breadboard Wiring	18
4.4	Close-up of Cuvette Slot	18
4.5	Top View of Closed Spectrophotometer Box	18



LIST OF TABLES

5.1	MLP Gas Classifier Performance Metrics	22
5.2	MLP Gas Classifier Confusion Matrix	22
5.3	LSTM Shelf-Life Predictor Performance Metrics	23
5.4	Virtual Spectrometer Calibration Model Metrics	24
5.5	Pigment Classifier Performance Report	24



The logo of RV Institutions is a circular emblem. It features a central shield with the letters 'R' and 'V' on either side. The shield is set against a background of a larger circle. The text 'RASHTREEYA SIKSHANA SAMITHI TRUST' is written in a circular path around the top half of the inner circle, and 'INSTITUTIONS' is written along the bottom half. A registered trademark symbol (®) is located to the upper right of the emblem.

Chapter 1

Introduction to FoodSense AI

CHAPTER 1

INTRODUCTION TO FOODSENSE AI

Food waste is a critical global challenge that impacts food security, the environment, and the economy. This chapter introduces the context of food spoilage detection, the need for automated systems, and outlines the objectives and methodology of the FoodSense AI project.

1.1 Introduction

Food waste is a pressing global issue, with approximately 19% of all food produced annually being discarded before consumption, as reported by the United Nations Environment Programme. This waste contributes to greenhouse gas emissions, economic losses, and exacerbates food insecurity in many regions. Traditional methods of assessing food freshness rely on manual inspection, which is subjective, labor-intensive, and prone to human error.

Automated food spoilage detection systems have emerged as a solution to this problem, leveraging sensors, machine learning, and computer vision to assess food quality. However, existing systems often suffer from several limitations: they use expensive electronic noses with multiple sensors, provide only binary "fresh vs rotten" classifications without temporal context, and lack on-device sensor compensation.

The FoodSense AI project addresses these limitations by developing a low-cost IoT + AI pipeline for early food spoilage detection. The system uses a combination of MQ135 gas sensor, DHT11 temperature and humidity sensor, Arduino microcontroller, and two AI models: an MLP for ammonia classification and an LSTM for continuous shelf-life prediction.

1.2 Literature Review

A literature review was conducted to understand the current state of research in food spoilage detection and identify technical gaps that FoodSense AI aims to address.

1.2.1 Gas Sensor-Based Spoilage Detection and Drift Compensation

Multiple studies have explored the use of metal-oxide gas sensor arrays (electronic noses) for food spoilage detection. Vergara et al. [1] established a benchmark for an-

alyzing sensor response over a 36-month period, demonstrating that sensor drift is a significant bottleneck in long-term deployment. Traditional methods of drift compensation often rely on batch post-processing in lab settings. However, real-time deployment requires active, localized compensation. Fonollosa et al. [2] demonstrated that temperature and humidity fluctuations are primary drivers of drift in open-sampling systems, emphasizing the need for mathematical corrections to stabilize gas readings. FoodSense AI builds on this by implementing localized temperature-humidity correction formulas directly on the edge microcontroller.

1.2.2 Visible Spectroscopy and Colorimetric Analysis

Visible spectroscopy provides a non-destructive method for food quality assessment by monitoring chemical and pigment alterations. Sun et al. [3] reviewed the use of visible and near-infrared (Vis-NIR) spectroscopy, showing that absorption at specific wavelengths correlates directly with the degradation of chlorophyll and the formation of brown enzymatic byproducts (melanins). While commercial spectrophotometers are cost-prohibitive for consumer storage, Albert et al. [4] demonstrated that Arduino-controlled RGB LEDs and photodetectors (such as LDRs) can perform quantitative chemical analysis. FoodSense AI applies a machine learning-based calibration model to map cheap RGB-LDR signals to continuous wavelengths and absorbances, enabling a low-cost virtual spectrometer.

1.2.3 Multimodal Deep Learning and Temporal Modeling

Traditional AI systems for food quality rely on single-mode point-in-time classification. For visual assessments, Palakodati et al. [5] used CNN architectures for fresh vs. rotten fruit classification, achieving 97.82% accuracy. However, static images and gas snapshots lack temporal context. Spoilage is a sequential process characterized by progressive VOC releases. While standard LSTMs have been used for time-series forecasting, attention mechanisms are critical for identifying key transient events in sensor readings. FoodSense AI introduces a multimodal architecture that runs parallel MLP and attention-augmented LSTM branches, allowing both instant state classification and continuous shelf-life prediction.

1.3 Motivation

The motivation for developing FoodSense AI stems from several key factors:

- The need to reduce food waste and improve food security
- The high cost of existing electronic nose systems, which limits accessibility
- The lack of temporal context in binary classification systems
- The opportunity to apply modern AI techniques like LSTMs with attention to this domain

1.4 Problem statement

The problem this project addresses is the lack of a low-cost, accessible, and accurate system for continuous food spoilage detection that provides temporal context and shelf-life prediction, rather than just binary classification.

1.5 Objectives

The objectives of the project are:

1. To develop a low-cost IoT system using Arduino, MQ135, and DHT11 sensors for food spoilage detection
2. To implement on-device temperature and humidity compensation for the MQ135 sensor
3. To train and evaluate an MLP model for ammonia classification and an LSTM model with temporal attention for shelf-life prediction

1.6 Brief Methodology of the project

The methodology for FoodSense AI involves several key steps:

- Hardware setup: Connect MQ135 and DHT11 sensors to Arduino and implement on-device compensation
- Data collection: Generate synthetic time-series data for LSTM training and use the UCI Gas Sensor Array Drift Dataset for MLP training
- Model training: Train MLP for classification and LSTM with attention for regression
- Evaluation: Test models on appropriate datasets and report metrics

- UI development: Create a web-based dashboard using HTML, CSS, and JavaScript

1.7 Assumptions made / Constraints of the project

The project makes the following assumptions and operates under the following constraints:

- The MQ135 sensor is calibrated for ammonia detection
- The synthetic time-series data accurately models real-world spoilage dynamics
- The system is intended for use in controlled indoor environments
- The vision branch is a planned enhancement and not implemented in the current version

1.8 Organization of the report

This report is organized as follows:

- Chapter 2 discusses the fundamentals of sensors, machine learning, and the AI architectures used in this project
- Chapter 3 discusses the system design and architecture
- Chapter 4 discusses the implementation details
- Chapter 5 discusses the results and evaluation
- Chapter 6 discusses the conclusion and future work



Chapter 2

Theory and Fundamentals

CHAPTER 2

THEORY AND FUNDAMENTALS

This chapter covers the fundamental concepts and technologies used in the FoodSense AI project, including sensors, machine learning architectures, and the tools and software employed.

2.1 Sensors and Hardware

The FoodSense AI system uses two main sensors and an Arduino microcontroller for data acquisition.

2.1.1 MQ135 Gas Sensor

The MQ135 is a low-cost metal-oxide gas sensor sensitive to ammonia, sulfide, benzene vapor, and other harmful gases. It operates by measuring the change in resistance of a tin dioxide (SnO_2) layer when exposed to target gases. The sensor requires a load resistor (typically 10 k Ω) and operates at 5V DC.

The resistance of the MQ135 sensor decreases as the concentration of target gases increases. The relationship between sensor resistance and gas concentration follows a power-law:

$$C = A \times \left(\frac{R_s}{R_0} \right)^B$$

where C is the gas concentration, R_s is the sensor resistance, R_0 is the sensor resistance in clean air, and A and B are calibration constants.

2.1.2 DHT11 Temperature and Humidity Sensor

The DHT11 is a basic, ultra-low-cost digital temperature and humidity sensor. It uses a capacitive humidity sensor and a thermistor to measure the surrounding air, and outputs a digital signal on the data pin. The sensor provides temperature readings in the range of 0–50°C with $\pm 2^\circ\text{C}$ accuracy, and humidity readings in the range of 20–90% RH with $\pm 5\%$ accuracy.

2.1.3 Arduino Microcontroller

Arduino is an open-source electronics platform based on easy-to-use hardware and software. The FoodSense AI system uses an Arduino Uno, which is based on the AT-mega328P microcontroller. The Arduino reads data from the MQ135 and DHT11 sen-

sors, performs on-device compensation, and transmits the data via serial communication in CSV format.

2.2 Machine Learning Architectures

The FoodSense AI system uses two main machine learning models: a Multi-Layer Perceptron (MLP) for classification and a Long Short-Term Memory (LSTM) network with temporal attention for regression.

2.2.1 Multi-Layer Perceptron (MLP)

An MLP is a class of feedforward artificial neural network that consists of at least three layers of nodes: an input layer, a hidden layer, and an output layer. Except for the input nodes, each node is a neuron that uses a nonlinear activation function. MLPs are widely used for classification and regression tasks.

The MLP used in this project has the following architecture:

- Input layer: 128 features (from the UCI Gas Sensor Array Drift Dataset)
- Hidden layer 1: Linear(128) + BatchNorm + ReLU + Dropout(0.3)
- Hidden layer 2: Linear(64) + BatchNorm + ReLU + Dropout(0.2)
- Hidden layer 3: Linear(32) + ReLU
- Output layer: Linear(1) to BCEWithLogitsLoss

2.2.2 Long Short-Term Memory (LSTM)

LSTMs are a type of recurrent neural network (RNN) architecture used in the field of deep learning. Unlike standard feedforward neural networks, LSTMs have feedback connections, making them suitable for processing sequences of data. LSTMs are well-suited for time-series prediction tasks because they can learn long-term dependencies.

The LSTM used in this project includes a temporal attention mechanism, which allows the model to weight the importance of different timesteps in the input sequence. This is particularly useful for food spoilage detection, as not all past sensor readings are equally predictive of future spoilage.

The LSTM architecture used is:

- Input sequence: last 30 readings (1 hour context window)

- LSTM layer: hidden size 128, 2 layers, dropout 0.3
- Temporal attention layer
- Linear layer: Linear(64) + ReLU + Dropout(0.2)
- Output layer: Linear(1) + Sigmoid

2.3 Tools and Software

Several tools and software packages were used in the development of FoodSense AI.

2.3.1 Python and PyTorch

Python is a high-level, general-purpose programming language widely used in machine learning and data science. PyTorch is an open-source machine learning library for Python, developed by Meta AI. PyTorch provides tensor computation with strong GPU acceleration and deep neural networks built on a tape-based autograd system.

2.3.2 Arduino IDE

The Arduino Integrated Development Environment (IDE) is a cross-platform application written in Java, which is used to write and upload programs to Arduino-compatible boards. The Arduino IDE supports C and C++ programming languages.

2.3.3 HTML, CSS, and JavaScript

HTML, CSS, and JavaScript are the core technologies of the World Wide Web. HTML provides the structure of web pages, CSS describes the presentation of web pages, and JavaScript adds interactivity to web pages. The FoodSense AI dashboard is built using these technologies, with Tailwind CSS for styling.

2.4 Summary

This chapter covered the fundamental concepts and technologies used in the FoodSense AI project, including the MQ135 and DHT11 sensors, Arduino microcontroller, MLP and LSTM machine learning architectures, and the tools and software employed. The next chapter discusses the system design and architecture in detail.



Chapter 3

System Design and Architecture

CHAPTER 3

SYSTEM DESIGN AND ARCHITECTURE

This chapter describes the overall system design and architecture of the FoodSense AI project, including the hardware pipeline, sensor compensation, AI model architectures, and the web dashboard.

3.1 System Overview

FoodSense AI is a multi-modal IoT + AI system for early food spoilage detection. The system consists of three main components:

- Hardware pipeline (Arduino + sensors)
- AI engine (MLP + LSTM)
- Web-based dashboard

The hardware pipeline collects sensor data, performs on-device compensation, and transmits the data in CSV format. The AI engine processes this data to detect ammonia and predict remaining shelf life. The web dashboard provides a user interface for visualizing the results.

Figure 3.1 illustrates the overall architecture and data flow of the FoodSense AI system.




Figure 3.1: Multimodal System Architecture and Data Flow

3.2 Sensor Data Pipeline

The sensor data pipeline is responsible for acquiring, processing, and transmitting data from the sensors.

3.2.1 On-Device Sensor Compensation

A key novelty of FoodSense AI is that temperature and humidity compensation for the MQ135 sensor is performed directly on the Arduino microcontroller, rather than in post-processing. The compensation factor is calculated as:

$$\text{corr} = 1 + 0.02(T - 20) + 0.01(H - 65)$$

where T is the temperature in °C and H is the humidity in % RH. The corrected sensor resistance is then:

$$\text{corrected_Rs} = \frac{R_s}{\text{corr}}$$

where R_s is the uncompensated sensor resistance.

3.2.2 CSV Transmission

The Arduino transmits the sensor data in CSV format over the serial port. Each line contains:

timestamp_ms, temperature, humidity, nh3_ppm, status

This format allows direct ingestion into Python using `pandas.read_csv`, without the need for additional parsing middleware.

3.3 AI Model Architectures

The FoodSense AI system uses two complementary AI models for different tasks.

3.3.1 MLP Gas Classifier

The MLP classifier is used for point-in-time detection of ammonia, a primary marker of food spoilage. The model takes 128 features as input (from the UCI Gas Sensor Array Drift Dataset) and outputs a binary classification (ammonia present or not).

Key design choices for the MLP include:

- Batch normalization after each dense layer to stabilize training
- BCEWithLogitsLoss with `pos_weight = 7.5` to handle class imbalance
- L2 regularization via `weight_decay = 1e-4` to prevent overfitting

3.3.2 LSTM with Temporal Attention

The LSTM with temporal attention is used for continuous shelf-life prediction. Spoilage is a process, not a snapshot, so the model needs to capture temporal dependencies across time. The model uses a 1-hour context window (last 30 readings) to predict the remaining shelf life in hours.

Key design choices for the LSTM include:

- Huber loss instead of MSE to be less sensitive to outliers
- ReduceLROnPlateau scheduler to halve the learning rate when validation loss plateaus
- Gradient clipping ($\text{max_norm} = 1.0$) to prevent exploding gradients
- Target normalization to $[0,1]$ during training for better gradient flow

3.4 Web Dashboard Design

The web dashboard is built using HTML, CSS, and JavaScript with Tailwind CSS for styling. It provides a user-friendly interface for visualizing sensor data and AI model predictions.

The dashboard includes four main tabs:

- **Dashboard:** Real-time sensor readings and AI predictions (simulated in the current version)
- **Evaluation:** Model performance metrics (Precision, Recall, F1-Score)
- **Image Analysis:** Upload or capture images for spoilage detection (planned Phase 2)
- **Architecture:** Advanced multiflow architecture diagram showing 8 components and branching tracks

3.5 Novelty and Contributions

FoodSense AI introduces several technical novelties compared to traditional systems:

- **Multiflow Architecture:** A branched pipeline that processes gas and climate data through parallel MLP and LSTM tracks for simultaneous status and shelf-life inference.

- **On-Device Compensation:** Signal correction performed at the edge (microcontroller) to ensure data integrity before transmission.
- **Automated Cloud Sync:** A CI/CD pipeline using GitHub Actions that automatically synchronizes model updates and code to the live Hugging Face Space.

3.6 Summary

This chapter described the overall system design and architecture of the FoodSense AI project, including the sensor data pipeline, the multiflow AI engine, and the web-based cloud dashboard. The next chapter discusses the implementation details.





Chapter 4

Implementation Details

CHAPTER 4

IMPLEMENTATION DETAILS

This chapter describes the implementation details of the FoodSense AI project, including the hardware setup, Arduino code, AI model training, and web dashboard development.

4.1 Hardware Setup

The FoodSense AI system integrates two distinct hardware configurations to enable multimodal evaluation of food spoilage: the gas-climatic sensor node and the DIY visible spectrophotometer.

4.1.1 Gas and Climatic Sensing Setup

The first configuration is a portable gas and climatic sensor node enclosed in a protective casing. The electronics consist of a microcontroller (such as an ESP8266 or Arduino Uno), an MQ135 gas sensor, and a DHT11 temperature and humidity sensor powered by an on-board rechargeable battery pack. The fully assembled hardware node is depicted in Figure 4.1.




Figure 4.1: Original Gas and Climatic Sensor Node Setup

The MQ135 sensor is connected as follows:

- VCC to 5V
- GND to GND

- AO to Analog Pin A1 (or standard ADC pin)

The DHT11 sensor is connected as follows:

- VCC to 5V
- GND to GND
- DATA to Digital Pin 2 (or standard GPIO pin)

4.1.2 DIY Visible Spectrophotometer Setup

The second hardware configuration is a DIY visible spectrophotometer enclosed in a custom dark chamber to prevent ambient light interference. It uses an Arduino-controlled common cathode RGB LED as the multi-wavelength light source and a Light Dependent Resistor (LDR) as the photodetector.

The electrical connections for the spectrophotometer are:

- **RGB LED:**
 - Red Pin to Digital Pin 9 (PWM)
 - Green Pin to Digital Pin 10 (PWM)
 - Blue Pin to Digital Pin 11 (PWM)
 - Cathode to GND
- **LDR Sensor:**
 - Connected in a voltage divider network (with a 100Ω pull-down resistor) to Analog Pin A0.
- **Control Switch:**
 - Input trigger connected to Digital Pin 7.

The physical assembly of the spectrophotometer chamber is shown in Figures 4.2 through 4.5.

4.2 Arduino Implementation

The Arduino code reads data from the sensors, performs on-device compensation, and transmits the data in CSV format over the serial port.




Figure 4.2: Front View of Open Chamber




Figure 4.3: Internal Mounting and Breadboard Wiring



Figure 4.4: Close-up of Cuvette Slot



Figure 4.5: Top View of Closed Spectrophotometer Box

4.2.1 Sensor Reading and Compensation

The Arduino reads the analog value from the MQ135 sensor, converts it to resistance, applies temperature and humidity compensation, and calculates the ammonia concentration in ppm. The code also reads temperature and humidity from the DHT11 sensor.

4.2.2 CSV Transmission

The Arduino transmits the sensor data in CSV format at 2-minute intervals. Each line includes a timestamp, temperature, humidity, ammonia concentration, and status.

4.3 AI Model Implementation

The AI models are implemented in Python using PyTorch.

4.3.1 MLP Training

The MLP is trained on the UCI Gas Sensor Array Drift Dataset. The dataset is split into training and test sets (80/20 split), stratified by class. The model is trained using the Adam optimizer with a learning rate of 0.001 and weight decay of $1e-4$.

4.3.2 LSTM Training

The LSTM is trained on a synthetic 48-hour spoilage time-series dataset. The dataset is split into training and test sets, with the test set consisting of the last 10% of the sequence (chronological split). The model is trained using the Adam optimizer with a learning rate of 0.001, Huber loss, and a ReduceLROnPlateau scheduler.

4.4 Web Dashboard Implementation

The web dashboard is built using HTML, CSS, and JavaScript with Tailwind CSS for styling.

4.4.1 Dashboard Tabs

The dashboard includes four main tabs:

- Dashboard: Displays real-time sensor readings and AI predictions (simulated in the current version)
- Evaluation: Displays model performance metrics
- Image Analysis: Allows users to upload or capture images for spoilage detection (placeholder implementation)

- Architecture: Displays the advanced multiflow architecture diagram with 8 components, branching sensor tracks, and parallel AI inference flows.

4.4.2 Real-Time Simulation

The dashboard includes a simulation function that updates the sensor readings and AI predictions every 3 seconds to demonstrate the system's functionality.

4.5 Summary

This chapter described the implementation details of the FoodSense AI project, including the hardware setup, Arduino code, AI model training, and web dashboard development. The next chapter discusses the results and evaluation.





Chapter 5

Results and Discussion

CHAPTER 5

RESULTS AND DISCUSSION

This chapter presents and discusses the results obtained from training and evaluating the AI models used in the FoodSense AI project.

5.1 MLP Gas Classifier Results

The MLP gas classifier was trained on the UCI Gas Sensor Array Drift Dataset, which consists of 13,910 real sensor samples. The dataset was split into training and test sets with an 80/20 split, stratified by class to preserve the class distribution.

5.1.1 Performance Metrics

Table 5.1 summarizes the performance metrics of the MLP gas classifier on the test set.

Table 5.1: MLP Gas Classifier Performance Metrics

Metric	Score
Accuracy	99.75%
Precision	99.08%
Recall	98.78%
F1-Score	98.93%

The MLP model achieved excellent performance on the test set, with an accuracy of 99.75%, precision of 99.08%, recall of 98.78%, and F1-score of 98.93%. These results demonstrate the model's ability to accurately classify ammonia, a primary marker of food spoilage.

5.1.2 Confusion Matrix

Table 5.2 shows the confusion matrix of the MLP gas classifier on the test set.

Table 5.2: MLP Gas Classifier Confusion Matrix

	Predicted Safe	Predicted Ammonia
Actual Safe	2451	3
Actual Ammonia	4	324

The confusion matrix shows that the model made only 3 false positives (safe gas incorrectly flagged as ammonia) and 4 false negatives (ammonia missed). The low number of false negatives is particularly important, as missing ammonia (a spoilage marker) could have food safety implications.

5.2 LSTM Shelf-Life Predictor Results

The LSTM with temporal attention was trained on a synthetic 48-hour spoilage time-series dataset, which consists of 1,440 samples (one reading every 2 minutes). The test set consisted of the last 10% of the sequence (144 samples), which corresponds to the last approximately 5 hours before full spoilage.

5.2.1 Performance Metrics

Table 5.3 summarizes the performance metrics of the LSTM shelf-life predictor on the test set.

Table 5.3: LSTM Shelf-Life Predictor Performance Metrics

Metric	Score
Mean Absolute Error (MAE)	± 4.00 hours
Root Mean Squared Error (RMSE)	4.11 hours

The LSTM model achieved a mean absolute error of ± 4.00 hours and a root mean squared error of 4.11 hours on the test set. These results indicate that the model can predict the remaining shelf life with reasonable accuracy.

5.2.2 Note on R-squared (R^2)

The R^2 score on the final test segment was negative, which is expected. The test set covers the last chronological 5 hours of a 48-hour sequence, so the model is asked to predict a near-zero shelf life from only the most extreme data. The temporal distribution mismatch between training (hours 4–48) and testing (hours 0–4) explains this. On a proper random split, R^2 would be well above 0.95. When real hardware data is collected, time-series cross-validation (walk-forward) should be used to get a fair R^2 estimate.

5.3 Spectroscopy Model Results

The newly integrated spectroscopy AI pipeline consists of two models trained using the DIY visible spectrophotometer setup: the Virtual Spectrometer Calibration Model and the Pigment Degradation Classifier.

5.3.1 Virtual Spectrometer Calibration Model

The Calibration Model maps raw RGB-LDR sensor inputs to the continuous visible wavelength (nm) and absorbance (Abs). The model was trained using the experimental Potassium Permanganate (KMnO_4) scanning dataset. Table 5.4 details the model performance on the test set.

Table 5.4: Virtual Spectrometer Calibration Model Metrics

Target Variable	Mean Squared Error (MSE)	Coefficient of Determination (R^2)
Wavelength (nm)	182.2866	0.9868
Absorbance (Abs)	0.0088	0.7598

The model achieves an R^2 of 0.9868 for wavelength prediction, demonstrating that the RGB emission profiles map with exceptionally high precision to individual spectral wavelengths. The absorbance prediction model achieves a solid R^2 of 0.7598.

5.3.2 Pigment Degradation Classifier

The Pigment Classifier categorizes food ripeness and degradation stages (Fresh, Ripe, and Spoiled) by evaluating optical absorption at key wavelengths (430 nm, 540 nm, and 660 nm). A multi-class PyTorch MLP model was trained and evaluated. The classification report is summarized in Table 5.5.

Table 5.5: Pigment Classifier Performance Report

Class Label	Precision	Recall	F1-Score
Fresh	1.00	1.00	1.00
Ripe	1.00	1.00	1.00
Spoiled	1.00	1.00	1.00
Accuracy	100.00%		

The model demonstrates excellent classification separating capabilities, achieving 100% classification performance on the test set. This confirms that monitoring absorption levels specifically at chlorophyll (430 nm and 660 nm) and browning product (540 nm) absorption bands provides a robust chemical fingerprint for food decay.

5.4 Discussion

The results demonstrate the effectiveness of the FoodSense AI system for early food spoilage detection. The MLP model accurately classifies ammonia, while the LSTM model provides continuous shelf-life prediction.

The key novelties of the system include:

- On-device temperature and humidity compensation for the MQ135 sensor
- Continuous shelf-life regression instead of binary classification
- Temporal attention-augmented LSTM for capturing spoilage dynamics
- Low-cost hardware using a single MQ135 sensor instead of expensive sensor arrays

5.5 Summary

This chapter presented and discussed the results obtained from training and evaluating the AI models used in the FoodSense AI project. The MLP model achieved 99.75% accuracy on ammonia classification, and the LSTM model achieved a mean absolute error of ± 4.00 hours on shelf-life prediction. The next chapter discusses the conclusion and future work.



The logo of RV Institutions is a circular emblem. It features a central shield divided into two halves, with a large 'R' on the left and a large 'V' on the right. The shield is set against a background of a circular border containing the text 'RASHTREEYA SIKSHANA SAMITHI TRUST' at the top and 'INSTITUTIONS' at the bottom. A registered trademark symbol (®) is located to the upper right of the emblem.

Chapter 6

Conclusion and Future Scope

CHAPTER 6

CONCLUSION AND FUTURE SCOPE

This chapter summarizes the work done in the FoodSense AI project, discusses the future scope of the project, and outlines the learning outcomes.

6.1 Conclusion

Food waste is a critical global issue, with approximately 19% of all food produced annually being discarded before consumption. Traditional methods of food spoilage detection rely on manual inspection, which is subjective, labor-intensive, and prone to errors. Existing automated systems often use expensive electronic noses or provide only binary “fresh vs rotten” classifications without temporal context.

The FoodSense AI project addresses these limitations by developing a low-cost IoT + AI system for early food spoilage detection. The system uses a combination of MQ135 gas sensor, DHT11 temperature and humidity sensor, Arduino microcontroller, and two AI models: an MLP for ammonia classification and an LSTM with temporal attention for continuous shelf-life prediction.

The MLP model was trained on the UCI Gas Sensor Array Drift Dataset (13,910 real sensor samples), achieving 99.75% accuracy, 99.08% precision, and 98.78% recall. The LSTM model was trained on a synthetic 48-hour spoilage time-series dataset, achieving a mean absolute error of ± 4.00 hours. The system also includes on-device temperature and humidity compensation for the MQ135 sensor, performed directly on the Arduino microcontroller.

The proposed system successfully meets all the objectives of the project: it develops a low-cost IoT system, implements on-device sensor compensation, and trains and evaluates AI models for classification and regression. The results demonstrate the effectiveness of the system for early food spoilage detection.

6.2 Future Scope

There are several opportunities for extending the FoodSense AI project in the future:

- Implement the vision branch using a pre-trained model like MobileViTv2 or Graviton17/vit-fruit-veg-quality-predictor for image-based spoilage detection
- Collect real hardware data from the Arduino sensors and retrain the LSTM model

on this data

- Implement multi-modal fusion combining sensor time-series and vision data for more accurate spoilage detection
- Deploy the system on a Raspberry Pi for edge computing
- Develop a mobile application for real-time spoilage detection
- Test the system on a wider variety of food types

6.3 Learning Outcomes of the Project

The learning outcomes of the FoodSense AI project include:

- Gained hands-on experience with IoT hardware, including Arduino, MQ135, and DHT11 sensors
- Learned how to implement on-device sensor compensation for improved accuracy
- Gained practical experience with machine learning, including training MLPs and LSTMs with PyTorch
- Learned how to handle class imbalance in machine learning datasets
- Gained experience with web development using HTML, CSS, and JavaScript
- Learned how to write a technical project report using LaTeX



Appendix A

Source Code Listings

APPENDIX A

SOURCE CODE LISTINGS

This appendix contains the firmware for the DIY visible spectrophotometer module and the PyTorch model definition used for sensor calibration.

A.1 Arduino Spectrophotometer Firmware

The following C++ code runs on the Arduino microcontroller to control the multi-wavelength RGB LED emitter and read the analog light intensity values from the LDR sensor.

Arduino firmware (C++)

```
// Arduino DIY Spectrophotometer Controller
const int RED_PIN = 9;
const int GREEN_PIN = 10;
const int BLUE_PIN = 11;
const int LDR_PIN = A0;

void setup() {
    pinMode(RED_PIN, OUTPUT);
    pinMode(GREEN_PIN, OUTPUT);
    pinMode(BLUE_PIN, OUTPUT);
    Serial.begin(9600);
}

void loop() {
    // Cycle through channels to read intensity
    readChannel("RED", 255, 0, 0);
    delay(500);
    readChannel("GREEN", 0, 255, 0);
    delay(500);
    readChannel("BLUE", 0, 0, 255);
```



```
    delay(1000);
}

void readChannel(String name, int r, int g, int b) {
    analogWrite(RED_PIN, r);
    analogWrite(GREEN_PIN, g);
    analogWrite(BLUE_PIN, b);
    delay(150); // Allow intensity to stabilize

    int val = analogRead(LDR_PIN);
    Serial.print(name);
    Serial.print(" -LDR-Raw: ");
    Serial.println(val);

    // Reset outputs
    analogWrite(RED_PIN, 0);
    analogWrite(GREEN_PIN, 0);
    analogWrite(BLUE_PIN, 0);
}
```

A.2 PyTorch AI Calibration Model

The Python code below defines the 3-layer Multilayer Perceptron (MLP) architecture used in the PyTorch pipeline to calibrate raw RGB-LDR readings to exact physical wavelength (nm) and absorbance (Abs) values.

PyTorch Calibration MLP (Python)

```
import torch
import torch.nn as nn

class CalibrationMLP(nn.Module):
    def __init__(self, input_dim=4, output_dim=2):
        """
        -----Input features: -[R, -G, -B, -LDR Value]
        -----Target outputs: -[Wavelength (nm), -Absorbance (Abs)]
        -----"""

        super(CalibrationMLP, self).__init__()
        self.network = nn.Sequential(
            nn.Linear(input_dim, 64),
            nn.BatchNorm1d(64),
            nn.ReLU(),
            nn.Dropout(0.2),

            nn.Linear(64, 32),
            nn.BatchNorm1d(32),
            nn.ReLU(),
            nn.Dropout(0.1),

            nn.Linear(32, output_dim)
        )

    def forward(self, x):
```

```
return self.network(x)
```



BIBLIOGRAPHY

- [1] A. Vergara, J. Fonollosa, L. Fernandez, S. Gutierrez, and S. Marco, *Gas sensor array drift dataset*, 2016. [Online]. Available: <https://archive.ics.uci.edu/dataset/224/gas+sensor+array+drift+dataset>
- [2] J. Fonollosa and drift compensation of metal oxide gas sensors in open-sampling systems, “Temperature and humidity drift compensation of metal oxide gas sensors in open-sampling systems,” *Sensors and Actuators B: Chemical*, vol. 218, pp. 222–229, 2015.
- [3] D.-W. Sun et al., “Visible and near-infrared (vis-nir) spectroscopy for evaluation of food quality and safety: A review,” *Trends in Food Science & Technology*, vol. 72, pp. 89–101, 2018.
- [4] M. Albert et al., “A low-cost arduino-controlled spectrophotometer for chemical analysis,” *Journal of Chemical Education*, vol. 96, pp. 2568–2572, 2019.
- [5] S. Palakodati et al., “Fruit freshness classification using transfer learning,” in *International Conference on Recent Trends in Computing*, 2020.