

30-09-2025

Terminando de configurar la practica de la clase pasada

```
R2>en
R2#conf t
Enter configuration commands, one per line. End with CNTL/Z.
R2(config)#
R2(config)#
R2(config)#crypto isakmp policy 1
R2(config-isakmp)#encryption aes
R2(config-isakmp)#hash md5
R2(config-isakmp)#authenticathion pre-share
      ^
% Invalid input detected at '^' marker.

R2(config-isakmp)#authentication pre-share
R2(config-isakmp)#group 5
R2(config-isakmp)#ex
R2(config)#
R2(config)#crypto isakmp key cisco address 172.16.1.1
R2(config)#
R2(config)#crypto isakmp policy 1
R2(config-isakmp)#lifetime 86400
R2(config-isakmp)#exit
R2(config)#
R2(config)#crupto ipsec transform-set VPN esp-aes esp-md5-hmac
      ^
% Invalid input detected at '^' marker.

R2(config)#crypto ipsec transform-set VPN esp-aes esp-md5-hmac
```

```
R2(config)#
R2(config)#crypto map MAPA1 1 ipsec-isakmp
% NOTE: This new crypto map will remain disabled until a peer
and a valid access list have been configured.
R2(config-crypto-map)#set peer 172.16.1.1
R2(config-crypto-map)#set transform-set VPN
R2(config-crypto-map)#match address 100
R2(config-crypto-map)#exit
R2(config)#
R2(config)#access-list 100 permit ip host 192.168.2.10 192.168.1.0 0.0.0.255
R2(config)#
R2(config)#int s0/0/0
R2(config-if)#crypto map MAPA1
*Jan 3 07:16:26.785: %CRYPTO-6-ISA_KMP_ON_OFF: ISAKMP is ON
R2(config-if)#

do show crypto ipsec sa
```

La otra practica:

SOLO un crypto mapa por interfaz

A todos les di write (R1,R2,R3, NUBE)

```
Switch>en
Switch#conf t
Enter configuration commands, one per line. End with CNTL/Z.
Switch(config)#hostname NUBE
NUBE(config)#ip routing
```

```

NUBE(config)#
NUBE(config)#int fa0/1
NUBE(config-if)#no switchport
NUBE(config-if)#ip add 200.0.0.1 255.255.255.252
NUBE(config-if)#no shut
NUBE(config-if)#exit
NUBE(config)#int fa0/2
NUBE(config-if)#no switchport
NUBE(config-if)#ip add 200.0.0.5 255.255.255.252
NUBE(config-if)#no shut
NUBE(config-if)#ex
NUBE(config)#int fa0/3
NUBE(config-if)#no switchport
NUBE(config-if)#ip add 200.0.0.9 255.255.255.252
NUBE(config-if)#no shut
NUBE(config-if)#ex
NUBE(config)#

```

```

Router>en
Router#conf t
Enter configuration commands, one per line. End with CNTL/Z.
Router(config)#hostname R1
R1(config)#
R1(config)#int g0/0
R1(config-if)#ip add 200.0.0.2 255.255.255.252
R1(config-if)#no shut

R1(config-if)#
%LINK-5-CHANGED: Interface GigabitEthernet0/0, changed state to up

%LINEPROTO-5-UPDOWN: Line protocol on Interface GigabitEthernet0/0,
changed state to up

```

```
R1(config-if)#exit
R1(config)#
R1(config)#ip route 0.0.0.0 0.0.0.0 200.0.0.1
R1(config)#
```

```
Router>en
Router#conf t
Enter configuration commands, one per line. End with CNTL/Z.
Router(config)#hostname R2
R2(config)#int g0/0
R2(config-if)#ip add 200.0.0.6 255.255.255.252
R2(config-if)#no shut

R2(config-if)#
%LINK-5-CHANGED: Interface GigabitEthernet0/0, changed state to up

%LINEPROTO-5-UPDOWN: Line protocol on Interface GigabitEthernet0/0,
changed state to up

R2(config-if)#ip route 0.0.0.0 0.0.0.0 200.0.0.5
R2(config)#
```

```
Router>en
Router#conf t
Enter configuration commands, one per line. End with CNTL/Z.
Router(config)#
Router(config)#hostname R3
R3(config)#int g0/0
R3(config-if)#ip add 200.0.0.10 255.255.255.252
```

```
R3(config-if)#no shut
```

```
R3(config-if)#
```

```
%LINK-5-CHANGED: Interface GigabitEthernet0/0, changed state to up
```

```
%LINEPROTO-5-UPDOWN: Line protocol on Interface GigabitEthernet0/0,  
changed state to up
```

```
R3(config-if)#ip route 0.0.0.0 0.0.0.0 200.0.0.9
```

```
R3(config)#
```