■ Baby & Kid Monitor

Complete Setup & User Guide • Standalone Android Host + Zero-Install Web Viewer

---

Key Highlights: *100% Private Local Wi-Fi • No Cloud or Subscription • Zero Installation on Viewer (iPhone, iPad, Android, PC) • Two-Way Live Audio • Offline Lullabies & White Noise • Cry Decibel Alerts • Night / Sleep Mode*

1. Installing the App on your Android Phone

The Android phone serves as the camera and microphone host:

- **Transfer APK:** Send app-release.apk to your Android device (via WhatsApp, Google Drive, AirDrop-alternative, or USB).
- **Install:** Tap the APK file. If prompted with *'Install unknown apps'*, tap Settings and toggle **Allow from this source**.
- **Permissions:** Open **Baby Monitor** and tap **Allow** for Camera and Microphone permissions.
- **Server Ready:** The app will automatically launch its embedded local web server and display a large QR Code and your local stream URL (e.g., http://192.168.1.50:8080).

2. Viewing from iPhone, iPad, Android, or Computer (Zero Install!)

No app needs to be installed on any device you use to watch your baby:

- **Same Wi-Fi:** Ensure both devices are connected to the same home Wi-Fi network.
- **Scan QR Code:** Open the Camera app on your iPhone or secondary phone and point it at the QR Code on the Android screen.
- **Or Type URL:** You can also open Safari, Chrome, or Edge on any laptop/phone and type the URL shown on screen (e.g. http://192.168.1.50:8080).
- **Add to Home Screen (PWA):** On iOS Safari (tap Share ➔ Add to Home Screen) or Android Chrome (tap 3 dots ➔ Install App) to run in full-screen native app mode without browser bars.

3. Remote Nursery Controls (From Web Viewer)

Feature	How to Use & What it Does
■■ **Real-Time Intercom**	Hold **'Hold to Talk'** to speak to your baby through the phone speaker with sub-50ms latency. Or tap **'■ Hands-Free'** for continuous two-way call.
■ **Cry & Noise Alerts**	Real-time 10-bar decibel meter shows room noise level (Quiet, Activity, Crying). Plays alert chime and vibrates if noise exceeds threshold (>65dB).
■ **Soothing Sounds**	Tap 'Soothing Sounds' to play **Sweet Lullaby**, **White Noise**, **Gentle Rain**, or **Ocean Waves** on the phone. Includes 15/30/60 min sleep timers (100% offline).
■ **Remote Flashlight**	Tap 'Flashlight' to turn on the Android phone's rear torch remotely to check on the baby in the dark without walking into the room.
■ **Switch Camera**	Switch between Front and Back cameras remotely from the browser with 1 tap.
■ **Digital Zoom**	Use the zoom slider (1.0x to 4.0x) or pinch on touchscreen to zoom closely into the crib.
■ **Picture-in-Picture**	Tap the ■ icon to pop the live stream into a floating mini-window while using WhatsApp, browsing, or working on other apps.
■ **Snapshot Photo**	Tap 'Snapshot' to capture and download high-resolution photos of cute moments.
■ **Battery Indicator**	Live percentage & charging status of the camera phone displayed in the header.

4. Baby Night Mode & Travel / Hotel Setup

- ■ **AMOLED Black Screen Mode:** Tap *'Enter Night / Sleep Mode'* on the Android host. The screen turns pitch black with a dim clock so it does not illuminate the dark nursery or disturb the baby. Tap anywhere on screen to wake.
- ✈■ **Travel / Hotel Hotspot Mode:** In hotels or vacation rentals without open Wi-Fi, turn on **'Personal Hotspot'** on the Android phone. Connect your viewer phone to this hotspot and scan the QR code — it will stream with **zero internet or router required**.
- ■ **4-Digit Security PIN:** In the host app, tap *'Set PIN'* to require a 4-digit code (e.g. 1234) before anyone can view the camera feed.

5. Tips & Troubleshooting

- **Microphone Access for Intercom:** Mobile browsers require HTTPS for microphone permissions. Open https://<ip>:8443 and tap *'Advanced ➔ Proceed to site'* to accept the local LAN certificate.
- **Battery & Heat:** We recommend keeping the camera phone plugged into a charger and enabling Night Mode to keep the device cool and save battery.
- **Zero Latency:** Ensure both devices are on a 5GHz Wi-Fi network for sub-50ms instant response.