

Reporter Name: Manan Ahmed Broti

GitHub: <https://github.com/AhmedManan>

LinkedIn: <https://www.linkedin.com/in/ahmedmanan/>

ColorOS Software QA: Technical Defect Logs

Bug Report 1: Smart Sidebar Refresh Rate Lock

Field	Details
Bug ID	BUG_COS_SB_089
Defect Title	Launching applications from Smart Sidebar forces display refresh rate to lock at 60Hz instead of 120Hz.
OS Version	ColorOS 14.1 / Android 14 Stable (Build: CPH2581_14.1.0.100)
Severity / Priority	Medium / Priority-3 (Performance issue impacting visual smoothness and UI fluidity)
Component	Smart Sidebar UI Component / Display Refresh Rate Controller
Pre-conditions	1. Display refresh rate is manually set to “High (120Hz)” in System Settings. 2. Smart Sidebar feature is enabled.
Steps to Reproduce	1. Navigate to the Home Screen and scroll continuously to verify smooth 120Hz rendering. 2. Swipe inward from the screen edge to open the Smart Sidebar overlay. 3. Launch any application (e.g., Chrome or Photos) directly from the sidebar shortcuts. 4. Observe the scrolling performance and UI smoothness inside the newly opened application.
Actual Result	The display subsystem immediately drops the dynamic refresh rate to a fixed 60Hz upon launching the app from the sidebar, causing noticeable screen stutter and lag during touch interactions.
Expected Result	The system must maintain the global 120Hz configuration fluidly, regardless of whether the application is launched from the home screen or the Smart Sidebar feature.
Reproducibility Rate	10/10 (Always reproducible).

Bug Report 2: System Cloner Notification Sync Delay

Field	Details
Bug ID	BUG_COS_SC.114
Defect Title	Real-time push notifications from the Main System profile fail to sync immediately while inside the System Cloner space.
OS Version	ColorOS 14.0 Stable Base (Build: CPH2447_14.0.0.500)
Severity / Priority	High / Priority-2 (Major functional defect resulting in missing time-sensitive alerts)
Component	Core Multi-User Service / Notification Dispatcher Framework
Pre-conditions	1. System Cloner profile is configured and active. 2. The option “Show notifications from Main System” is explicitly enabled inside the Clone space settings.
Steps to Reproduce	1. Log into the secondary private space (System Cloner) via the assigned fingerprint/PIN. 2. Leave the device idle on a surface for 5 minutes to allow background optimization to trigger. 3. Send a high-priority push message (e.g., a WhatsApp text or server alert) to the Main System user profile. 4. Check the status bar and notification drawer of the active System Cloner space.
Actual Result	No immediate audio, haptic, or visual notification banner is received. Incoming alerts are severely delayed by 25 to 30 minutes, or only appear when the user manually wakes up the display.
Expected Result	The notification service must bridge profiles instantly, delivering cross-space incoming alerts in real-time without background delays.
Reproducibility Rate	7/10 (Intermittent based on device idle state duration).

Bug Report 3: Storage Analyzer Miscalculation

Field	Details
Bug ID	BUG_COS_SYS.201
Defect Title	Native Device Storage Manager miscalculates “System” files data size, showing highly inflated storage consumption (up to 95GB).
OS Version	ColorOS 13.2 & 14.0 Upgrade Matrix (Global ROM formats)
Severity / Priority	High / Priority-2 (Usability and data visualization defect causing false low-storage alerts)
Component	Settings Application / System Storage Analyzer Module
Pre-conditions	Device has been upgraded via incremental dirty OTA flashes without a factory reset for over 3 months.
Steps to Reproduce	1. Open the native Settings application. 2. Navigate to About Device → Storage. 3. Wait for the storage categorizer thread to complete its data scan and check the “System” folder size.
Actual Result	The Settings UI displays an inaccurate system size ranging from 70GB to 100GB. Terminal debugging shows the actual system core image takes only 14GB, proving that the analyzer is wrongly clustering third-party app media caches into the system category.
Expected Result	The storage indexer must scan file directories accurately, isolating core system files from user application caches and logging them under their respective categories.
Reproducibility Rate	9/10 (Commonly observed on dirty-flashed upgrade devices).