


Electromagnetics

الکترومغناطیس



Ferdowsi University of Mashhad

دانشگاه فردوسی مشهد

Instructor: سید محمد سعید ماجدی

Compiled and edited by: Aidin Shekari

Electromagnetics

الکترومغناطیس

Lecture Notes

Instructor: سید محمد سعید ماجدی

Compiled and edited by: Aidin Shekari



Ferdowsi University of Mashhad


دانشگاه فردوسی مشهد

Contents

1	Vector Analysis	1
1.1	Course Outline	2
1.2	Vector Analysis	2
1.3	Vector Algebra	3
1.4	Addition of Vectors	4
1.5	Subtraction of Vectors	4
1.6	Multiplication of Vectors	5
1.7	Dot or Scalar Product	5
1.8	Cross or Vector Product	7
1.9	Product of Three Vectors	9
1.10	Orthogonal Coordinate Systems	10
1.11	Cartesian Coordinate System	11
1.12	Cylindrical Coordinate System	15
1.13	Spherical Coordinate System	19
1.14	Integrals Containing Vector Functions	24
1.15	Differential Operations - Gradient	32
1.16	Differential Operations - Divergence	35
1.17	Differential Operations - Curl	37
1.18	Important Vector Theorems	39
1.19	Important Vector Identities	42
2	Static Electric Fields	44
2.1	Course Outline	45
2.2	Static Electric Fields	46
2.3	Fundamental Postulates of Electrostatics in Free Space	47
2.4	Coulomb's Law	49
2.5	Gauss's Law	56
2.6	Electric Potential	61
2.7	Behaviour of the Static Electric Field in Material Media	68
2.8	Conductors in Static Electric Field	69
2.9	Dielectrics in Static Electric Field	71
2.10	Electric Flux Density	72
2.11	Dielectric Constant	73
2.12	Dielectric Strength	75

2.13	Boundary Conditions for Static Electric Fields	77
2.14	Capacitance and Capacitors	80
2.15	Electrostatic Energy	89
3	Solution of Electrostatic Problems	94
3.1	Course Outline	95
3.2	Solution of Electrostatic Problems	96
3.3	Poisson's and Laplace's Equations	96
3.4	Uniqueness Theorem	99
3.5	Method of Images	100
3.6	Boundary-Value Problems	104
4	Steady Electric Currents	113
4.1	Course Outline	114
4.2	Steady Electric Currents	115
4.3	Current Density and Ohm's Law	116
4.4	Equation of Continuity and Kirchhoff's Current Law	118
4.5	Power Dissipation and Joule's Law	119
4.6	Boundary Conditions for Current Density	120
4.7	Resistance Calculations	123

1



CHAPTER


Vector Analysis

آنالیز برداری

In this chapter

1.1	Course Outline	2	1.11	Cartesian Coordinate System	11
1.2	Vector Analysis	2	1.12	Cylindrical Coordinate System	15
1.3	Vector Algebra	3	1.13	Spherical Coordinate System	19
1.4	Addition of Vectors	4	1.14	Integrals Containing Vector Functions ...	24
1.5	Subtraction of Vectors	4	1.15	Differential Operations - Gradient	32
1.6	Multiplication of Vectors	5	1.16	Differential Operations - Divergence	35
1.7	Dot or Scalar Product	5	1.17	Differential Operations - Curl	37
1.8	Cross or Vector Product	7	1.18	Important Vector Theorems	39
1.9	Product of Three Vectors	9	1.19	Important Vector Identities	42
1.10	Orthogonal Coordinate Systems	10			

1.1 Course Outline




1.2 Vector Analysis

- **Vector analysis** is a mathematical tool with which the expression and understanding of electromagnetic concepts become simple.
- Quantities in electromagnetics are divided into the following two groups.
 - **Scalar:** a quantity that is completely specified by its magnitude (positive or negative). For example: charge, electric current, energy, ...
 - **Vector:** a quantity that is described by a magnitude and a direction. For example the electric and magnetic field intensity, ...
- Both of the above quantities can be functions of position and time.

Example 1-1

- In your opinion, of what type are the following quantities?
 - Temperature
 - Power
 - Force
 - Potential difference
 - Velocity
- Apart from the above, which other scalar and vector quantities in physics can you name?



- How can two vector quantities be added or subtracted graphically?
- How can vectors be multiplied? What is the meaning of this product? Where is it used?


$$\mathbf{A} = 2\mathbf{a}_x + 3\mathbf{a}_y + \mathbf{a}_z \quad \mathbf{B} = \mathbf{a}_x - 2\mathbf{a}_y + 3\mathbf{a}_z \quad \mathbf{C} = -\mathbf{a}_x + 4\mathbf{a}_y - \mathbf{a}_z$$

- Find the magnitude of the projection of vector $\mathbf{A}$ on vector $\mathbf{B}$.
- What is the angle between vectors $\mathbf{A}$ and $\mathbf{B}$?
- What is the area of the triangle formed by the two vectors $\mathbf{A}$ and $\mathbf{B}$?
- Find the unit vector normal to the plane containing the two vectors $\mathbf{A}$ and $\mathbf{B}$.
- What is the volume of the parallelepiped formed by the 3 vectors $\mathbf{A}$, $\mathbf{B}$ and $\mathbf{C}$?

1.3 Vector Algebra

- Every vector has a magnitude and a direction.

$$\mathbf{A} = \mathbf{a}_A A, \quad \mathbf{a}_A = \frac{\mathbf{A}}{|\mathbf{A}|} = \frac{\mathbf{A}}{A} \quad (\text{unit vector})$$




① Remark

For every vector quantity both the magnitude and the direction must be known. Leaving the direction of a vector quantity unspecified means ignoring part of the information of that quantity.

1.4 Addition of Vectors

► Adding two vectors graphically

- The **parallelogram rule**
- The **head-to-tail rule**



► Laws governing the addition of vectors

- **Commutative law**

$$\mathbf{A} + \mathbf{B} = \mathbf{B} + \mathbf{A}$$


- **Associative law**

$$\mathbf{A} + (\mathbf{B} + \mathbf{C}) = (\mathbf{A} + \mathbf{B}) + \mathbf{C}$$


1.5 Subtraction of Vectors

► Vector subtraction

$$\mathbf{A} - \mathbf{B} = \mathbf{A} + (-\mathbf{B})$$



1.6 Multiplication of Vectors



- Multiplication of a vector by a scalar:

$$k\mathbf{A} = \mathbf{a}_A(kA)$$

1.7 Dot or Scalar Product

≡ Definition | Mathematical definition

$$\mathbf{A} \cdot \mathbf{B} \triangleq AB \cos \theta_{AB}$$

- It equals the product of the magnitude of one vector and the projection of the other vector on the first.




Figure 1.1 | θ_{AB} : the smaller angle between the two vectors when their tails are joined

► Properties of the dot product

- The dot product of two vectors is a scalar quantity.
- It is less than or equal to the product of their magnitudes.
- Depending on the angle between them it can be positive or negative.
- If the vectors are perpendicular to each other, it is zero.
- It is commutative and distributive.


$$\mathbf{A} \cdot \mathbf{B} = \mathbf{B} \cdot \mathbf{A}, \quad \mathbf{A} \cdot (\mathbf{B} + \mathbf{C}) = \mathbf{A} \cdot \mathbf{B} + \mathbf{A} \cdot \mathbf{C}$$

- The dot product of a vector with itself


$$\mathbf{A} \cdot \mathbf{A} = A^2, \quad A = +\sqrt{\mathbf{A} \cdot \mathbf{A}}$$

Example 1-2

Using the concept of the dot product, find the projection of vector $\mathbf{A}$ on $\mathbf{B}$.



► **Solution.**



Magnitude of the projection of vector $\mathbf{A}$ on $\mathbf{B}$:

$$A \cos \theta_{AB} = \frac{\mathbf{A} \cdot \mathbf{B}}{B}$$


Projection of vector $\mathbf{A}$ on $\mathbf{B}$:

$$\frac{\mathbf{A} \cdot \mathbf{B}}{B} \mathbf{a}_B = \left(\frac{\mathbf{A} \cdot \mathbf{B}}{B} \right) \frac{\mathbf{B}}{B} = \frac{\mathbf{A} \cdot \mathbf{B}}{B^2} \mathbf{B}$$


Example 1-3

Prove the law of cosines for a triangle using the concept of the dot product.

$$C = \sqrt{A^2 + B^2 - 2AB \cos \alpha}$$



► **Solution.**



$$\mathbf{C} = \mathbf{A} + \mathbf{B}$$

$$\begin{aligned} C^2 &= \mathbf{C} \cdot \mathbf{C} = (\mathbf{A} + \mathbf{B}) \cdot (\mathbf{A} + \mathbf{B}) \\ &= \mathbf{A} \cdot \mathbf{A} + \mathbf{B} \cdot \mathbf{B} + 2\mathbf{A} \cdot \mathbf{B} \\ &= A^2 + B^2 + 2AB \cos \theta_{AB} \end{aligned}$$

$$\cos \theta_{AB} = \cos(180^\circ - \alpha) = -\cos \alpha$$


$$C^2 = A^2 + B^2 - 2AB \cos \alpha$$

1.8 Cross or Vector Product

Definition

$$\mathbf{A} \times \mathbf{B} \triangleq \mathbf{a}_n |AB \sin \theta_{AB}|$$

- The magnitude of this product equals the area of the parallelogram formed by the vectors **A** and **B**, and its direction is perpendicular to both vectors.



- Properties of the cross product

- The cross product of two vectors is a vector quantity.
- It is not commutative

$$\mathbf{B} \times \mathbf{A} = -\mathbf{A} \times \mathbf{B}$$

- It is distributive

$$\mathbf{A} \times (\mathbf{B} + \mathbf{C}) = \mathbf{A} \times \mathbf{B} + \mathbf{A} \times \mathbf{C}$$


- It is not associative

$$\mathbf{A} \times (\mathbf{B} \times \mathbf{C}) \neq (\mathbf{A} \times \mathbf{B}) \times \mathbf{C}$$

Example 1-4

Prove the law of sines for a triangle using the concept of the cross product.

$$\frac{\sin A}{a} = \frac{\sin B}{b} = \frac{\sin C}{c}$$



► Solution.

Area of the triangle:

$$\left| \frac{1}{2} \mathbf{a} \times \mathbf{b} \right| = \left| \frac{1}{2} \mathbf{b} \times \mathbf{c} \right| = \left| \frac{1}{2} \mathbf{c} \times \mathbf{a} \right|$$

$$ab \sin C = bc \sin A = ca \sin B$$

$$\frac{\sin A}{a} = \frac{\sin B}{b} = \frac{\sin C}{c}$$


1.9 Product of Three Vectors

➤ Scalar triple product

$$\mathbf{A} \cdot (\mathbf{B} \times \mathbf{C}) = \mathbf{B} \cdot (\mathbf{C} \times \mathbf{A}) = \mathbf{C} \cdot (\mathbf{A} \times \mathbf{B})$$

➤ Its magnitude equals the volume of the parallelepiped formed by the three vectors $\mathbf{A}$, $\mathbf{B}$ and $\mathbf{C}$.

- Area of the base: $|\mathbf{B} \times \mathbf{C}| = |BC \sin \theta_1|$
- Height: $|A \cos \theta_2|$
- Volume of the parallelepiped: $|ABC \sin \theta_1 \cos \theta_2|$



➤ Vector triple product

- Known as the back-cab rule

$$\mathbf{A} \times (\mathbf{B} \times \mathbf{C}) = \mathbf{B}(\mathbf{A} \cdot \mathbf{C}) - \mathbf{C}(\mathbf{A} \cdot \mathbf{B})$$

🔗 Example 1-5


The expression $(\mathbf{A} \times \mathbf{B}) \times \mathbf{C}$ is equal to which of the following expressions?

- $\mathbf{B}(\mathbf{A} \cdot \mathbf{C}) - \mathbf{C}(\mathbf{A} \cdot \mathbf{B})$
- $-\mathbf{B}(\mathbf{A} \cdot \mathbf{C}) + \mathbf{C}(\mathbf{A} \cdot \mathbf{B})$
- $-\mathbf{A}(\mathbf{C} \cdot \mathbf{B}) + \mathbf{B}(\mathbf{C} \cdot \mathbf{A})$
- $\mathbf{A}(\mathbf{C} \cdot \mathbf{B}) - \mathbf{B}(\mathbf{C} \cdot \mathbf{A})$

➤ Solution.


$$\begin{aligned} (\mathbf{A} \times \mathbf{B}) \times \mathbf{C} &= -\mathbf{C} \times (\mathbf{A} \times \mathbf{B}) \\ &= -\mathbf{A}(\mathbf{C} \cdot \mathbf{B}) + \mathbf{B}(\mathbf{C} \cdot \mathbf{A}) \end{aligned}$$

1.10 Orthogonal Coordinate Systems




- What are the principal surfaces in the different coordinate systems?
- How are the unit vectors defined in the different coordinate systems?
- How are the position vector of a point and the distance vector between two points computed in the different coordinate systems?
- Determine the differential length, surface and volume in the different coordinate systems, for use in integration.
- Find the representation of the vector $\mathbf{A} = \mathbf{a}_r(3 \cos \phi) - \mathbf{a}_\phi 2r + \mathbf{a}_z 5$ in Cartesian coordinates.
- The position of point P in spherical coordinates is $(8, 120^\circ, 330^\circ)$. Express the position of this point in cylindrical and Cartesian coordinates.
- To describe the spatial variations of physical quantities, we must be able to describe all points of space uniquely and appropriately.
 - This requires the use of an appropriate coordinate system.
- The laws of electromagnetics do not depend on the coordinate system.
- For simplicity of the calculations, a coordinate system that suits the geometry of the problem is used.
- In three-dimensional space a point can be located at the intersection of three surfaces.
 - If these three surfaces are mutually perpendicular, we have an orthogonal coordinate system.
- The three orthogonal systems used in this course
 - Cartesian (rectangular) coordinates
 - Cylindrical coordinates
 - Spherical coordinates

1.11 Cartesian Coordinate System



- Every point $P(x_1, y_1, z_1)$ is the intersection of the three planes $x = x_1$, $y = y_1$ and $z = z_1$.
- Unit vector $\mathbf{a}_x \rightarrow$ the unit vector normal to the x -constant plane, in the positive direction
- Unit vector $\mathbf{a}_y \rightarrow$ the unit vector normal to the y -constant plane, in the positive direction
- Unit vector $\mathbf{a}_z \rightarrow$ the unit vector normal to the z -constant plane, in the positive direction
- Cross and dot products of the unit vectors

$$\mathbf{a}_x \times \mathbf{a}_y = \mathbf{a}_z, \quad \mathbf{a}_y \times \mathbf{a}_z = \mathbf{a}_x, \quad \mathbf{a}_z \times \mathbf{a}_x = \mathbf{a}_y$$



$$\mathbf{a}_x \cdot \mathbf{a}_y = \mathbf{a}_y \cdot \mathbf{a}_z = \mathbf{a}_z \cdot \mathbf{a}_x = 0$$

$$\mathbf{a}_x \cdot \mathbf{a}_x = \mathbf{a}_y \cdot \mathbf{a}_y = \mathbf{a}_z \cdot \mathbf{a}_z = 1$$

- Representation of an arbitrary vector $\mathbf{A}$ in Cartesian coordinates

⚡ Important result

$$\mathbf{A} = \mathbf{a}_x A_x + \mathbf{a}_y A_y + \mathbf{a}_z A_z$$

$$A = \sqrt{A_x^2 + A_y^2 + A_z^2}$$

► **Position vector**


- The position vector of point P is the directed distance from the origin to P .

$$\mathbf{R}_1 = x_1 \mathbf{a}_x + y_1 \mathbf{a}_y + z_1 \mathbf{a}_z, \quad \mathbf{R}_2 = x_2 \mathbf{a}_x + y_2 \mathbf{a}_y + z_2 \mathbf{a}_z$$

► **Distance vector**

- The displacement vector from one point to another.

$$\mathbf{R}_{12} = \mathbf{R}_2 - \mathbf{R}_1 = (x_2 - x_1) \mathbf{a}_x + (y_2 - y_1) \mathbf{a}_y + (z_2 - z_1) \mathbf{a}_z$$



$$\mathbf{A} = A_x \mathbf{a}_x + A_y \mathbf{a}_y + A_z \mathbf{a}_z, \quad \mathbf{B} = B_x \mathbf{a}_x + B_y \mathbf{a}_y + B_z \mathbf{a}_z$$

► **Dot product of the two vectors $\mathbf{A}$ and $\mathbf{B}$**

⚡ **Important result**

$$\mathbf{A} \cdot \mathbf{B} = A_x B_x + A_y B_y + A_z B_z$$

► **Cross product of the two vectors $\mathbf{A}$ and $\mathbf{B}$**

$$\begin{aligned} \mathbf{A} \times \mathbf{B} &= A_x B_x \mathbf{a}_x \times \mathbf{a}_x + A_x B_y \mathbf{a}_x \times \mathbf{a}_y + A_x B_z \mathbf{a}_x \times \mathbf{a}_z \\ &\quad + A_y B_x \mathbf{a}_y \times \mathbf{a}_x + A_y B_y \mathbf{a}_y \times \mathbf{a}_y + A_y B_z \mathbf{a}_y \times \mathbf{a}_z \\ &\quad + A_z B_x \mathbf{a}_z \times \mathbf{a}_x + A_z B_y \mathbf{a}_z \times \mathbf{a}_y + A_z B_z \mathbf{a}_z \times \mathbf{a}_z \\ &= (A_y B_z - A_z B_y) \mathbf{a}_x + (A_z B_x - A_x B_z) \mathbf{a}_y + (A_x B_y - A_y B_x) \mathbf{a}_z \end{aligned}$$

⚡ **Important result**

$$\mathbf{A} \times \mathbf{B} = \begin{vmatrix} \mathbf{a}_x & \mathbf{a}_y & \mathbf{a}_z \\ A_x & A_y & A_z \\ B_x & B_y & B_z \end{vmatrix}$$

- Differential length → **vector**

$$d\ell = \mathbf{a}_x dx + \mathbf{a}_y dy + \mathbf{a}_z dz$$


- Differential surface → **vector**

$$d\mathbf{S} = dS \mathbf{a}_n$$

$$d\mathbf{S} = dy dz \mathbf{a}_x, \quad d\mathbf{S} = dx dz \mathbf{a}_y, \quad d\mathbf{S} = dx dy \mathbf{a}_z$$

- Differential volume → **scalar**


$$dv = dx dy dz$$



Example 1-6

- (a) Find the vector whose initial point is $P_1(1, 3, 2)$ and whose terminal point is $P_2(3, -2, 4)$.
 (b) What is the length of this vector?

► Solution.



$$\begin{aligned}
 \overrightarrow{P_1P_2} &= \overrightarrow{OP_2} - \overrightarrow{OP_1} \\
 (a) \quad &= (\mathbf{a}_x 3 - \mathbf{a}_y 2 + \mathbf{a}_z 4) - (\mathbf{a}_x + \mathbf{a}_y 3 + \mathbf{a}_z 2) \\
 &= \mathbf{a}_x 2 - \mathbf{a}_y 5 + \mathbf{a}_z 2 \\
 (b) \quad P_1P_2 &= |\overrightarrow{P_1P_2}| = \sqrt{2^2 + (-5)^2 + 2^2} = \sqrt{33}
 \end{aligned}$$

Example 1-7


Given $\mathbf{A} = \mathbf{a}_x 5 - \mathbf{a}_y 2 + \mathbf{a}_z$, find the unit vector $\mathbf{B}$ such that

- (a) $\mathbf{B} \parallel \mathbf{A}$
- (b) $\mathbf{B}$ lies in the xy -plane and is perpendicular to $\mathbf{A}$

► Solution.

$$\begin{aligned}
 (a) \quad \mathbf{B} &= \frac{\mathbf{A}}{A} = \frac{\mathbf{a}_x 5 - \mathbf{a}_y 2 + \mathbf{a}_z}{\sqrt{5^2 + 2^2 + 1^2}} = \frac{\mathbf{a}_x 5 - \mathbf{a}_y 2 + \mathbf{a}_z}{\sqrt{30}} \\
 (b) \quad &\begin{cases} B = \sqrt{B_x^2 + B_y^2 + B_z^2} = 1 \\ B_z = 0 \\ \mathbf{B} \cdot \mathbf{A} = 5B_x - 2B_y = 0 \end{cases} \Rightarrow \begin{cases} B_x = \frac{2}{\sqrt{29}} \\ B_y = \frac{5}{\sqrt{29}} \end{cases}
 \end{aligned}$$

1.12 Cylindrical Coordinate System




- Every point $P(r_1, \phi_1, z_1)$ is the intersection of the cylinder $r = r_1$, the half-plane $\phi = \phi_1$ and the plane $z = z_1$.
- Unit vector $\mathbf{a}_r \rightarrow$ the unit vector normal to the r -constant cylinder, in the positive direction
- Unit vector $\mathbf{a}_\phi \rightarrow$ the unit vector normal to the ϕ -constant half-plane, in the positive direction
- Unit vector $\mathbf{a}_z \rightarrow$ the unit vector normal to the z -constant plane, in the positive direction

① Remark

The directions of the vectors $\mathbf{a}_r$ and $\mathbf{a}_\phi$ change from point to point in space. This must be taken into account in integration.

- Cross and dot products of the unit vectors

$$\mathbf{a}_r \times \mathbf{a}_\phi = \mathbf{a}_z, \quad \mathbf{a}_\phi \times \mathbf{a}_z = \mathbf{a}_r, \quad \mathbf{a}_z \times \mathbf{a}_r = \mathbf{a}_\phi$$



$$\mathbf{a}_r \cdot \mathbf{a}_r = \mathbf{a}_\phi \cdot \mathbf{a}_\phi = \mathbf{a}_z \cdot \mathbf{a}_z = 1$$

$$\mathbf{a}_r \cdot \mathbf{a}_\phi = \mathbf{a}_\phi \cdot \mathbf{a}_z = \mathbf{a}_z \cdot \mathbf{a}_r = 0$$


- Representation of an arbitrary vector $\mathbf{A}$ in cylindrical coordinates

⚡ Important result

$$\mathbf{A} = \mathbf{a}_r A_r + \mathbf{a}_\phi A_\phi + \mathbf{a}_z A_z$$

$$A = \sqrt{A_r^2 + A_\phi^2 + A_z^2}$$

► Position vector




$$\mathbf{R} = r\mathbf{a}_r + z\mathbf{a}_z$$

Example 1-8

The cylindrical coordinates of an arbitrary point P are $(r, \phi, 0)$. Find the unit vector from the point $z = h$ on the z -axis toward the point P .

► Solution.



$$\overrightarrow{QP} = \overrightarrow{OP} - \overrightarrow{OQ} = (\mathbf{a}_r r) - (\mathbf{a}_z h)$$

$$\mathbf{a}_{QP} = \frac{\overrightarrow{QP}}{|\overrightarrow{QP}|} = \frac{1}{\sqrt{r^2 + h^2}} (\mathbf{a}_r r - \mathbf{a}_z h)$$

► Differential length → vector


$$d\ell = \mathbf{a}_r dr + \mathbf{a}_\phi r d\phi + \mathbf{a}_z dz$$

► Differential surface → vector

$$d\mathbf{S} = r d\phi dz \mathbf{a}_r, \quad d\mathbf{S} = dr dz \mathbf{a}_\phi, \quad d\mathbf{S} = r dr d\phi \mathbf{a}_z$$


► Differential volume → scalar

$$dv = r dr d\phi dz$$



- Transformation of the representation of a vector from cylindrical to Cartesian coordinates

$$\mathbf{A} = \mathbf{a}_r A_r + \mathbf{a}_\phi A_\phi + \mathbf{a}_z A_z \quad \Rightarrow \quad \mathbf{A} = \mathbf{a}_x A_x + \mathbf{a}_y A_y + \mathbf{a}_z A_z$$



$$\mathbf{a}_r = \cos \phi \mathbf{a}_x + \sin \phi \mathbf{a}_y, \quad \mathbf{a}_\phi = -\sin \phi \mathbf{a}_x + \cos \phi \mathbf{a}_y, \quad \mathbf{a}_z = \mathbf{a}_z$$

$$\begin{aligned} \mathbf{A} &= (\cos \phi \mathbf{a}_x + \sin \phi \mathbf{a}_y) A_r + (-\sin \phi \mathbf{a}_x + \cos \phi \mathbf{a}_y) A_\phi + \mathbf{a}_z A_z \\ &\Rightarrow \mathbf{A} = \mathbf{a}_x (\cos \phi A_r - \sin \phi A_\phi) + \mathbf{a}_y (\sin \phi A_r + \cos \phi A_\phi) + \mathbf{a}_z A_z \end{aligned}$$

- Transformation of the representation of a vector from Cartesian to cylindrical coordinates

$$\mathbf{A} = \mathbf{a}_x A_x + \mathbf{a}_y A_y + \mathbf{a}_z A_z \quad \Rightarrow \quad \mathbf{A} = \mathbf{a}_r A_r + \mathbf{a}_\phi A_\phi + \mathbf{a}_z A_z$$

$$\mathbf{a}_x = \cos \phi \mathbf{a}_r - \sin \phi \mathbf{a}_\phi, \quad \mathbf{a}_y = \sin \phi \mathbf{a}_r + \cos \phi \mathbf{a}_\phi, \quad \mathbf{a}_z = \mathbf{a}_z$$

$$\begin{aligned} \mathbf{A} &= (\cos \phi \mathbf{a}_r - \sin \phi \mathbf{a}_\phi) A_x + (\sin \phi \mathbf{a}_r + \cos \phi \mathbf{a}_\phi) A_y + \mathbf{a}_z A_z \\ &\Rightarrow \mathbf{A} = \mathbf{a}_r (\cos \phi A_x + \sin \phi A_y) + \mathbf{a}_\phi (-\sin \phi A_x + \cos \phi A_y) + \mathbf{a}_z A_z \end{aligned}$$

- Transformation of the representation of a vector from cylindrical to Cartesian coordinates

⚡ Important result

$$\begin{bmatrix} A_x \\ A_y \\ A_z \end{bmatrix} = \begin{bmatrix} \cos \phi & -\sin \phi & 0 \\ \sin \phi & \cos \phi & 0 \\ 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} A_r \\ A_\phi \\ A_z \end{bmatrix}$$

- Transformation of the representation of a vector from Cartesian to cylindrical coordinates

⚡ Important result


$$\begin{bmatrix} A_r \\ A_\phi \\ A_z \end{bmatrix} = \begin{bmatrix} \cos \phi & \sin \phi & 0 \\ -\sin \phi & \cos \phi & 0 \\ 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} A_x \\ A_y \\ A_z \end{bmatrix}$$

- Transformation from cylindrical to Cartesian coordinates


$$x = r \cos \phi, \quad y = r \sin \phi, \quad z = z$$

- Transformation from Cartesian to cylindrical coordinates

$$r = \sqrt{x^2 + y^2}, \quad \phi = \tan^{-1} \frac{y}{x}, \quad z = z$$



1.13 Spherical Coordinate System




- Every point $P(R_1, \theta_1, \phi_1)$ is the intersection of the sphere $R = R_1$, the cone $\theta = \theta_1$ and the half-plane $\phi = \phi_1$
- Unit vector $\mathbf{a}_R \rightarrow$ the unit vector normal to the R -constant sphere, in the positive direction
- Unit vector $\mathbf{a}_\theta \rightarrow$ the unit vector normal to the θ -constant cone, in the positive direction
- Unit vector $\mathbf{a}_\phi \rightarrow$ the unit vector normal to the ϕ -constant half-plane, in the positive direction

Remark

The directions of the vectors $\mathbf{a}_R$, $\mathbf{a}_\theta$ and $\mathbf{a}_\phi$ change from point to point in space. This must be taken into account in integration.

- Cross and dot products of the unit vectors

$$\mathbf{a}_R \times \mathbf{a}_\theta = \mathbf{a}_\phi, \quad \mathbf{a}_\theta \times \mathbf{a}_\phi = \mathbf{a}_R, \quad \mathbf{a}_\phi \times \mathbf{a}_R = \mathbf{a}_\theta$$



$$\mathbf{a}_R \cdot \mathbf{a}_R = \mathbf{a}_\theta \cdot \mathbf{a}_\theta = \mathbf{a}_\phi \cdot \mathbf{a}_\phi = 1$$

$$\mathbf{a}_R \cdot \mathbf{a}_\theta = \mathbf{a}_\theta \cdot \mathbf{a}_\phi = \mathbf{a}_\phi \cdot \mathbf{a}_R = 0$$


- Representation of an arbitrary vector $\mathbf{A}$ in spherical coordinates

⚡ Important result

$$\mathbf{A} = \mathbf{a}_R A_R + \mathbf{a}_\theta A_\theta + \mathbf{a}_\phi A_\phi$$

$$A = \sqrt{A_R^2 + A_\theta^2 + A_\phi^2}$$

- Position vector



$$\mathbf{R} = R_1 \mathbf{a}_R$$

- Differential length → **vector**


$$d\ell = \mathbf{a}_R dR + \mathbf{a}_\theta R d\theta + \mathbf{a}_\phi R \sin \theta d\phi$$

- Differential surface → **vector**

$$d\mathbf{S} = R^2 \sin \theta d\theta d\phi \mathbf{a}_R, \quad d\mathbf{S} = R \sin \theta dR d\phi \mathbf{a}_\theta, \quad d\mathbf{S} = R dR d\theta \mathbf{a}_\phi$$


- Differential volume → **scalar**

$$dv = R^2 \sin \theta dR d\theta d\phi$$



- Transformation of the representation of a vector from spherical to cylindrical coordinates

$$\mathbf{A} = \mathbf{a}_R A_R + \mathbf{a}_\theta A_\theta + \mathbf{a}_\phi A_\phi \quad \Rightarrow \quad \mathbf{A} = \mathbf{a}_r A_r + \mathbf{a}_\phi A_\phi + \mathbf{a}_z A_z$$



$$\mathbf{a}_R = \sin \theta \mathbf{a}_r + \cos \theta \mathbf{a}_z, \quad \mathbf{a}_\theta = \cos \theta \mathbf{a}_r - \sin \theta \mathbf{a}_z, \quad \mathbf{a}_\phi = \mathbf{a}_\phi$$

$$\begin{aligned} \mathbf{A} &= (\sin \theta \mathbf{a}_r + \cos \theta \mathbf{a}_z) A_R \\ &\quad + (\cos \theta \mathbf{a}_r - \sin \theta \mathbf{a}_z) A_\theta \\ &\quad + \mathbf{a}_\phi A_\phi \end{aligned} \quad \Rightarrow \quad \begin{aligned} \mathbf{A} &= \mathbf{a}_r (\sin \theta A_R + \cos \theta A_\theta) \\ &\quad + \mathbf{a}_\phi A_\phi \\ &\quad + \mathbf{a}_z (\cos \theta A_R - \sin \theta A_\theta) \end{aligned}$$

- Transformation of the representation of a vector from cylindrical to spherical coordinates

$$\mathbf{A} = \mathbf{a}_r A_r + \mathbf{a}_\phi A_\phi + \mathbf{a}_z A_z \quad \Rightarrow \quad \mathbf{A} = \mathbf{a}_R A_R + \mathbf{a}_\theta A_\theta + \mathbf{a}_\phi A_\phi$$

$$\mathbf{a}_r = \sin \theta \mathbf{a}_R + \cos \theta \mathbf{a}_\theta, \quad \mathbf{a}_\phi = \mathbf{a}_\phi, \quad \mathbf{a}_z = \cos \theta \mathbf{a}_R - \sin \theta \mathbf{a}_\theta$$

$$\begin{aligned} \mathbf{A} &= (\sin \theta \mathbf{a}_R + \cos \theta \mathbf{a}_\theta) A_r \\ &\quad + \mathbf{a}_\phi A_\phi \\ &\quad + (\cos \theta \mathbf{a}_R - \sin \theta \mathbf{a}_\theta) A_z \end{aligned} \quad \Rightarrow \quad \begin{aligned} \mathbf{A} &= \mathbf{a}_R (\sin \theta A_r + \cos \theta A_z) \\ &\quad + \mathbf{a}_\theta (\cos \theta A_r - \sin \theta A_z) \\ &\quad + \mathbf{a}_\phi A_\phi \end{aligned}$$

- Transformation of the representation of a vector from spherical to cylindrical coordinates

⚡ Important result

$$\begin{bmatrix} A_r \\ A_\phi \\ A_z \end{bmatrix} = \begin{bmatrix} \sin \theta & \cos \theta & 0 \\ 0 & 0 & 1 \\ \cos \theta & -\sin \theta & 0 \end{bmatrix} \begin{bmatrix} A_R \\ A_\theta \\ A_\phi \end{bmatrix}$$

- Transformation of the representation of a vector from cylindrical to spherical coordinates

⚡ Important result

$$\begin{bmatrix} A_R \\ A_\theta \\ A_\phi \end{bmatrix} = \begin{bmatrix} \sin \theta & 0 & \cos \theta \\ \cos \theta & 0 & -\sin \theta \\ 0 & 1 & 0 \end{bmatrix} \begin{bmatrix} A_r \\ A_\phi \\ A_z \end{bmatrix}$$

- Transformation of the representation of a vector from Cartesian to spherical coordinates

$$\mathbf{A} = \mathbf{a}_x A_x + \mathbf{a}_y A_y + \mathbf{a}_z A_z \quad \Rightarrow \quad \mathbf{A} = \mathbf{a}_R A_R + \mathbf{a}_\theta A_\theta + \mathbf{a}_\phi A_\phi$$

$$\begin{cases} \mathbf{a}_x = \cos \phi \mathbf{a}_r - \sin \phi \mathbf{a}_\phi \\ \mathbf{a}_y = \sin \phi \mathbf{a}_r + \cos \phi \mathbf{a}_\phi \\ \mathbf{a}_z = \mathbf{a}_z \end{cases} \quad \begin{cases} \mathbf{a}_r = \sin \theta \mathbf{a}_R + \cos \theta \mathbf{a}_\theta \\ \mathbf{a}_\phi = \mathbf{a}_\phi \\ \mathbf{a}_z = \cos \theta \mathbf{a}_R - \sin \theta \mathbf{a}_\theta \end{cases}$$

$$\Rightarrow \begin{cases} \mathbf{a}_x = \sin \theta \cos \phi \mathbf{a}_R + \cos \theta \cos \phi \mathbf{a}_\theta - \sin \phi \mathbf{a}_\phi \\ \mathbf{a}_y = \sin \theta \sin \phi \mathbf{a}_R + \cos \theta \sin \phi \mathbf{a}_\theta + \cos \phi \mathbf{a}_\phi \\ \mathbf{a}_z = \cos \theta \mathbf{a}_R - \sin \theta \mathbf{a}_\theta \end{cases}$$

⚡ Important result

$$\begin{bmatrix} A_R \\ A_\theta \\ A_\phi \end{bmatrix} = \begin{bmatrix} \sin \theta \cos \phi & \sin \theta \sin \phi & \cos \theta \\ \cos \theta \cos \phi & \cos \theta \sin \phi & -\sin \theta \\ -\sin \phi & \cos \phi & 0 \end{bmatrix} \begin{bmatrix} A_x \\ A_y \\ A_z \end{bmatrix}$$

- Transformation of the representation of a vector from spherical to Cartesian coordinates

$$\mathbf{A} = \mathbf{a}_R A_R + \mathbf{a}_\theta A_\theta + \mathbf{a}_\phi A_\phi \quad \Rightarrow \quad \mathbf{A} = \mathbf{a}_x A_x + \mathbf{a}_y A_y + \mathbf{a}_z A_z$$

$$\begin{cases} \mathbf{a}_R = \sin \theta \mathbf{a}_r + \cos \theta \mathbf{a}_z \\ \mathbf{a}_\theta = \cos \theta \mathbf{a}_r - \sin \theta \mathbf{a}_z \\ \mathbf{a}_\phi = \mathbf{a}_\phi \end{cases} \quad \begin{cases} \mathbf{a}_r = \cos \phi \mathbf{a}_x + \sin \phi \mathbf{a}_y \\ \mathbf{a}_\phi = -\sin \phi \mathbf{a}_x + \cos \phi \mathbf{a}_y \\ \mathbf{a}_z = \mathbf{a}_z \end{cases}$$

$$\Rightarrow \begin{cases} \mathbf{a}_R = \sin \theta \cos \phi \mathbf{a}_x + \sin \theta \sin \phi \mathbf{a}_y + \cos \theta \mathbf{a}_z \\ \mathbf{a}_\theta = \cos \theta \cos \phi \mathbf{a}_x + \cos \theta \sin \phi \mathbf{a}_y - \sin \theta \mathbf{a}_z \\ \mathbf{a}_\phi = -\sin \phi \mathbf{a}_x + \cos \phi \mathbf{a}_y \end{cases}$$

⚡ Important result

$$\begin{bmatrix} A_x \\ A_y \\ A_z \end{bmatrix} = \begin{bmatrix} \sin \theta \cos \phi & \cos \theta \cos \phi & -\sin \phi \\ \sin \theta \sin \phi & \cos \theta \sin \phi & \cos \phi \\ \cos \theta & -\sin \theta & 0 \end{bmatrix} \begin{bmatrix} A_R \\ A_\theta \\ A_\phi \end{bmatrix}$$

- Transformation from cylindrical to spherical coordinates

$$R = \sqrt{r^2 + z^2}, \quad \theta = \tan^{-1} \frac{r}{z}, \quad \phi = \phi$$

- Transformation from spherical to cylindrical coordinates


$$r = R \sin \theta, \quad \phi = \phi, \quad z = R \cos \theta$$

- Transformation from spherical to Cartesian coordinates


$$x = R \sin \theta \cos \phi, \quad y = R \sin \theta \sin \phi, \quad z = R \cos \theta$$

- Transformation from Cartesian to spherical coordinates

$$R = \sqrt{x^2 + y^2 + z^2}, \quad \theta = \tan^{-1} \frac{\sqrt{x^2 + y^2}}{z}, \quad \phi = \tan^{-1} \frac{y}{x}$$



1.14 Integrals Containing Vector Functions



- The kinds of integrals containing vector functions that we deal with

$$\begin{aligned}
 &\int_C \mathbf{F} d\ell \quad \iint_S \mathbf{F} ds \quad \iiint_V \mathbf{F} dv \\
 &\int_C V d\ell \\
 &\int_C \mathbf{F} \cdot d\ell \quad \iint_S \mathbf{A} \cdot ds \\
 &\int_C \mathbf{F} \times d\ell
 \end{aligned}$$

Remark

Important points about integration involving vector functions

- Using an appropriate coordinate system
- Correct determination of the differential length, surface and volume
- Attention to the variation of the unit vectors $\mathbf{a}_r$, $\mathbf{a}_R$, $\mathbf{a}_\theta$ and $\mathbf{a}_\phi$ over the range of integration

- The integral of a vector function over a specified curve, surface and volume

$$\int_C \mathbf{F} d\ell \quad \iint_S \mathbf{F} ds \quad \iiint_V \mathbf{F} dv$$


- The result is a vector.
- Important applications in electromagnetics: computing the electric field intensity due to a line, surface and volume charge distribution

$$\begin{cases} \mathbf{E} = \frac{1}{4\pi\epsilon_0} \int_C \frac{\rho_\ell d\ell' (\mathbf{R} - \mathbf{R}')}{|\mathbf{R} - \mathbf{R}'|^3} \\ \mathbf{E} = \frac{1}{4\pi\epsilon_0} \iint_S \frac{\rho_s ds' (\mathbf{R} - \mathbf{R}')}{|\mathbf{R} - \mathbf{R}'|^3} \\ \mathbf{E} = \frac{1}{4\pi\epsilon_0} \iiint_V \frac{\rho_v dv' (\mathbf{R} - \mathbf{R}')}{|\mathbf{R} - \mathbf{R}'|^3} \end{cases}$$


Example 1-9

Evaluate the following integral over the curve C .

$$\int_C \mathbf{F} d\ell, \quad \mathbf{F} = 3a\mathbf{a}_r$$



► **Solution.**



$$d\ell = r d\phi = a d\phi$$

$$\int_C \mathbf{F} d\ell = \int_0^\pi 3a\mathbf{a}_r a d\phi = 3a \int_0^\pi (\cos \phi \mathbf{a}_x + \sin \phi \mathbf{a}_y) d\phi = 6a\mathbf{a}_y$$

- ▶ The integral of a scalar function along a specified path

$$\int_C V \, d\ell$$

- ▶ The result is a vector.
- ▶ Important applications in electromagnetics: computing the magnetic potential due to a line current


$$\mathbf{A} = \frac{\mu_0 I}{4\pi} \oint_C \frac{d\ell'}{|\mathbf{R} - \mathbf{R}'|}$$

Example 1-10

Evaluate the following integral along the following paths

$$\int_O^P r^2 d\ell, \quad r^2 = x^2 + y^2$$

- Path OP
- Path OP_1P
- Path OP_2P



➤ Solution.

- Along the path OP

$$\begin{aligned} \int_O^P r^2 d\ell &= \mathbf{a}_r \int_0^{\sqrt{2}} r^2 dr = \mathbf{a}_r \frac{2\sqrt{2}}{3} \\ &= \frac{2\sqrt{2}}{3} (\mathbf{a}_x \cos 45^\circ + \mathbf{a}_y \sin 45^\circ) \\ &= \mathbf{a}_x \frac{2}{3} + \mathbf{a}_y \frac{2}{3} \end{aligned}$$

- Along the path OP_1P

$$\begin{aligned} \int_O^P (x^2 + y^2) d\ell &= \mathbf{a}_y \int_O^{P_1} y^2 dy + \mathbf{a}_x \int_{P_1}^P (x^2 + 1) dx \\ &= \mathbf{a}_y \frac{1}{3} y^3 \Big|_0^1 + \mathbf{a}_x \left(\frac{1}{3} x^3 + x \right) \Big|_0^1 \\ &= \mathbf{a}_x \frac{4}{3} + \mathbf{a}_y \frac{1}{3} \end{aligned}$$

- Along the path OP_2P

$$\begin{aligned} \int_O^P (x^2 + y^2) d\ell &= \mathbf{a}_x \int_O^{P_2} x^2 dx + \mathbf{a}_y \int_{P_2}^P (1 + y^2) dy \\ &= \mathbf{a}_x \frac{1}{3} x^3 \Big|_0^1 + \mathbf{a}_y \left(y + \frac{1}{3} y^3 \right) \Big|_0^1 \\ &= \mathbf{a}_x \frac{1}{3} + \mathbf{a}_y \frac{4}{3} \end{aligned}$$

► Scalar line integral

$$\int_C \mathbf{F} \cdot d\ell$$

► The result is a scalar.

► If $\mathbf{F}$ is a force

- the work done by the force in moving a body from point P_1 to point P_2 along the specified path C

► Important applications in electromagnetics

- Computing the electric potential difference between the points P_1 and P_2 :

$$V = - \int_{P_1}^{P_2} \mathbf{E} \cdot d\ell$$


- Ampère's circuital law:

$$\mu_0 I = - \oint_C \mathbf{B} \cdot d\ell$$

Example 1-11

Evaluate the following integral along the quarter-circle path of the figure.

$$\int_A^B \mathbf{F} \cdot d\ell, \quad \mathbf{F} = \mathbf{a}_x xy - \mathbf{a}_y 2x$$



► Solution.

$$\begin{bmatrix} F_r \\ F_\phi \\ F_z \end{bmatrix} = \begin{bmatrix} \cos \phi & \sin \phi & 0 \\ -\sin \phi & \cos \phi & 0 \\ 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} xy \\ -2x \\ 0 \end{bmatrix}$$

$$\mathbf{F} = \mathbf{a}_r(xy \cos \phi - 2x \sin \phi) - \mathbf{a}_\phi(xy \sin \phi + 2x \cos \phi)$$

$$d\ell = \mathbf{a}_\phi 3 d\phi \quad \mathbf{F} \cdot d\ell = -3(xy \sin \phi + 2x \cos \phi) d\phi$$

$$x = 3 \cos \phi \quad y = 3 \sin \phi$$

$$\int_A^B \mathbf{F} \cdot d\ell = \int_0^{\pi/2} -3(9 \sin^2 \phi \cos \phi + 6 \cos^2 \phi) d\phi = -9 \left(1 + \frac{\pi}{2} \right)$$

- Scalar surface integral

$$\iint_S \mathbf{A} \cdot d\mathbf{s}$$

- The result is a scalar.
- Result of the integral $\rightarrow$ the flux of the vector field $\mathbf{A}$ passing through the surface S
- Vector differential surface

$$d\mathbf{s} = \mathbf{a}_n ds$$




Figure 1.2 | Direction of $\mathbf{a}_n$ for a closed surface: normal to the surface, pointing out of the volume; for an open surface: depends on the direction of travel along the rim of the open surface, by the right-hand rule

- Important applications in electromagnetics

- Gauss's law in free space:

$$\oiint_S \mathbf{E} \cdot d\mathbf{s} = \frac{Q}{\epsilon_0}$$


- Computing the electric current:

$$\iint_S \mathbf{J} \cdot d\mathbf{s} = I$$

Example 1-12

Evaluate the following integral over the closed surface about the z -axis specified by $z = \pm 3$ and $r = 2$

$$\oint_S \mathbf{F} \cdot d\mathbf{s}, \quad \mathbf{F} = \mathbf{a}_r \frac{k_1}{r} + \mathbf{a}_z k_2 z$$



► Solution.

$$\oint_S \mathbf{F} \cdot d\mathbf{s} = \oint_S \mathbf{F} \cdot \mathbf{a}_n ds = \int_{\text{top face}} \mathbf{F} \cdot \mathbf{a}_n ds + \int_{\text{bottom face}} \mathbf{F} \cdot \mathbf{a}_n ds + \int_{\text{side wall}} \mathbf{F} \cdot \mathbf{a}_n ds$$

► Top face

$$z = 3, \quad \mathbf{a}_n = \mathbf{a}_z, \quad \mathbf{F} \cdot \mathbf{a}_n = k_2 z = 3k_2, \quad ds = r dr d\phi$$

$$\int_{\text{top face}} \mathbf{F} \cdot \mathbf{a}_n ds = \int_0^{2\pi} \int_0^2 3k_2 r dr d\phi = 12\pi k_2$$

► Bottom face

$$z = -3, \quad \mathbf{a}_n = -\mathbf{a}_z, \quad \mathbf{F} \cdot \mathbf{a}_n = -k_2 z = 3k_2, \quad ds = r dr d\phi$$

$$\int_{\text{bottom face}} \mathbf{F} \cdot \mathbf{a}_n ds = 12\pi k_2$$

► Side wall

$$r = 2, \quad \mathbf{a}_n = \mathbf{a}_r, \quad \mathbf{F} \cdot \mathbf{a}_n = \frac{k_1}{r} = \frac{k_1}{2}, \quad ds = r d\phi dz = 2 d\phi dz$$

$$\int_{\text{side wall}} \mathbf{F} \cdot \mathbf{a}_n ds = \int_{-3}^3 \int_0^{2\pi} k_1 d\phi dz = 12\pi k_1$$

$$\oint_S \mathbf{F} \cdot d\mathbf{s} = 12\pi k_2 + 12\pi k_2 + 12\pi k_1 = 12\pi(k_1 + 2k_2)$$

► Vector line integral

$$\int_C \mathbf{F} \times d\ell$$

- The result is a vector.
- Important applications in electromagnetics

– Biot–Savart law:

$$\mathbf{B} = \frac{\mu_0 I}{4\pi} \oint_C \frac{d\ell \times (\mathbf{R} - \mathbf{R}')}{|\mathbf{R} - \mathbf{R}'|^3}$$


– Computing the magnetic force on a current-carrying wire in a magnetic field:

$$\mathbf{F} = I \oint_C d\ell \times \mathbf{B}$$

Example 1-13

Evaluate the following integral along the path C .

$$\int_C \mathbf{F} \times d\ell, \quad \mathbf{F} = 2\mathbf{a}_z$$



► Solution.


$$d\ell = r d\phi \mathbf{a}_\phi = a d\phi \mathbf{a}_\phi$$

$$\begin{aligned} \int_C \mathbf{F} \times d\ell &= \int_{2\pi}^0 2\mathbf{a}_z \times a d\phi \mathbf{a}_\phi = -2a \int_{2\pi}^0 \mathbf{a}_r d\phi \\ &= -2a \int_{2\pi}^0 (\cos \phi \mathbf{a}_x + \sin \phi \mathbf{a}_y) d\phi = 0 \end{aligned}$$

1.15 Differential Operations - Gradient

► Prerequisite concepts for the discussion of the gradient

- The concept of the derivative of a function of one variable
 - The rate of change of the function at the point of interest
- The concept of the directional derivative of a function of several variables
 - The rate of change of the function at the point of interest and in a specified direction



△ Definition | Gradient


The gradient of a **scalar quantity** is a **vector quantity** that lies in the direction in which the scalar quantity increases most, and whose magnitude equals the maximum rate of increase of the scalar quantity.

$$\text{grad } v = \nabla v = \mathbf{a}_n \frac{dv}{dn}$$

- The directional derivative of v in the direction of $d\ell$:

$$\frac{dv}{d\ell} = \nabla v \cdot \mathbf{a}_\ell$$

- The gradient of v is normal to the surfaces of constant v .



- The gradient in Cartesian coordinates is as follows

⚡ Important result

$$\nabla v = \frac{\partial v}{\partial x} \mathbf{a}_x + \frac{\partial v}{\partial y} \mathbf{a}_y + \frac{\partial v}{\partial z} \mathbf{a}_z$$

- The general expression of the gradient



⚡ Important result

$$\nabla V = \mathbf{a}_{u_1} \frac{\partial V}{h_1 \partial u_1} + \mathbf{a}_{u_2} \frac{\partial V}{h_2 \partial u_2} + \mathbf{a}_{u_3} \frac{\partial V}{h_3 \partial u_3}$$

Metric coefficients	Cartesian	Cylindrical	Spherical
h_1	1	1	1
h_2	1	r	R
h_3	1	1	$R \sin \theta$

- **The concept of the gradient**

- Representing a hill by contours of height $\rightarrow h(x, y)$
- If a ball is placed at point P , in which direction does it move and what is the magnitude of the force acting on it?
 - The answer is proportional to $-\nabla h$.



Example 1-14

The electric field intensity $\mathbf{E}$ can be obtained as the negative of the gradient of the scalar electric potential V . Find $\mathbf{E}$ at the point $(1, 1, 0)$ if

$$V = E_0 R \cos \theta$$

► **Solution.**

$$\mathbf{E} = -\nabla V$$


$$\begin{aligned}\mathbf{E} &= -\left[\mathbf{a}_R \frac{\partial}{\partial R} + \mathbf{a}_\theta \frac{1}{R} \frac{\partial}{\partial \theta} + \mathbf{a}_\phi \frac{1}{R \sin \theta} \frac{\partial}{\partial \phi}\right] E_0 R \cos \theta \\ &= -(\mathbf{a}_R \cos \theta - \mathbf{a}_\theta \sin \theta) E_0\end{aligned}$$

$$\mathbf{E} = -\mathbf{a}_z E_0$$

1.16 Differential Operations - Divergence

► Prerequisite concepts for the discussion of the divergence


- In studying vector fields it is easier to represent the variations of the field graphically by flux lines. These are directed lines or curves that indicate the direction of the vector field at each point.



- The flux of a vector field is analogous to the flow of a fluid such as water.
- If $\mathbf{A}$ is a flux density vector, the total flux leaving the surface S equals

$$\oint_S \mathbf{A} \cdot d\mathbf{s}$$

- In a volume with a closed surface, there will be an excess of inward or outward flux only when the volume contains a sink or a source, respectively.
 - The net outward flux from v_a is positive: there is a source in the volume v_a
 - The net outward flux from v_b is negative: there is a sink in the volume v_b
 - The net outward flux from v_c is zero.



≡ Definition | Divergence

The divergence of a **vector field** $\mathbf{A}$ at a point is the net outward flux of $\mathbf{A}$ per unit volume as the volume about the point tends to zero

$$\text{div } \mathbf{A} \triangleq \lim_{\Delta v \rightarrow 0} \frac{\oint_S \mathbf{A} \cdot d\mathbf{s}}{\Delta v}$$

- In Cartesian coordinates the divergence is as follows

⚡ Important result

$$\operatorname{div} \mathbf{A} = \frac{\partial A_x}{\partial x} + \frac{\partial A_y}{\partial y} + \frac{\partial A_z}{\partial z} \quad \nabla \cdot \mathbf{A} \equiv \operatorname{div} \mathbf{A}$$

- The general expression of the divergence

⚡ Important result

$$\nabla \cdot \mathbf{A} = \frac{1}{h_1 h_2 h_3} \left[\frac{\partial}{\partial u_1} (h_2 h_3 A_1) + \frac{\partial}{\partial u_2} (h_1 h_3 A_2) + \frac{\partial}{\partial u_3} (h_1 h_2 A_3) \right]$$

🔗 Example 1-15

The magnetic flux density $\mathbf{B}$ outside a long current-carrying wire is circular and inversely proportional to the distance from the axis of the wire. Find the divergence of $\mathbf{B}$.


► Solution.

- Assuming the wire coincides with the z -axis

$$\mathbf{B} = \mathbf{a}_\phi \frac{k}{r}$$

$$\nabla \cdot \mathbf{B} = \frac{1}{r} \frac{\partial}{\partial r} (r B_r) + \frac{1}{r} \frac{\partial B_\phi}{\partial \phi} + \frac{\partial B_z}{\partial z}$$

$$\nabla \cdot \mathbf{B} = 0$$



1.17 Differential Operations - Curl

► Prerequisite concepts for the discussion of the curl

- The circulation of a vector field around a closed path

$$\text{Circulation of } \mathbf{A} \text{ around contour } C \triangleq \oint_C \mathbf{A} \cdot d\boldsymbol{\ell}$$

- The physical meaning of the circulation depends on the kind of field that the vector $\mathbf{A}$ represents.
 - If $\mathbf{A}$ is the force acting on a body, the circulation of $\mathbf{A}$ is the work done by the force in moving the body around the path.

$\triangleq$ Definition | Curl

The curl of a **vector field** $\mathbf{A}$ at a point is a **vector** whose magnitude is the maximum net circulation of $\mathbf{A}$ per unit area as the area about the point tends to zero, and whose direction is the direction of the normal to the area when the area is oriented so as to make the net circulation maximum.

$$\text{curl } \mathbf{A} \equiv \nabla \times \mathbf{A} \triangleq \lim_{\Delta s \rightarrow 0} \frac{1}{\Delta s} \left[\mathbf{a}_n \oint_C \mathbf{A} \cdot d\boldsymbol{\ell} \right]_{\max}$$

- In Cartesian coordinates the curl is as follows

⚡ Important result

$$\nabla \times \mathbf{A} = \begin{vmatrix} \mathbf{a}_x & \mathbf{a}_y & \mathbf{a}_z \\ \frac{\partial}{\partial x} & \frac{\partial}{\partial y} & \frac{\partial}{\partial z} \\ A_x & A_y & A_z \end{vmatrix}$$


- The general expression of the curl

⚡ Important result

$$\nabla \times \mathbf{A} = \frac{1}{h_1 h_2 h_3} \begin{vmatrix} \mathbf{a}_{u_1} h_1 & \mathbf{a}_{u_2} h_2 & \mathbf{a}_{u_3} h_3 \\ \frac{\partial}{\partial u_1} & \frac{\partial}{\partial u_2} & \frac{\partial}{\partial u_3} \\ h_1 A_1 & h_2 A_2 & h_3 A_3 \end{vmatrix}$$

► **The concept of the curl**

- The rotation of a paddle wheel in a stream of water with velocity vector u
 - The maximum angular velocity of the paddle wheel is proportional to the magnitude of the curl of the velocity vector.
 - The axis of the wheel, by the right-hand rule, lies in the direction of the curl.




Example 1-16

Find the curl of the following vector


$$\mathbf{A} = \mathbf{a}_\phi \left(\frac{k}{r} \right)$$

► **Solution.**

$$\nabla \times \mathbf{A} = \frac{1}{r} \begin{vmatrix} \mathbf{a}_r & \mathbf{a}_\phi r & \mathbf{a}_z \\ \frac{\partial}{\partial r} & \frac{\partial}{\partial \phi} & \frac{\partial}{\partial z} \\ 0 & k & 0 \end{vmatrix} = 0$$




1.18 Important Vector Theorems



▽ Theorem | Divergence theorem

The volume integral of the divergence of a vector field equals the total outward flux of the vector through the surface enclosing the volume.


$$\int_V \nabla \cdot \mathbf{A} \, dv = \oint_S \mathbf{A} \cdot d\mathbf{s}$$



▽ Theorem | Stokes's theorem

The surface integral of the curl of a vector field over an open surface equals the closed line integral of the vector along the contour bounding the surface.

$$\int_S (\nabla \times \mathbf{A}) \cdot d\mathbf{s} = \oint_C \mathbf{A} \cdot d\boldsymbol{\ell}$$


**▽ Theorem** | Helmholtz's theorem

A vector field is determined to within an additive constant if both its divergence and its curl are specified.

Example 1-17

Verify the divergence theorem for the shell region enclosed by the spherical surfaces $R = R_1$ and $R = R_2$ ($R_2 > R_1$) centred at the origin, for the following vector field.

$$\mathbf{F} = \mathbf{a}_R kR$$



► **Solution.**

$$\int_V \nabla \cdot \mathbf{A} dv = \oint_S \mathbf{A} \cdot d\mathbf{s}$$

► For the outer surface

$$R = R_2, \quad d\mathbf{s} = \mathbf{a}_R R_2^2 \sin \theta d\theta d\phi$$

$$\int_{\text{outer surface}} \mathbf{F} \cdot d\mathbf{s} = \int_0^{2\pi} \int_0^\pi (kR_2) R_2^2 \sin \theta d\theta d\phi = 4\pi k R_2^3$$

► For the inner surface

$$R = R_1, \quad d\mathbf{s} = -\mathbf{a}_R R_1^2 \sin \theta d\theta d\phi$$

$$\int_{\text{inner surface}} \mathbf{F} \cdot d\mathbf{s} = - \int_0^{2\pi} \int_0^\pi (kR_1) R_1^2 \sin \theta d\theta d\phi = -4\pi k R_1^3$$

$$\oint_S \mathbf{F} \cdot d\mathbf{s} = 4\pi k (R_2^3 - R_1^3)$$


$$\nabla \cdot \mathbf{F} = \frac{1}{R^2} \frac{\partial}{\partial R} (R^2 F_R) = \frac{1}{R^2} \frac{\partial}{\partial R} (kR^3) = 3k$$

$$\int_V \nabla \cdot \mathbf{F} dv = (\nabla \cdot \mathbf{F}) V = 4\pi k (R_2^3 - R_1^3)$$

Example 1-18

Verify Stokes's theorem over a quarter of a circular disk of radius 3 in the first quadrant for the following vector field.

$$\mathbf{F} = \mathbf{a}_x xy - \mathbf{a}_y 2x$$



► **Solution.**

$$\int_S (\nabla \times \mathbf{A}) \cdot d\mathbf{s} = \oint_C \mathbf{A} \cdot d\boldsymbol{\ell}$$

$$\nabla \times \mathbf{F} = \begin{vmatrix} \mathbf{a}_x & \mathbf{a}_y & \mathbf{a}_z \\ \frac{\partial}{\partial x} & \frac{\partial}{\partial y} & \frac{\partial}{\partial z} \\ xy & -2x & 0 \end{vmatrix} = -\mathbf{a}_z (2 + x)$$

$$\int_S (\nabla \times \mathbf{F}) \cdot d\mathbf{s} = \int_0^{\pi/2} \int_0^3 -\mathbf{a}_z (2 + r \cos \phi) \cdot r dr d\phi \mathbf{a}_z = -9 \left(1 + \frac{\pi}{2} \right)$$

► From B to O

$$x = 0, \text{ and } \mathbf{F} \cdot d\boldsymbol{\ell} = \mathbf{F} \cdot (\mathbf{a}_y dy) = 2x dy = 0$$

► From O to A

$$y = 0, \text{ and } \mathbf{F} \cdot d\boldsymbol{\ell} = \mathbf{F} \cdot (\mathbf{a}_x dx) = xy dx = 0$$

$$\oint_{ABOA} \mathbf{F} \cdot d\boldsymbol{\ell} = \int_A^B \mathbf{F} \cdot d\boldsymbol{\ell} = -9 \left(1 + \frac{\pi}{2} \right)$$

(examined in Example 1-11)

1.19 Important Vector Identities

⚡ Important result | Identity I

The curl of the gradient of any scalar quantity is zero

$$\nabla \times (\nabla V) \equiv 0$$

- A curl-free vector field is called an **irrotational** or **conservative** field.
- If a vector quantity is curl-free, it can be expressed as the gradient of a scalar quantity.


⚡ **Important result** | Identity II

The divergence of the curl of any vector field is zero.

$$\nabla \cdot (\nabla \times \mathbf{A}) \equiv 0$$

- A divergence-free vector field is called a **solenoidal** field.
- If a vector quantity is divergence-free, it can be expressed as the curl of a vector quantity.

2



CHAPTER


Static Electric Fields

میدان‌های الکتریکی ساکن

In this chapter


2.1	Course Outline	45	2.8	Conductors in Static Electric Field	69
2.2	Static Electric Fields	46	2.9	Dielectrics in Static Electric Field	71
2.3	Fundamental Postulates of Electrostatics in Free Space	47	2.10	Electric Flux Density	72
2.4	Coulomb's Law	49	2.11	Dielectric Constant	73
2.5	Gauss's Law	56	2.12	Dielectric Strength	75
2.6	Electric Potential	61	2.13	Boundary Conditions for Static Electric Fields	77
2.7	Behaviour of the Static Electric Field in Material Media	68	2.14	Capacitance and Capacitors	80
			2.15	Electrostatic Energy	89

2.1 Course Outline



2.2 Static Electric Fields

- In electrostatics the electric charges are at rest and the electric fields do not change with time.
 - In this case there are no magnetic fields.
- In introductory physics the development of electrostatics usually begins with Coulomb's experimental law for the force between two charges.
- In this course, instead of following the historical development of electrostatics, we introduce the subject by postulating the divergence and the curl of the electric field intensity in free space.



- What are the fundamental postulates of electrostatics from which the other relations and laws of the subject can be derived?
- How are Coulomb's and Gauss's laws derived from these postulates?
- How is the electric field of a point charge, of a number of discrete point charges and of a continuous charge distribution computed?

2.3 Fundamental Postulates of Electrostatics in Free Space

► Electric field intensity

- The force on a small test charge placed in the field, divided by the charge. $\rightarrow$ N/C (newtons per coulomb), equivalent to V/m (volts per metre)

$\triangleq$ Definition

$$\mathbf{E} = \lim_{q \rightarrow 0} \frac{\mathbf{F}}{q} \quad (\text{V/m})$$

- The electric field intensity is proportional to the force and in the same direction.
- The two fundamental postulates of electrostatics in free space

⚡ Important result

$$\nabla \cdot \mathbf{E} = \frac{\rho}{\epsilon_0} \quad \nabla \times \mathbf{E} = 0$$

- ρ : volume charge density (C/m^3); ϵ_0 : permittivity of free space (F/m)
- $\mathbf{E}$ is not solenoidal unless $\rho = 0$
- $\mathbf{E}$ is irrotational
- Integral form of the first equation $\rightarrow$ integration over an arbitrary volume V

$$\int_V \nabla \cdot \mathbf{E} \, dv = \frac{1}{\epsilon_0} \int_V \rho \, dv$$

- $\int_V \rho \, dv$: the total charge contained in the volume V enclosed by the surface S
- Using the divergence theorem:

⚡ Important result

$$\oint_S \mathbf{E} \cdot d\mathbf{s} = \frac{Q}{\epsilon_0}$$

- This relation is a form of **Gauss's law**
 - The total outward flux of the electric field intensity through any closed surface equals the total charge enclosed in the surface divided by ϵ_0 .
- Integral form of the second equation $\rightarrow$ integration over an arbitrary open surface S


$$\int_S (\nabla \times \mathbf{E}) \cdot d\mathbf{s} = 0$$

- Using Stokes's theorem:

⚡ Important result

$$\oint_C \mathbf{E} \cdot d\ell = 0$$

- The scalar line integral of the static electric field intensity around any closed path is zero.
- The scalar product $\mathbf{E} \cdot d\ell$ integrated over any path is the voltage along that path.
- This equation is an expression of **Kirchhoff's voltage law**
 - The algebraic sum of the voltage drops around any closed path is zero.
- The line integrals of the irrotational field $\mathbf{E}$ are independent of the path and depend only on the initial and final points.



$$\oint_C \mathbf{E} \cdot d\ell = 0$$


$$\int_{C_1} \mathbf{E} \cdot d\ell + \int_{C_2} \mathbf{E} \cdot d\ell = 0$$

$$\int_{P_1}^{P_2} \mathbf{E} \cdot d\ell + \int_{P_2}^{P_1} \mathbf{E} \cdot d\ell = 0$$

$$\int_{\text{Along } C_1}^{P_2}_{P_1} \mathbf{E} \cdot d\ell = - \int_{\text{Along } C_2}^{P_1}_{P_2} \mathbf{E} \cdot d\ell$$


$$\int_{\text{Along } C_1}^{P_2}_{P_1} \mathbf{E} \cdot d\ell = \int_{\text{Along } C_2}^{P_2}_{P_1} \mathbf{E} \cdot d\ell$$

2.4 Coulomb's Law



► The electric field intensity of a point charge q in free space

- We consider a hypothetical spherical surface of radius R centred at q .
- Since a point charge has no preferred direction, we expect the field to be radial everywhere and its intensity to be constant over the spherical surface.



► The electric field intensity on the spherical surface:

$$\mathbf{E} = E_R \mathbf{a}_R$$


$$\oint_S \mathbf{E} \cdot d\mathbf{s} = \oint_S (\mathbf{a}_R E_R) \cdot \mathbf{a}_R ds = \frac{q}{\epsilon_0}$$

$$E_R \oint_S ds = E_R (4\pi R^2) = \frac{q}{\epsilon_0}$$

⚡ Important result

$$\mathbf{E} = \mathbf{a}_R E_R = \mathbf{a}_R \frac{q}{4\pi\epsilon_0 R^2} \quad (\text{V/m})$$

- If the charge is not at the origin of the coordinate system



$$\mathbf{E}_P = \mathbf{a}_{qP} \frac{q}{4\pi\epsilon_0 |\mathbf{R} - \mathbf{R}'|^2}, \quad \mathbf{a}_{qP} = \frac{\mathbf{R} - \mathbf{R}'}{|\mathbf{R} - \mathbf{R}'|}$$

⚡ Important result

$$\mathbf{E}_P = \frac{q(\mathbf{R} - \mathbf{R}')}{4\pi\epsilon_0 |\mathbf{R} - \mathbf{R}'|^3} \quad (\text{V/m})$$

- When a point charge q_2 is placed in the electric field of another point charge q_1 , the force acting on it is

⚡ Important result | Mathematical statement of Coulomb's law


$$\mathbf{F}_{12} = q_2 \mathbf{E}_{12} = \mathbf{a}_R \frac{q_1 q_2}{4\pi\epsilon_0 R^2} \quad (\text{N})$$



► The electric field intensity of a set of discrete charges

⚡ Important result

$$\mathbf{E} = \frac{1}{4\pi\epsilon_0} \sum_{k=1}^n \frac{q_k(\mathbf{R} - \mathbf{R}'_k)}{|\mathbf{R} - \mathbf{R}'_k|^3} \quad (\text{V/m})$$



► **The electric field intensity of a continuous charge distribution**

- The field of a differential charge dq is

$$d\mathbf{E} = \frac{dq(\mathbf{R} - \mathbf{R}')}{4\pi\epsilon_0|\mathbf{R} - \mathbf{R}'|^3}$$

► **Line charge distribution**

$$dq = \rho_\ell d\ell' \quad \mathbf{E} = \int_{L'} \frac{\rho_\ell d\ell' (\mathbf{R} - \mathbf{R}')}{4\pi\epsilon_0|\mathbf{R} - \mathbf{R}'|^3}$$

► **Surface charge distribution**

$$dq = \rho_s ds' \quad \mathbf{E} = \int_{S'} \frac{\rho_s ds' (\mathbf{R} - \mathbf{R}')}{4\pi\epsilon_0|\mathbf{R} - \mathbf{R}'|^3}$$

► **Volume charge distribution**


$$dq = \rho_v dv' \quad \mathbf{E} = \int_{V'} \frac{\rho_v dv' (\mathbf{R} - \mathbf{R}')}{4\pi\epsilon_0|\mathbf{R} - \mathbf{R}'|^3}$$

► **Steps in computing the electric field intensity of a continuous charge distribution**

- Choosing an appropriate coordinate system
- Correctly determining the differential element $d\ell'$, ds' and dv' (note that in these relations the magnitudes of the differential length and surface vectors are used)
- Correctly determining the position vector of the field point ($\mathbf{R}$)
- Correctly determining the position vector of the source point ($\mathbf{R}'$)
- Evaluating the integral
 - Note that we integrate with respect to the primed coordinates.

Example 2-1

Determine the electric field intensity of an infinitely long straight line charge of uniform density ρ_ℓ .



► Solution.

$$\mathbf{E} = \int_{L'} \frac{\rho_\ell d\ell' (\mathbf{R} - \mathbf{R}')}{4\pi\epsilon_0 |\mathbf{R} - \mathbf{R}'|^3}$$

► Choosing cylindrical coordinates

$$d\ell' = dz' \quad \mathbf{R} = r\mathbf{a}_r \quad \mathbf{R}' = z'\mathbf{a}_z$$

$$\mathbf{E} = \frac{\rho_\ell}{4\pi\epsilon_0} \int_{-\infty}^{\infty} \frac{r\mathbf{a}_r - z'\mathbf{a}_z}{(r^2 + z'^2)^{3/2}} dz'$$


► It is intuitively clear that the field has no component along z .

$$\mathbf{E} = \mathbf{a}_r E_r = \mathbf{a}_r \frac{\rho_\ell r}{4\pi\epsilon_0} \int_{-\infty}^{\infty} \frac{dz'}{(r^2 + z'^2)^{3/2}}$$

$$\mathbf{E} = \mathbf{a}_r \frac{\rho_\ell}{2\pi\epsilon_0 r} \quad (\text{V/m})$$

Example 2-2

A ring of radius a carries a line charge density ρ_ℓ . Find the electric field intensity on the axis of the ring at a distance h from it.



► Solution.

$$\mathbf{E} = \int_{L'} \frac{\rho_\ell d\ell' (\mathbf{R} - \mathbf{R}')}{4\pi\epsilon_0 |\mathbf{R} - \mathbf{R}'|^3}$$

► Choosing cylindrical coordinates

$$d\ell' = a d\phi' \quad \mathbf{R} = h\mathbf{a}_z \quad \mathbf{R}' = a\mathbf{a}_{r'}$$


$$\mathbf{E} = \frac{\rho_\ell}{4\pi\epsilon_0} \int_0^{2\pi} \frac{h\mathbf{a}_z - a\mathbf{a}_{r'}}{(a^2 + h^2)^{3/2}} a d\phi'$$

► It is intuitively clear that the field has no component along r .

$$\mathbf{E} = \frac{\rho_\ell a h}{4\pi\epsilon_0 (a^2 + h^2)^{3/2}} \mathbf{a}_z \int_0^{2\pi} d\phi' = \frac{\rho_\ell a h}{2\epsilon_0 (a^2 + h^2)^{3/2}} \mathbf{a}_z$$

Example 2-3

Determine the electric field intensity of an infinite planar charge with a uniform surface charge density ρ_s .



► **Solution.**

$$\mathbf{E} = \int_{S'} \frac{\rho_s ds' (\mathbf{R} - \mathbf{R}')}{4\pi\epsilon_0 |\mathbf{R} - \mathbf{R}'|^3}$$

► Choosing cylindrical coordinates


$$ds' = r' dr' d\phi' \quad \mathbf{R} = h\mathbf{a}_z \quad \mathbf{R}' = r'\mathbf{a}_{r'}$$

$$\mathbf{E} = \frac{\rho_s}{4\pi\epsilon_0} \int_0^{2\pi} \int_0^\infty \frac{h\mathbf{a}_z - r'\mathbf{a}_{r'}}{(h^2 + r'^2)^{3/2}} r' dr' d\phi'$$

► It is intuitively clear that the field has no component along r .

$$\mathbf{E} = \frac{\rho_s h \mathbf{a}_z}{4\pi\epsilon_0} \int_0^{2\pi} \int_0^\infty \frac{r' dr' d\phi'}{(h^2 + r'^2)^{3/2}} = \frac{\rho_s}{2\epsilon_0} \mathbf{a}_z$$

2.5 Gauss's Law



⚡ Important result

$$\oint_S \mathbf{E} \cdot d\mathbf{s} = \frac{Q}{\epsilon_0}$$

- Q : the total charge contained in the volume V enclosed by the surface S
- The total outward flux of the electric field intensity through any closed surface equals the total charge enclosed in the surface divided by ϵ_0 .
- The surface S can be any closed surface, chosen for convenience.


📌 Remark

Gauss's law always holds, but in using it to determine the electric field intensity the following point must be observed.

- The basis of applying Gauss's law to determine the electric field intensity lies, first, in recognizing the conditions of symmetry and, second, in choosing an appropriate surface over which the normal component of $\mathbf{E}$ due to a given charge distribution is constant (the Gaussian surface).

Example 2-4

Using Gauss's law, determine the electric field intensity of an infinitely long straight line charge of uniform density ρ_ℓ at a distance r from it.



► Solution.

$$\mathbf{E} = \mathbf{a}_r E_r$$

► Choosing a cylinder of length L and radius r as the Gaussian surface


- For the top and bottom faces: $\mathbf{E} \cdot d\mathbf{s} = 0$
- For the side surface: $d\mathbf{s} = \mathbf{a}_r r d\phi dz$

$$\oint_S \mathbf{E} \cdot d\mathbf{s} = \int_0^L \int_0^{2\pi} E_r r d\phi dz = 2\pi r L E_r$$

$$Q = \rho_\ell L \quad 2\pi r L E_r = \frac{\rho_\ell L}{\epsilon_0} \quad \mathbf{E} = \mathbf{a}_r E_r = \mathbf{a}_r \frac{\rho_\ell}{2\pi \epsilon_0 r}$$

Example 2-5

Determine the electric field intensity of an infinite planar charge with a uniform surface charge density ρ_s .



► Solution.

$$\mathbf{E} = \pm E_z \mathbf{a}_z$$

- Choosing a box as the Gaussian surface
- For the top face

$$\mathbf{E} \cdot d\mathbf{s} = (\mathbf{a}_z E_z) \cdot (\mathbf{a}_z ds) = E_z ds$$

- For the bottom face

$$\mathbf{E} \cdot d\mathbf{s} = (-\mathbf{a}_z E_z) \cdot (-\mathbf{a}_z ds) = E_z ds$$

- For the side faces

$$\mathbf{E} \cdot d\mathbf{s} = 0$$

- Therefore

$$\oint_S \mathbf{E} \cdot d\mathbf{s} = 2E_z \int_A ds = 2E_z A$$

$$Q = \rho_s A \quad 2E_z A = \frac{\rho_s A}{\epsilon_0}$$


⚡ Important result

$$\mathbf{E} = \mathbf{a}_z E_z = \mathbf{a}_z \frac{\rho_s}{2\epsilon_0}, \quad z > 0$$

$$\mathbf{E} = -\mathbf{a}_z E_z = -\mathbf{a}_z \frac{\rho_s}{2\epsilon_0}, \quad z < 0$$

Example 2-6

Determine the field $\mathbf{E}$ of an electron cloud with volume charge density $\rho = -\rho_0$ in the region $0 \leq R \leq b$ and $\rho = 0$ in the region $R > b$.



► Solution.

$$\mathbf{E} = \mathbf{a}_R E_R$$

► (a) $0 \leq R \leq b$

– Choosing a sphere as the Gaussian surface

$$d\mathbf{s} = \mathbf{a}_R ds$$

$$\oint_{S_i} \mathbf{E} \cdot d\mathbf{s} = E_R \int_{S_i} ds = E_R 4\pi R^2$$

$$Q = \int_V \rho dv = -\rho_0 \int_V dv = -\rho_0 \frac{4\pi}{3} R^3 \quad \mathbf{E} = -\mathbf{a}_R \frac{\rho_0}{3\epsilon_0} R$$

► (b) $R \geq b$

– Choosing a sphere as the Gaussian surface

$$d\mathbf{s} = \mathbf{a}_R ds$$


$$\oint_{S_o} \mathbf{E} \cdot d\mathbf{s} = E_R \int_{S_o} ds = E_R 4\pi R^2$$

$$Q = -\rho_0 \frac{4\pi}{3} b^3 \quad \mathbf{E} = -\mathbf{a}_R \frac{\rho_0 b^3}{3\epsilon_0 R^2}$$

Example 2-7

A spherical charge distribution of radius b has the following density. Find the electric field intensity at all points of space.

$$\rho_v = \begin{cases} \frac{\rho_0 R}{b} & 0 \leq R \leq b \\ 0 & R > b \end{cases}$$



► Solution.

$$\mathbf{E} = \mathbf{a}_R E_R$$

- (a) $0 \leq R \leq b$

– Choosing a sphere as the Gaussian surface

$$d\mathbf{s} = \mathbf{a}_R ds$$

$$\oint_{S_i} \mathbf{E} \cdot d\mathbf{s} = E_R \int_{S_i} ds = E_R 4\pi R^2$$

$$Q = \int_v \rho_v dv = \int_0^{2\pi} \int_0^\pi \int_0^R \frac{\rho_0 R}{b} R^2 \sin \theta dR d\theta d\phi = \frac{\rho_0 \pi R^4}{b}$$

$$\mathbf{E} = E_R \mathbf{a}_R = \frac{\rho_0 R^2}{4\epsilon_0 b} \mathbf{a}_R$$

- (b) $R \geq b$


– Choosing a sphere as the Gaussian surface

$$d\mathbf{s} = \mathbf{a}_R ds$$


$$\oint_{S_o} \mathbf{E} \cdot d\mathbf{s} = E_R \int_{S_o} ds = E_R 4\pi R^2 \quad Q = \rho_0 \pi b^3$$

$$\mathbf{E} = E_R \mathbf{a}_R = \frac{\rho_0 b^3}{4\epsilon_0 R^2} \mathbf{a}_R$$

2.6 Electric Potential



- What is the concept of the electric potential difference between two points and of the electric potential of a point?
- How is the electric potential of a point charge, of a number of discrete point charges and of a continuous charge distribution computed?
- How can the electric field intensity be computed from the electric potential, and what is the advantage of this over computing the electric field intensity directly?
- Suppose we want to move a point charge q , located in the electric field $\mathbf{E}$, by $d\ell$.



- The force exerted on the charge by the electric field:

$$\mathbf{F}_E = q\mathbf{E}$$

- The magnitude of the component of this force along $d\ell$:

$$F_{EL} = \mathbf{F}_E \cdot \mathbf{a}_\ell = q\mathbf{E} \cdot \mathbf{a}_\ell$$

- The force that must be applied to the charge:

$$F_{\text{apply}} = -F_{EL} = -q\mathbf{E} \cdot \mathbf{a}_\ell$$

- ▶ The work done in moving the charge by $d\ell$:

$$dW = F_{\text{apply}} d\ell = -q\mathbf{E} \cdot d\ell$$

- ▶ The work done in moving the charge from point P_1 to point P_2 :

$$W = -q \int_{P_1}^{P_2} \mathbf{E} \cdot d\ell$$

$$\nabla \times \mathbf{E} = 0 \Rightarrow \mathbf{E} = -\nabla V$$

$$\nabla V \cdot \mathbf{a}_\ell = \frac{dV}{d\ell}$$

$$q = +1 \text{ C} \quad W = \int_{P_1}^{P_2} \nabla V \cdot d\ell \quad \Rightarrow \quad W = \int_{P_1}^{P_2} dV = V_2 - V_1$$

Definition | Electric potential difference

The electric potential difference between two points is the work done by an external source in moving a unit positive charge from one point to the other.

$$V_2 - V_1 = - \int_{P_1}^{P_2} \mathbf{E} \cdot d\ell$$

- ▶ It does not depend on the path of integration
- ▶ In many cases a reference point at infinity with zero potential is chosen, and the potential differences of the various points are expressed with respect to this reference point.

Important result

$$V_P = - \int_{\infty}^P \mathbf{E} \cdot d\ell$$


Remark | Remark 1

The minus sign in the potential relation is needed for consistency with the fact that moving against the direction of the field increases the electric potential.

Remark | Remark 2

The gradient of V is normal to the surfaces of constant V ; consequently the electric field lines are normal to the equipotential surfaces.

- ▶ The electric potential of a point charge q at a distance R from it



$$V = - \int_{\infty}^R \left(\frac{q}{4\pi\epsilon_0 R^2} \mathbf{a}_R \right) \cdot dR \mathbf{a}_R = \frac{q}{4\pi\epsilon_0 R}$$

- ▶ The electric potential of n discrete point charges

$$V = \frac{1}{4\pi\epsilon_0} \sum_{k=1}^n \frac{q_k}{|\mathbf{R} - \mathbf{R}'_k|}$$

- ▶ $\mathbf{R}$: position vector of the field point; $\mathbf{R}'_k$: position vectors of the source points

- ▶ The electric potential of a continuous charge distribution

- Line charge distribution

$$V = \frac{1}{4\pi\epsilon_0} \int_{L'} \frac{\rho_\ell d\ell'}{|\mathbf{R} - \mathbf{R}'|}$$

- Surface charge distribution

$$V = \frac{1}{4\pi\epsilon_0} \int_{S'} \frac{\rho_s ds'}{|\mathbf{R} - \mathbf{R}'|}$$

- Volume charge distribution


$$V = \frac{1}{4\pi\epsilon_0} \int_{V'} \frac{\rho_v dv'}{|\mathbf{R} - \mathbf{R}'|}$$

Example 2-8

Find the electric potential and the electric field intensity of an electric dipole at an arbitrary point very far from it.

► **Solution.**

$$V = \frac{1}{4\pi\epsilon_0} \sum_{k=1}^2 \frac{q_k}{|\mathbf{R} - \mathbf{R}'_k|} = \frac{1}{4\pi\epsilon_0} \left[\frac{q}{|\mathbf{R} - \mathbf{d}/2|} + \frac{-q}{|\mathbf{R} + \mathbf{d}/2|} \right]$$



$$V = \frac{q}{4\pi\epsilon_0} \left(\frac{1}{R_+} - \frac{1}{R_-} \right)$$


$$\frac{1}{R_+} \cong \left(R - \frac{d}{2} \cos \theta \right)^{-1} \cong R^{-1} \left(1 + \frac{d}{2R} \cos \theta \right)$$

$$\frac{1}{R_-} \cong \left(R + \frac{d}{2} \cos \theta \right)^{-1} \cong R^{-1} \left(1 - \frac{d}{2R} \cos \theta \right)$$

► $\mathbf{p} = q\mathbf{d}$: the electric dipole moment vector


$$V = \frac{qd \cos \theta}{4\pi\epsilon_0 R^2} \quad \mathbf{d} = d\mathbf{a}_z \quad \Rightarrow \quad V = \frac{q\mathbf{d} \cdot \mathbf{a}_R}{4\pi\epsilon_0 R^2} \quad \mathbf{p} = q\mathbf{d} \quad \Rightarrow \quad V = \frac{\mathbf{p} \cdot \mathbf{a}_R}{4\pi\epsilon_0 R^2}$$

$$\begin{aligned} \mathbf{E} &= -\nabla V = -\mathbf{a}_R \frac{\partial V}{\partial R} - \mathbf{a}_\theta \frac{1}{R} \frac{\partial V}{\partial \theta} \\ &= \frac{p}{4\pi\epsilon_0 R^3} (\mathbf{a}_R 2 \cos \theta + \mathbf{a}_\theta \sin \theta) \end{aligned}$$



Example 2-9

Find the electric potential and the electric field intensity of a charged disk of radius b with surface charge density ρ_s on its axis.



► **Solution.**

$$V = \frac{1}{4\pi\epsilon_0} \int_{S'} \frac{\rho_s ds'}{|\mathbf{R} - \mathbf{R}'|}$$


$$ds' = r' dr' d\phi' \quad \mathbf{R} = z\mathbf{a}_z \quad \mathbf{R}' = r'\mathbf{a}_{r'}$$

$$V = \frac{\rho_s}{4\pi\epsilon_0} \int_0^{2\pi} \int_0^b \frac{r' dr' d\phi'}{\sqrt{z^2 + r'^2}} = \frac{\rho_s}{2\epsilon_0} \left[\sqrt{z^2 + b^2} - z \right] \quad z > 0$$

$$\mathbf{E} = -\nabla V = \mathbf{a}_z \frac{\rho_s}{2\epsilon_0} \left[1 - \frac{z}{\sqrt{z^2 + b^2}} \right] \quad z > 0$$

Example 2-10

Find the electric potential and the electric field intensity of a line charge of length L and charge density ρ_ℓ along its extension.



► **Solution.**

$$V = \frac{1}{4\pi\epsilon_0} \int_{L'} \frac{\rho_\ell d\ell'}{|\mathbf{R} - \mathbf{R}'|}$$


$$d\ell' = dz' \quad \mathbf{R} = z\mathbf{a}_z \quad \mathbf{R}' = z'\mathbf{a}_z$$

$$V = \frac{\rho_\ell}{4\pi\epsilon_0} \int_{-L/2}^{L/2} \frac{dz'}{z - z'} = \frac{\rho_\ell}{4\pi\epsilon_0} \ln \left[\frac{z + L/2}{z - L/2} \right] \quad z > L/2$$

$$\mathbf{E} = -\nabla V = -\mathbf{a}_z \frac{dV}{dz} = \mathbf{a}_z \frac{\rho_\ell L}{4\pi\epsilon_0 [z^2 - (L/2)^2]} \quad z > L/2$$

Example 2-11

A volume charge of density $\rho = -\rho_0$ exists in the region $0 \leq R \leq b$. What is the electric potential at an arbitrary point inside this volume?




► **Solution.**

$$\mathbf{E} = -\mathbf{a}_R \frac{\rho_0}{3\epsilon_0} R, \quad 0 \leq R \leq b$$

$$\mathbf{E} = -\mathbf{a}_R \frac{\rho_0 b^3}{3\epsilon_0 R^2}, \quad R \geq b$$

$$\begin{aligned} V &= -\int_{\infty}^R \mathbf{E} \cdot d\ell = -\int_{\infty}^b \frac{-\rho_0 b^3}{3\epsilon_0 R^2} \mathbf{a}_R \cdot dR \mathbf{a}_R - \int_b^R \frac{-\rho_0 R}{3\epsilon_0} \mathbf{a}_R \cdot dR \mathbf{a}_R \\ &= -\frac{\rho_0 b^2}{3\epsilon_0} - \frac{\rho_0}{6\epsilon_0} (b^2 - R^2) \end{aligned}$$

2.7 Behaviour of the Static Electric Field in Material Media




- Classification of materials according to their electrical properties
 - Conductors
 - Semiconductors
 - Insulators (dielectrics)
- In conductors the electrons of the outer shells of the atoms are held by a weak force and pass easily from one atom to another.
- But the electrons in the atoms of insulators are tightly bound to their orbits and under normal conditions cannot be detached.
- The electrical properties of semiconductors lie between those of conductors and insulators.
- How does the static electric field intensity behave in the presence of a conductor?
- How does the static electric field intensity behave in the presence of a dielectric?
- What is the concept of electric flux density, and how is it related to the electric field intensity?
- What is the concept of the dielectric constant?
- How does the static electric field intensity behave at the boundary between two different media?

2.8 Conductors in Static Electric Field

- If we release charges inside a conductor, a field forms in it that drives the charges apart and to the surface.
 - Under static conditions the charge and the electric field inside a conductor are zero.

$$\rho = 0 \quad \mathbf{E} = 0$$
 - The time needed for the charges to distribute themselves on the surface of the conductor and reach equilibrium depends on the conductivity of the conductor.
- If under static conditions the electric field on the surface of a conductor had a tangential component, it would produce a tangential force, set the charges in motion, and there would be no charge equilibrium.
 - Therefore, under static conditions the electric field on the surface of a conductor is everywhere normal to the surface. In other words, under static conditions the surface of a conductor is an equipotential surface. In fact, since $\mathbf{E} = 0$ at all points inside the conductor, the whole conductor has the same electric potential.
- **Boundary conditions at a conductor / free-space interface**



- Normal component:

$$\oint_S \mathbf{E} \cdot d\mathbf{s} = E_n \Delta S = \frac{\rho_s \Delta S}{\epsilon_0} \quad \Rightarrow \quad E_n = \frac{\rho_s}{\epsilon_0}$$


- Tangential component:

$$\oint \mathbf{E} \cdot d\mathbf{L} = 0$$

$$E_t \Delta w - E_{N, \text{at } b} \frac{1}{2} \Delta h + E_{N, \text{at } a} \frac{1}{2} \Delta h = 0 \quad \Rightarrow \quad E_t = 0$$

Example 2-12

A point charge $+Q$ is at the centre of a conducting spherical shell of inner radius R_i and outer radius R_o . Find $\mathbf{E}$ and V in all space.



► Solution.

$$\mathbf{E} = E_R \mathbf{a}_R$$

► For $R > R_o$

$$\oint_S \mathbf{E} \cdot d\mathbf{s} = E_{R1} 4\pi R^2 = \frac{Q}{\epsilon_0}$$

$$E_{R1} = \frac{Q}{4\pi\epsilon_0 R^2} \quad V_1 = -\int_{\infty}^R (E_{R1}) dR = \frac{Q}{4\pi\epsilon_0 R}$$

► For $R_i < R < R_o$


$$E_{R2} = 0 \quad V_2 = V_1|_{R=R_o} = \frac{Q}{4\pi\epsilon_0 R_o}$$

► For $R < R_i$

$$E_{R3} = \frac{Q}{4\pi\epsilon_0 R^2}$$


$$V_3 = -\int_{\infty}^{R_o} E_{R1} dR - \int_{R_o}^{R_i} E_{R2} dR - \int_{R_i}^R E_{R3} dR$$

$$V_3 = \frac{Q}{4\pi\epsilon_0} \left(\frac{1}{R} + \frac{1}{R_o} - \frac{1}{R_i} \right)$$



2.9 Dielectrics in Static Electric Field

- ▶ Ideal dielectrics have no free charges. As a result, their charge density and internal electric field are not zero, as they are in conductors.
- ▶ Dielectrics have **bound charges**; applying an external field to a dielectric creates electric dipoles and polarizes the dielectric material.
- ▶ The induced electric dipoles change the electric field inside and outside the dielectric material.



▶ Equivalent charge distributions in polarized dielectrics

- To analyse the macroscopic effect of the induced dipoles, we define the polarization vector $\mathbf{P}$ as follows

Definition

$$\mathbf{P} = \lim_{\Delta v \rightarrow 0} \frac{\sum_{k=1}^{n\Delta v} \mathbf{p}_k}{\Delta v} \quad (\text{C/m}^2)$$

- ▶ n : number of dipoles per unit volume; $\mathbf{p}_k$: dipole moment
- ▶ If $d\mathbf{p}$ is the dipole moment of a small volume dv' , then

$$d\mathbf{p} = \mathbf{P} dv' \quad dV = \frac{\mathbf{P} \cdot \mathbf{a}_R}{4\pi\epsilon_0 R^2} dv' \quad V = \frac{1}{4\pi\epsilon_0} \int_{V'} \frac{\mathbf{P} \cdot \mathbf{a}_R}{R^2} dv'$$

$$V = \frac{1}{4\pi\epsilon_0} \oint_{S'} \frac{\mathbf{P} \cdot \mathbf{a}'_n}{R} ds' + \frac{1}{4\pi\epsilon_0} \int_{V'} \frac{(-\nabla' \cdot \mathbf{P})}{R} dv'$$

- ▶ The electric potential, and hence the electric field intensity, of a polarized dielectric can be computed from the effect of two charge distributions, a surface one and a volume one, with the following densities, called the **polarization charge densities** or **bound charge densities**

Important result


$$\begin{aligned} \rho_{ps} &= \mathbf{P} \cdot \mathbf{a}_n & \rho_p &= -\nabla \cdot \mathbf{P} \\ V &= \frac{1}{4\pi\epsilon_0} \oint_{S'} \frac{\rho_{ps}}{R} ds' + \frac{1}{4\pi\epsilon_0} \int_{V'} \frac{\rho_p}{R} dv' \end{aligned}$$

① Remark

Since we are dealing with an electrically neutral dielectric body, the total charge of the body after polarization must still be zero

$$\begin{aligned}\text{Total charge} &= \oint_S \rho_{ps} ds + \int_V \rho_p dv \\ &= \oint_S \mathbf{P} \cdot \mathbf{a}_n ds - \int_V \nabla \cdot \mathbf{P} dv = 0\end{aligned}$$

2.10 Electric Flux Density



- Since a dielectric gives rise to an equivalent volume charge density ρ_p , we expect the electric field intensity due to a given charge distribution in a dielectric to differ from the electric field intensity in free space.

$$\nabla \cdot \mathbf{E} = \frac{1}{\epsilon_0}(\rho + \rho_p)$$

$$\nabla \cdot (\epsilon_0 \mathbf{E} + \mathbf{P}) = \rho$$

- The electric flux density or electric displacement $\mathbf{D}$ is defined as follows

≡ Definition

$$\mathbf{D} = \epsilon_0 \mathbf{E} + \mathbf{P} \quad (\text{C/m}^2)$$

- Using the vector $\mathbf{D}$, the relation between the electric field and the free charge distributions in any medium can be written without having to deal with the polarization vector $\mathbf{P}$ or the polarization charge densities.

⚡ Important result

$$\nabla \cdot \mathbf{D} = \rho \quad (\text{C/m}^3)$$

- Integral form

$$\int_V \nabla \cdot \mathbf{D} dv = \int_V \rho dv$$

⚡ Important result | Another form of Gauss's law

$$\oint_S \mathbf{D} \cdot d\mathbf{s} = Q \quad (\text{C})$$

- The fundamental equations of electrostatics in any medium

⚡ Important result

$$\begin{cases} \nabla \cdot \mathbf{D} = \rho \\ \nabla \times \mathbf{E} = 0 \end{cases}$$

2.11 Dielectric Constant

- The relation between the polarization vector and the electric field intensity

$$\mathbf{P} = \epsilon_0 \chi_e \mathbf{E}$$

- χ_e : electric susceptibility
- The relation between the electric field intensity and the electric flux density

⚡ Important result


$$\begin{aligned} \mathbf{D} &= \epsilon_0(1 + \chi_e)\mathbf{E} \\ &= \epsilon_0\epsilon_r\mathbf{E} = \epsilon\mathbf{E} \quad (\text{C/m}^2) \end{aligned}$$

$$\epsilon_r = 1 + \chi_e = \frac{\epsilon}{\epsilon_0}$$

- ▶ ϵ_r : a dimensionless constant called the relative permittivity or dielectric constant
- ▶ A dielectric medium is **linear** if ϵ_r is independent of $\mathbf{E}$, **homogeneous** if ϵ_r is independent of the space coordinates, and isotropic if ϵ_r is a scalar.
 - A linear, homogeneous and isotropic medium is called a simple medium.
 - In anisotropic media the dielectric constant is a matrix. In such media $\mathbf{D}$ and $\mathbf{E}$ are not necessarily in the same direction.

Example 2-13

A point charge $+Q$ is at the centre of a dielectric spherical shell of inner radius R_i and outer radius R_o . The dielectric constant of the shell is ϵ_r . Find $\mathbf{E}$, V , $\mathbf{D}$ and $\mathbf{P}$ in all space.



Solution.

$$\mathbf{E} = E_R \mathbf{a}_R$$

- ▶ For $R > R_o$

$$E_{R1} = \frac{Q}{4\pi\epsilon_0 R^2} \quad V_1 = \frac{Q}{4\pi\epsilon_0 R}$$

$$D_{R1} = \epsilon_0 E_{R1} = \frac{Q}{4\pi R^2} \quad P_{R1} = 0$$

- ▶ For $R_i < R < R_o$

$$D_{R2} = \frac{Q}{4\pi R^2}$$

$$E_{R2} = \frac{Q}{4\pi\epsilon_0\epsilon_r R^2} = \frac{Q}{4\pi\epsilon R^2}$$

$$P_{R2} = \left(1 - \frac{1}{\epsilon_r}\right) \frac{Q}{4\pi R^2}$$

$$V_2 = - \int_{\infty}^{R_o} E_{R1} dR - \int_{R_o}^R E_{R2} dR$$

$$= V_1|_{R=R_o} - \frac{Q}{4\pi\epsilon} \int_{R_o}^R \frac{1}{R^2} dR$$

$$= \frac{Q}{4\pi\epsilon_0} \left[\left(1 - \frac{1}{\epsilon_r}\right) \frac{1}{R_o} + \frac{1}{\epsilon_r R} \right]$$

- ▶ For $R < R_i$

$$E_{R3} = \frac{Q}{4\pi\epsilon_0 R^2} \quad D_{R3} = \frac{Q}{4\pi R^2} \quad P_{R3} = 0$$

$$\begin{aligned} V_3 &= V_2|_{R=R_i} - \int_{R_i}^R E_{R3} dR \\ &= \frac{Q}{4\pi\epsilon_0} \left[\left(1 - \frac{1}{\epsilon_r}\right) \frac{1}{R_o} - \left(1 - \frac{1}{\epsilon_r}\right) \frac{1}{R_i} + \frac{1}{R} \right] \end{aligned}$$

$$\begin{aligned} \rho_{ps}|_{R=R_i} &= \mathbf{P} \cdot (-\mathbf{a}_R)|_{R=R_i} = -P_{R2}|_{R=R_i} \\ &= -\left(1 - \frac{1}{\epsilon_r}\right) \frac{Q}{4\pi R_i^2} \end{aligned}$$

$$\begin{aligned} \rho_{ps}|_{R=R_o} &= \mathbf{P} \cdot \mathbf{a}_R|_{R=R_o} = P_{R2}|_{R=R_o} \\ &= \left(1 - \frac{1}{\epsilon_r}\right) \frac{Q}{4\pi R_o^2} \end{aligned}$$


$$\begin{aligned} \rho_p &= -\nabla \cdot \mathbf{P} \\ &= -\frac{1}{R^2} \frac{\partial}{\partial R} (R^2 P_{R2}) = 0 \end{aligned}$$

2.12 Dielectric Strength

- An external electric field causes small displacements of the bound charges and creates electric dipoles.
- If the electric field is strong, it completely detaches electrons from the molecules, accelerates them and makes them collide with the molecular lattice structure.
- In this case the material may become conducting and large currents may arise.
 - This phenomenon is called **dielectric breakdown**.
- The maximum electric field intensity that a dielectric material can withstand without breakdown is called the **dielectric strength** of the material.
 - For example, the dielectric strength of air is 3 kV/mm.

Example 2-14

When a coaxial cable is used to carry electric power, the radius of the inner conductor is determined by the load current, and the overall size by the voltage and the insulating material used. Suppose that the radius of the inner conductor is 0.4 cm and that two layers, rubber with relative permittivity $\epsilon_{rr} = 3.2$ and polystyrene with relative permittivity $\epsilon_{rp} = 2.6$, are used as the insulating material. Design this cable so that it can operate at a voltage of 20 kV. To avoid breakdown due to abnormal external conditions, the maximum electric field intensity in the insulating materials must not exceed 25% of their dielectric strengths. (The dielectric strength of rubber is 25×10^6 V/m and that of polystyrene is 20×10^6 V/m.)



► Solution.

- The aim is to determine the order of the insulating layers and the values of r_o and r_m .
- Assuming that the free charge density on the surface of the inner conductor is ρ_s , Gauss's law gives

$$D_r 2\pi r L = \rho_s 2\pi r_i L \quad D_r = \rho_s \frac{r_i}{r} \quad E_r = \frac{\rho_s}{\epsilon_0 \epsilon_{r1,2}} \frac{r_i}{r}$$

$$\text{Rubber} \quad \max\{E_{rr}\} = 0.25 \times 25 \times 10^6 \text{ V/m} = \frac{\rho_s}{\epsilon_0 \epsilon_{rr}} \frac{r_i}{r_{r \min}} \quad r_{r \min} = r_i \text{ or } r_m$$

$$\text{Polystyrene} \quad \max\{E_{rp}\} = 0.25 \times 20 \times 10^6 \text{ V/m} = \frac{\rho_s}{\epsilon_0 \epsilon_{rp}} \frac{r_i}{r_{p \min}} \quad r_{p \min} = r_i \text{ or } r_m$$

$$\frac{25}{20} = \frac{\epsilon_{rp}}{\epsilon_{rr}} \times \frac{r_{p \min}}{r_{r \min}} \quad r_{p \min} > r_{r \min} \Rightarrow \begin{cases} r_{r \min} = r_i \\ r_{p \min} = r_m \end{cases}$$



$$\frac{25}{20} = \frac{2.6}{3.2} \times \frac{r_m}{0.4} \Rightarrow r_m = 0.616 \text{ cm}$$

$$\begin{aligned} - \int_{r_o}^{r_m} E_{rp} dr - \int_{r_m}^{r_i} E_{rr} dr &= \frac{\rho_s r_i}{\epsilon_0} \left(\frac{1}{\epsilon_{rp}} \ln \left(\frac{r_o}{r_m} \right) + \frac{1}{\epsilon_{rr}} \ln \left(\frac{r_m}{r_i} \right) \right) \\ &= 20000 \text{ V} \end{aligned}$$

$$\frac{\rho_s r_i}{\epsilon_0} = 0.25 \times 25 \times 10^6 \epsilon_{rr} r_i = 8 \times 10^4$$

$$\Rightarrow r_o = 0.832 \text{ cm}$$

2.13 Boundary Conditions for Static Electric Fields



► Tangential component:

$$\oint_{ab c d a} \mathbf{E} \cdot d\boldsymbol{\ell} = \mathbf{E}_1 \cdot \Delta \mathbf{w} + \mathbf{E}_2 \cdot (-\Delta \mathbf{w}) = E_{1t} \Delta w - E_{2t} \Delta w = 0$$

⚡ Important result

$$E_{1t} = E_{2t} \qquad \frac{D_{1t}}{\epsilon_1} = \frac{D_{2t}}{\epsilon_2}$$

- Normal component:


$$\begin{aligned}\oint_S \mathbf{D} \cdot d\mathbf{s} &= (\mathbf{D}_1 \cdot \mathbf{a}_{n2} + \mathbf{D}_2 \cdot \mathbf{a}_{n1}) \Delta S \\ &= \mathbf{a}_{n2} \cdot (\mathbf{D}_1 - \mathbf{D}_2) \Delta S \\ &= \rho_s \Delta S\end{aligned}$$

⚡ Important result

$$\mathbf{a}_{n2} \cdot (\mathbf{D}_1 - \mathbf{D}_2) = \rho_s \qquad \mathbf{a}_{n2} \cdot (\epsilon_1 \mathbf{E}_1 - \epsilon_2 \mathbf{E}_2) = \rho_s$$

Example 2-15

Two dielectric media with permittivities ϵ_1 and ϵ_2 are separated by a charge-free boundary as shown in the figure below. The electric field intensity in medium 1 at the point P_1 has magnitude E_1 and makes an angle α_1 with the normal. Determine the magnitude and direction of the electric field intensity at the point P_2 in region 2.



► **Solution.**

$$E_{1t} = E_{2t} \quad \Rightarrow \quad E_2 \sin \alpha_2 = E_1 \sin \alpha_1$$

$$\mathbf{a}_{n2} \cdot (\epsilon_1 \mathbf{E}_1 - \epsilon_2 \mathbf{E}_2) = \epsilon_1 E_{1n} - \epsilon_2 E_{2n} = 0 \quad \Rightarrow \quad \epsilon_2 E_2 \cos \alpha_2 = \epsilon_1 E_1 \cos \alpha_1$$

⚡ Important result


$$\frac{\tan \alpha_2}{\tan \alpha_1} = \frac{\epsilon_2}{\epsilon_1}$$

$$\begin{aligned} E_2 &= \sqrt{E_{2t}^2 + E_{2n}^2} = \sqrt{(E_2 \sin \alpha_2)^2 + (E_2 \cos \alpha_2)^2} \\ &= \left[(E_1 \sin \alpha_1)^2 + \left(\frac{\epsilon_1}{\epsilon_2} E_1 \cos \alpha_1 \right)^2 \right]^{1/2} \end{aligned}$$

⚡ Important result

$$E_2 = E_1 \left[\sin^2 \alpha_1 + \left(\frac{\epsilon_1}{\epsilon_2} \cos \alpha_1 \right)^2 \right]^{1/2}$$

2.14 Capacitance and Capacitors




- What kind of element is a capacitor, and what is the concept of capacitance?
- How is the capacitance of various structures computed?
- How can the electric energy stored in a set of charges, or the work needed to assemble a set of charges, be found?
- How can the electric energy stored in capacitive structures be computed?
- Suppose a charge Q is placed on an arbitrary conductor. This charge distributes itself over the surface of the conductor and forms the charge density ρ_s .
- Increasing the total charge by a factor k increases the charge density ρ_s by the factor k , and consequently the potential due to this charge also increases by the factor k .
 - Therefore the ratio of Q to V remains constant

⚡ Important result

$$Q = CV$$

- ▶ The constant of proportionality (C) is called the **capacitance of the isolated conducting body**; it is the electric charge that must be added to the body to raise its electric potential by one unit.
 - Its unit is the coulomb per volt, or farad (F).
- ▶ Two conductors separated by free space or by a dielectric medium are called a capacitor.



- ▶ The capacitance of a capacitor is defined as follows

△ Definition

$$C = \frac{Q}{V_{12}} \quad (\text{F})$$


- ▶ The capacitance of a capacitor depends on its geometry and on the permittivity of the medium between the two conductors.
- ▶ Procedure for computing the capacitance of a capacitor
 - Choosing an appropriate coordinate system
 - Placing the charges $+Q$ and $-Q$ on the conductors
 - Finding $\mathbf{E}$ from Q
 - Computing the potential difference between the two conductors from the following relation, from the charge $-Q$ to the charge $+Q$

$$V = - \int_{P-Q}^{P+Q} \mathbf{E} \cdot d\ell$$

- Finding the capacitance from the ratio Q/V

Example 2-16

A parallel-plate capacitor consists of two parallel conducting plates of area S separated by d . The space between the plates is filled with a dielectric of constant permittivity ϵ . Find the capacitance of this capacitor.



► Solution.

- Using Cartesian coordinates
- Placing the charges $+Q$ and $-Q$ on the plates $\rightarrow \rho_s = \frac{Q}{S}$
- Computing the electric field intensity in the space between the two conducting plates with Gauss's law, neglecting the fringing fields

$$\mathbf{E} = -\mathbf{a}_y \frac{\rho_s}{\epsilon} = -\mathbf{a}_y \frac{Q}{\epsilon S}$$

- Computing the potential difference between the conducting plates in terms of Q


$$V_{12} = - \int_{y=0}^{y=d} \mathbf{E} \cdot d\ell = - \int_0^d \left(-\mathbf{a}_y \frac{Q}{\epsilon S} \right) \cdot (\mathbf{a}_y dy) = \frac{Q}{\epsilon S} d$$

- Determining the capacitance

$$C = \frac{Q}{V_{12}} = \epsilon \frac{S}{d}$$

Example 2-17

A cylindrical capacitor consists of an inner conductor of radius a and an outer conductor of radius b . The space between the two conductors is filled with a dielectric of constant permittivity ϵ , and the length of the capacitor is L . Find the capacitance of this capacitor.



► Solution.

- Using cylindrical coordinates
- Placing the charges $+Q$ and $-Q$ on the inner and outer conductors respectively
- Computing the electric field intensity in the space between the two conductors with Gauss's law

$$\mathbf{E} = \mathbf{a}_r E_r = \mathbf{a}_r \frac{Q}{2\pi\epsilon Lr}$$

- Computing the potential difference between the conductors in terms of Q


$$\begin{aligned} V_{ab} &= - \int_{r=b}^{r=a} \mathbf{E} \cdot d\ell = - \int_b^a \left(\mathbf{a}_r \frac{Q}{2\pi\epsilon Lr} \right) \cdot (\mathbf{a}_r dr) \\ &= \frac{Q}{2\pi\epsilon L} \ln\left(\frac{b}{a}\right) \end{aligned}$$

- Determining the capacitance

$$C = \frac{Q}{V_{ab}} = \frac{2\pi\epsilon L}{\ln\left(\frac{b}{a}\right)}$$

Example 2-18

A spherical capacitor consists of an inner conducting sphere of radius R_i and an outer conducting sphere of radius R_o . The space between the two conductors is filled with a dielectric of constant permittivity ϵ . Determine the capacitance of this capacitor.



► Solution.

- Using spherical coordinates
- Placing the charges $+Q$ and $-Q$ on the inner and outer conductors respectively
- Computing the electric field intensity in the space between the two conductors with Gauss's law

$$\mathbf{E} = \mathbf{a}_R E_R = \mathbf{a}_R \frac{Q}{4\pi\epsilon R^2}$$


- Computing the potential difference between the conductors in terms of Q

$$V = - \int_{R_o}^{R_i} \mathbf{E} \cdot (\mathbf{a}_R dR) = - \int_{R_o}^{R_i} \frac{Q}{4\pi\epsilon R^2} dR = \frac{Q}{4\pi\epsilon} \left(\frac{1}{R_i} - \frac{1}{R_o} \right)$$

- Determining the capacitance

$$C = \frac{Q}{V} = \frac{4\pi\epsilon}{\frac{1}{R_i} - \frac{1}{R_o}}$$

► Capacitors connected in parallel




$$Q = Q_1 + Q_2 + \dots + Q_n$$

$$= C_1 V + C_2 V + \dots + C_n V = C_{\parallel} V$$

⚡ Important result

$$C_{\parallel} = C_1 + C_2 + \dots + C_n$$

► Capacitors connected in series




$$V = \frac{Q}{C_{sr}} = \frac{Q}{C_1} + \frac{Q}{C_2} + \dots + \frac{Q}{C_n}$$

⚡ Important result

$$\frac{1}{C_{sr}} = \frac{1}{C_1} + \frac{1}{C_2} + \dots + \frac{1}{C_n}$$

🔍 Example 2-19

A cylindrical capacitor of length L is formed by coaxial cylindrical conducting surfaces of radii r_i and r_o . Two dielectric materials of permittivities ϵ_1 and ϵ_2 fill the space between the conductors as shown in the figure below. Determine the capacitance of this capacitor.



► **Solution.**

► **First method**

- The capacitance of a cylindrical capacitor $\rightarrow C = \frac{2\pi\epsilon L}{\ln\left(\frac{r_o}{r_i}\right)}$
- Since each dielectric fills half of the space, the capacitance of each half is


$$C_1 = \frac{\pi\epsilon_1 L}{\ln\left(\frac{r_o}{r_i}\right)} \quad C_2 = \frac{\pi\epsilon_2 L}{\ln\left(\frac{r_o}{r_i}\right)}$$

- Since the two capacitors C_1 and C_2 are in parallel, the total capacitance is

$$C = C_1 + C_2 = \frac{2\pi L}{\ln\left(\frac{r_o}{r_i}\right)} \left(\frac{\epsilon_1 + \epsilon_2}{2} \right)$$

► **Second method**

- Using cylindrical coordinates
- Placing the charges $+Q$ and $-Q$ on the inner and outer conductors respectively
- Computing the electric field intensity in the space between the two conductors with Gauss's law



$$\left. \begin{aligned} E_{r1} &= \frac{Q_1}{\pi r \epsilon_1 L} \\ E_{r2} &= \frac{Q_2}{\pi r \epsilon_2 L} \end{aligned} \right\} E_{r1} = E_{r2} \Rightarrow \left. \begin{aligned} \frac{Q_1}{\epsilon_1} &= \frac{Q_2}{\epsilon_2} \\ Q_1 + Q_2 &= Q \end{aligned} \right\} \left\{ \begin{aligned} Q_1 &= \frac{Q\epsilon_1}{\epsilon_1 + \epsilon_2} \\ Q_2 &= \frac{Q\epsilon_2}{\epsilon_1 + \epsilon_2} \end{aligned} \right.$$

- Computing the potential difference between the conductors in terms of Q


$$V = - \int_{r_o}^{r_i} \frac{Q_1}{\pi r \epsilon_1 L} dr = - \int_{r_o}^{r_i} \frac{Q}{\pi r L (\epsilon_1 + \epsilon_2)} dr = \frac{Q}{\pi L (\epsilon_1 + \epsilon_2)} \ln\left(\frac{r_o}{r_i}\right)$$

- Determining the capacitance

$$C = \frac{2\pi L}{\ln\left(\frac{r_o}{r_i}\right)} \left(\frac{\epsilon_1 + \epsilon_2}{2} \right)$$

Example 2-20

A capacitor is formed by two concentric conducting spherical shells of radii R_i and R_o . The space between the shells is filled with a dielectric of relative permittivity ϵ_r from R_i to b and a dielectric of relative permittivity $2\epsilon_r$ from b to R_o . Determine the capacitance of this capacitor.



► Solution.

► First method

- The capacitance of a spherical capacitor $\rightarrow C = \frac{Q}{V} = \frac{4\pi\epsilon}{\frac{1}{R_i} - \frac{1}{R_o}}$
- This capacitor can be regarded as two capacitors in series, as follows

$$C_1 = \frac{4\pi\epsilon_0\epsilon_r}{\frac{1}{R_i} - \frac{1}{b}} \quad C_2 = \frac{4\pi\epsilon_0(2\epsilon_r)}{\frac{1}{b} - \frac{1}{R_o}}$$

- Therefore the total capacitance is

$$C = \frac{1}{1/C_1 + 1/C_2} = \frac{4\pi\epsilon_0\epsilon_r}{\frac{1}{R_i} - \frac{1}{2b} - \frac{1}{2R_o}}$$

► Second method

- Using spherical coordinates
- Placing the charges $+Q$ and $-Q$ on the inner and outer conductors respectively
- Computing the electric field intensity in the space between the two conductors with Gauss's law

$$E_{R1} = \frac{Q}{4\pi\epsilon_0\epsilon_r R^2} \quad E_{R2} = \frac{Q}{4\pi\epsilon_0(2\epsilon_r)R^2}$$


- Computing the potential difference between the conductors in terms of Q

$$V = - \int_{R_o}^b \frac{Q}{4\pi\epsilon_0(2\epsilon_r)R^2} dR - \int_b^{R_i} \frac{Q}{4\pi\epsilon_0\epsilon_r R^2} dR = \frac{Q}{4\pi\epsilon_0\epsilon_r} \left(\frac{1}{R_i} - \frac{1}{2b} - \frac{1}{2R_o} \right)$$


- Determining the capacitance

$$C = \frac{4\pi\epsilon_0\epsilon_r}{\frac{1}{R_i} - \frac{1}{2b} - \frac{1}{2R_o}}$$

2.15 Electrostatic Energy



- The electric potential of a point in an electric field is equal to the work needed to bring a unit positive charge from infinity (the zero-potential reference) to that point.
- To bring a charge Q_2 from infinity to the distance R_{12} from the charge Q_1 , the work needed is




$$W_2 = Q_2 V_2 = Q_2 \frac{Q_1}{4\pi\epsilon_0 R_{12}}$$

- V_2 : the potential at the location of the charge Q_2

$$W_2 = Q_1 \frac{Q_2}{4\pi\epsilon_0 R_{12}} = Q_1 V_1$$

$$W_2 = \frac{1}{2}(Q_1 V_1 + Q_2 V_2)$$

- This work is stored in the system of two charges as potential energy.
- Now suppose another charge Q_3 is brought from infinity to a point at the distance R_{13} from Q_1 and R_{23} from Q_2 ; the additional work needed is



$$\Delta W = Q_3 V_3 = Q_3 \left(\frac{Q_1}{4\pi\epsilon_0 R_{13}} + \frac{Q_2}{4\pi\epsilon_0 R_{23}} \right)$$

- V_3 : the potential at the location of the charge Q_3
- Thus the potential energy stored in the system of three charges is

$$\begin{aligned} W_3 &= W_2 + \Delta W = \frac{1}{4\pi\epsilon_0} \left(\frac{Q_1 Q_2}{R_{12}} + \frac{Q_1 Q_3}{R_{13}} + \frac{Q_2 Q_3}{R_{23}} \right) \\ W_3 &= \frac{1}{2} \left[Q_1 \left(\frac{Q_2}{4\pi\epsilon_0 R_{12}} + \frac{Q_3}{4\pi\epsilon_0 R_{13}} \right) + Q_2 \left(\frac{Q_1}{4\pi\epsilon_0 R_{12}} + \frac{Q_3}{4\pi\epsilon_0 R_{23}} \right) \right. \\ &\quad \left. + Q_3 \left(\frac{Q_1}{4\pi\epsilon_0 R_{13}} + \frac{Q_2}{4\pi\epsilon_0 R_{23}} \right) \right] = \frac{1}{2} (Q_1 V_1 + Q_2 V_2 + Q_3 V_3) \end{aligned}$$

- Thus the potential energy of N discrete point charges at rest is

⚡ Important result

$$W_e = \frac{1}{2} \sum_{k=1}^N Q_k V_k \quad (\text{J})$$

- where V_k is the electric potential at the point of Q_k due to the other charges.
- The SI unit of energy is the joule, which is a large unit. Here another unit, the electron-volt (eV), is used.
 - One electron-volt is the energy or work needed to move an electron against a potential difference of one volt.

$$1 \text{ (eV)} = (1.60 \times 10^{-19}) \times 1 = 1.60 \times 10^{-19} \quad (\text{J})$$

- In a continuous charge distribution of density ρ the stored energy is

⚡ Important result

$$W_e = \frac{1}{2} \int_{V'} \rho V dv \quad (\text{J})$$

- ▶ where V is the potential at the point where the volume charge density is ρ , and V' is the volume of the region in which ρ exists.

Example 2-21

Find the energy required to assemble a uniformly charged sphere of radius b and volume charge density ρ .

▶ **Solution.**

$$\begin{aligned}
 W_e &= \frac{\rho}{2} \int_{V'} V dv = \frac{\rho}{2} \int_0^b V 4\pi R^2 dR \\
 \mathbf{E}_{R1} &= \mathbf{a}_R \frac{Q}{4\pi\epsilon_0 R^2} = \mathbf{a}_R \frac{\rho b^3}{3\epsilon_0 R^2}, \quad R \geq b \\
 \mathbf{E}_{R2} &= \mathbf{a}_R \frac{Q_R}{4\pi\epsilon_0 R^2} = \mathbf{a}_R \frac{\rho R}{3\epsilon_0}, \quad 0 < R \leq b \\
 V &= - \int_{\infty}^R \mathbf{E} \cdot d\mathbf{R} = - \left[\int_{\infty}^b E_{R1} dR + \int_b^R E_{R2} dR \right] \\
 &= - \left[\int_{\infty}^b \frac{\rho b^3}{3\epsilon_0 R^2} dR + \int_b^R \frac{\rho R}{3\epsilon_0} dR \right] \\
 &= \frac{\rho}{3\epsilon_0} \left(b^2 + \frac{b^2}{2} - \frac{R^2}{2} \right) = \frac{\rho}{3\epsilon_0} \left(\frac{3}{2}b^2 - \frac{R^2}{2} \right) \\
 W_e &= \frac{\rho}{2} \int_0^b \frac{\rho}{3\epsilon_0} \left(\frac{3}{2}b^2 - \frac{R^2}{2} \right) 4\pi R^2 dR = \frac{4\pi\rho^2 b^5}{15\epsilon_0}
 \end{aligned}$$

- ▶ Earlier we obtained the electrostatic energy of a charge distribution in terms of the charge density and the potential.
- ▶ Sometimes it is better to express this energy in terms of field quantities.
- ▶ It can be shown that

Important result

$$W_e = \frac{1}{2} \int_{V'} \mathbf{D} \cdot \mathbf{E} dv \quad (\text{J})$$

$$W_e = \frac{1}{2} \int_{V'} \epsilon E^2 dv \quad (\text{J})$$

$$W_e = \frac{1}{2} \int_{V'} \frac{D^2}{\epsilon} dv \quad (\text{J})$$

► V' : all space

Example 2-22

Solve Example 2-21 using the expression of the energy in terms of field quantities.

► **Solution.**


$$\mathbf{E}_{R1} = \mathbf{a}_R \frac{Q}{4\pi\epsilon_0 R^2} = \mathbf{a}_R \frac{\rho b^3}{3\epsilon_0 R^2}, \quad R \geq b$$

$$\mathbf{E}_{R2} = \mathbf{a}_R \frac{Q_R}{4\pi\epsilon_0 R^2} = \mathbf{a}_R \frac{\rho R}{3\epsilon_0}, \quad 0 < R \leq b$$

$$\begin{aligned} W_e &= \frac{1}{2} \epsilon_0 \int_{V'} |\mathbf{E}|^2 dv = \frac{1}{2} \epsilon_0 \int_0^b \left(\frac{\rho R}{3\epsilon_0} \right)^2 4\pi R^2 dR \\ &\quad + \frac{1}{2} \epsilon_0 \int_b^\infty \left(\frac{\rho b^3}{3\epsilon_0 R^2} \right)^2 4\pi R^2 dR = \frac{4\pi \rho^2 b^5}{15\epsilon_0} \end{aligned}$$

Example 2-23

In the figure below a parallel-plate capacitor of area S and plate separation d is charged by the voltage V . The permittivity of the insulator is ϵ . Find the stored energy.



► **Solution.**

$$E = \frac{V}{d}$$

$$W_e = \frac{1}{2} \int_{V'} \epsilon \left(\frac{V}{d} \right)^2 dv = \frac{1}{2} \epsilon \left(\frac{V}{d} \right)^2 (Sd) = \frac{1}{2} \left(\epsilon \frac{S}{d} \right) V^2$$

⚡ Important result

$$W_e = \frac{1}{2} CV^2 \quad (\text{J}) \qquad W_e = \frac{1}{2} QV \quad (\text{J}) \qquad W_e = \frac{Q^2}{2C} \quad (\text{J})$$

📌 Remark


It can be proved that the above equations hold for any capacitor made of two conductors.

Example 2-24


Using the energy relation, find the capacitance of a cylindrical capacitor of length L consisting of an inner conductor of radius a and an outer conductor of radius b , with permittivity ϵ .

► **Solution.**

$$\begin{aligned}\mathbf{E} &= \mathbf{a}_r E_r = \mathbf{a}_r \frac{Q}{2\pi\epsilon L r}, \quad a < r < b \\ W_e &= \frac{1}{2} \int_a^b \epsilon \left(\frac{Q}{2\pi\epsilon L r} \right)^2 (L 2\pi r dr) \\ &= \frac{Q^2}{4\pi\epsilon L} \int_a^b \frac{dr}{r} = \frac{Q^2}{4\pi\epsilon L} \ln \frac{b}{a} \\ \frac{Q^2}{2C} &= \frac{Q^2}{4\pi\epsilon L} \ln \frac{b}{a} \quad \Rightarrow \quad C = \frac{2\pi\epsilon L}{\ln \frac{b}{a}}\end{aligned}$$



3



CHAPTER


Solution of Electrostatic Problems

حل مسائل الكتريسيته ساكن

In this chapter


3.1	Course Outline	95	3.4	Uniqueness Theorem	99
3.2	Solution of Electrostatic Problems	96	3.5	Method of Images	100
3.3	Poisson's and Laplace's Equations	96	3.6	Boundary-Value Problems	104

3.1 Course Outline



3.2 Solution of Electrostatic Problems

- Electrostatic problems are problems that deal with the effects of electric charges at rest. Solving such problems usually involves determining the electric potential, the electric field intensity or the electric charge distribution.
- If the charge distribution is given, both the potential and the electric field can be computed with the relations of the previous chapter.
 - In many practical problems the exact charge distribution is not known everywhere, and finding the potential and the electric field directly with the formulas of the previous chapter is not possible. → the method of images can be used for a particular class of problems
 - In another kind of problem the potentials of all conducting bodies are known, and we want to find the potential and the electric field intensity in the surrounding space as well as the surface charge distributions on the conducting boundaries. → solving boundary-value problems



- What is the form of Poisson's and Laplace's equations that govern the electric potential, and when is each of them used?
- How can the electric potential and the electric field intensity be obtained by solving Poisson's and Laplace's equations?
- Is a solution of Poisson's equation that satisfies given boundary conditions unique?

3.3 Poisson's and Laplace's Equations

- The two fundamental equations of electrostatics in all media

$$\nabla \cdot \mathbf{D} = \rho \qquad \nabla \times \mathbf{E} = 0$$

- On the other hand we have

$$\mathbf{E} = -\nabla V$$

$$\mathbf{D} = \epsilon \mathbf{E} \quad \Rightarrow \quad \nabla \cdot \epsilon \mathbf{E} = \rho \quad \Rightarrow \quad \nabla \cdot (\epsilon \nabla V) = -\rho$$

- If the medium is homogeneous (ϵ constant)

⚡ Important result

$$\nabla^2 V = -\frac{\rho}{\epsilon}$$

- ρ : free charge density
- In the above equation, known as **Poisson's equation**, the **Laplacian** operator (the divergence of the gradient) is used.
- The Laplacian of a scalar quantity in the different coordinate systems

- Cartesian

$$\nabla^2 V = \frac{\partial^2 V}{\partial x^2} + \frac{\partial^2 V}{\partial y^2} + \frac{\partial^2 V}{\partial z^2}$$

- Cylindrical

$$\nabla^2 V = \frac{1}{r} \frac{\partial}{\partial r} \left(r \frac{\partial V}{\partial r} \right) + \frac{1}{r^2} \frac{\partial^2 V}{\partial \phi^2} + \frac{\partial^2 V}{\partial z^2}$$

- Spherical

$$\nabla^2 V = \frac{1}{R^2} \frac{\partial}{\partial R} \left(R^2 \frac{\partial V}{\partial R} \right) + \frac{1}{R^2 \sin \theta} \frac{\partial}{\partial \theta} \left(\sin \theta \frac{\partial V}{\partial \theta} \right) + \frac{1}{R^2 \sin^2 \theta} \frac{\partial^2 V}{\partial \phi^2}$$

- Solving Poisson's equation in three-dimensional space with given boundary conditions is usually not a simple task.
- At points of a simple medium where there is no free charge

⚡ Important result

$$\nabla^2 V = 0$$


- The above equation is called **Laplace's equation**.
 - This equation governs problems involving a set of conductors held at different potentials.
 - Once V has been found from this equation, $\mathbf{E}$ and the charge distribution on the conducting surfaces are easily obtained

$$\mathbf{E} = -\nabla V \qquad \rho_s = -\epsilon E_n$$

Example 3-1

The two plates of a parallel-plate capacitor are separated by the distance d and held at the potentials 0 and V_0 as shown in the figure below. Neglecting the fringing fields, find

- (a) the potential at all points between the plates
- (b) the surface charge densities on the plates



➤ Solution.

- (a) Using Laplace's equation

$$\nabla^2 V = 0 \quad \Rightarrow \quad \frac{d^2 V}{dy^2} = 0 \quad \Rightarrow \quad \frac{dV}{dy} = C_1 \quad \Rightarrow \quad V = C_1 y + C_2$$

- Boundary conditions:

$$\left. \begin{array}{l} \text{At } y = 0, \quad V = 0 \\ \text{At } y = d, \quad V = V_0 \end{array} \right\} \Rightarrow V = \frac{V_0}{d} y$$

- (b)

$$\mathbf{E} = -\nabla V \quad \Rightarrow \quad \mathbf{E} = -\mathbf{a}_y \frac{dV}{dy} = -\mathbf{a}_y \frac{V_0}{d}$$

$$E_n = \mathbf{a}_n \cdot \mathbf{E} = \frac{\rho_s}{\epsilon}$$

- For the lower plate

$$\mathbf{a}_n = \mathbf{a}_y, \quad E_{n\ell} = -\frac{V_0}{d}, \quad \rho_{s\ell} = -\frac{\epsilon V_0}{d}$$

- For the upper plate

$$\mathbf{a}_n = -\mathbf{a}_y, \quad E_{nu} = \frac{V_0}{d}, \quad \rho_{su} = \frac{\epsilon V_0}{d}$$

Example 3-2

Solving Poisson's and Laplace's equations for V , determine the field $\mathbf{E}$ inside and outside a spherical electron cloud with uniform volume charge density $\rho = -\rho_0$ for $0 \leq R \leq b$ and $\rho = 0$ for $R > b$.

► Solution.

- Inside the electron cloud $\rightarrow$ using Poisson's equation

$$\nabla^2 V = -\frac{\rho}{\epsilon} \Rightarrow \frac{1}{R^2} \frac{d}{dR} \left(R^2 \frac{dV_i}{dR} \right) = \frac{\rho_0}{\epsilon_0} \Rightarrow \frac{d}{dR} \left(R^2 \frac{dV_i}{dR} \right) = \frac{\rho_0}{\epsilon_0} R^2 \Rightarrow R^2 \frac{dV_i}{dR} = \frac{\rho_0}{3\epsilon_0} R^3 + C_1$$

$$\frac{dV_i}{dR} = \frac{\rho_0}{3\epsilon_0} R + \frac{C_1}{R^2} \Rightarrow \mathbf{E}_i = -\nabla V_i = -\mathbf{a}_R \left(\frac{dV_i}{dR} \right)$$

- Since the field at $R = 0$ cannot be infinite

$$C_1 = 0 \Rightarrow \mathbf{E}_i = -\mathbf{a}_R \frac{\rho_0}{3\epsilon_0} R, \quad 0 \leq R \leq b$$

- Outside the electron cloud $\rightarrow$ using Laplace's equation


$$\nabla^2 V = 0 \Rightarrow \frac{1}{R^2} \frac{\partial}{\partial R} \left(R^2 \frac{dV_o}{dR} \right) = 0 \Rightarrow \frac{dV_o}{dR} = \frac{C_2}{R^2}$$

$$\mathbf{E}_o = -\nabla V_o = -\mathbf{a}_R \frac{dV_o}{dR} = -\mathbf{a}_R \frac{C_2}{R^2}$$

- Because the medium is continuous, the fields $\mathbf{E}_i$ and $\mathbf{E}_o$ are equal at $R = b$


$$\frac{C_2}{b^2} = \frac{\rho_0}{3\epsilon_0} b \Rightarrow C_2 = \frac{\rho_0 b^3}{3\epsilon_0} \Rightarrow \mathbf{E}_o = -\mathbf{a}_R \frac{\rho_0 b^3}{3\epsilon_0 R^2}, \quad R \geq b$$

3.4 Uniqueness Theorem




- A solution of Poisson's equation (and, as a special case, of Laplace's equation) that satisfies the given boundary conditions is the unique solution of that equation.
- The consequence of this theorem is that a solution of any electrostatic problem that satisfies the boundary conditions is the only possible solution, regardless of the method by which it was obtained.

3.5 Method of Images



- What is the method of images, and how can it be used to solve a particular class of electrostatic problems?
- In a class of electromagnetic problems, solving Laplace's equation while satisfying the boundary conditions is very difficult. In these problems, however, the boundary conditions can be satisfied with the help of **image charges**.
 - This method, which consists of replacing the boundary surfaces by equivalent image charges, is called the **method of images**.
- As an example consider the following problem. We want to find the potential at all points $y > 0$.



- Gauss's law cannot be used to compute the field and then the potential, because a Gaussian surface cannot be determined.
- Nor can the potential be computed directly, because the presence of the positive charge Q induces negative charges on the surface of the conductor, giving a surface charge density ρ_s . We have

$$V(x, y, z) = \frac{Q}{4\pi\epsilon_0\sqrt{x^2 + (y-d)^2 + z^2}} + \frac{1}{4\pi\epsilon_0} \int_S \frac{\rho_s}{R_1} ds$$

- The difficulty is that ρ_s must be found first, and even when ρ_s is known the surface integral is difficult to evaluate.
- Solving Laplace's equation to obtain the solution is also impossible or very difficult. In fact the solution of Laplace's equation must satisfy the following conditions

$$V(x, 0, z) = 0$$

$$V \rightarrow \frac{Q}{4\pi\epsilon_0 R}, \text{ as } R \rightarrow 0$$

- At points very far from the charge Q the potential must be zero


$$V(x, y, z) = V(-x, y, z)$$

$$V(x, y, z) = V(x, y, -z)$$

- Such a problem can be solved easily with the method of images.

➤ Point Charge and Conducting Plane

- We remove the conducting plane and replace it by an image point charge $-Q$ at $y = -d$



⚡ Important result

$$V(x, y, z) = \frac{Q}{4\pi\epsilon_0} \left(\frac{1}{R_+} - \frac{1}{R_-} \right)$$


$$R_+ = [x^2 + (y - d)^2 + z^2]^{1/2}, \quad R_- = [x^2 + (y + d)^2 + z^2]^{1/2}$$

- It can easily be shown that this solution satisfies Laplace's equation and the boundary conditions. Therefore it is a solution of the problem and, by the uniqueness theorem, also its only solution.
- Once the potential is known, computing the field and the surface charge distribution on the conductor is easy.

① Remark

Note that this method cannot be used to compute the potential in the region $y < 0$.

➤ Line Charge and Parallel Conducting Cylinder



- ▶ The aim is to find the potential outside the conducting cylinder.
- ▶ The image must be a parallel line charge inside the cylinder that makes the cylinder surface $r = a$ an equipotential surface. The aim is to find d_i and ρ_i .
- ▶ We assume

⚡ Important result

$$\rho_i = -\rho_\ell$$

- ▶ The potential at the distance r from a line charge of density ρ_ℓ , with the reference at r_0 , is


$$V = - \int_{r_0}^r E_r dr = - \frac{\rho_\ell}{2\pi\epsilon_0} \int_{r_0}^r \frac{1}{r} dr = \frac{\rho_\ell}{2\pi\epsilon_0} \ln \frac{r_0}{r}$$

- ▶ The potential at the point M on the surface of the cylinder is

$$\begin{aligned} V_M &= \frac{\rho_\ell}{2\pi\epsilon_0} \ln \frac{r_0}{r} - \frac{\rho_\ell}{2\pi\epsilon_0} \ln \frac{r_0}{r_i} \\ &= \frac{\rho_\ell}{2\pi\epsilon_0} \ln \frac{r_i}{r} \end{aligned}$$

- ▶ Therefore the equipotential surfaces are specified by

$$\frac{r_i}{r} = \text{Constant}$$



- ▶ If the condition $\frac{d_i}{a} = \frac{a}{d}$ holds, then by the similarity of the two triangles OMP_i and OPM the ratio $\frac{r_i}{r}$ is always constant. Therefore

⚡ Important result

$$d_i = \frac{a^2}{d}$$


- ▶ Thus the line charge $-\rho_\ell$ can replace the conducting cylindrical surface, and the potential and the electric field at any point outside the cylinder can be found.

📌 Remark

Note that this method cannot be used to compute the potential in the region inside the conducting cylinder.

Example 3-3

Find the capacitance per unit length between two very long parallel circular conducting wires of radius a separated by D .



► Solution.

- We place the charges $+Q$ and $-Q$ on conductors 1 and 2 respectively.
- With the method of images, the equipotential surfaces of the wires can be replaced by two line charges $+\rho_\ell$ and $-\rho_\ell$.

$$V_2 = \frac{\rho_\ell}{2\pi\epsilon_0} \ln \frac{a}{d}$$

$$V_1 = -\frac{\rho_\ell}{2\pi\epsilon_0} \ln \frac{a}{d}$$

$$C = \frac{\rho_\ell}{V_1 - V_2} = \frac{\pi\epsilon_0}{\ln(d/a)}$$


$$d = D - d_i = D - \frac{a^2}{d} \Rightarrow d = \frac{1}{2} \left(D + \sqrt{D^2 - 4a^2} \right)$$

$$C = \frac{\pi\epsilon_0}{\ln \left[(D/2a) + \sqrt{(D/2a)^2 - 1} \right]} \quad (\text{F/m})$$

⚡ Important result

$$C = \frac{\pi\epsilon_0}{\cosh^{-1}(D/2a)} \quad (\text{F/m})$$

3.6 Boundary-Value Problems



- The method of images applies to problems involving free charges near conducting boundaries of simple geometry.
- If the problem involves a set of conductors held at given potentials, with no isolated free charges, it cannot be solved by the method of images, and Laplace's equation must be solved.
- Laplace's equation is a partial differential equation. Problems governed by partial differential equations with given boundary conditions are called **boundary-value problems**.
- Boundary-value problems for potential functions are divided into classes
 - Dirichlet problems: the value of the potential is specified at all points of the boundaries.
 - Neumann problems: the normal derivative of the potential is specified on all boundaries.
 - Mixed boundary-value problems: the potential is specified on some of the boundaries and the normal derivative of the potential on the rest.
- How are electrostatic boundary-value problems solved in the different coordinate systems to obtain the potential distribution?

➤ Cartesian Coordinates

- Laplace's equation in Cartesian coordinates

$$\frac{\partial^2 V}{\partial x^2} + \frac{\partial^2 V}{\partial y^2} + \frac{\partial^2 V}{\partial z^2} = 0$$

- Using the method of separation of variables

$$\begin{aligned}
 V(x, y, z) &= X(x)Y(y)Z(z) \\
 Y(y)Z(z)\frac{d^2 X(x)}{dx^2} + X(x)Z(z)\frac{d^2 Y(y)}{dy^2} + X(x)Y(y)\frac{d^2 Z(z)}{dz^2} &= 0 \\
 \underbrace{\frac{1}{X(x)}\frac{d^2 X(x)}{dx^2}}_{-k_x^2} + \underbrace{\frac{1}{Y(y)}\frac{d^2 Y(y)}{dy^2}}_{-k_y^2} + \underbrace{\frac{1}{Z(z)}\frac{d^2 Z(z)}{dz^2}}_{-k_z^2} &= 0 \\
 k_x^2 + k_y^2 + k_z^2 &= 0
 \end{aligned}$$

⚡ Important result


$$\frac{d^2X(x)}{dx^2} + k_x^2 X(x) = 0 \quad \frac{d^2Y(y)}{dy^2} + k_y^2 Y(y) = 0 \quad \frac{d^2Z(z)}{dz^2} + k_z^2 Z(z) = 0$$

Possible Solutions of $X''(x) + k_x^2 X(x) = 0$

k_x^2	k_x	$X(x)$	Exponential forms of $X(x)$
0	0	$A_0x + B_0$	
+	k	$A_1 \sin kx + B_1 \cos kx$	$C_1 e^{jkx} + D_1 e^{-jkx}$
-	jk	$A_2 \sinh kx + B_2 \cosh kx$	$C_2 e^{kx} + D_2 e^{-kx}$

Example 3-4

Two grounded, semi-infinite, parallel conducting plates are separated by the distance d . A third plate, perpendicular to both and insulated from them, is held at the potential V_0 . Determine the potential distribution in the region enclosed by the plates.



► Solution.

► Boundary conditions

$$(1) \quad V(x, y, z) = V(x, y) \quad (2) \quad V(0, y) = V_0 \quad (3) \quad V(\infty, y) = 0 \quad (4) \quad V(x, 0) = 0$$

$$(5) \quad V(x, b) = 0$$

$$(1) \Rightarrow \frac{\partial V}{\partial z} = 0 \Rightarrow Z(z) = B_0$$

$$\left. \begin{aligned} k_z^2 &= -\frac{1}{Z(z)} \frac{d^2 Z(z)}{dz^2} = 0 \\ k_x^2 + k_y^2 + k_z^2 &= 0 \end{aligned} \right\} \quad k_y^2 = -k_x^2 = k^2 \quad (k \text{ real})$$

$$k_x = jk \Rightarrow X(x) = C_2 e^{kx} + D_2 e^{-kx} \xrightarrow{(3)} X(x) = D_2 e^{-kx}$$

$$k_y = k \Rightarrow Y(y) = A_1 \sin ky + B_1 \cos ky \xrightarrow{(4)} Y(y) = A_1 \sin ky$$

$$\begin{aligned} V_n(x, y) &= (B_0 D_2 A_1) e^{-kx} \sin ky \\ &= C_n e^{-kx} \sin ky \end{aligned}$$

$$\xrightarrow{(5)} V_n(x, b) = C_n e^{-kb} \sin kb = 0 \Rightarrow \sin kb = 0 \Rightarrow kb = n\pi$$

$$k = \frac{n\pi}{b}, \quad n = 1, 2, 3, \dots$$


$$V_n(x, y) = C_n e^{-n\pi x/b} \sin \frac{n\pi}{b} y$$

- ▶ The above relation satisfies Laplace's equation but by itself cannot satisfy the second boundary condition at $x = 0$ for all y from 0 to b .
- ▶ Since Laplace's equation is a linear partial differential equation, a combination of V_n of the above form for different values of n is also a solution.

$$V(x, y) = \sum_{n=1}^{\infty} V_n(x, y)$$

$$\begin{aligned} \stackrel{(2)}{\Rightarrow} V(0, y) &= \sum_{n=1}^{\infty} V_n(0, y) = \sum_{n=1}^{\infty} C_n \sin \frac{n\pi}{b} y \\ &= V_0, \quad 0 < y < b \end{aligned}$$

- ▶ The above relation is the Fourier series expansion of a periodic odd function whose value on the interval $0 < y < b$ is V_0 .



Remark | Reminder

$$f(t) = a_0 + \sum_{n=1}^{\infty} \left[a_n \cos \left(\frac{2n\pi}{T} t \right) + b_n \sin \left(\frac{2n\pi}{T} t \right) \right]$$

$$\begin{aligned} b_n &= \frac{2}{T} \int_{-T/2}^{T/2} f(t) \sin \left(\frac{2n\pi}{T} t \right) dt & a_n &= \frac{2}{T} \int_{-T/2}^{T/2} f(t) \cos \left(\frac{2n\pi}{T} t \right) dt & a_0 \\ &= \frac{1}{T} \int_{-T/2}^{T/2} f(t) dt \end{aligned}$$

$$\begin{aligned} C_n &= \frac{2}{2b} \left[\int_0^b V_0 \sin \left(\frac{2n\pi}{2b} y \right) dy + \int_b^{2b} -V_0 \sin \left(\frac{2n\pi}{2b} y \right) dy \right] \\ &= \frac{V_0}{n\pi} (-2 \cos n\pi + 2) = \begin{cases} \frac{4V_0}{n\pi} & \text{if } n \text{ is odd} \\ 0 & \text{if } n \text{ is even} \end{cases} \end{aligned}$$

⚡ Important result

$$\begin{aligned}
 V(x, y) &= \sum_{n=1}^{\infty} C_n e^{-n\pi x/b} \sin \frac{n\pi}{b} y \\
 &= \frac{4V_0}{\pi} \sum_{n=\text{odd}}^{\infty} \frac{1}{n} e^{-n\pi x/b} \sin \frac{n\pi}{b} y, \\
 n &= 1, 3, 5, \dots, \quad x > 0 \quad \text{and} \quad 0 < y < b
 \end{aligned}$$

► Cylindrical Coordinates

- Laplace's equation in cylindrical coordinates

$$\frac{1}{r} \frac{\partial}{\partial r} \left(r \frac{\partial V}{\partial r} \right) + \frac{1}{r^2} \frac{\partial^2 V}{\partial \phi^2} + \frac{\partial^2 V}{\partial z^2} = 0$$

- Assuming the length is large compared with the radius, in cylindrical geometry the potential is independent of z .

$$\frac{1}{r} \frac{\partial}{\partial r} \left(r \frac{\partial V}{\partial r} \right) + \frac{1}{r^2} \frac{\partial^2 V}{\partial \phi^2} = 0$$

- Using the method of separation of variables

$$\begin{aligned}
 V(r, \phi) &= R(r)\Phi(\phi) \\
 \underbrace{\frac{r}{R(r)} \frac{d}{dr} \left[r \frac{dR(r)}{dr} \right]}_{k^2} + \underbrace{\frac{1}{\Phi(\phi)} \frac{d^2 \Phi(\phi)}{d\phi^2}}_{-k^2} &= 0
 \end{aligned}$$

- The differential equation in ϕ

⚡ Important result

$$\frac{d^2 \Phi(\phi)}{d\phi^2} + k^2 \Phi(\phi) = 0$$

► **When $k \neq 0$**

– In circular cylindrical configurations the potential functions, and hence $\Phi(\phi)$, are periodic in ϕ , and the hyperbolic functions are not used.

► If the range of ϕ is not restricted, k must be an integer ($k = n$)

$$\Phi(\phi) = A_\phi \sin n\phi + B_\phi \cos n\phi$$

► The differential equation in r (Euler's equation)

$$r^2 \frac{d^2 R(r)}{dr^2} + r \frac{dR(r)}{dr} - n^2 R(r) = 0$$

$$R(r) = A_r r^n + B_r r^{-n}$$

⚡ **Important result**

$$V_n(r, \phi) = r^n (A_n \sin n\phi + B_n \cos n\phi) + r^{-n} (A'_n \sin n\phi + B'_n \cos n\phi), \quad n \neq 0$$

► When the region of interest includes $r = 0$, the terms containing r^{-n} cannot exist, and when the region of interest includes infinity, the terms containing r^n cannot exist.

► **When $k = 0$**

$$\frac{d^2 \Phi(\phi)}{d\phi^2} = 0$$

$$\Phi(\phi) = A_0 \phi + B_0 \quad \Rightarrow \quad \Phi(\phi) = B_0$$


► If there is no circumferential variation

$$\frac{d}{dr} \left[r \frac{dR(r)}{dr} \right] = 0$$

$$R(r) = C_0 \ln r + D_0$$

Example 3-5

Consider a very long coaxial cable. The inner conductor has radius a and is held at the potential V_0 . The outer conductor has radius b and is grounded. Find the potential distribution in the space between the two conductors.



► Solution.

- Since the cable is long, there is no dependence on z .
- By symmetry, there is no dependence on ϕ ($k = 0$).


$$V(r) = C_1 \ln r + C_2$$

$$V(b) = 0, \quad V(a) = V_0$$

$$C_1 = -\frac{V_0}{\ln(b/a)}, \quad C_2 = \frac{V_0 \ln b}{\ln(b/a)} \quad \Rightarrow \quad V(r) = \frac{V_0}{\ln(b/a)} \ln \left(\frac{b}{r} \right)$$

Example 3-6

Two semi-infinite conducting plates are held at the potentials V_0 and zero as shown in the figure below. Assuming that the plates are very long along the z -axis, find the potential distribution in all space.



► Solution.

- Since the plates are long, there is no dependence on z .
- There is no dependence on r ($k = 0$).

$$\Phi(\phi) = A_0\phi + B_0$$

$$V(\phi) = \begin{cases} 0 & \phi = 0, 2\pi \\ V_0 & \phi = \alpha \end{cases}$$

- $0 \leq \phi \leq \alpha$


$$V(\phi) = \frac{V_0}{\alpha}\phi$$

- $\alpha \leq \phi \leq 2\pi$

$$V(\phi) = \frac{V_0}{2\pi - \alpha}(2\pi - \phi)$$

Example 3-7

A very long, thin conducting cylindrical tube of radius b is split into two parts. The upper half is held at the potential V_0 and the lower half at the potential $-V_0$. Find the potential distribution inside and outside the tube.



► Solution.

- Since the tube is long, there is no dependence on z .

$$V_n(r, \phi) = r^n(A_n \sin n\phi + B_n \cos n\phi) + r^{-n}(A'_n \sin n\phi + B'_n \cos n\phi)$$

$$V(b, \phi) = \begin{cases} V_0 & \text{for } 0 < \phi < \pi \\ -V_0 & \text{for } \pi < \phi < 2\pi \end{cases}$$

- Inside the tube ($r < b$)
- Since the region of interest includes $r = 0$, the terms containing r^{-n} cannot exist.
 - Since $V(r, \phi)$ is an odd function of ϕ , therefore

$$V_n(r, \phi) = A_n r^n \sin n\phi$$

- The above term alone cannot satisfy the boundary conditions. Therefore

$$\begin{aligned} V(r, \phi) &= \sum_{n=1}^{\infty} V_n(r, \phi) \\ &= \sum_{n=1}^{\infty} A_n r^n \sin n\phi \end{aligned}$$

$$\sum_{n=1}^{\infty} A_n b^n \sin n\phi = \begin{cases} V_0 & \text{for } 0 < \phi < \pi \\ -V_0 & \text{for } \pi < \phi < 2\pi \end{cases}$$

- The above relation is the Fourier series expansion of a periodic odd function whose value is V_0 on the interval $0 < \phi < \pi$ and $-V_0$ on the interval $\pi < \phi < 2\pi$.

$$A_n = \begin{cases} \frac{4V_0}{n\pi b^n} & \text{if } n \text{ is odd} \\ 0 & \text{if } n \text{ is even} \end{cases} \quad V(r, \phi) = \frac{4V_0}{\pi} \sum_{n=\text{odd}} \frac{1}{n} \left(\frac{r}{b}\right)^n \sin n\phi, \quad r < b$$

- Outside the tube ($r > b$)
- Since the region of interest includes $r \rightarrow \infty$, the terms containing r^n cannot exist.
 - $V(r, \phi)$ is an odd function of ϕ .
 - A single term cannot satisfy the boundary conditions. Therefore


$$\begin{aligned} V(r, \phi) &= \sum_{n=1}^{\infty} V_n(r, \phi) & V(b, \phi) &= \sum_{n=1}^{\infty} B'_n b^{-n} \sin n\phi \\ &= \sum_{n=1}^{\infty} B'_n r^{-n} \sin n\phi & &= \begin{cases} V_0 & \text{for } 0 < \phi < \pi \\ -V_0 & \text{for } \pi < \phi < 2\pi \end{cases} \end{aligned}$$

$$B'_n = \begin{cases} \frac{4V_0 b^n}{n\pi} & \text{if } n \text{ is odd} \\ 0 & \text{if } n \text{ is even} \end{cases}$$

⚡ Important result

$$V(r, \phi) = \frac{4V_0}{\pi} \sum_{n=\text{odd}}^{\infty} \frac{1}{n} \left(\frac{b}{r}\right)^n \sin n\phi, \quad r > b$$

4



CHAPTER


Steady Electric Currents

جریان‌های الکتریکی دائم

In this chapter


4.1	Course Outline	114	4.5	Power Dissipation and Joule's Law	119
4.2	Steady Electric Currents	115	4.6	Boundary Conditions for Current Density	120
4.3	Current Density and Ohm's Law	116	4.7	Resistance Calculations	123
4.4	Equation of Continuity and Kirchhoff's Current Law	118			

4.1 Course Outline




4.2 Steady Electric Currents

- In the previous chapters we dealt with electrostatic problems due to electric charges at rest.
 - In this chapter we turn to moving electric charges, which produce electric current.
- Electric currents due to the motion of free charges are divided into three kinds
 - **Conduction currents:** produced in conductors and semiconductors by the drift motion of electrons or holes.
 - **Electrolytic currents:** due to the motion of positive and negative ions
 - **Convection currents:** due to the motion of electrons or ions in vacuum
- In this chapter we concentrate on conduction currents, which are governed by Ohm's law.



- What is the concept of the **volume current density**, and what is the relation for the **convection current density**?
- What is the relation for the **conduction current density**?
- What is the point form of **Ohm's law**?
- What is the **equation of continuity**, and how is **Kirchhoff's current law** derived from it?
- What is **Joule's law**, which gives the power dissipated by a current flowing in a conducting body?

4.3 Current Density and Ohm's Law



- Consider the steady motion of charge carriers, each with charge q , moving with velocity $\mathbf{u}$ across a small surface element Δs
- If N is the number of charge carriers per unit volume, the charge passing through the surface Δs in the time Δt is

$$\Delta Q = Nq\mathbf{u} \cdot \mathbf{a}_n \Delta s \Delta t \quad (\text{C})$$

- Since current is the time rate of change of charge, we have

$$\Delta I = \frac{\Delta Q}{\Delta t} = Nq\mathbf{u} \cdot \mathbf{a}_n \Delta s = Nq\mathbf{u} \cdot \Delta \mathbf{s} \quad (\text{A})$$

- We define the volume current density, in amperes per square metre, as follows

$$\mathbf{J} = Nq\mathbf{u} \quad (\text{A/m}^2)$$

⚡ Important result | Convection current density

$$\mathbf{J} = \rho\mathbf{u} \quad (\text{A/m}^2)$$

- Therefore

$$\Delta I = \mathbf{J} \cdot \Delta \mathbf{s}$$

- Thus the total current flowing through an arbitrary surface S is

⚡ Important result

$$I = \int_S \mathbf{J} \cdot d\mathbf{s} \quad (\text{A})$$

- Conduction currents are the result of the drift motion of charge carriers under the influence of an applied electric field.
- For most conducting materials the average drift velocity is directly proportional to the electric field intensity.

– For metallic conductors we have

$$\mathbf{u} = -\mu_e \mathbf{E} \quad (\text{m/s})$$

- μ_e : electron mobility, in $\text{m}^2/\text{V} \cdot \text{s}$


$$\mathbf{J} = -\rho_e \mu_e \mathbf{E}$$

- $\rho_e = -Ne$: the volume charge density of the drifting electrons, a negative quantity

⚡ Important result | Point form of Ohm's law

$$\mathbf{J} = \sigma \mathbf{E} \quad (\text{A/m}^2)$$

- $\sigma = -\rho_e \mu_e$: a fundamental parameter of the medium, called the conductivity
- The unit of conductivity is $\text{A/V} \cdot \text{m}$, or siemens per metre. The reciprocal of conductivity is called resistivity, in $\Omega \cdot \text{m}$.
- Obtaining the relation between the voltage and the current of a piece of homogeneous material of conductivity σ , length ℓ and uniform cross-section S from the point form of Ohm's law



$$\left. \begin{aligned} V_{12} = E\ell &\Rightarrow E = \frac{V_{12}}{\ell} \\ I = \int_S \mathbf{J} \cdot d\mathbf{s} = JS &\Rightarrow J = \frac{I}{S} \end{aligned} \right\} \frac{I}{S} = \sigma \frac{V_{12}}{\ell}$$

$$V_{12} = \left(\frac{\ell}{\sigma S} \right) I = RI$$


⚡ Important result

$$R = \frac{\ell}{\sigma S} \quad (\Omega)$$

$$G = \frac{1}{R} = \sigma \frac{S}{\ell} \quad (\text{S})$$

- G : conductance, the reciprocal of resistance, in mhos or siemens

4.4 Equation of Continuity and Kirchhoff's Current Law



- The principle of conservation of charge is one of the fundamental postulates of physics.
 - Electric charge can be neither created nor destroyed.
- Consider an arbitrary volume V bounded by the surface S , containing a net charge Q . If a net current I flows out of the region through the surface, the charge in the volume must decrease at a rate equal to the current. Conversely, if a net current flows into the region through the surface, the charge in the volume must increase at a rate equal to the current.
- The current leaving the region is the total outward flux of the current density vector through the surface S

$$I = \oint_S \mathbf{J} \cdot d\mathbf{s} = -\frac{dQ}{dt} = -\frac{d}{dt} \int_V \rho \, dv$$

$$\int_V \nabla \cdot \mathbf{J} \, dv = - \int_V \frac{\partial \rho}{\partial t} \, dv$$

- Since the above equation must hold regardless of the choice of V

⚡ Important result | Equation of continuity

$$\nabla \cdot \mathbf{J} = -\frac{\partial \rho}{\partial t} \quad (\text{A/m}^3)$$

- If there are no time variations

$$\nabla \cdot \mathbf{J} = 0$$

⚡ Important result | Kirchhoff's current law


$$\oint_S \mathbf{J} \cdot d\mathbf{s} = 0$$

- We said earlier that charges placed inside a conductor move to its surface, so that at equilibrium $\rho = 0$ inside the conductor. We now want to prove this statement

$$\left. \begin{array}{l} \sigma \nabla \cdot \mathbf{E} = -\frac{\partial \rho}{\partial t} \\ \nabla \cdot \mathbf{E} = \rho / \epsilon \end{array} \right\} \quad \frac{\partial \rho}{\partial t} + \frac{\sigma}{\epsilon} \rho = 0 \quad \Rightarrow \quad \rho = \rho_0 e^{-(\sigma/\epsilon)t} \quad (\text{C/m}^3)$$

- ρ_0 : initial charge density
- The above equation states that the charge density at a given point decreases exponentially with time.
- The initial density decays to $1/e$, or 36.8%, of its value in a time equal to $\tau = \epsilon/\sigma$.
 - For a good conductor such as copper, $\tau = 1.52 \times 10^{-19}$ s.
 - For a good insulator this time may be hours or days.

4.5 Power Dissipation and Joule's Law



- Under the influence of an electric field, the free electrons in a conductor move and collide with the atoms of the crystal lattice. Energy is thus transferred from the electric field to the vibrating atoms.
- The work done by the electric field in moving a charge q through the distance $\Delta \ell$ is

$$\Delta W = \mathbf{F} \cdot \Delta \ell = q\mathbf{E} \cdot \Delta \ell$$

- This work corresponds to the power

$$p = \lim_{\Delta t \rightarrow 0} \frac{\Delta w}{\Delta t} = q\mathbf{E} \cdot \mathbf{u}$$

- $\mathbf{u}$: the velocity of the charge carriers

$$dp = \rho dv \mathbf{E} \cdot \mathbf{u}$$

$$dP = \mathbf{E} \cdot \mathbf{J} dv$$

- For a given volume V the total power converted into heat is

⚡ Important result | Joule's law

$$P = \int_V \mathbf{E} \cdot \mathbf{J} dv \quad (\text{W})$$

- In a conductor of constant cross-section we have


$$P = \int_L E d\ell \int_S J ds = VI$$

⚡ Important result

$$P = I^2 R \quad (\text{W})$$

- which is the familiar relation for ohmic power and gives the heat dissipated in the resistance R .

4.6 Boundary Conditions for Current Density



- When a current crosses the interface between two media of different conductivities obliquely, the current density vector changes in both direction and magnitude.
- The governing equations for the steady current density are

Governing Equations for Steady Current Density

Differential Form	Integral Form
$\nabla \cdot \mathbf{J} = 0$	$\oint_S \mathbf{J} \cdot d\mathbf{s} = 0$
$\nabla \times \left(\frac{\mathbf{J}}{\sigma} \right) = 0$	$\oint_C \frac{1}{\sigma} \mathbf{J} \cdot d\boldsymbol{\ell} = 0$

- The boundary conditions are as follows

⚡ Important result

$$\nabla \cdot \mathbf{J} = 0 \quad \Rightarrow \quad J_{1n} = J_{2n} \quad (\text{A/m}^2)$$

$$\nabla \times (\mathbf{J}/\sigma) = 0 \quad \Rightarrow \quad \frac{J_{1t}}{J_{2t}} = \frac{\sigma_1}{\sigma_2}$$

- When a steady current crosses the boundary between two different lossy dielectrics

$$J_{1n} = J_{2n} \rightarrow \sigma_1 E_{1n} = \sigma_2 E_{2n}$$

$$D_{1n} - D_{2n} = \rho_s \rightarrow \epsilon_1 E_{1n} - \epsilon_2 E_{2n} = \rho_s$$

$$\rho_s = \left(\epsilon_1 \frac{\sigma_2}{\sigma_1} - \epsilon_2 \right) E_{2n} = \left(\epsilon_1 - \epsilon_2 \frac{\sigma_1}{\sigma_2} \right) E_{1n}$$

- $E_{1n} = \mathbf{a}_{n2} \cdot \mathbf{E}_1$ and $E_{2n} = \mathbf{a}_{n2} \cdot \mathbf{E}_2$
- If medium 2 is a much better conductor than medium 1


$$\rho_s = \epsilon_1 E_{1n} = D_{1n}$$

- which is the boundary condition of a conductor.

Example 4-1

A potential difference $\mathcal{V}$ is applied to a parallel-plate capacitor of area S . The space between the conducting plates is filled with two lossy dielectric materials of thicknesses d_1 and d_2 , permittivities ϵ_1 and ϵ_2 , and conductivities σ_1 and σ_2 . Find

- (a) the electric field intensity in the two media
- (b) the current density in the two media
- (c) the surface charge densities on the conducting plates and at the interface of the two dielectrics



Solution.

- (a)

$$J_1 = J_2 \quad \Rightarrow \quad \begin{aligned} \mathcal{V} &= E_1 d_1 + E_2 d_2 \\ \sigma_1 E_1 &= \sigma_2 E_2 \end{aligned}$$

$$E_1 = \frac{\sigma_2 \mathcal{V}}{\sigma_2 d_1 + \sigma_1 d_2} \quad E_2 = \frac{\sigma_1 \mathcal{V}}{\sigma_2 d_1 + \sigma_1 d_2}$$


- (b)

$$J_1 = J_2 = \sigma_1 E_1 = \sigma_2 E_2 = \frac{\sigma_1 \sigma_2 \mathcal{V}}{\sigma_2 d_1 + \sigma_1 d_2}$$

- (c)

$$\begin{aligned} \mathbf{a}_n \cdot \mathbf{E}_1 &= \frac{\rho_{s1}}{\epsilon_1} \quad \Rightarrow \quad \rho_{s1} = \epsilon_1 E_1 = \frac{\epsilon_1 \sigma_2 \mathcal{V}}{\sigma_2 d_1 + \sigma_1 d_2} \\ \mathbf{a}_n \cdot \mathbf{E}_2 &= \frac{\rho_{s2}}{\epsilon_2} \quad \Rightarrow \quad \rho_{s2} = -\epsilon_2 E_2 = -\frac{\epsilon_2 \sigma_1 \mathcal{V}}{\sigma_2 d_1 + \sigma_1 d_2} \\ \rho_{si} &= \left(\epsilon_1 - \epsilon_2 \frac{\sigma_1}{\sigma_2} \right) E_{1n} \quad \Rightarrow \quad \begin{aligned} \rho_{si} &= \left(\epsilon_2 \frac{\sigma_1}{\sigma_2} - \epsilon_1 \right) \frac{\sigma_2 \mathcal{V}}{\sigma_2 d_1 + \sigma_1 d_2} \\ &= \frac{(\epsilon_2 \sigma_1 - \epsilon_1 \sigma_2) \mathcal{V}}{\sigma_2 d_1 + \sigma_1 d_2} \quad (\text{C/m}^2) \end{aligned} \end{aligned}$$

4.7 Resistance Calculations



- How is the **leakage resistance** of capacitive structures computed?
- How is the resistance of various structures computed?
- The capacitance between two conductors separated by a dielectric medium is

$$C = \frac{Q}{V} = \frac{\oint_S \mathbf{D} \cdot d\mathbf{s}}{-\int_L \mathbf{E} \cdot d\boldsymbol{\ell}} = \frac{\oint_S \epsilon \mathbf{E} \cdot d\mathbf{s}}{-\int_L \mathbf{E} \cdot d\boldsymbol{\ell}}$$

- The surface integral is taken over a surface enclosing the positive conductor, and the line integral from the negative conductor to the positive conductor.
- If the dielectric medium is lossy, a current flows from the positive to the negative conductor. The resistance between the conductors (the leakage resistance) is

$$R = \frac{V}{I} = \frac{-\int_L \mathbf{E} \cdot d\boldsymbol{\ell}}{\oint_S \mathbf{J} \cdot d\mathbf{s}} = \frac{-\int_L \mathbf{E} \cdot d\boldsymbol{\ell}}{\oint_S \sigma \mathbf{E} \cdot d\mathbf{s}}$$

- If the permittivity and the conductivity have the same space dependence ($\epsilon(x, y, z) = k\sigma(x, y, z)$), or if the dielectric medium is homogeneous (ϵ and σ independent of the space coordinates)

⚡ Important result

$$RC = \frac{C}{G} = \frac{\epsilon}{\sigma}$$

Example 4-2

Find the leakage resistance per unit length

- (a) between the inner and outer conductors of a coaxial cable with inner-conductor radius a , outer-conductor radius b and a dielectric of conductivity σ
- (b) of a two-wire transmission line consisting of two wires of radius a separated by D , in a medium of conductivity σ

➤ Solution.

- (a) The capacitance per unit length of a coaxial cable

$$C_1 = \frac{2\pi\epsilon}{\ln(b/a)} \quad (\text{F/m})$$

- The leakage resistance per unit length

$$R_1 = \frac{\epsilon}{\sigma} \left(\frac{1}{C_1} \right) = \frac{1}{2\pi\sigma} \ln \left(\frac{b}{a} \right) \quad (\Omega \cdot \text{m})$$

- (b) The capacitance per unit length of a two-wire transmission line

$$C'_1 = \frac{\pi\epsilon}{\cosh^{-1} \left(\frac{D}{2a} \right)} \quad (\text{F/m})$$

- The leakage resistance per unit length

$$\begin{aligned} R'_1 &= \frac{\epsilon}{\sigma} \left(\frac{1}{C'_1} \right) = \frac{1}{\pi\sigma} \cosh^{-1} \left(\frac{D}{2a} \right) \\ &= \frac{1}{\pi\sigma} \ln \left[\frac{D}{2a} + \sqrt{\left(\frac{D}{2a} \right)^2 - 1} \right] \quad (\Omega \cdot \text{m}) \end{aligned}$$

- In certain situations electrostatic and steady-current problems are not exactly analogous.
- **First method** for computing the resistance of a piece of conducting material between two surfaces or terminals

- Choosing an appropriate coordinate system
- Applying a potential difference V_0 between the two terminals
- Finding the electric field intensity (if the material is homogeneous, by solving Laplace's equation for the electric potential and then computing the electric field intensity)
- Finding the total current

$$I = \int_S \mathbf{J} \cdot d\mathbf{s} = \int_S \sigma \mathbf{E} \cdot d\mathbf{s}$$

- S : the cross-section through which the current flows
- The resistance is V_0/I

- **Second method** for computing the resistance of a piece of conducting material between two surfaces or terminals (when J can easily be determined from I)


- Choosing an appropriate coordinate system
- Passing a current I between the two terminals
- Finding J from I
- Computing the electric field intensity $\mathbf{E} = \mathbf{J}/\sigma$ and the potential difference V_0

$$V_0 = - \int \mathbf{E} \cdot d\boldsymbol{\ell}$$

- The integration is carried out from the terminal at the lower potential to the terminal at the higher potential.
- The resistance is V_0/I

Example 4-3

Consider a conducting material of uniform thickness h and conductivity σ in the shape shown in the figure below. Find the resistance between its two end faces.



► Solution.

► Choosing cylindrical coordinates

$$V = 0 \quad \text{at} \quad \phi = 0, \quad V = V_0 \quad \text{at} \quad \phi = \pi/2$$

$$\frac{d^2 V}{d\phi^2} = 0 \quad \Rightarrow \quad V = c_1 \phi + c_2 \quad \Rightarrow \quad V = \frac{2V_0}{\pi} \phi$$

$$\begin{aligned} \mathbf{J} &= \sigma \mathbf{E} = -\sigma \nabla V \\ &= -\mathbf{a}_\phi \sigma \frac{\partial V}{r \partial \phi} = -\mathbf{a}_\phi \frac{2\sigma V_0}{\pi r} \end{aligned}$$

$$\begin{aligned} I &= \int_S \mathbf{J} \cdot d\mathbf{s} = \int_0^h \int_a^b \left(-\mathbf{a}_\phi \frac{2\sigma V_0}{\pi r} \right) \cdot (-\mathbf{a}_\phi dr dz) \\ &= \frac{2\sigma h V_0}{\pi} \ln \frac{b}{a} \end{aligned}$$

$$R = \frac{V_0}{I} = \frac{\pi}{2\sigma h \ln(b/a)}$$