


5



CHAPTER


Static Magnetic Fields

میدان‌های مغناطیسی ساکن

In this chapter

5.1	Course Outline	2	5.6	The Static Magnetic Field in Material Media	15
5.2	Static Magnetic Fields	2	5.7	Magnetic Field Intensity and Relative Permeability	18
5.3	Fundamental Postulates of Magnetostatics in Free Space	3	5.8	Magnetic Circuits	21
5.4	Vector Magnetic Potential	7	5.9	Boundary Conditions for Magnetostatic Fields	26
5.5	The Biot–Savart Law	9			

5.1 Course Outline



5.2 Static Magnetic Fields

- When a small test charge is placed in an electric field $\mathbf{E}$, the following force acts on it

$$\mathbf{F}_e = q\mathbf{E} \quad (\text{N})$$


- When this test charge moves in a magnetic field, another force acts on it, equal to

$$\mathbf{F}_m = q\mathbf{u} \times \mathbf{B} \quad (\text{N})$$

- $\mathbf{B}$: the magnetic flux density, in webers per square metre or teslas
- So the total electromagnetic force on the charge q is

⚡ **Important result** | Lorentz's force equation

$$\mathbf{F} = q(\mathbf{E} + \mathbf{u} \times \mathbf{B}) \quad (\text{N})$$



- What are the fundamental postulates of magnetostatics, from which the other relations and laws of the field can be derived?
- How is **Ampère's circuital law** derived from these postulates?
- How can the magnetic flux density of a current be found with Ampère's circuital law?

5.3 Fundamental Postulates of Magnetostatics in Free Space

- The two fundamental postulates of magnetostatics in free space

⚡ Important result

$$\nabla \cdot \mathbf{B} = 0$$

$$\nabla \times \mathbf{B} = \mu_0 \mathbf{J}$$

- $\mu_0 = 4\pi \times 10^{-7}$ (H/m): the permeability of free space
- $\mathbf{J}$: the volume current density (A/m²)
- Since the divergence of the curl of any vector field is zero, it follows that

$$\nabla \cdot \mathbf{J} = 0$$

- There is no magnetic analogue of the electric charge density.
- The integral form of the first relation → integrate over an arbitrary volume V and apply the divergence theorem

⚡ **Important result** | Law of conservation of magnetic flux

$$\oint_S \mathbf{B} \cdot d\mathbf{s} = 0$$

- This equation is called the **law of conservation of magnetic flux**.
 - There are no magnetic flow sources, and the magnetic flux lines always close upon themselves.
- The integral form of the second relation → integrate over an arbitrary open surface S and apply Stokes's theorem

$$\int_S (\nabla \times \mathbf{B}) \cdot d\mathbf{s} = \mu_0 \int_S \mathbf{J} \cdot d\mathbf{s}$$


⚡ **Important result** | Ampère's circuital law

$$\oint_C \mathbf{B} \cdot d\boldsymbol{\ell} = \mu_0 I$$

- C : the contour bounding the surface S (the contour C and the current I follow the right-hand rule)
- I : the current passing through the surface S
- This equation is a form of **Ampère's circuital law**.
 - The circulation of the magnetic flux density in free space around any closed path is equal to μ_0 times the total current flowing through the surface bounded by the path.
- Ampère's circuital law is useful for finding the magnetic flux density caused by a current I when there is a closed path C around the current such that $\mathbf{B}$ is constant on the path.

Example 5-1

An infinitely long, straight conductor with a circular cross-section of radius b carries a current I . Determine the magnetic flux density both inside and outside the conductor.



► Solution.

- If the conductor lies along the z -axis, $\mathbf{B}$ is in the ϕ direction and its magnitude is constant along any circular path about the z -axis.

– Inside the conductor


$$\left. \begin{aligned} \mathbf{B}_1 &= \mathbf{a}_\phi B_{\phi 1}, & d\ell &= \mathbf{a}_\phi r_1 d\phi \\ \oint_{C_1} \mathbf{B}_1 \cdot d\ell &= \int_0^{2\pi} B_{\phi 1} r_1 d\phi = 2\pi r_1 B_{\phi 1} \\ I_1 &= \frac{\pi r_1^2}{\pi b^2} I = \left(\frac{r_1}{b}\right)^2 I \end{aligned} \right\} \mathbf{B}_1 = \mathbf{a}_\phi B_{\phi 1} = \mathbf{a}_\phi \frac{\mu_0 r_1 I}{2\pi b^2}$$

- Outside the conductor

$$\begin{aligned} \mathbf{B}_2 &= \mathbf{a}_\phi B_{\phi 2}, & d\ell &= \mathbf{a}_\phi r_2 d\phi \\ \oint_{C_2} \mathbf{B}_2 \cdot d\ell &= 2\pi r_2 B_{\phi 2} \\ \mathbf{B}_2 &= \mathbf{a}_\phi B_{\phi 2} = \mathbf{a}_\phi \frac{\mu_0 I}{2\pi r_2} \end{aligned}$$

Example 5-2

Determine the magnetic flux density inside a closely wound toroidal coil with an air core, having N turns of wire carrying a current I .



► Solution.


- Cylindrical symmetry ensures that $\mathbf{B}$ has only a ϕ component and that its magnitude is constant along any circular path about the axis of the coil.

$$\oint \mathbf{B} \cdot d\ell = 2\pi r B_\phi = \mu_0 NI$$

$$\mathbf{B} = \mathbf{a}_\phi B_\phi = \mathbf{a}_\phi \frac{\mu_0 NI}{2\pi r}, \quad (b - a) < r < (b + a)$$

Example 5-3

Determine the magnetic flux density inside an infinitely long solenoid with an air core, having n turns of wire per unit length carrying a current I .




► Solution.

- Outside the solenoid the magnetic field is zero.
- By the symmetry of the structure, $\mathbf{B}$ is parallel to the axis of the solenoid and its magnitude is constant along the solenoid.

$$BL = \mu_0 nLI$$

$$B = \mu_0 nI$$

5.4 Vector Magnetic Potential



- What is the vector magnetic potential, where is it used, and how is it calculated?
- What is the Biot–Savart law, and how is it used to calculate the magnetic flux density?

$$\nabla \cdot \mathbf{B} = 0 \quad \Rightarrow \quad \boxed{\mathbf{B} = \nabla \times \mathbf{A} \quad (\text{T})}$$

- $\mathbf{A}$ is called the **vector magnetic potential**. Its unit is the weber per metre.
 - If $\mathbf{A}$ can be found for a current distribution, $\mathbf{B}$ follows easily (exactly as with V and $\mathbf{E}$).
- A vector is defined by its curl and its divergence. To specify the divergence of $\mathbf{A}$ we proceed as follows

$$\nabla \times \mathbf{B} = \mu_0 \mathbf{J} \quad \Rightarrow \quad \nabla \times \nabla \times \mathbf{A} = \mu_0 \mathbf{J}$$

- We define the **Laplacian of a vector quantity** as

$$\nabla^2 \mathbf{A} = \nabla(\nabla \cdot \mathbf{A}) - \nabla \times \nabla \times \mathbf{A}$$

- For example, the Laplacian of $\mathbf{A}$ in Cartesian coordinates is

$$\nabla^2 \mathbf{A} = \mathbf{a}_x \nabla^2 A_x + \mathbf{a}_y \nabla^2 A_y + \mathbf{a}_z \nabla^2 A_z$$

- Therefore

$$\nabla(\nabla \cdot \mathbf{A}) - \nabla^2 \mathbf{A} = \mu_0 \mathbf{J}$$

- To simplify this relation we choose

$$\nabla \cdot \mathbf{A} = 0 \quad \Rightarrow \quad \boxed{\nabla^2 \mathbf{A} = -\mu_0 \mathbf{J}}$$

- This last relation is the **vector Poisson's equation**.
- In Cartesian coordinates

$$\nabla^2 A_x = -\mu_0 J_x, \quad \nabla^2 A_y = -\mu_0 J_y, \quad \nabla^2 A_z = -\mu_0 J_z$$

- Each of these three equations is mathematically the same as Poisson's equation in electrostatics.
- Earlier we had

$$\nabla^2 V = -\frac{\rho}{\epsilon_0} \quad \Rightarrow \quad V = \frac{1}{4\pi\epsilon_0} \int_{V'} \frac{\rho}{|\mathbf{R} - \mathbf{R}'|} dv'$$

- In the same way we obtain

⚡ Important result

$$\mathbf{A} = \frac{\mu_0}{4\pi} \int_{V'} \frac{\mathbf{J}}{|\mathbf{R} - \mathbf{R}'|} dv'$$

- So $\mathbf{A}$ can be found from the current density with this relation, and $\mathbf{B}$ then follows by taking its curl.
- The physical meaning of the vector magnetic potential

$$\Phi = \int_S \mathbf{B} \cdot d\mathbf{s}$$


- Φ : the magnetic flux, in webers

⚡ Important result

$$\Phi = \int_S (\nabla \times \mathbf{A}) \cdot d\mathbf{s} = \oint_C \mathbf{A} \cdot d\boldsymbol{\ell} \quad (\text{Wb})$$

- The line integral of $\mathbf{A}$ around any closed path C equals the total magnetic flux passing through the surface bounded by the path.

5.5 The Biot–Savart Law



- For a thin wire carrying a current I , with cross-section S , we have

$$\mathbf{J} dv' = JS d\ell' = I d\ell' \quad \Rightarrow \quad \mathbf{A} = \frac{\mu_0 I}{4\pi} \oint_{C'} \frac{d\ell'}{|\mathbf{R} - \mathbf{R}'|}$$

- It can be shown that

$$\mathbf{B} = \nabla \times \mathbf{A} = \nabla \times \left[\frac{\mu_0 I}{4\pi} \oint_{C'} \frac{d\ell'}{|\mathbf{R} - \mathbf{R}'|} \right]$$


⚡ Important result | Biot–Savart law

$$\mathbf{B} = \frac{\mu_0 I}{4\pi} \oint_{C'} \frac{d\ell' \times (\mathbf{R} - \mathbf{R}')}{|\mathbf{R} - \mathbf{R}'|^3}$$

- This equation is called the **Biot–Savart law**.
- In general the Biot–Savart law is more difficult to use than Ampère's circuital law. But when no closed path can be found on which $\mathbf{B}$ is constant, Ampère's circuital law cannot be used to determine $\mathbf{B}$.

Example 5-4

A direct current I flows in a straight wire of length $2L$. Find the magnetic flux density at a point at a distance r from the wire in the bisecting plane.



► Solution.

- Currents exist only in closed circuits. The wire in this example must therefore be part of a current-carrying loop. Since we know nothing about the rest of the circuit, Ampère's circuital law cannot be used.

► First method

$$\left. \begin{aligned} \mathbf{A} &= \frac{\mu_0 I}{4\pi} \oint_{C'} \frac{d\ell'}{|\mathbf{R} - \mathbf{R}'|} \\ d\ell' &= dz' \mathbf{a}_z \\ \mathbf{R} &= r \mathbf{a}_r \\ \mathbf{R}' &= z' \mathbf{a}_z \end{aligned} \right\} \quad \begin{aligned} \mathbf{A} &= \mathbf{a}_z \frac{\mu_0 I}{4\pi} \int_{-L}^L \frac{dz'}{\sqrt{z'^2 + r^2}} \\ &= \mathbf{a}_z \frac{\mu_0 I}{4\pi} \ln \frac{\sqrt{L^2 + r^2} + L}{\sqrt{L^2 + r^2} - L} \end{aligned}$$

$$\mathbf{B} = \nabla \times \mathbf{A} = \nabla \times (\mathbf{a}_z A_z) = \mathbf{a}_r \frac{1}{r} \frac{\partial A_z}{\partial \phi} - \mathbf{a}_\phi \frac{\partial A_z}{\partial r}$$


$$\begin{aligned} \mathbf{B} &= -\mathbf{a}_\phi \frac{\partial}{\partial r} \left[\frac{\mu_0 I}{4\pi} \ln \frac{\sqrt{L^2 + r^2} + L}{\sqrt{L^2 + r^2} - L} \right] \\ &= \mathbf{a}_\phi \frac{\mu_0 I L}{2\pi r \sqrt{L^2 + r^2}} \end{aligned}$$

► Second method

$$\left. \begin{aligned} \mathbf{B} &= \frac{\mu_0 I}{4\pi} \oint_{C'} \frac{d\ell' \times (\mathbf{R} - \mathbf{R}')}{|\mathbf{R} - \mathbf{R}'|^3} \\ \mathbf{R} - \mathbf{R}' &= r \mathbf{a}_r - z' \mathbf{a}_z \\ d\ell' \times (\mathbf{R} - \mathbf{R}') &= dz' \mathbf{a}_z \times (r \mathbf{a}_r - z' \mathbf{a}_z) = r dz' \mathbf{a}_\phi \end{aligned} \right\} \quad \begin{aligned} \mathbf{B} &= \int d\mathbf{B} = \mathbf{a}_\phi \frac{\mu_0 I}{4\pi} \int_{-L}^L \frac{r dz'}{(z'^2 + r^2)^{3/2}} \\ &= \mathbf{a}_\phi \frac{\mu_0 I L}{2\pi r \sqrt{L^2 + r^2}} \end{aligned}$$

Example 5-5

Find the magnetic flux density at the centre of a square loop of side w carrying a current I .



► Solution.


- Assume the loop lies in the xy -plane. $\mathbf{B}$ at the centre of the loop is four times the magnetic flux density caused by one side of length w . Therefore
- The magnitude of the magnetic flux density of a straight wire of length $2L$ at a distance r from it

$$B = \frac{\mu_0 I L}{2\pi r \sqrt{L^2 + r^2}} \quad L = \frac{w}{2}, \quad r = \frac{w}{2}$$

$$\mathbf{B} = \mathbf{a}_z \frac{\mu_0 I}{\sqrt{2}\pi w} \times 4 = \mathbf{a}_z \frac{2\sqrt{2}\mu_0 I}{\pi w}$$

Example 5-6

Find the magnetic flux density on the axis of a circular loop of radius b carrying a current I .



► **Solution.**

$$\left. \begin{aligned} \mathbf{B} &= \frac{\mu_0 I}{4\pi} \oint_{C'} \frac{d\ell' \times (\mathbf{R} - \mathbf{R}')}{|\mathbf{R} - \mathbf{R}'|^3} \\ d\ell' &= b d\phi' \mathbf{a}_{\phi'}, \quad \mathbf{R} = z\mathbf{a}_z, \quad \mathbf{R}' = b\mathbf{a}_{r'} \\ \mathbf{R} - \mathbf{R}' &= z\mathbf{a}_z - b\mathbf{a}_{r'} \\ d\ell' \times (\mathbf{R} - \mathbf{R}') &= b d\phi' \mathbf{a}_{\phi'} \times (z\mathbf{a}_z - b\mathbf{a}_{r'}) \\ &= bz d\phi' \mathbf{a}_{r'} + b^2 d\phi' \mathbf{a}_z \end{aligned} \right\} \quad \mathbf{B} = \frac{\mu_0 I}{4\pi} \int_0^{2\pi} \mathbf{a}_z \frac{b^2 d\phi'}{(z^2 + b^2)^{3/2}}$$


► It is evident from the geometry that the r -component of the magnetic flux density is zero.

⚡ Important result

$$\mathbf{B} = \mathbf{a}_z \frac{\mu_0 I b^2}{2(z^2 + b^2)^{3/2}} \quad (\text{T})$$

Example 5-7

Find the magnetic flux density at a distant point of a magnetic dipole of radius b carrying a current I .



► **Solution.**


$$\mathbf{A} = \frac{\mu_0 I}{4\pi} \oint_{C'} \frac{d\ell'}{|\mathbf{R} - \mathbf{R}'|}$$

- Because of the symmetry of the geometry, the magnetic field is independent of the angle ϕ . For simplicity, the field point is therefore placed in the yz -plane.

$$d\ell' = b d\phi' \mathbf{a}_{\phi'} = b d\phi' (-\mathbf{a}_x \sin \phi' + \mathbf{a}_y \cos \phi')$$

$$\mathbf{A} = -\mathbf{a}_x \frac{\mu_0 I}{4\pi} \int_0^{2\pi} \frac{b \sin \phi'}{|\mathbf{R} - \mathbf{R}'|} d\phi' + \mathbf{a}_y \frac{\mu_0 I}{4\pi} \int_0^{2\pi} \frac{b \cos \phi'}{|\mathbf{R} - \mathbf{R}'|} d\phi'$$

- It is evident from the geometry that the y -component of $\mathbf{A}$ is zero.



$$\begin{aligned} \mathbf{R} &= R\mathbf{a}_R = R(\sin \theta \cos(\pi/2)\mathbf{a}_x + \sin \theta \sin(\pi/2)\mathbf{a}_y + \cos \theta \mathbf{a}_z) \\ &= R(\sin \theta \mathbf{a}_y + \cos \theta \mathbf{a}_z) \end{aligned}$$

$$\mathbf{R}' = b\mathbf{a}_{r'} = b(\cos \phi' \mathbf{a}_x + \sin \phi' \mathbf{a}_y)$$

$$\mathbf{R} - \mathbf{R}' = -b \cos \phi' \mathbf{a}_x + (R \sin \theta - b \sin \phi') \mathbf{a}_y + R \cos \theta \mathbf{a}_z$$

$$\begin{aligned} |\mathbf{R} - \mathbf{R}'|^2 &= R^2 + b^2 - 2bR \sin \theta \sin \phi' \\ &= R^2 \left(1 + \frac{b^2}{R^2} - \frac{2b}{R} \sin \theta \sin \phi' \right) \end{aligned}$$

$$\begin{aligned} \frac{1}{|\mathbf{R} - \mathbf{R}'|} &= \frac{1}{R} \left(1 + \frac{b^2}{R^2} - \frac{2b}{R} \sin \theta \sin \phi' \right)^{-1/2} \\ &\cong \frac{1}{R} \left(1 - \frac{2b}{R} \sin \theta \sin \phi' \right)^{-1/2} \cong \frac{1}{R} \left(1 + \frac{b}{R} \sin \theta \sin \phi' \right) \end{aligned}$$

$$\begin{aligned} \mathbf{A} &= -\mathbf{a}_x \frac{\mu_0 I b}{4\pi R} \int_0^{2\pi} \left(1 + \frac{b}{R} \sin \theta \sin \phi' \right) \sin \phi' d\phi' \\ &= -\mathbf{a}_x \frac{\mu_0 I b^2}{4R^2} \sin \theta \end{aligned}$$

- At an arbitrary field point, the vector magnetic potential is then

$$\mathbf{A} = \mathbf{a}_\phi \frac{\mu_0 I b^2}{4R^2} \sin \theta \quad \Rightarrow \quad \mathbf{A} = \mathbf{a}_\phi \frac{\mu_0 (I\pi b^2)}{4\pi R^2} \sin \theta$$

- The magnetic dipole moment vector

$$\mathbf{m} = \mathbf{a}_z I\pi b^2 = \mathbf{a}_z IS = \mathbf{a}_z m$$



⚡ Important result

$$\mathbf{A} = \frac{\mu_0 \mathbf{m} \times \mathbf{a}_R}{4\pi R^2}$$


$$\mathbf{B} = \nabla \times \mathbf{A} \quad \Rightarrow \quad \mathbf{B} = \frac{\mu_0 I b^2}{4R^3} (\mathbf{a}_R 2 \cos \theta + \mathbf{a}_\theta \sin \theta)$$

⚡ Important result

$$\mathbf{B} = \frac{\mu_0 m}{4\pi R^3} (\mathbf{a}_R 2 \cos \theta + \mathbf{a}_\theta \sin \theta)$$




5.6 The Static Magnetic Field in Material Media



- All materials consist of atoms with a positively charged nucleus and a number of negatively charged electrons orbiting around it.
- The motion of the electrons produces circulating currents and hence microscopic magnetic dipoles.
- In the absence of an external magnetic field, the magnetic dipoles of the atoms of most materials (except permanent magnets) have random orientations, and no net magnetic moment results. When an external magnetic field is applied, the magnetic moments of the orbiting electrons align.
- How do different materials behave when exposed to a magnetic field, and how can this behaviour be analysed?

► Magnetization and Equivalent Current Densities

⊙ $\mathbf{M}$, out of the paper



- The magnetization vector (and the polarization vector in electrostatics)

$$\mathbf{M} = \lim_{\Delta v \rightarrow 0} \frac{\sum_{k=1}^{n\Delta v} \mathbf{m}_k}{\Delta v} \quad (\text{A/m}) \qquad \mathbf{P} = \lim_{\Delta v \rightarrow 0} \frac{\sum_{k=1}^{n\Delta v} \mathbf{p}_k}{\Delta v} \quad (\text{C/m}^2)$$

- The vector magnetic potential of a magnetized material (and the electric potential of a polarized material)

$$\mathbf{A} = \frac{\mu_0}{4\pi} \int_{V'} \frac{\nabla' \times \mathbf{M}}{R} dv' + \frac{\mu_0}{4\pi} \oint_{S'} \frac{\mathbf{M} \times \mathbf{a}'_n}{R} ds'$$

$$V = \frac{1}{4\pi\epsilon_0} \oint_{S'} \frac{\mathbf{P} \cdot \mathbf{a}'_n}{R} ds' + \frac{1}{4\pi\epsilon_0} \int_{V'} \frac{(-\nabla' \cdot \mathbf{P})}{R} dv'$$

- The equivalent magnetization surface and volume current densities

⚡ Important result

$$\mathbf{J}_{ms} = \mathbf{M} \times \mathbf{a}_n, \qquad \mathbf{J}_m = \nabla \times \mathbf{M}$$


- The equivalent polarization surface and volume charge densities

$$\rho_{ps} = \mathbf{P} \cdot \mathbf{a}_n, \qquad \rho_p = -\nabla \cdot \mathbf{P}$$

- The problem of finding the magnetic flux density $\mathbf{B}$ caused by a given volume density of magnetic dipole moment $\mathbf{M}$ becomes one of finding the equivalent magnetization current densities, then $\mathbf{A}$, and then $\mathbf{B}$.

Example 5-8

Determine the magnetic flux density on the axis of a magnetized cylinder. The cylinder has a radius b , a length L and a magnetization vector $\mathbf{M} = \mathbf{a}_z M_0$.



► Solution.

$$\mathbf{J}_m = \nabla \times \mathbf{M} = 0$$

- The equivalent surface current density on the side wall

$$\mathbf{J}_{ms} = \mathbf{M} \times \mathbf{a}_n = \mathbf{a}_z M_0 \times \mathbf{a}_r = \mathbf{a}_\phi M_0$$


- The equivalent surface current density on the top and bottom faces is zero.

$$\left. \begin{aligned} \mathbf{B} &= \frac{\mu_0}{4\pi} \int_{S'} \frac{\mathbf{J}_{ms} \times (\mathbf{R} - \mathbf{R}')}{|\mathbf{R} - \mathbf{R}'|^3} ds' \\ ds' &= b d\phi' dz' \\ \mathbf{R} &= z\mathbf{a}_z \\ \mathbf{R}' &= b\mathbf{a}_{r'} + z'\mathbf{a}_z \\ \mathbf{R} - \mathbf{R}' &= (z - z')\mathbf{a}_z - b\mathbf{a}_{r'} \\ \mathbf{J}_{ms} \times (\mathbf{R} - \mathbf{R}') &= M_0 \mathbf{a}_\phi \times ((z - z')\mathbf{a}_z - b\mathbf{a}_{r'}) \\ &= M_0(z - z')\mathbf{a}_{r'} + bM_0\mathbf{a}_z \end{aligned} \right\}$$

- It is evident from the geometry that the r -component of the magnetic flux density is zero.

$$\begin{aligned} \mathbf{B} &= \int d\mathbf{B} = \mathbf{a}_z \int_0^L \frac{\mu_0 M_0 b^2 dz'}{2[(z - z')^2 + b^2]^{3/2}} \\ &= \mathbf{a}_z \frac{\mu_0 M_0}{2} \left[\frac{z}{\sqrt{z^2 + b^2}} - \frac{z - L}{\sqrt{(z - L)^2 + b^2}} \right] \end{aligned}$$

5.7 Magnetic Field Intensity and Relative Permeability



► Magnetic Field Intensity

- Since an external magnetic field aligns the internal dipole moments and induces a magnetic moment in a magnetic material, we expect the resulting magnetic flux density in the presence of the magnetic material to differ from its value in free space.
- Taking the equivalent volume current density in the material into account, we have

$$\frac{1}{\mu_0} \nabla \times \mathbf{B} = \mathbf{J} + \mathbf{J}_m = \mathbf{J} + \nabla \times \mathbf{M} \quad \Rightarrow \quad \nabla \times \left(\frac{\mathbf{B}}{\mu_0} - \mathbf{M} \right) = \mathbf{J}$$

- We define the magnetic field intensity as

⚡ Important result

$$\mathbf{H} = \frac{\mathbf{B}}{\mu_0} - \mathbf{M} \quad (\text{A/m})$$

- The vector $\mathbf{H}$ lets us write the curl equation relating the magnetic field and the distribution of free currents in any medium without using $\mathbf{M}$ or $\mathbf{J}_m$

⚡ Important result

$$\nabla \times \mathbf{H} = \mathbf{J} \quad (\text{A/m}^2)$$

- **J**: the density of the free current
- The integral form

$$\int_S (\nabla \times \mathbf{H}) \cdot d\mathbf{s} = \int_S \mathbf{J} \cdot d\mathbf{s} \quad \Rightarrow \quad \oint_C \mathbf{H} \cdot d\boldsymbol{\ell} = I \quad (\text{A})$$

- This last relation is another form of Ampère's circuital law.
- The two fundamental governing equations for magnetostatics in any medium

⚡ Important result

$$\begin{cases} \nabla \cdot \mathbf{B} = 0 \\ \nabla \times \mathbf{H} = \mathbf{J} \end{cases}$$

➤ Relative Permeability

- The relation between the magnetization vector and the magnetic field intensity

$$\mathbf{M} = \chi_m \mathbf{H}$$

- χ_m : the magnetic susceptibility
- The relation between the magnetic field intensity and the magnetic flux density

⚡ Important result

$$\begin{aligned} \mathbf{B} &= \mu_0 (1 + \chi_m) \mathbf{H} \\ &= \mu_0 \mu_r \mathbf{H} = \mu \mathbf{H} \quad (\text{Wb/m}^2) \end{aligned}$$

$$\mu_r = 1 + \chi_m = \frac{\mu}{\mu_0}$$

- μ_r : a dimensionless quantity called the relative permeability of the medium
- The relations of electrostatics and of magnetostatics are dual to each other

Electrostatics	Magnetostatics
$\mathbf{E}$	$\mathbf{B}$
$\mathbf{D}$	$\mathbf{H}$
ϵ	$\frac{1}{\mu}$
$\mathbf{P}$	$-\mathbf{M}$
ρ	$\mathbf{J}$
V	$\mathbf{A}$
$\cdot$	$\times$
$\times$	$\cdot$

► Behaviour of Magnetic Materials

- Magnetic materials can be roughly classified into three main groups according to their relative permeability
 - **Diamagnetic materials:** $\mu_r < 1$ (χ_m is a very small negative number)
 - In these materials the net magnetic moment is zero in the absence of an applied external magnetic field. → copper, lead, mercury, silver and gold → $\chi_m \approx -10^{-5}$
 - **Paramagnetic materials:** $\mu_r > 1$ (χ_m is a very small positive number)
 - In these materials there is a net average magnetic moment in the absence of an applied external magnetic field. → aluminium, magnesium and tungsten → $\chi_m \approx 10^{-5}$
 - **Ferromagnetic materials:** $\mu_r \gg 1$ (χ_m is a large positive number)
 - In these materials the magnetic moment is many times larger than in paramagnetic materials. → cobalt, nickel and iron
 - The relation between $\mathbf{B}$ and $\mathbf{H}$ in a ferromagnetic material is nonlinear.





Figure 5.1 | The hysteresis phenomenon

5.8 Magnetic Circuits



- As with electric circuits, it is sometimes necessary to calculate the magnetic flux and the magnetic field intensity produced in a magnetic circuit by current-carrying windings.
- To analyse magnetic circuits we have

$$\nabla \cdot \mathbf{B} = 0, \quad \nabla \times \mathbf{H} = \mathbf{J}$$


$$\oint_C \mathbf{H} \cdot d\ell = NI = \mathcal{V}_m$$

- $\mathcal{V}_m$: the magnetomotive force, in A. It is the analogue of the electromotive force in electric circuits.

Example 5-9


Assume that N turns of wire are wound around a toroidal core of a magnetic material with permeability μ . The core has a mean radius r_0 , a circular cross-section of radius a and a narrow air gap of length ℓ_g . A steady current I_0 flows in the wire. Determine

- (a) the magnetic flux density in the magnetic core,
- (b) the magnetic field intensity in the magnetic core,
- (c) the magnetic field intensity in the air gap.



► **Solution.**

- **First assumption:** the leakage flux is neglected



$$\nabla \cdot \mathbf{B} = 0 \quad \Rightarrow \quad \oint_S \mathbf{B} \cdot d\mathbf{s} = 0$$

- The flux in the core and in the air gap is the same.
- **Second assumption:** the fringing of the flux in the air gap is neglected.
- The flux density in the core and in the air gap is the same.

$$\mathbf{B}_f = \mathbf{B}_g = \mathbf{a}_\phi B_f$$

$$\mathbf{H}_f = \mathbf{a}_\phi \frac{B_f}{\mu}, \quad \mathbf{H}_g = \mathbf{a}_\phi \frac{B_f}{\mu_0}$$

$$\oint_C \mathbf{H} \cdot d\boldsymbol{\ell} = NI_0 \quad \Rightarrow \quad \frac{B_f}{\mu} (2\pi r_0 - \ell_g) + \frac{B_f}{\mu_0} \ell_g = NI_0$$

- (a)

$$\mathbf{B}_f = \mathbf{a}_\phi \frac{\mu_0 \mu N I_0}{\mu_0 (2\pi r_0 - \ell_g) + \mu \ell_g}$$

► (b)

$$\mathbf{H}_f = \mathbf{a}_\phi \frac{\mu_0 N I_0}{\mu_0 (2\pi r_0 - \ell_g) + \mu \ell_g}$$

► (c)

$$\mathbf{H}_g = \mathbf{a}_\phi \frac{\mu N I_0}{\mu_0 (2\pi r_0 - \ell_g) + \mu \ell_g}$$


- If the radius of the cross-section of the core is much smaller than the mean radius of the toroid, the magnetic flux density in the core is approximately constant, and

$$\Phi \cong BS \Rightarrow \Phi = \frac{N I_0}{(2\pi r_0 - \ell_g)/\mu S + \ell_g/\mu_0 S} \Rightarrow \Phi = \frac{\mathcal{V}_m}{\mathcal{R}_f + \mathcal{R}_g}$$


⚡ Important result

$$\mathcal{R}_f = \frac{2\pi r_0 - \ell_g}{\mu S} = \frac{\ell_f}{\mu S}, \quad \mathcal{R}_g = \frac{\ell_g}{\mu_0 S}$$

- $\mathcal{R}_f$ and $\mathcal{R}_g$: reluctances, in 1/H
 ► This magnetic circuit is analogous to an electric circuit as follows



(a) Magnetic circuit



(b) Electric circuit

$$\Phi = \frac{\mathcal{V}_m}{\mathcal{R}_f + \mathcal{R}_g}, \quad I = \frac{\mathcal{V}}{R_f + R_g}$$

Magnetic Circuits	Electric Circuits
mmf, $\mathcal{V}_m (= NI)$	emf, $\mathcal{V}$
magnetic flux, Φ	electric current, I
reluctance, $\mathcal{R}$	resistance, R
permeability, μ	conductivity, σ

- In analogy to Kirchhoff's voltage law in electric circuits, in magnetic circuits we have

⚡ Important result

$$\sum_j N_j I_j = \sum_k \mathcal{R}_k \Phi_k$$

- So around any closed path in a magnetic circuit, the algebraic sum of the ampere-turns equals the algebraic sum of the products of the reluctances and the fluxes.
- In analogy to Kirchhoff's current law in electric circuits, in magnetic circuits we have


⚡ Important result

$$\sum_j \Phi_j = 0$$

- which states that the algebraic sum of all the magnetic fluxes flowing out of a junction in a magnetic circuit is zero.
- Despite this simple analogy, an exact analysis of magnetic circuits is very difficult, for the following reasons
 - the leakage fluxes,
 - the fringing effects, which make the magnetic flux lines spread out and bulge in the air gap,
 - the dependence of the permeability of ferromagnetic materials on the magnetic field intensity, that is, the nonlinear relation between $\mathbf{B}$ and $\mathbf{H}$.


Example 5-10

Consider the magnetic circuit shown below. Steady currents I_1 and I_2 flow in windings of N_1 and N_2 turns respectively. The core has a cross-sectional area S_c and a permeability μ . Determine the magnetic flux in the middle leg.



► Solution.

- The equivalent circuit




$$\mathcal{R}_1 = \frac{\ell_1}{\mu S_c}, \quad \mathcal{R}_2 = \frac{\ell_2}{\mu S_c}, \quad \mathcal{R}_3 = \frac{\ell_3}{\mu S_c}$$

$$\text{Loop 1 :} \quad N_1 I_1 = (\mathcal{R}_1 + \mathcal{R}_3) \Phi_1 + \mathcal{R}_1 \Phi_2$$

$$\text{Loop 2 :} \quad N_1 I_1 - N_2 I_2 = \mathcal{R}_1 \Phi_1 + (\mathcal{R}_1 + \mathcal{R}_2) \Phi_2$$

$$\Phi_1 = \frac{\mathcal{R}_2 N_1 I_1 + \mathcal{R}_1 N_2 I_2}{\mathcal{R}_1 \mathcal{R}_2 + \mathcal{R}_1 \mathcal{R}_3 + \mathcal{R}_2 \mathcal{R}_3}$$

5.9 Boundary Conditions for Magnetostatic Fields



- The boundary condition for the normal components


$$\nabla \cdot \mathbf{B} = 0 \quad \Rightarrow \quad B_{1n} = B_{2n} \quad (\text{T})$$

- In linear media

⚡ Important result

$$\mu_1 H_{1n} = \mu_2 H_{2n}$$

- The boundary condition for the tangential components



$$\oint_C \mathbf{H} \cdot d\boldsymbol{\ell} = I$$

$$\oint_{abcda} \mathbf{H} \cdot d\boldsymbol{\ell} = \mathbf{H}_1 \cdot \Delta \mathbf{w} + \mathbf{H}_2 \cdot (-\Delta \mathbf{w}) = J_{sn} \Delta w$$

$$H_{1t} - H_{2t} = J_{sn} \quad (\text{A/m})$$

⚡ Important result

$$\mathbf{a}_{n2} \times (\mathbf{H}_1 - \mathbf{H}_2) = \mathbf{J}_s \quad (\text{A/m})$$