SMART CHICK INCUBATOR SYSTEM

GROUP MEMBERS

1. TETTEH BENEDICT 7283723
2. SUFYAN ALBAN 7283423
3. RAJI ABDUL-NUR 7283723
4. YEBOAH CECIL 7284923
5. JACKSON OPOKU 7279623
6. EMMANUEL NIKOI ROBERTSON 7282423
7. WILLIAM QUARTEY-PAPAFIO 7282223
8. SENCHEREY HOWARD 7283223
9. OLIVER LOID QUARCOO 7282123

Table of Contents

1. Introduction 4
2. Problem Statement 4
2.1 Limitations of Traditional Methods 4
2.2 Justification for Automation 5
3. System Overview 5
3.1 System Architecture 5
3.2 Functional Block Diagram Description 5
3.3 Key Design Principles 6
4. Components and Hardware 6
4.1 Component List 6
4.2 Component Justification 6
4.2.1 Arduino Uno R3 6
4.2.2 DHT22 Sensor 7
4.2.3 Relay Modules 7
4.2.4 Heating Element and Fan 7
5. Circuit Design 7
5.1 Circuit Overview 7
5.2 Sensor Connections 7
5.3 Relay Module Connections 8
5.4 Display Connections 8
5.5 Power Supply Considerations 8
5.6 Safety and Grounding 8
6. Software Implementation 8
6.1 Development Environment 8
6.2 Program Structure 8
6.3 Control Logic 9
6.4 Sensor Reading and Error Handling 9
7. Working Principle 9
7.1 Closed-Loop Feedback Control 9
7.2 Temperature Regulation Cycle 10
7.3 Humidity Regulation 10

7.4 Egg Turning 10
7.5 System States..... 10
8. Testing and Demonstration 10
8.1 Testing Methodology 10
8.2 Unit Testing..... 10
8.3 Integration Testing 11
8.5 Observed Limitations 11
9. Conclusion and Future Improvements..... 11
9.1 Conclusion 11
9.2 Future Improvements..... 12
9.2.1 IoT Integration and Remote Monitoring 12
9.2.2 Active Humidity Control 12
9.2.3 Backup Power System 12

SMART CHICK INCUBATOR SYSTEM

Design, Implementation & Technical Documentation

An Automated Egg Incubation System Using Arduino Microcontroller

1. Introduction

Egg incubation is a critical biological process that requires meticulous environmental control. In natural settings, the parent bird regulates temperature and humidity through physical contact, instinctively adjusting its behaviour to maintain optimal conditions. When eggs are incubated artificially — whether for commercial poultry farming, conservation breeding, or small-scale hobbyist use — it becomes necessary to replicate these conditions mechanically and precisely.

The Smart Chick Incubator System is designed to automate the egg incubation process by continuously monitoring and regulating two of the most vital environmental parameters: temperature and relative humidity. Using an Arduino microcontroller paired with a DHT sensor, relay modules, a heating element, and a fan, the system creates a self-regulating environment that closely mimics the conditions of a brooding hen.

The motivation for this project stems from the widespread limitations of traditional manual incubation methods, which are prone to human error, inconsistency, and neglect. By leveraging embedded systems technology, this project delivers a reliable, cost-effective, and scalable solution suitable for small to medium-scale poultry operations as well as educational and research purposes.

This documentation provides a comprehensive overview of the system — from problem identification and hardware selection through circuit design, software logic, testing, and future development pathways.

2. Problem Statement

Successful egg hatching depends on maintaining very narrow environmental parameters throughout the entire incubation period, which typically spans 21 days for chicken eggs. The recommended temperature range is 37.5°C to 38.0°C (99.5°F), and relative humidity should be maintained at approximately 50–55% for the first 18 days, rising to 65–70% during the final 3 days (lockdown). Even minor deviations from these thresholds can have serious consequences for embryo viability.

2.1 Limitations of Traditional Methods

Conventional manual incubation relies entirely on periodic human observation and intervention. Common problems associated with this approach include:

- Inconsistent temperature regulation due to infrequent checks and slow human response times.

- Inadequate humidity monitoring, as most non-automated setups lack accurate hygrometers.
- Human fatigue and oversight errors, particularly during critical developmental windows at night or over weekends.
- Inability to maintain conditions during power outages without a contingency plan.
- Higher mortality rates attributed to prolonged environmental imbalances.

2.2 Justification for Automation

An automated system addresses each of these limitations by providing round-the-clock sensor-driven monitoring, near-instantaneous actuator response, and consistent maintenance of pre-programmed environmental thresholds. The result is a significant improvement in hatch rates, reduced labour demands, and a more reliable incubation outcome across all batches.

3. System Overview

The Smart Chick Incubator System is structured around three functional layers: sensing, processing, and actuation. These layers work together in a continuous closed-loop feedback mechanism to maintain the desired environmental conditions inside the incubation chamber.

3.1 System Architecture

At a high level, the system operates as follows:

- The DHT sensor continuously measures temperature and humidity inside the chamber.
- The Arduino microcontroller reads this sensor data at regular intervals.
- The measured values are compared against pre-defined threshold values stored in the program.
- Based on the comparison results, the controller sends digital HIGH or LOW signals to relay modules.
- The relays switch the heating element and fan on or off to bring conditions back within range.
- A display unit provides real-time feedback to the operator.

3.2 Functional Block Diagram Description

The input stage consists of the DHT sensor, which serves as the primary data acquisition point. The processing stage is handled entirely by the Arduino, which runs the control logic. The output stage includes the relay-controlled heater (for temperature management), the relay-controlled fan (for both temperature reduction and humidity distribution), and a liquid crystal or serial display for status output.

3.3 Key Design Principles

The system was designed around three core engineering principles:

- Reliability: Components were selected for proven performance in embedded systems applications.
- Affordability: The total bill of materials was kept low to ensure accessibility for small-scale users.
- Scalability: The design allows for future expansion, including additional sensors, IoT connectivity, and enhanced control logic.

4. Components and Hardware

4.1 Component List

The following table summarises the key components used in the system:

Component	Specification	Role in System
Arduino Uno R3	ATmega328P, 14 digital I/O, 6 PWM	Central processing & control logic
DHT22 Sensor	±0.5°C temp accuracy, ±2–5% RH	Real-time temp & humidity sensing
2-Channel Relay Module	5V coil, 10A/250VAC contacts	Switching heater and fan
Heating Element	12V DC, 10–20W ceramic PTC	Raising and maintaining temperature
DC Fan	12V, 80mm blade	Air circulation and cooling
16x2 LCD Display	HD44780 compatible	Real-time data display
Power Supply	12V 2A DC adapter	System power
Connecting Wires	Dupont jumper wires, AWG22	Circuit interconnections
Breadboard / PCB	Full-size breadboard or custom PCB	Component mounting

4.2 Component Justification

4.2.1 Arduino Uno R3

The Arduino Uno was chosen for its extensive community support, well-documented libraries, and sufficient I/O resources for this application. Its 5V logic level is compatible

with both the DHT22 sensor and the relay modules. The onboard USB interface simplifies programming and debugging without additional hardware.

4.2.2 DHT22 Sensor

The DHT22 was selected over the lower-cost DHT11 due to its superior accuracy (±0.5°C vs ±2°C for temperature, and ±2% vs ±5% for humidity). Given the tight environmental tolerances required for successful incubation, the improved accuracy of the DHT22 directly contributes to better hatch rates. The sensor communicates over a single-wire protocol, simplifying wiring.

4.2.3 Relay Modules

Relay modules provide electrical isolation between the low-voltage Arduino logic (5V) and the higher-power heating and fan circuits (12V DC). This isolation protects the microcontroller from voltage spikes and ensures safe operation. The 2-channel relay module allows independent control of both output devices using just two Arduino digital pins.

4.2.4 Heating Element and Fan

A ceramic PTC (Positive Temperature Coefficient) heating element was selected for its self-limiting temperature characteristics, which reduce the risk of overheating. The DC fan serves a dual purpose: it distributes heat evenly throughout the incubation chamber and assists in reducing temperature when the heater is switched off. Uniform temperature distribution is critical, as temperature gradients inside the chamber can cause uneven embryo development.

5. Circuit Design

5.1 Circuit Overview

The circuit is divided into two voltage domains: the 5V logic domain (Arduino, DHT22 sensor, relay control coils, and LCD) and the 12V power domain (heating element and fan). These domains are bridged by the relay modules, which act as electromechanical switches under Arduino control.

5.2 Sensor Connections

The DHT22 sensor is connected to the Arduino as follows:

- VCC pin connected to Arduino 5V rail.
- GND pin connected to common ground.
- DATA pin connected to Arduino digital pin D2, with a 10kΩ pull-up resistor to VCC to ensure signal integrity.

The pull-up resistor is essential for the DHT22's single-wire communication protocol. Without it, the data line may float, causing erratic sensor readings.

5.3 Relay Module Connections

Each relay channel is connected as follows:

- IN1 (heater relay) connected to Arduino digital pin D4.
- IN2 (fan relay) connected to Arduino digital pin D5.
- VCC and GND of the relay module connected to the 5V rail and ground.
- The NO (Normally Open) and COM (Common) terminals of each relay connected in series with the respective 12V load.

The relay modules used are active-LOW type, meaning the relay engages when the control pin is pulled LOW. This is accounted for in the software logic.

5.4 Display Connections

The 16x2 LCD is connected to the Arduino via pins D7–D12, with the RS and Enable pins on D11 and D12 respectively. A 10kΩ potentiometer is used to adjust display contrast. The LCD displays the current temperature and humidity readings on alternating lines.

5.5 Power Supply Considerations

A single 12V DC power supply feeds the entire system. A 5V voltage regulator (or the Arduino's onboard regulator via the Vin pin) steps down 12V to 5V for the logic components. Care was taken to ensure the power supply is rated for at least 2A to handle the combined current draw of the heater, fan, and logic components without voltage sag.

5.6 Safety and Grounding

All ground lines are tied to a common reference point to prevent ground loops. The relay module's optical isolation ensures that high-side switching faults do not propagate to the Arduino. Appropriate wire gauges (AWG22 for signal lines, AWG18 for power lines) were used to handle expected current loads safely.

6. Software Implementation

6.1 Development Environment

The system firmware was developed using the Arduino Integrated Development Environment (IDE), version 2.x. The DHT sensor library (by Adafruit) was used to abstract the low-level communication protocol of the DHT22, allowing the developer to retrieve calibrated temperature and humidity values with a single function call.

6.2 Program Structure

The firmware is organized into three logical sections:

- Initialisation: Pins are configured, the serial monitor is started for debugging, the LCD is initialised, and the sensor is attached.

- Main Loop: Sensor data is read, compared against thresholds, and actuators are updated accordingly. The display is refreshed each cycle.
- Helper Functions: Separate functions handle heater control, fan control, and display updates for code clarity and reuse.

6.3 Control Logic

The core control logic implements a simple hysteresis-based on/off controller with the following defined constants:

Parameter	Lower Threshold	Upper Threshold
Temperature (Days 1–18)	37.5°C	38.0°C
Temperature (Days 19–21)	37.2°C	37.8°C
Relative Humidity (Days 1–18)	50%	55%
Relative Humidity (Days 19–21)	65%	70%

The heater is activated when temperature drops below the lower threshold and deactivated when it exceeds the upper threshold. Similarly, the fan is activated when temperature exceeds the upper threshold or when humidity needs redistribution. This hysteresis band prevents rapid on/off switching (relay chattering), which could shorten the relay's mechanical lifespan.

6.4 Sensor Reading and Error Handling

The DHT22 returns NaN (Not a Number) in cases where the reading fails — typically due to communication errors or sensor warm-up delays. The firmware checks for NaN values before processing and skips actuator updates for that cycle, maintaining the last known safe state. A counter tracks consecutive failed readings and triggers an error flag on the display if failures persist beyond five cycles.

7. Working Principle

7.1 Closed-Loop Feedback Control

The system operates as a negative feedback closed-loop control system. In this model, the output (temperature/humidity inside the incubator) is continuously measured and fed back to the controller (Arduino). The controller compares the measured output with the desired set point and computes an error signal. If the actual value deviates from the set point, the controller activates the appropriate actuator to correct the deviation.

This closed-loop architecture is fundamentally more reliable than open-loop control (where actuators are operated on a timer without feedback), because it responds dynamically to actual conditions rather than assuming idealised behaviour.

7.2 Temperature Regulation Cycle

When the chamber temperature falls below 37.5°C, the Arduino activates the heater relay. Heat energy is transferred from the heating element into the air inside the chamber. The sensor continuously monitors temperature until it reaches 38.0°C, at which point the heater is switched off. The fan may then activate briefly to redistribute warm air and prevent localised hot spots near the element.

7.3 Humidity Regulation

In the current implementation, humidity is passively regulated through a water tray placed inside the chamber. The rate of evaporation from the tray naturally maintains humidity within the target range under normal conditions. The DHT22 monitors humidity and alerts the operator via the display if it falls outside bounds. Future versions will incorporate an ultrasonic mist maker controlled via a third relay channel for active humidity management.

7.4 Egg Turning

Manual egg turning (at least 3 times per day during days 1–18) is required in the current implementation. Egg turning prevents the embryo from adhering to the shell membrane and promotes even heat distribution. The system design reserves an additional relay channel and digital output pin for a future servo-driven automatic turning mechanism.

7.5 System States

The system operates in one of four possible states at any given time:

- Steady State: All parameters within range; no actuators active.
- Heating State: Temperature below threshold; heater engaged.
- Cooling State: Temperature above upper threshold; fan engaged, heater off.
- Alert State: Sensor failure or sustained out-of-range condition; error displayed.

8. Testing and Demonstration

8.1 Testing Methodology

A series of structured tests were conducted to validate both the hardware and software components of the system before full incubation trials. Testing was divided into three phases: unit testing of individual components, integration testing of the assembled system, and performance testing under simulated incubation conditions.

8.2 Unit Testing

Each component was tested independently before integration:

- DHT22 Sensor: Serial monitor readings were compared against a calibrated reference thermometer and hygrometer. Readings were consistent within the manufacturer-stated accuracy of ±0.5°C and ±2–5% RH.
- Relay Modules: Each relay was tested by sending digital HIGH and LOW signals from the Arduino. Relay click sounds and LED indicators on the module confirmed correct operation.
- Heating Element: Connected to 12V through the relay, the element reached operating temperature within approximately 90 seconds.
- Fan: Confirmed correct directional airflow and adequate circulation inside the test chamber.

8.3 Integration Testing

With all components assembled, the system was powered on and allowed to stabilise. The following scenarios were tested:

- Cold-start behaviour: System correctly identified sub-threshold temperature and activated the heater.
- Overshoot response: Artificial heating beyond the upper threshold confirmed fan activation and heater cut-off.
- Sensor disconnection: Removal of the DHT22 during operation triggered the error state and halted actuator changes.
- Display accuracy: LCD readings matched serial monitor output throughout all test scenarios.

8.5 Observed Limitations

During testing, two minor limitations were identified:

- Temperature equilibration time: After the heater is switched off, it takes approximately 15–20 seconds for residual heat to dissipate, occasionally causing brief overshoot beyond the upper threshold. This can be addressed with a predictive control algorithm in future versions.
- Humidity passivity: The reliance on a passive water tray means humidity cannot be rapidly increased in response to sudden drops. Active humidification control is identified as a priority improvement.

9. Conclusion and Future Improvements

9.1 Conclusion

The Smart Chick Incubator System successfully demonstrates the application of embedded systems technology to automate and improve the egg incubation process. The system reliably monitors temperature and humidity using the DHT22 sensor and maintains these parameters within the required biological thresholds through automated heater and fan control. All unit and integration tests yielded positive results, confirming that the design is both functional and dependable.

The system offers significant advantages over manual methods: it eliminates the need for constant human supervision, reduces the probability of human error, and ensures consistent environmental conditions throughout the incubation period. At a total component cost that remains accessible for small-scale farmers and educational institutions, it represents a practical and scalable solution to a real-world agricultural challenge.

9.2 Future Improvements

Several enhancements are planned for subsequent versions of the system:

9.2.1 IoT Integration and Remote Monitoring

Replacing the Arduino Uno with an ESP32 or ESP8266 microcontroller would add built-in Wi-Fi capability, enabling real-time data logging to a cloud platform such as Blynk or ThingSpeak. Operators could monitor temperature, humidity, and system status from any location via a mobile application and receive push notifications for out-of-range conditions.

9.2.2 Active Humidity Control

Integration of an ultrasonic mist maker or a small water pump, controlled via a third relay channel, would allow the system to actively raise humidity when it falls below the lower threshold. A 3.5V ultrasonic atomiser module is a low-cost candidate for this feature.

9.2.3 Backup Power System

Integration of a rechargeable battery pack with automatic switchover logic would ensure uninterrupted operation during power outages. Given that even brief exposure to cold temperatures can be fatal to developing embryos, reliable backup power is an important reliability enhancement.

— End of Document —