NEIL ARMSTRONG
MICHAEL COLLINS
EDWIN ALDRIN

Apollo 11 Mission Overview

Relatório Intermédio

Palavras Chave

texto livro, arquitetura, história, construção, materiais de construção, saber tradicional.

Resumo

Um resumo é um pequeno apanhado de um trabalho mais longo (como uma tese, dissertação ou trabalho de pesquisa). O resumo relata de forma concisa os objetivos e resultados da sua pesquisa, para que os leitores saibam exatamente o que se aborda no seu documento.
Embora a estrutura possa variar um pouco dependendo da sua área de estudo, o seu resumo deve descrever o propósito do seu trabalho, os métodos que você usou e as conclusões a que chegou.
Uma maneira comum de estruturar um resumo é usar a estrutura IMRaD. Isso significa:

- Introdução
- Métodos
- Resultados
- Discussão

Veja mais pormenores aqui:
`https://www.scribbr.com/dissertation/abstract/`

Keywords

textbook, architecture, history, construction, construction materials, traditional knowledge.

Abstract

An abstract is a short summary of a longer work (such as a thesis, dissertation or research paper).
The abstract concisely reports the aims and outcomes of your research, so that readers know exactly what your paper is about.
Although the structure may vary slightly depending on your discipline, your abstract should describe the purpose of your work, the methods you've used, and the conclusions you've drawn.
One common way to structure your abstract is to use the IMRaD structure. This stands for:

- Introduction
- Methods
- Results
- Discussion

Check for more details here:
`https://www.scribbr.com/dissertation/abstract/`

Contents

1 Introduction **5**
1.1 Background 5
1.2 Problem Statement 5
1.3 Objectives 5
1.4 Significance of the Study 5
1.5 Scope 5
1.6 Work Breakdown Structure (WBS) 5

2 Literature Review **6**
2.1 Influence of IMPs on LDH growth 6
2.1.1 Pre-Treatment 7
2.2 Equivalent Circuit Models for EIS 8

3 Methodology **10**
3.1 Determine ECM for EIS 10
3.2 Pre-treatments 12

4 Results **13**

5 Discussion **14**

6 Conclusion & Future Work **15**

Bibliography **16**

List of Figures

List of Tables

Chapter 1

Introduction

1.1 Background

Context or background of the project.

1.2 Problem Statement

Clearly state the problem that you will address in your project.

1.3 Objectives

Clearly state the objectives or goals of your project.

1.4 Significance of the Study

Explain the importance of your project.

1.5 Scope

Define the scope of your project through requirements and allocate priorities in accordance with the relevance and uncertainty of each one.

1.6 Work Breakdown Structure (WBS)

Define the WBS, including Work Packages (WPs), tasks, Gantt Chart, indentifying risks and mitigation strategy.

Chapter 2

Literature Review

2.1 Influence of IMPs on LDH growth

AC46000 contains a diverse range of intermetallic particles (IMPs), including copper-rich phases such as Al_2Cu and Al_7Cu_2Fe, iron-rich phases such as Al_5FeSi and $Al_{15}(Fe, Mn)_3Si_2$, and eutectic silicon particles. To assess the influence of these IMPs on LDH growth and corrosion behavior, it is important to consider their electrochemical potential relative to the aluminium matrix [7, 9].

The copper-rich phases are strongly cathodic relative to the Al matrix, with Al_2Cu exhibiting a potential difference of approximately +400 mV [7]. This drives intense localized micro-galvanic coupling, promoting rapid oxygen reduction and a sharp rise in local pH. In the context of LDH growth, these conditions trigger the preferential and rapid precipitation of thick, "flower-like" LDH islands directly over the cathodic sites [3]. This localized growth is sustained by the anodic dissolution of the surrounding aluminium matrix, commonly referred to as trenching [2]. The trenching process generates voids at the periphery of the intermetallic particles where LDH flakes fail to nucleate [2]. These uncoated gaps compromise the corrosion resistance of the substrate, as chloride ions and other aggressive species can readily penetrate the exposed defects and initiate pitting corrosion [2]. The resulting inhomogeneous LDH film also reduces the adhesion of subsequently applied polymer coatings or paints [2], and in severe cases extensive trenching can render the intermetallic particles prone to detachment, further undermining the integrity of overlying layers [2].

The iron-rich phases are also strongly cathodic, approximately +300 mV above the aluminium matrix [7], and the galvanic coupling they generate similarly leads to inhomogeneous LDH growth and increased susceptibility to corrosion.

Although eutectic silicon particles are likewise cathodic, with a potential

difference of approximately +250 mV relative to the Al matrix, they are electrochemically inert and do not act as nucleation sites for LDH. Since they provide no source of the metal cations (Al^{2+}/Al^{3+}, Mg^{2+}) required for LDH formation, no coating growth is triggered at these sites [7, 6].

2.1.1 Pre-Treatment

Given the detrimental influence of these IMPs on LDH growth homogeneity and overall coating quality, their removal from the alloy surface prior to conversion coating is essential. To this end, various pre-treatment strategies have been developed, but the most widely adopted approach consists of a multistep procedure comprising degreasing, alkaline etching, and acid pickling, applied sequentially [11].

Degreasing constitutes the first pre-treatment step, with the primary objective of removing surface contamination, most notably oils and lubricants introduced during the manufacturing process. This step is critical to ensure full surface wettability, thereby guaranteeing that subsequent processing stages act uniformly across the substrate [11].

The second step, alkaline etching, is aimed at dissolving the native oxide layer that forms spontaneously on aluminium surfaces, as well as removing surface-exposed intermetallic particles. The cathodic IMPs act as highly active sites for oxygen reduction, generating a localised rise in pH at their immediate vicinity. This accelerates the anodic dissolution of the surrounding aluminium matrix, progressively undermining the mechanical support of the particles [13]. As the matrix recedes, scallop-shaped voids form at the particle periphery, eventually causing the IMPs to detach from the surface, a process known as selective dealloying [13, 8]. Since many of the constituent alloying elements released during this process are insoluble in alkaline media, they accumulate on the surface as a loosely adherent residue known as smut, the removal of which necessitates a subsequent acid pickling step [11, 13, 8].

Nitric acid (HNO_3) is widely used for desmutting because it naturally passivates the aluminum matrix while acting as a powerful oxidant [8]. It successfully targets and dissolves the dealloyed metallic smut, including copper, iron, and manganese residues. Despite this, Nitric acid alone is ineffective against silicon-rich intermetallic residues [4]. To remove these, fluorides (such as hydrofluoric acid or ammonium bifluoride) must be added to the pickling bath [1, 10]. The fluoride ions dissolve the silica and complex the remaining silicon remnants so they can be washed away [1, 10].

2.2 Equivalent Circuit Models for EIS

Determining an appropriate equivalent circuit model (ECM) for electrochemical impedance spectroscopy (EIS) spectra is among the most important steps in impedance analysis, as it enables the deconvolution of overlapping electrochemical processes and their quantification through physically meaningful parameters. One of the most commonly used circuit is the Randles equivalent circuit composed of a resistance in series with a resistance and a capacitor in parallel, as represented in FIGURE [5]. As labeled in the figure, the first resistance is the solution resistance and as the name suggests it represents the resistance of the bulk electrolyte between the reference electrode and the working electrode[12]. The second resistance on the other hand is known as the charge-transfer resistance and is a kinetic parameter associated with the energy barrier that electrons must overcome to cross the electrode/electrolyte interface during a Faradaic reaction. It is inversely proportional to the exchange current density, reflecting the inherent "speed" of the electrochemical reaction. The capacitor is known as the double layer capacitor, associated with the double layer fenomena explained earlier. Its value is a function of the electrode potential, the ionic concentration, and the effective surface area of the metal.

As previously mentioned a high charge-transfer resistance means there is a large kinetic energy barrier preventing electrons from crossing the interface, which correlates directly to a very slow corrosion rate. Conversly an increase in Cdl indicates that the protective film has failed, exposing a larger "film-free" area of bare metal directly to the corrosive electrolyte. Additionally, as the metal dissolves and localized corrosion (like pitting) occurs, the surface becomes physically rougher and more fractal; this increased effective surface area directly drives the double layer capacitance higher. This can be related to the formula of a planar capacitor:

Determining an appropriate equivalent circuit model (ECM) for electrochemical impedance spectroscopy (EIS) spectra is among the most critical steps in impedance analysis, as it enables the deconvolution of overlapping electrochemical processes and their quantification through physically meaningful parameters. One of the most widely used models is the Randles equivalent circuit, which consists of a solution resistance (R_{s}) in series with a parallel combination of a charge-transfer resistance (R_{ct}) and a double-layer capacitance (C_{dl}), as represented in [REFERENCIAR FIGURE] [5]. The R_{s}, represents the ohmic resistance of the bulk electrolyte between the reference electrode and the working electrode [12]. The R_{ct}, is a kinetic parameter associated with the energy barrier that must be overcome for electrons to cross the electrode/electrolyte interface during a Faradaic reaction. It is inversely proportional to the exchange current density, thereby reflecting the intrinsic rate of the electrochemical

reaction at equilibrium. The C_{dl}, arises from the charge separation at the electrode/electrolyte interface, the electric double layer phenomenon described in [REFERENCIAR EARLIER DOUBLE LAYER], and its magnitude is governed by the electrode potential, the ionic concentration of the electrolyte, and the effective surface area of the electrode.

$$C = \frac{\epsilon \epsilon_0 A}{d} \tag{2.1}$$

Where ϵ is the permittivity, ϵ_0 is the vacuum permittivity, A is the area of the plates, and d is the separation distance.

Chapter 3

Methodology

3.1 Determine ECM for EIS

Determining an appropriate equivalent circuit model (ECM) for electrochemical impedance spectroscopy (EIS) spectra is among the most important steps in impedance analysis, as it enables the deconvolution of overlapping electrochemical processes and their quantification through physically meaningful parameters, such as charge transfer resistance (R_{ct}), film or oxide layer resistance (R_{ox}), and double-layer capacitance (C_{dl}).

Despite its centrality to the analysis, ECM identification remains a laborious task. Commercial software packages such as ZView and Gamry Echem Analyst rely on nonlinear least-squares (NLLS) fitting routines, most commonly the Levenberg-Marquardt algorithm, which are inherently sensitive to the choice of initial parameter estimates. While heuristic approaches exist to guide these estimates, such as reading characteristic resistances from the diameters of semicircular arcs in the Nyquist representation or extracting time constants from Bode phase plots, the process remains largely manual and iterative, demanding considerable operator experience to avoid convergence to local minima or physically unreasonable solutions.

In response to these limitations, a number of open-source, programmatic alternatives have been developed, predominantly in Python. Among these, `impedance.py` provides a flexible framework for ECM fitting and validation. More recently, tools such as `AutoECM` and `AutoEIS` have incorporated machine learning methodologies into the workflow. AutoECM employs supervised classification models such as Random Forest, XGBoost (XGB), and convolutional neural network (CNN) architectures. These are trained on libraries of previously validated circuit-spectrum pairs to predict candidate ECMs for new datasets. AutoEIS, by contrast, adopts a probabilistic framework grounded in Bayesian inference, enabling uncertainty quantification in both circuit structure selection and parameter

estimation. A notable limitation shared by both tools, however, is the apparent discontinuation of active maintenance by their respective developers. As a consequence, dependency incompatibilities with more recent versions of core scientific Python libraries have rendered them largely non-functional in current environments.

Given this landscape, `impedance.py` emerges as the most viable open-source option. In its standard implementation, it operates analogously to commercial software: the user must supply the impedance dataset, an *a priori* circuit string, and initial parameter guesses. Two optional fitting configurations are available. The first, `weight_by_modulus`, applies the modulus of the complex impedance as a frequency-dependent weighting factor which ensures that data points spanning several decades of impedance magnitude contribute proportionally to the objective function. The second, `global_opt`, invokes a basin-hopping algorithm, which combines stochastic perturbation of parameter coordinates with local minimization and a Metropolis-type acceptance criterion to escape local minima. Importantly, `global_opt` is incompatible with `weight_by_modulus` and given that EIS datasets span several decades in frequency, commonly from 10 mHz to 100 kHz, and correspondingly large ranges in impedance magnitude, modulus weighting is generally considered essential to prevent low-frequency, high-impedance data from disproportionately dominating the fit residuals.

To overcome the dependence on user-supplied initial guesses while retaining the precision of local optimization, a hybrid fitting framework was developed building upon impedance.py and the Differential Evolution (DE) algorithm. DE is a stochastic, population-based global optimization metaheuristic well-suited to high-dimensional, non-differentiable, and multimodal objective functions. The algorithm evolves a population of candidate solutions across successive generations through three operators: mutation, which generates trial vectors via linear combinations of population members; crossover, which probabilistically exchanges parameter values between candidate and trial vectors; and selection, which retains whichever vector yields a lower objective function value. Crucially, DE requires no gradient information and treats the cost function as a black box, making it particularly appropriate for the complex, rugged parameter landscapes characteristic of multi-element ECM fitting.

In the proposed workflow, the user supplies only physically motivated bounds for each circuit element rather than precise initial estimates. The DE algorithm then explores this parameter space to identify the order of magnitude and approximate value of each component. To accelerate convergence, given that circuit element values typically span many orders of magnitude, the optimization is performed in logarithmic space, transforming the search domain such that each decade is treated uniformly. This logarithmic reparameterization substantially improves the efficiency of

the population-based search and reduces sensitivity to the scale disparity between, for example, charge-transfer resistances on the order of kilohms and double-layer capacitances on the order of microfarads. Once the DE stage yields a sufficiently accurate global estimate, the resulting parameter vector is passed as the initial condition to the Levenberg-Marquardt local optimizer within `impedance.py`, with `weight_by_modulus` activated, to refine the solution and obtain statistically meaningful parameter estimates together with their associated uncertainties.

3.2 Pre-treatments

As previously discussed, the presence of intermetallic phases (IMPs) on the surface of the aluminum alloy can negatively affect LDH growth and must therefore be removed prior to coating. Two different pre-treatment procedures were tested: a chemical treatment and an industrial treatment.

The first procedure consisted of cleaning at room temperature for 120 s in a 0.1 M NaOH solution, followed by etching for 480 s in a 0.1 M HNO_3 solution. Each step was followed by rinsing with deionized water and final drying in air.

The second procedure consisted of cleaning in Metaclean T2001 (alkaline cleaner based on metal silicates with complexing and surface-active agents) at approximately 65 °C for 25 min, followed by rinsing with deionized water. The specimens were then etched in TurcoLiquid Aluminetch N2 (sodium hydroxide and phosphate-based solution) at 65 °C for 45 s, rinsed with deionized water, and desmutted in TurcoLiquid Smutgo NC (based on ferric sulfate, nitric acid, sodium hydrogendifluoride, and sulfuric acid) at 30 °C for approximately 5 min, before a final rinse with deionized water and drying in air.

Chapter 4

Results

Present the results of your project clearly and concisely, using tables and figures where necessary.

Chapter 5

Discussion

Interpret the results and discuss their implications. Compare your findings with previous research. Discuss any limitations of your study.

Chapter 6

Conclusion & Future Work

Sum up the main findings and their importance, and discuss how they have the WBS going forward.

Bibliography

[1] Albert L. Askin and Paul B. Schultz. Method for desmutting aluminum alloys having a highly reflective surface. US Patent 5,417,819, May 1995. Assigned to Aluminum Company of America.

[2] A. C. Bouali, M. Serdechnova, K. A. Yasakau, A. Lutz, G. Wiese, H. Terryn, M. G. S. Ferreira, and M. L. Zheludkevich. The Role of Cu-Based Intermetallic on the Direct Growth of a ZnAl LDH Film on AA2024. *Journal of The Electrochemical Society*, 169(8):081501, 2022.

[3] Yanhui Cao, Shenao Wang, Congshu Huang, Jingjing Wang, Haixia Qi, Lieji Yang, Hui Li, Dajiang Zheng, and Changjian Lin. Study on the influence mechanism of intermetallic compounds (IMCs) in aluminum alloy AA7075 on the growth behavior and corrosion resistance of layered double hydroxide films. *Corrosion Science*, 265:113809, 2026.

[4] C. M. Cotell, J. A. Sprague, and F. A. Smidt. *Surface Engineering of Aluminum and Aluminum Alloys*, pages 784–804. ASM International, 1994.

[5] Sutanu Das, Ankita Banerjee, Upendranath Nandi, and Aswini Ghosh. Critical review on the analysis of electrochemical impedance spectroscopy data. *Journal of Applied Physics*, 138(12):125002, 2025.

[6] Rubén del Olmo, Reynier I. Revilla, Francesco Andreatta, and Iris De Graeve. Layered double hydroxides on additively manufactured Al–Si alloy: Growth mechanism, microstructure and corrosion performance. *Applied Surface Science*, 710:163891, 2025.

[7] Senka Gudić, Ladislav Vrsalović, Jure Krolo, Aleš Nagode, Ivana Dumanić Labetić, and Branimir Lela. Corrosion Behaviour of Recycled Aluminium AlSi9Cu3(Fe) Machining Chips by Hot Extrusion and Thixoforming. *Sustainability*, 16(4):1358, 2024.

[8] Zelong Jin, Changrun Cai, Yudie Yuan, DaeHoon Kang, John Hunter, and Xiaorong Zhou. The behaviour of AA5754 and AA5052 aluminium alloys in alkaline etching solution: Similarity and difference. *Materials Characterization*, 168:110534, 2020.

[9] Justyna Kasińska, Dana Bolibruchová, and Marek Matejka. The Influence of Remelting on the Properties of AlSi9Cu3 Alloy with Higher Iron Content. *Materials (Basel)*, 13(3):575, 2020.

[10] Eul-Kyu Lee. Surface treatment composition and method for removing Si component and reduced metal salt produced on the aluminum die cast material in etching process. US Patent 7,405,189, Jul 2008. Assigned to Cheon Young Chemical Co., Ltd.

[11] Mariana Paz Martínez-Viademonte, Shoshan T. Abrahami, Theodor Hack, Malte Burchardt, and Herman Terryn. A Review on Anodizing of Aerospace Aluminum Alloys for Corrosion Protection. *Coatings*, 10(11):1106, 2020.

[12] Metrohm Autolab. Electrochemical Impedance Spectroscopy Part 3 – Data Analysis. EC Application Note AN-EIS-003, Metrohm AG, 2021.

[13] K. J. H. Nelson, A. E. Hughes, R. J. Taylor, B. R. W. Hinton, L. Wilson, and M. Henderson. Characterisation of aluminium alloys after $HNO_3/HF - NaOH - HNO_3/HF$ pretreatment. *Materials Science and Technology*, 17(10):1211, 2001.