

LAB 8 – TESTING

1. Test Case Template

Test Case #:	Test Case Name:
System:	Subsystem:
Designed by:	Design Date:
Executed by	Execution Date:
Short Description:	

Pre-conditions:

Step	Action	Expected System Response	Pass/Fail	Comments

Post-Conditions

2. Example:

Test Case #: 2.2	Test Case Name: Change PIN
System: ATM	Subsystem: PIN
Designed by: Mr. Nguyen Van A	Design Date: 30/08/2023
Executed by: Ms. Nguyen Thi B	Execution Date: 04/09/2023
Short Description: Test the ATM change pin service	

Pre-conditions:

- The current has valid ATM card – The user has accessed the ATM by placing his ATM card in the machine
- The current PIN is 1234
- The system display the main menu

Step	Action	Expected System Response	Pass/Fail	Comments
1	Click the “Change PIN” button	The system displays the message asking user to input the new PIN		
2	Enter “5555”	The system displays the message asking user to re-input the new PIN		
3	Re-enter “5555”	The system displays the message of successful operation The system asks the user if he wants to perform other operations		
4	Click “YES” button	The system displays main menu		
5	Check post-condition 1			
6	Repeat step 1,2,3 using another PIN say “6666” and click “NO” button	The system is exited and display the greeting message asking user to input his ATM card in the machine		
7	Check post-condition 2			
8	Repeat step 1,2 and using another PIN say “7777”	The system displays the message asking user to re-input the new PIN		
9	Enter wrong confirmation	The system displays unsuccessful message and ask user to confirm correct PIN		
10	Re-enter “7777”	The system displays the message of successful operation The system asks the user if he wants to perform other operations		

Post-Conditions

- The new PIN “5555” is saved in the database
- The new PIN “6666” is saved in the database
- The new PIN “7777” is saved in the database