

OTIS INDIA B.W		I - O LIST LCB-II WITH YASKAA L7 DRIVE CONTROLLER UP TO 24 STOPS. FOR MODELS ONLY		Prep By: Madhu Rev0. Date : 16-02-2007 Rev1. Date : 05-01-2008	
I/O No	SYMBOL	DESCRIPTION	ACTUAL	DEF	TYPE
0	DOL	Door Open Limit	12-4	1/0	in
1	DOB ✓	Door Open Button	08-3	0/0	in
2	EDP	Electronic Door Protection	00-0	0/0	in
3	DCB	Door Close Button	08-4	0/0	in
4	ISS	Independent Service Switch ✓	09-3	0/0	in
5	LWO	Load Weighting Overload	13-3	0/0	in
6	LNS / DIS1	Load Non Stop / Delayed Releveling	14-3	0/0	in
7	LWX / ACS	ANS Load Weight / Anti Creeping Switch	12-3	1/0	in
8	UIS	Start/stop relevel down	01-0	1/0	in
9	DIS	Start/stop relevel up	01-0	1/0	in
10	CTL / PKS	Car To Landing/Parking Switch	00-0	0/0	in
11	PKS	Parking Switch	21-4	0/0	in
12	-	-	-	0/0	-
13	CCTL	Car Call to Top Landing	00-0	0/0	in
14	CCBL	Car Call to Bottom Landing	00-0	0/0	in
15	-	-	-	-	-
16	EFK	Emergency Fireman Keyswitch	21-3	0/0	in
17	NU	Emergency power	01-0	1/0	in
18	NUSD / NUSD-1	Enable rescue operation	01-0	1/0	i/o
19	NUG / NUG-1	Enable normal operation	01-0	1/0	i/o
20	CUDL	Car Up Direction Light	10-3	0/0	out
21	CDDL	Car Down Direction Light	11-3	0/0	out
22	OLS	Over Load Signal	12-3	0/0	out
23	BUZ	Buzzer	13-3	0/0	out
24	FSL	Fireman Service Light	09-3	0/0	out
25	HEL	Hospital Emergency Light	00-0	0/0	out
26	LR	Light Relay.	15-3	0/0	out
27	NDG	Nudging	00-0	0/0	out
28	-	-	-	0/0	-
29	STH	Stop Signal Hall	57.1	0/0	out
30	STC	Stop Signal Car	57.1	0/0	out
31	DMD	Demand	00-0	0/0	out
32	CB / CTTL 0	Car Button / Tell Tale Light 0 B	08-1	0/0	i/o
33	CB / CTTL 1	Car Button / Tell Tale Light 1 1	09-1	0/0	i/o
34	CB / CTTL 2	Car Button / Tell Tale Light 2 2	10-1	0/0	i/o
35	CB / CTTL 3	Car Button / Tell Tale Light 3 3	11-1	0/0	i/o
36	CB / CTTL 4	Car Button / Tell Tale Light 4 4	12-1	0/0	i/o
37	CB / CTTL 5	Car Button / Tell Tale Light 5 5	13-1	0/0	i/o
38	CB / CTTL 6	Car Button / Tell Tale Light 6 6	14-1	0/0	i/o
39	CB / CTTL 7	Car Button / Tell Tale Light 7	15-1	0/0	i/o
40	CB / CTTL 8	Car Button / Tell Tale Light 8	08-2	0/0	i/o
41	CB / CTTL 9	Car Button / Tell Tale Light 9	09-2	0/0	i/o
42	CB / CTTL 10	Car Button / Tell Tale Light 10	10-2	0/0	i/o
43	CB / CTTL 11	Car Button / Tell Tale Light 11	11-2	0/0	i/o
44	CB / CTTL 12	Car Button / Tell Tale Light 12	12-2	0/0	i/o
45	CB / CTTL 13	Car Button / Tell Tale Light 13	13-2	0/0	i/o
46	CB / CTTL 14	Car Button / Tell Tale Light 14	14-2	0/0	i/o
47	CB / CTTL 15	Car Button / Tell Tale Light 15	15-2	0/0	i/o
48	CB / CTTL 16	Car Button / Tell Tale Light 16	04-1	0/0	i/o
49	CB / CTTL 17	Car Button / Tell Tale Light 17	04-2	0/0	i/o
50	CB / CTTL 18	Car Button / Tell Tale Light 18	04-3	0/0	i/o
51	CB / CTTL 19	Car Button / Tell Tale Light 19	04-4	0/0	i/o
52	CB / CTTL 20	Car Button / Tell Tale Light 20	05-1	0/0	i/o
53	CB / CTTL 21	Car Button / Tell Tale Light 21	05-2	0/0	i/o
54	CB / CTTL 22	Car Button / Tell Tale Light 22	05-3	0/0	i/o
55	CB / CTTL 23	Car Button / Tell Tale Light 23	05-4	0/0	i/o

OTIS INDIA B.W		I - O LIST LCB-II WITH YASKAA L7 DRIVE CONTROLLER UP TO 24 STOPS. FOR MODELS ONLY		Prep By: Madhu Rev0. Date : 16-02-2007 Rev1. Date : 05-01-2008		
I/O No	SYMBOL	DESCRIPTION		ACTUAL	DEF	TYPE
56	CB / CTTL 24	Car Button / Tell Tale Light 24		00-0	0/0	i/o
		Up Hall Button / Tell Tale Light 0.	ALWAYS			
64	UHB / UHTTL 0	TO ADDRESSED IN I/O LOCATION "96".	22-1	00-0	0/0	i/o
65	UHB / UHTTL 1	Up Hall Button / Tell Tale Light 1	23-1	22-1	0/0	i/o
66	UHB / UHTTL 2	Up Hall Button / Tell Tale Light 2	24-1	23-1	0/0	i/o
67	UHB / UHTTL 3	Up Hall Button / Tell Tale Light 3	25-1	24-1	0/0	i/o
68	UHB / UHTTL 4	Up Hall Button / Tell Tale Light 4	26-1	25-1	0/0	i/o
69	UHB / UHTTL 5	Up Hall Button / Tell Tale Light 5		26-1	0/0	i/o
70	UHB / UHTTL 6	Up Hall Button / Tell Tale Light 6		27-1	0/0	i/o
71	UHB / UHTTL 7	Up Hall Button / Tell Tale Light 7		28-1	0/0	i/o
72	UHB / UHTTL 8	Up Hall Button / Tell Tale Light 8		29-1	0/0	i/o
73	UHB / UHTTL 9	Up Hall Button / Tell Tale Light 9		30-1	0/0	i/o
74	UHB / UHTTL 10	Up Hall Button / Tell Tale Light 10		31-1	0/0	i/o
75	UHB / UHTTL 11	Up Hall Button / Tell Tale Light 11		32-1	0/0	i/o
76	UHB / UHTTL 12	Up Hall Button / Tell Tale Light 12		33-1	0/0	i/o
77	UHB / UHTTL 13	Up Hall Button / Tell Tale Light 13		34-1	0/0	i/o
78	UHB / UHTTL 14	Up Hall Button / Tell Tale Light 14		35-1	0/0	i/o
79	UHB / UHTTL 15	Up Hall Button / Tell Tale Light 15		36-1	0/0	i/o
80	UHB / UHTTL 16	Up Hall Button / Tell Tale Light 16		37-1	0/0	i/o
81	UHB / UHTTL 17	Up Hall Button / Tell Tale Light 17		38-1	0/0	i/o
82	UHB / UHTTL 18	Up Hall Button / Tell Tale Light 18		39-1	0/0	i/o
83	UHB / UHTTL 19	Up Hall Button / Tell Tale Light 19		40-1	0/0	i/o
84	UHB / UHTTL 20	Up Hall Button / Tell Tale Light 20		41-1	0/0	i/o
85	UHB / UHTTL 21	Up Hall Button / Tell Tale Light 21		42-1	0/0	i/o
86	UHB / UHTTL 22	Up Hall Button / Tell Tale Light 22		43-1	0/0	i/o
87	UHB / UHTTL 23	Up Hall Button / Tell Tale Light 23		00-0	0/0	i/o
96	HB / HBTTL 0	Up Hall Button / Tell Tale Light 0	22-2	21-1	0/0	i/o
97	DHB / HBTTL 1	Hall Button / Tell Tale Light 1	23-2	22-2	0/0	i/o
98	DHB / HBTTL 2	Hall Button / Tell Tale Light 2	24-2	23-2	0/0	i/o
99	DHB / HBTTL 3	Hall Button / Tell Tale Light 3	25-2	24-2	0/0	i/o
100	DHB / HBTTL 4	Hall Button / Tell Tale Light 4	26-2	25-2	0/0	i/o
101	DHB / HBTTL 5	Hall Button / Tell Tale Light 5	27-2	26-2	0/0	i/o
102	DHB / HBTTL 6	Hall Button / Tell Tale Light 6	28-2	27-2	0/0	i/o
103	DHB / HBTTL 7	Hall Button / Tell Tale Light 7	29-2	28-2	0/0	i/o
104	DHB / HBTTL 8	Hall Button / Tell Tale Light 8		29-2	0/0	i/o
105	DHB / HBTTL 9	Hall Button / Tell Tale Light 9		30-2	0/0	i/o
106	DHB / HBTTL 10	Hall Button / Tell Tale Light 10		31-2	0/0	i/o
107	DHB / HBTTL 11	Hall Button / Tell Tale Light 11		32-2	0/0	i/o
108	DHB / HBTTL 12	Hall Button / Tell Tale Light 12		33-2	0/0	i/o
109	DHB / HBTTL 13	Hall Button / Tell Tale Light 13		34-2	0/0	i/o
110	DHB / HBTTL 14	Hall Button / Tell Tale Light 14		35-2	0/0	i/o
111	DHB / HBTTL 15	Hall Button / Tell Tale Light 15		36-2	0/0	i/o
112	DHB / HBTTL 16	Hall Button / Tell Tale Light 16		37-2	0/0	i/o
113	DHB / HBTTL 17	Hall Button / Tell Tale Light 17		38-2	0/0	i/o
114	DHB / HBTTL 18	Hall Button / Tell Tale Light 18		39-2	0/0	i/o
115	DHB / HBTTL 19	Hall Button / Tell Tale Light 19		40-2	0/0	i/o
116	DHB / HBTTL 20	Hall Button / Tell Tale Light 20		41-2	0/0	i/o
117	DHB / HBTTL 21	Hall Button / Tell Tale Light 21		42-2	0/0	i/o
118	DHB / HBTTL 22	Hall Button / Tell Tale Light 22		43-2	0/0	i/o
119	DHB / HBTTL 23	Hall Button / Tell Tale Light 23		44-2	0/0	i/o
120	DHB / HBTTL 24	Hall Button / Tell Tale Light 24		00-0	0/0	i/o
128	UHL 0	Up Hall Lantern 0		21-4	0/0	out
129	UHL 1	Up Hall Lantern 1		22-4	0/0	out
130	UHL 2	Up Hall Lantern 2		24-4	0/0	out
131	UHL 3	Up Hall Lantern 3		25-4	0/0	out
132	UHL 4	Up Hall Lantern 4		26-4	0/0	out

OTIS INDIA B.W		I - O LIST LCB-II WITH YASKAA L7 DRIVE CONTROLLER UP TO 24 STOPS. FOR MODELS ONLY	Prep By: Madhu Rev0. Date : 16-02-2007 Rev1. Date : 05-01-2008		
I/O No	SYMBOL	DESCRIPTION	ACTUAL	DEF	TYPE
133	UHL 5	Up Hall Lantern 5	27-4	0/0	out
134	UHL 6	Up Hall Lantern 6	28-4	0/0	out
135	UHL 7	Up Hall Lantern 7	29-4	0/0	out
136	UHL 8	Up Hall Lantern 8	30-4	0/0	out
137	UHL 9	Up Hall Lantern 9	31-4	0/0	out
138	UHL 10	Up Hall Lantern 10	32-4	0/0	out
139	UHL 11	Up Hall Lantern 11	33-4	0/0	out
140	UHL 12	Up Hall Lantern 12	34-4	0/0	out
141	UHL 13	Up Hall Lantern 13	35-4	0/0	out
142	UHL 14	Up Hall Lantern 14	36-4	0/0	out
143	UHL 15	Up Hall Lantern 15	37-4	0/0	out
144	UHL 16	Up Hall Lantern 16	38-4	0/0	out
145	UHL 17	Up Hall Lantern 17	39-4	0/0	out
146	UHL 18	Up Hall Lantern 18	40-4	0/0	out
147	UHL 19	Up Hall Lantern 19	41-4	0/0	out
148	UHL 20	Up Hall Lantern 20	42-4	0/0	out
149	UHL 21	Up Hall Lantern 21	43-4	0/0	out
150	UHL 22	Up Hall Lantern 22	44-4	0/0	out
151	UHL 23	Up Hall Lantern 23	00-0	0/0	out
160	DHL 0	Down Hall Lantern 0	00-0	0/0	out
161	DHL 1	Down Hall Lantern 1	22-3	0/0	out
162	DHL 2	Down Hall Lantern 2	24-3	0/0	out
163	DHL 3	Down Hall Lantern 3	25-3	0/0	out
164	DHL 4	Down Hall Lantern 4	26-3	0/0	out
165	DHL 5	Down Hall Lantern 5	27-3	0/0	out
166	DHL 6	Down Hall Lantern 6	28-3	0/0	out
167	DHL 7	Down Hall Lantern 7	29-3	0/0	out
168	DHL 8	Down Hall Lantern 8	30-3	0/0	out
169	DHL 9	Down Hall Lantern 9	31-3	0/0	out
170	DHL 10	Down Hall Lantern 10	32-3	0/0	out
171	DHL 11	Down Hall Lantern 11	33-3	0/0	out
172	DHL 12	Down Hall Lantern 12	34-3	0/0	out
173	DHL 13	Down Hall Lantern 13	35-3	0/0	out
174	DHL 14	Down Hall Lantern 14	36-3	0/0	out
175	DHL 15	Down Hall Lantern 15	37-3	0/0	out
176	DHL 16	Down Hall Lantern 16	38-3	0/0	out
177	DHL 17	Down Hall Lantern 17	39-3	0/0	out
178	DHL 18	Down Hall Lantern 18	40-3	0/0	out
179	DHL 19	Down Hall Lantern 19	41-3	0/0	out
180	DHL 20	Down Hall Lantern 20	42-3	0/0	out
181	DHL 21	Down Hall Lantern 21	43-3	0/0	out
182	DHL 22	Down Hall Lantern 22	44-3	0/0	out
183	DHL 23	Down Hall Lantern 23	45-3	0/0	out
192	EHC / ETTL 0 - 24	Emerg. Hosp. Call 0 - 24	00-0	0/0	i/o
224	FPD 0 - 24	Fire Proof Door 0 - 24	01-0	1/0	in
256	CPC 0 - 24	Car Position Contact 0 - 24	00-0	0/0	out
288	RCB / RCTTL 0-24	Rear Car Button / Tell Tale Light 0-24	00-0	0/0	i/o
320	RUHB / RUTTL 0-24	Rear Up Hall Button / Tell Tale Light 0-24	00-0	0/0	i/o
352	RDHB / RDTTL 0-24	Rear Down Hall Button / Tell Tale Light 0-24	00-0	0/0	out
384	RUHL 0-24	Rear Up Hall Lantern 0-24	00-0	0/0	i/o
448	REHC / RETTL 0-24	Rear Emerg. Hosp. Call / Tell Tale Light 0-24	01-0	1/0	in
480	CRS 0-24	Card Reader Security (Car) 0-24	00-0	0/0	in
512	SEC 0-24	Card Reader Security (Hall) 0-24	01-0	1/0	in
544	RDOL	Rear Door Open Limit	00-0	0/0	in
545	RDOB	Rear Door Open Button	00-0	0/0	in
546	REDP	Rear Electronic Door Protection			

OTIS INDIA B.W		I - O LIST LCB-II WITH YASKAA L7 DRIVE CONTROLLER UP TO 24 STOPS. FOR MODELS ONLY	Rev0. Date : 16-02-2007 Rev1. Date : 05-01-2008		
I/O No	SYMBOL	DESCRIPTION	ACTUAL	DEF	TYPE
547	RDCB	Rear Door Close Button	00-0	0/0	in
548	ATK	Attendant Key Switch	11-3	0/0	in
549	HUDL (UDL)	Hall Up Direction Light	56-3	0/0	out
550	HDDL (DDL)	Hall Down Direction Light	56-4	0/0	out
551	GCB	Up General Control Button	00-0	0/0	in
552	DDP	Car Motion Control Signal	00-0	0/0	out
553	PKL	Parking Light	56-1	0/0	out
554	DCP	Delayed Car Signal	00-0	0/0	out
555	DTP	Door Time Protection	00-0	0/0	out
556	EPR	Emergency Power Rescue	00-0	0/0	out
557	OOS1B	Out of Service Break1	00-0	0/0	out
558	OOS1M	Out of Service Make1	00-0	0/0	out
559	OOS2B	Out of Service Break 2	00-0	0/0	out
560	OOS2M	Out of Service Make 2	00-0	0/0	out
561	ROLS	Rear Over Load Signal	00-0	0/0	out
562	RHEL	Rear Hospital Emergency Light	00-0	0/0	out
563	RFSL	Rear Fireman Service Light	00-0	0/0	out
564	RCUDL	Rear Car Up Direction Lantern	00-0	0/0	out
565	RCDDL	Rear Car Down Direction Lantern	00-0	0/0	out
566	RHUDL	Rear Hall Up Direction Lantern	00-0	0/0	out
567	RHDDL	Rear Hall Down Direction Lantern	00-0	0/0	out
568	RIOTS	Riot Operation Switch	00-0	0/0	in
569	SR1	Gamma160 s Speed1	00-0	0/0	out
570	SR2	Gamma160 s Speed 2	00-0	0/0	out
571	SR3	Gamma160 s Speed 3	00-0	0/0	out
572	RSTH	Rear Stop Signal Hall	00-0	0/0	out
573	RSTC	Rear Stop Signal Car	00-0	0/0	out
574	MDD	Passenger Move Detector	00-0	0/0	in
575	RMDD	Rear Passenger Move Detector	00-0	0/0	in
576	UP	Car Direction Memory Up	00-0	0/0	out
577	DN	Car Direction Memory Down	00-0	0/0	out
578	CDLU	Car Direction Lantern Up	00-0	0/0	out
579	CDLD	Car Direction Lantern Down	00-0	0/0	out
580	CDGU (GNCUP)	Car Direction Gong Up	12-4	0/0	out
581	CDGD (GNCDN)	Car Direction Gong Down	13-4	0/0	out
582	RCDLU	Rear Car Direction Lantern Up	00-0	0/0	out
583	RCDLD	Rear Car Direction Lantern Down	00-0	0/0	out
584	RCDGU	Rear Car Direction Gong Up	00-0	0/0	out
585	RCDGD	Rear Car Direction Gong Down	00-0	0/0	out
586	ASL	Alternate Service Landing	00-0	0/0	in
587	FLT	Drive Fault Contact	00-0	0/0	in
588	MTC	Motor Temperature Contact	01-0	1/0	in
589	OVH	Drive Overheat Contact	00-0	0/0	in
590	ATTU	Attendant Up Start Switch	09-4	0/0	in
591	ATTD	Attendant Down Start Switch	10-4	0/0	in
592	FDLU	Further Demand Up Lantern	00-0	0/0	out
593	FOLD	Further Demand Down Lantern	00-0	0/0	out
594	NSB	Non Stop Button	11-4	0/0	in
595	NSL	Non Stop Lantern	00-0	0/0	out
596	INLC	Independent Light Car	00-0	0/0	out
597	INLH	Independent Light Hall	00-0	0/0	out
598	CHCSC	Cut Hall Call Signal Car	00-0	0/0	out
599	CHCSH	Cut Hall Call Signal Hall	00-0	0/0	out
600	PFL	Power Fail Light	00-0	0/0	out
601	EPW	Emergency Power Wait	00-0	0/0	out
602	INS	Car Inspection Signal	00-0	0/0	out

I/O No	SYMBOL	DESCRIPTION	ACTUAL	DEF	TYPE
603	FSR	Fireman Service Relay	00-0	0/0	out
604	EHS	Emergency Hospital Service	00-0	0/0	out
605	DOS ✓	Door Open Signal	13-4	0/0	in
606	RDOS / RSGS	Rear Door Open Signal / Rear SGS	00-0	0/0	in
607	LRD/SGS	Light Ray Device	14-4	0/0	in
608	RLRD	Rear Light Ray Device	01-0	0/0	in
609	XEPR	Not able to rescue	00-0	0/0	out
610	CCOC	Cut Car Calls for car link	01-0	1/0	in
611	CCOH	Cut Car Calls for hall link	01-0	1/0	in
612	HCCO	Hall Call Cut Off	01-0	1/0	in
613	GCCO	Group Call Cut Off	01-0	1/0	in
614	CTLC	Car to Landing / Car	00-0	0/0	out
615	CTLH	Car to Landing / Hall	00-0	0/0	out
616	ACSC	Anti Crime Switch Car	00-0	0/0	in
617	ACSH	Anti Crime Switch Hall	00-0	0/0	in
618	CHCC	Cut Hall Call Car	00-0	0/0	in
619	DFD	Disable Front Doors	00-0	0/0	in
620	DHB ✓	Door Hold Button	15-4	0/0	in
621	DRD	Disable Rear Doors	00-0	0/0	in
622	EFKB	Emergency Fireman Key Bypass	00-0	0/0	in
623	EQS	Earth Quake Switch	00-0	0/0	in
624	EFO	Emergency Fireman Operation	01-0	1/0	in
625	ESH	Emergency Service Hold	01-0	0/0	in
626	ESK	Emergency Service Keyswitch	00-0	0/0	in
627	RB	Reset Button	00-0	0/0	in
628	RDHB	Rear Door Hold Button	00-0	0/0	in
629	AMCLK	AM Clock Input	00-0	0/0	in
630	LPT	Landing passing Tone	07-4	0/0	out
631	WCOS	Wild Car Operation Switch	00-0	0/0	in
632	1MOTIM	One more time signal	00-0	0/0	in
633	ESSR	Emergency Stop Switch Reset	00-0	0/0	out
634	CRV	Cancel Relevelling	00-0	0/0	out
635	ZR	Front door Zone Relay	00-0	0/0	out
636	RZR	Rear ZR	00-0	0/0	out
637	RNDG	Rear Nudging Relay	00-0	0/0	in
638	ISPS	Independent Service Parking Switch	00-0	0/0	in
639	CRC	Card Reader Contact	00-0	0/0	in
640	SDB	Special Door Open Button	00-0	0/0	in
641	RSDB	Rear SDB	00-0	0/0	in
642	GRIOT	Group RIOT	00-0	0/0	out
643	FPDL	Fire Proof Door Light	00-0	0/0	out
644	AEPS	Available for EPS L.	00-0	0/0	in
645	EQCW	Earthquake Counterweight Switch	00-0	0/0	in
646	EQRS	Earthquake Reset Signal	00-0	0/0	out
647	SSM1	Speech Synth. Cmd 1	00-0	0/0	out
648	SSM2	Speech Synth. Cmd 2	00-0	0/0	out
649	SSM3	Speech Synth. Cmd 3	00-0	0/0	out
650	SSM4	Speech Synth. Cmd 4	00-0	0/0	out
651	SSM5	Speech Synth. Cmd 5	00-0	0/0	out
652	SSM6	Speech Synth. Cmd 6	00-0	0/0	out
653	SSM7	Speech Synth. Cmd 7	00-0	0/0	in
654	SSMB	Speech Synth. Busy	00-0	0/0	out
655	SSMR	Speech Synth. Reset	00-0	0/0	out
656	SSMS	Speech Synth. Start	07-3	0/0	in
657	LPTB	Landg. pass. Tone B.	00-0	0/0	in
658	CTLPC	CTL park close door			

OTIS INDIA B.W		I - O LIST LCB-II WITH YASKAA L7 DRIVE CONTROLLER UP TO 24 STOPS. FOR MODELS ONLY	Rev0. Date : 16-02-2007 Rev1. Date : 05-01-2008		
I/O No	SYMBOL	DESCRIPTION	ACTUAL	DEF	TYPE
			00-0	0/0	in
659	CTLPO	CTL park open door	00-0	0/0	out
660	ULV	Gamma L speed dict.	00-0	0/0	in
661	RDZ	Rear Door Zone	00-0	0/0	in
662	CFSON	Car Fire. Serv. On	00-0	0/0	in
663	CFSST	Car Fire. Serv. Start	00-0	0/0	out
664	LHL	Not used in this version	00-0	0/0	in
665	BOS	Boss Cardreader override	00-0	0/0	in
666	SHAC	Shabat Operation Switch	00-0	0/0	in
667	SHAT	Shabat Operation Timer	00-0	0/0	out
668	SHLC	Shabat Operation Light Car	00-0	0/0	out
669	NDGL	Nudging Light	00-0	0/0	out
670	SSMRL	Speech Synthesizer Audio relay	00-0	0/0	out
671	CBT	Car Button Tone	00-0	0/0	out
672	HCLR	Handicap Call Light relay	00-0	0/0	out
673	BUT	Button Signal for REM	57.4	0/0	out
674	DO	Door Opening for REM	00-0	0/0	out
675	CPR	Car Park Recog. REM	00-0	0/0	out
676	NORM	Normal Operation for REM	00-0	0/0	out
677	LDO	Limited Door Open.	00-0	0/0	out
678	RLDO	Rear LDO	00-0	0/0	in
679	8LS2	Limit Switch 8LS2 for Hydro	00-0	0/0	in
680	LDT_5	50 % of full load	00-0	0/0	in
681	C2_1IN	C2: bolt1 position in	00-0	0/0	in
682	C2_2IN	C2: bolt 2 position in	00-0	0/0	in
683	C2_1OUT	C2: bolt1 position out	00-0	0/0	in
684	C2_2OUT	C2: bolt 2 position out	00-0	0/0	out
685	C2_DO_1IN	C2: move bolt1 in	00-0	0/0	out
686	C2_DO_2IN	C2: move bolt 2 in	00-0	0/0	out
687	C2_DO_1OUT	C2: move bolt1 out	00-0	0/0	out
688	C2_DO_2OUT	C2: move bolt 2 out	00-0	0/0	out
689	UP_IN	Up Inspection Button	00-0	0/0	in
690	DN_IN	Down Inspection Button	00-0	0/0	in
691	TCI	Top of car Inspection Switch	10-3	0/0	in
692	1LS	Limit switch 1LS	00-0	0/0	in
693	2LS	Limit switch 2LS	00-0	0/0	in
694	DCL	Door Close Limit Switch	01-0	0/0	in
695	RDCL	Rear Door Close Limit Switch	00-0	0/0	in
696	DO_BEL	Door Open Bell Sig.	00-0	0/0	out
697	MCLS	Machine Room Car Light Switch (SKL-3)	01-0	1/0	in
698	IPU	Impuls UP	00-0	0/0	in
699	IPD	Impuls Down	00-0	0/0	in
700	SLU	Short Landing Up	00-0	0/0	in
701	SLD	Short Landing Down	00-0	0/0	in
702	OFF	input Off	00-0	0/0	in
703	ON	input On	01-0	1/0	in
704	C-CHK	C-Circuit check Sig.	00-0	0/0	in
705	TDOB	Top of car Door Open Button	00-0	0/0	in
706	TDCB	Top of car Door Close Button	00-0	0/0	in
707	RTDOB	Rear Top of car DOB	00-0	0/0	in
708	RTDCB	Rear Top of car DCB	00-0	0/0	in
709	EML	Evacuation Message Light	09-3	0/0	out
710	REML	Rear Evacuation Message Light	00-0	0/0	out
711	MF	Master Floor for REM	00-0	0/0	out
712	LND	Landing for REM	00-0	0/0	out
713	OOS	Out Of Service for REM	00-0	0/0	out
714	RISS	Rear Independent Service Switch	00-0	0/0	in

OTIS INDIA B.W		I - O LIST LCB-II WITH YASKAA L7 DRIVE CONTROLLER UP TO 24 STOPS. FOR MODELS ONLY	Prep By:Madhu Rev0. Date : 16-02-2007 Rev1. Date : 05-01-2008		
I/O No	SYMBOL	DESCRIPTION	ACTUAL	DEF	TYPE
715	RGCB	Rear GCB	00-0	0/0	in
716	EFL	Emergency Fireman Light	09-3	0/0	out
717	GOOL	Group Out of Service Light	00-0	0/0	out
718	DHDI	Down Hall Direction Indicator	00-0	0/0	out
719	UHDl	Up Hall Direction Indicator	00-0	0/0	out
720	FR	Fireman Operation Relay	00-0	0/0	out
721	LNS-M	LNS in machine room	00-0	0/0	in
722	LWO-M	LWO in machine room	00-0	0/0	in
723	FCDGU	Front Car Direction Gong Up	00-0	0/0	out
724	FCDGD	Front Car Direction Gong Down	00-0	0/0	out
725	RRB	Rear Reset Button	00-0	0/0	in
726	XDSR	Delayed Start Relay for LSCH-2	00-0	0/0	out
727	AT20LRD	Light Ray Device for AT20	00-0	0/0	out
728	AT20RLRD	Rear Light Ray Device for AT20	00-0	0/0	out
729	ITLH	Incoming Traffic Light Hall	00-0	0/0	out
730	OTLH	Outgoing Traffic Light Hall	00-0	0/0	out
731	ITLC	Incoming Traffic Light Car	00-0	0/0	out
732	OTLC	Outgoing Traffic Light Car	00-0	0/0	out
733	DPC	Down Peak Clock	00-0	0/0	in
734	UPC	Up Peak Clock	00-0	0/0	in
735	DUPC	Dual Up Peak Clock	00-0	0/0	in
736	DUPL	Dual Up Peak Light	00-0	0/0	out
737	OOL	Out Of Order Light	00-0	0/0	out
738	EQL	Earthquake Light	00-0	0/0	out
739	ERL	Express Running Light	00-0	0/0	out
740	FDL	Further Demand Light	00-0	0/0	out
741	NSLH	Non Stop Light Hall	00-0	0/0	out
742	ARL	Auto Running Light	00-0	0/0	out
743	IL	In Use Light (for SAPB)	00-0	0/0	out
744	SROS	Seperate Riser Operation Switch	00-0	0/0	in
745	ISTS	Intermittent Sop Switch	01-0	1/0	in
746	HCOC	Hall Call Cutoff from Car	00-0	0/0	out
747	DHBL	Door Hold Button Light	00-0	0/0	out
748	RDHBL	Rear Door Hold Button Light	00-0	0/0	out
749	CHMI	Chime Board Initiate	00-0	0/0	out
750	CHMU	Chime Board Up Direction	00-0	0/0	out
751	SHBUZ	Shabbat Operation Door Buzzer	00-0	0/0	out
752	SHLH	Shabbat Operation Light Hall	00-0	0/0	in
753	PCLK 1	Park Car Clock 1	00-0	0/0	in
754	PCLK 2	Park Car Clock 2	00-0	0/0	in
755	PCLK 3	Park Car Clock 3	00-0	0/0	in
756	PCLK 4	Park Car Clock 4	00-0	0/0	in
757	PCLK 5	Park Car Clock 5	00-0	0/0	in
758	PCLK 6	Park Car Clock 6	00-0	0/0	in
759	PCLK 7	Park Car Clock 7	00-0	0/0	in
760	PCLK 8	Park Car Clock 8	00-0	0/0	in
761	CSA1	Car Secure Access Button 1	SET	0/0	in
762	CSA2	Car Secure Access Button 2	BUTTON	0/0	in
763	CSA3	Car Secure Access Button 3	ADDRES	0/0	in
764	CSA4	Car Secure Access Button 4	S TO BE	0/0	in
765	CSA5	Car Secure Access Button 5	CODED	0/0	in
766	CSA6	Car Secure Access Button 6	07-2	0/0	in
767	CSAC	Car Secure Access Clear Switch	07-1	0/0	in
768	CSAK	Car Secure Access Keyswitch	00-0	0/0	out
769	CSAL	Car Secure Access Light	00-0	0/0	in
		Group Secure Access Keyswitch			

OTIS INDIA B.W		I - O LIST LCB-II WITH YASKAA L7 DRIVE CONTROLLER UP TO 24 STOPS. FOR MODELS ONLY	Prep By: Madhu Rev0. Date : 16-02-2007 Rev1. Date : 05-01-2008		
I/O No	SYMBOL	DESCRIPTION	ACTUAL	DEF	TYPE
771	GSAL	Group Secure Access Light	00-0	0/0	out
772	AEFO	Alternative EFO	01-0	1/0	in
773	ASLDOB	Alternative Service Landing DOB	00-0	0/0	in
774	EFODOB	Emergency Fireman Operation DOB	00-0	0/0	in
775	XEFO	Override EFO	01-0	1/0	in
776	APC 0	Absolute Position Contact 0	00-0	0/0	in
777	APC 1	Absolute Position Contact 1	00-0	0/0	in
778	APC 2	Absolute Position Contact 2	00-0	0/0	in
779	APC 3	Absolute Position Contact 3	00-0	0/0	in
780	APC 4	Absolute Position Contact 4	00-0	0/0	in
781	APC 5	Absolute Position Contact 5	00-0	0/0	in
782	APC 6	Absolute Position Contact 6	00-0	0/0	in
783	TCIB	Top Of Car Inspection Button	15-3	1/0	in
784	PDS	Partition Door Switch	01-0	1/0	in
785	CMR	CAM Relay	00-0	0/0	out
786	DCDS	Disable-Call-And-Door-Switch	00-0	0/0	in
787	DCM	Door Closing Management	00-0	0/0	out
788	RDCM	Rear Door Closing Management	00-0	0/0	out
789	STOP	Stop Signal	00-0	0/0	out
790	OLDL	Overload Light	00-0	0/0	out
791	NDG_M	Nudging Signal in Machine Room	00-0	0/0	out
792	RNDG_M	Rear Nudging Signal in Machine Room	00-0	0/0	out
793	LEV	Level Signal for REM	00-0	0/0	in
794	-	-	00-0	0/0	-
795	PI7S-RA	CPI-3 / HPI-3	00-0	0/0	out
796	PI7S-RB	CPI-3 / HPI-3	00-0	0/0	out
797	PI7S-RC	CPI-3 / HPI-3	00-0	0/0	out
798	PI7S-RD	CPI-3 / HPI-3	00-0	0/0	out
799	PI7S-RE	CPI-3 / HPI-3	00-0	0/0	out
800	PI7S-RF	CPI-3 / HPI-3	00-0	0/0	out
801	PI7S-RG	CPI-3 / HPI-3	00-0	0/0	out
802	PI7S-LB	CPI-3 / HPI-3	00-0	0/0	out
803	PI7S-LC	CPI-3 / HPI-3	00-0	0/0	out
804	PI7S-LG	CPI-3 / HPI-3	00-0	0/0	out
805	UD	DOC-X: Up/Down	00-0	0/0	out
806	REV	DOC-X: Reversal	00-0	0/0	out
807	TI	Trouble Indicator for french SSM	00-0	0/0	out
808	RREV	DOC-X: Rear Reversal	00-0	0/0	out
809	LWDE	Load Weighing Device Electronical	00-0	0/0	out
810	DESB	Disable ESB Relay (Generic Firemen Service)	00-0	0/0	out
811	DDSR1	Disable DS Relay (Generic Firemen Service)	00-0	0/0	out
812	DEECR	Disable EEC Relay (Generic Firemen Service)	00-0	0/0	out
813	DSGSR	Disable SGS Relay (Generic Firemen Service)	00-0	0/0	out
814	UHDL 0-24	Up Hall Direction Lantern 0-24	00-0	0/0	out
846	DHDL 0-24	Down Hall Direction Lantern 0-24	00-0	0/0	out
878	OOL 0-24	Out Of Order Light 0-24	00-0	0/0	out
910	DOC 0-24	Door Open Contact 0 -24	00-0	0/0	in
942	BCP1	Binary Coded Position	00-0	0/0	out
943	BCP2	Binary Coded Position	00-0	0/0	out
944	BCP4	Binary Coded Position	00-0	0/0	out
945	BCP8	Binary Coded Position	00-0	0/0	out
946	BCP16	Binary Coded Position	00-0	0/0	out
947	CPMT	Car Position Message Trigger	00-0	0/0	out
948	DCMT	Door Close Message Trigger	00-0	0/0	out
949	DOMT	Door Open Message Trigger	00-0	0/0	out
950	EMMT	Emergency Message Trigger	00-0	0/0	out

OTIS INDIA B.W		I - O LIST LCB-II WITH YASKAA L7 DRIVE CONTROLLER UP TO 24 STOPS. FOR MODELS ONLY	Prep By: Madhu Rev0. Date : 16-02-2007 Rev1. Date : 05-01-2008		
I/O No	SYMBOL	DESCRIPTION	ACTUAL	DEF	TYPE
951	OLMT	Overload Message Trigger	00-0	0/0	out
952	DDMT	Down Direction Message Trigger	00-0	0/0	out
953	UDMT	Up Direction Message Trigger	00-0	0/0	out
954	DNMT	Door Nudging Message Trigger	00-0	0/0	out
955	1EFS	1st Emergency Fire Service Car	00-0	0/0	in
956	2EFS	2nd Emergency Fire Service Car	00-0	0/0	in
957	EFOL	Emergency Fire Operation Light	00-0	0/0	out
958	CRFL	Car Returning to Floor Light	00-0	0/0	out
959	EFLM	Emergency Fire Light Machine Room	00-0	0/0	out
960	EFLTC	Emergency Fire Light Top of Car	00-0	0/0	out
961	CSABUZ	Buzzer for Car Secure Access	00-0	0/0	out
962	AT20NDG	Nudging for AT20	00-0	0/0	out
963	AT20RNDG	Rear Nudging for AT20	00-0	0/0	out
964	LRTS (OKR)	Light Ray Test Start	00-0	0/0	out
965	LRCR	Light Ray Check Relay	00-0	0/0	in
966	RLRCR	Rear Light Ray Check Relay	00-0	0/0	in
967	LBG	Light Beam Gate	00-0	0/0	in
968	RLBG	Rear Light Beam Gate	00-0	0/0	in
969	ESBUZ	Emergency Stop Buzzer	00-0	0/0	out
970	DDSRC	Disable DS relay contact (Korean Fire Service)	00-0	0/0	in
971	DEMERC	Disable Emergency relay contact (Korea)	00-0	0/0	in
972	GSSI	Group Successive Starting In	00-0	0/0	in
973	GSSO	Group Successive Starting Out	00-0	0/0	out
974	DDSR2	Disable DS relay 2 (Korea)	00-0	0/0	out
975	DMOOS	Dot Matrix OOS (PI=5,6)	00-0	0/0	in
976	DMOLD	Dot Matrix OLD (PI=5,6)	00-0	0/0	in
977	GPIN1	General Purpose input 1.REV3. NEWLY ADDED	00-0	0/0	in
978	GPOUT1	General Purpose output 1.REV3. NEWLY ADDED	00-0	0/0	out
979	GPIN2	General Purpose input 2	00-0	0/0	in
980	GPOUT2	General Purpose output 2	00-0	0/0	out
981	GPIN3	General Purpose input 3	00-0	0/0	in
982	GPOUT3	General Purpose output 3	00-0	0/0	out
983	GPIN4	General Purpose input 4	00-0	0/0	in
984	GPOUT4	General Purpose output 4	00-0	0/0	out
985	GPIN5	General Purpose input 5	00-0	0/0	in
986	GPOUT5	General Purpose output 5	00-0	0/0	out
987	1LV	1LV for CSP-5	00-0	0/0	out
988	2LV	2LV for CSP-5	00-0	0/0	out
989	TARGET	enable DZ for CSP-5	00-0	0/0	out
990	LBGCHK	Light Beam Gate Check for CSP-5	00-0	0/0	out
991	DOOR_ST1	ST1 for front DO1000 (DCSS5)	09-4	0/0	out
992	DOOR_ST2	ST2 for front DO1000 (DCSS5)	10-4	0/0	out
993	DOOR_ST3	ST3 for front+rear DO1000 (DCSS5)	11-4	0/0	out
994	DOOR_ST1R	ST1 for rear DO1000 (DCSS5)	00-0	0/0	out
995	DOOR_ST2R	ST2 for rear DO1000 (DCSS5)	00-0	0/0	out
996	DOOR_ST3R	ST3 for rear DO1000 (DCSS5)	00-0	0/0	out
997	DDM	Deenergize Door Motor	00-0	0/0	out
998	RDDM	Deenergize Rear Door Motor	00-0	0/0	out
999	EFSL	Emergency Fire Service Light	09-3	0/0	out
1024	LNSL	Full light	56-2	0/0	out
1053	ATB	Attendant Buzzer.	14-4	0/0	out