MIC1/MCI2 (XLR 3-pin, Male)



– EXT VIEW –

(0 dBu = 0.775 Vrms)

No.	Signal	Specifications
1	MIC OUT (G)	0 dBu/–20 dBu
2	MIC OUT (X)	(Selectable with S502,
3	MIC OUT (Y)	S503/AVP-4)

MIC REMOTE (D-sub 15-pin, Female)
(**WF REMOTE** (D-sub 15-pin, Female))



– EXT VIEW –

In the case of MIC REMOTE mode : S423-3/AT-149 → OFF

No.	Signal		Specifications
1	+5.5 V OUT		Max. 250 mA
2	TALLY GND		GND for TALLY
3	G TALLY OUT		ON (GND) : Max. 30 mA IN
4	R TALLY OUT		ON (GND) : Max. 30 mA IN
5	CHU MIC AMP GAIN IN	CONT2	∗1 Refer to the right column.
6		CONT1	
7		CONT0	
8	MIC1 GAIN CONT ON/OFF IN		∗2 Refer to the right column.
9	GND		GND for +5.5 V
10	TALLY OUT		R/G TALLY OUT ON (GND) : Max. 30 mA IN
11	NC		No connection
12	ASPECT REMOTE ON/OFF		L : REMOTE
13	ASPECT CTL	CONT1	∗3 Refer to the right column.
14		CONT2	
15	MIC2 GAIN CONT ON/OFF IN		∗2 Refer to the right column.

∗1 : CHU MIC 1/2 AMP GAIN

CONT0	CONT1	CONT2	CHU MIC AMP GAIN
H	H	H	60 dB
L	H	H	50 dB
H	L (H)	H (L)	40 dB
L	L (H)	H (L)	30 dB
H	H (L)	L (H)	20 dB

The setup for HDCU-700A mode is shown in parenthesis ( ).
In the case of HDCU-700A mode : S423-2/AT-149 → ON

∗2 :

8pin	15pin	MIC GAIN CONT
L	L	MIC 1 and 2 ON
L	H	MIC 1 ON
H	L	MIC 2 ON
H	H	INTERNAL set

∗3 :

CONT1	CONT2	ASPECT
L	H	SQ (16 : 9)
H	H	EC (4 : 3)
L	L	INTERNAL set
H	L	LB (4 : 3)

In the case of WF REMOTE mode : S423-3/AT-149→ ON
Recall system

No.	Signal	Specifications
1	NC	No connection
2	NC	No connection
3	NC	No connection
4	NC	No connection
5	RECALL2 (G)	LOW ACTIVE
6	RECALL3 (B)	
7	RECALL1 (R)	
8	RECALL4 (SEQ)	
9	GND	
10	NC	No connection
11	NC	No connection
12	RECALL5 (ENC)	LOW ACTIVE
13	RECALL6 (R+B)	
14	RECALL7 (R+G)	
15	RECALL8 (G+B)	