




Template for Create/Modify Data Group



Operations Guide

Version	Remarks	Date
1.0	Provisioning Template Operation Guide for Create/Modify DataGroup	28/07/2016

1. Create/Modify Data Group




1. Login to AppViewX.
2. On the left navigation menu, select **Provisioning**; and click **Request**
3. On the upper right portion of the screen, click the  **Create** button.
4. Select the provisioning template name from the list – ‘**Generic_Create_Modify_DataGroup**’
Note: *If no template is available, this indicates that the user role does not have permission to the requesting template.*
5. Enter the provisioning request description – ‘*Create or Modify Data Group on F5 device*’.
6. Add a default Request scenario name relevant to the template. **E.g.:** VIP creation on F5/Citrix ADC.
7. Click on ‘**Fetch Device List**’ button to populate the list of available F5 devices from the inventory.
8. Select the F5 device from the available list of device in the **Select Device** field.
9. Choose the operation to be performed on the selected F5 device in the **Data Group** field. ‘*Create new*’ and ‘*Modify*’ are the available operations.

If **Create New** is selected, then

- i. Please input the name of the DataGroup to be created in the **Enter the Data Group Name** field.
- ii. The DataGroup type can be selected from the **Select Type** field. The available DataGroup types would be *Integer, Address* and *String*.
- iii. The appropriate *Key (String, Address or Integer)* and corresponding *Value* are entered in the next 2 fields.
- iv. The Data Group entry can be added into the tabular for creation of Data Group on the selected device by clicking on the .
- v. Click  Button; ensure that the Scenario is displayed on the right hand pane.
- vi. Click on **Submit** to generate work order(s) for the provisioning request.

If **Modify** is selected, then

- i. Click on ‘**Fetch Data Group**’ button to fetch the list of available Data Groups on the selected device.

- ii. In the **Select Data Group** field, list of data groups are populated based on the *device* selected. Please select the data group to be modified.
- iii. The **Get Data Group Type** button can be used to check the type of the selected data group.
- iv. If data group members are to be deleted, click *Yes* in the **Do you want to delete members in Data Group** field.
- v. The **Get Member List** button fetched the list of members in the selected data group.
- vi. Please select the member to be deleted from the dropdown list and add appropriate *Comments* in the **Comments** field.
- vii. *Member* to be deleted can be added to the tabular by clicking on the .
- viii. If data group members are to be added, click *Yes* in the **Do you want to add members in Data Group** field.
- ix. Please enter the *Data Group member name* and the appropriate *value*.
- x. *Member* to be added can be appended to the tabular by clicking on the .
- vii. Click  Button; ensure that the Scenario is displayed on the right hand pane.
- viii. Click on *Submit* to generate work order(s) for the provisioning request.