

SIGNED	DATE	DESCRIPTION	REV.
PANEL A	11/05/21	See ECO-30221	00.1
Assembly	13/02/23	See ECO-31158, Add GB-34-016	00.8
U01_C	16/09/24	Change front screws to B-1-F-5 ECO C31564	00.9

14.12.15.90.07 MODULE ASSEMBLY

FOR PANEL P/N SEE TABLE 1.

TABLE 1.

Front Panel Options Table		
Option description	Panel p/n	GB p/n
ETX-2i-10GbE/24SFP/1PPS	41.14.12.13.09	-
ETX-2i-10GbE/24UTP/1PPS	41.14.12.13.02	-
ETX-2i-10GbE/12COMBO/1PPS	41.14.12.13.10	-
ETX-2i-10GbE/12SFP-12UTP/1PPS	41.14.12.13.11	-
ETX-2i-10GbE/24SFP/GNSS	41.14.12.13.05	-
ETX-2i-10GbE/24UTP/GNSS	41.14.12.13.06	-
ETX-2i-10GbE/12COMBO/GNSS	41.14.12.13.07	-
ETX-2i-10GbE/12SFP-12UTP/GNSS	41.14.12.13.08	-
ETX-2i-10GbE/24SFP	-	GB-34-016

Notes:

- Items with item number blocked by rectangle – assembled according to job requirement
- Secure pan head screws without lock washers with Thread Locking Adhesive according to RAD standard
- When no location marks exists, Attach the rubber button bumpers close to the 4 corners at a distance of 30mm from the both edges

INSTALLATION KIT		
19"	RM-34	
23"	RM-34-23	
ETSI	RM-34-ETSI	

ITEM	QTY	PART NUMBER	DESCRIPTION
1	1	GB-33-005	ASSY MECH TYPE-3 BOX ETSI COVER WITH FAN
2	1	14.12.13.04	MECH PCB MECHANICAL LAYOUT
4	1	00.02.04.06.02	COVER-ASSEMBLY
5	1	68.67.10.43	MECH LOGO RAD (NEW LOOK)
6	20	B-1-F	MECH BOLT FLAT-H 100.PH.440UNC"3.96.ST.ZINC.HD5.1
7	2	B-12-C	MECH BOLT FLAT-H100.PH.440UNC"7.94.ST.ZINC.HD5.5
8	1	D-3	MECH DISC SERRATED 3.9"X1.2.55.PASS
9	1	BY18M37P	MECH. HARDWARE CABLE SHOE-6-32UNC
10	1	B-1-7	MECH BOLT PAN-H+DISC.PH.632UNC"6.35.ST.ZINC.HD6.68
11	8	B-P-25	MECH BOLT FLAT-H 100.PH.SELF-T"10.ST.ZINC.HD5.1
12	3	B-1-5	MECH BOLT PAN-H+DISC.PH.440UNC"6.35.ST.ZINC.HD5.38
13	1	12.07.21.90.07	MECH MODULE ASSEMBLY
14	1	63.12.07.21.01	MECH ISOLATOR
15	4	SJ-5012/3M	MECH. HARDWARE. STAND. RUBBER BUTTON BUMPERS
16	1	14.12.15.90.02	MECH MODULE ASSEMBLY
17	1	14.12.15.90.03	MECH MODULE ASSEMBLY
18	1	14.12.15.90.04	MECH MODULE ASSEMBLY
19	1	14.12.15.90.06	MECH MODULE ASSEMBLY
20	2	SB-600G(50x19x2.5)	MECH.HARDWARE.THERM. PAD. COND.3.15 W/MK. 50x19x2.5 MM
21	1	12.07.21.90.08	MECH MODULE ASSEMBLY
22	1	14.12.15.90.07	MECH MODULE ASSEMBLY
23	1	TP600-120X70X4-DWG	MECH.HARDWARE.THERM. PAD. COND.6.0 W/MK. 120X70X4 MM
24	1	THA0412ADAHL	MECH.FAN,12VDC.PWM.(40X40X20), 20.56 CFM
25	1	80.14.12.15	MECH JIG
26	1	THA0412ADFSY-REV00	MECH.FAN,12VDC.PWM.(40X40X20), 20.56 CFM, WIRES 470MM
27	4	B-1-F-S	MECHBOLTFLAT-H 100PH440UNC"3.175STSTHD5.1



UNLESS OTHERWISE SPECIFIED,
DIMENSIONS ARE IN MILLIMETERS.
ALL DIMENSIONS SHOWN TO 0.01 MM.
COLOR AND SERIAL SHARP EDGES (0.1-0.3)
SURFACE FINISH (0.1-0.3)



NAME: DATE: DRAWING CONTAINS THE DRAWING OF THE
PROPERTY OF RAD. ANY REPRODUCTION OF THIS DRAWING
WITHOUT THE WRITTEN PERMISSION OF RAD IS PROHIBITED.

data communications			ETX-2i-10GbE	
MATERIAL:			MECH ASSEMBLY	
FINISH:			CAT. NO.	
PAINT:			DWG. NO.	
PRINT:			14.12.15	
NOTE-1:			REV. 00.9	
NOTE-2:			SCALE: 1:1 (DO NOT SCALE DRAWING)	

A
B
C
D
E
F
G
H
J
K
L
M

EH

THERMAL PAD ASSEMBLY VIEW

USE JIG FOR THERMAL PAD PLACEMENT.

ATTACH THERMAL PAD P/N
TP600-120X70X4-DWG TO THE
TOP SIDE OF THE CHASSIS
BOTTOM AREA.

