13

```
mov al,05h
not al
mov [2000h],al
inc al
mov [2001h],al
hlt
```

14

```
; MEMORY LOAD
mov si,2000h
mov al,01h
mov cx,0Ah
load:
mov [si],al
inc si
inc al
dec cx
jnz load
; REVERSE OPERATION
mov si,2000h
mov di,2009h
mov cx,05h
reverse:
mov al,[si]
mov bl,[di]
mov [si],bl
mov [di],al
inc si
dec di
dec cx
jnz reverse
HLT
```

15

```
; MEMORY LOAD
mov si,2000h
mov al,01h
mov cx,0Ah
load:
mov [si],al
inc si
inc al
dec cx
jnz load
; ODD EVEN CHECK
mov si,2000h
mov bl,00h
mov dl,00h
mov cx,0Ah
CHECK:
mov al,[si]
test al,01h
jnz odd
inc dl
jmp next
odd:
inc bl
next:
inc si
loop CHECK
mov [200Ah],dl
mov [200Bh],bl
hlt
```