torch.full#

https://pytorch.org/docs/stable/generated/torch.full.html

Description:

Creates a tensor of size size filled with fill_value. The tensor's dtype is inferred from fill_value. size (int...) – a list, tuple, or torch.Size of integers defining the shape of the output tensor. fill_value (Scalar) – the value to fill the output tensor with. out (Tensor, optional) – the output tensor. dtype (torch.dtype, optional) – the desired data type of returned tensor. Default: if None, uses a global default (see torch.set_default_dtype()).

Function Signature

```
torch.full(size, fill_value, *, out=None, dtype=None,
layout=torch.strided, device=None, requires_grad=False) →
Tensor#

Parameters

Keyword Arguments
```

Parameters

Keyword

out (Tensor, optional) – the output tensor. dtype (torch.dtype, optional) – the desired data type of returned tensor. Default: if None, uses a global default (see torch.set_default_dtype()). layout (torch.layout, optional) – the desired layout of returned Tensor. Default: torch.strided. device (torch.device, optional) – the desired device of returned tensor. Default: if None, uses the current device for the default tensor type (see torch.set_default_device()). device will be the CPU for CPU tensor types and the current CUDA device for CUDA tensor types. requires_grad (bool, optional) – If autograd should record operations on the returned tensor. Default: False.

Code Examples

```
>>> torch.full((2, 3), 3.141592)
tensor([[ 3.1416,  3.1416,  3.1416],
        [ 3.1416,  3.1416,  3.1416]])
```

Detailed Documentation

Documentation

Creates a tensor of size size filled with fill_value. The tensor's dtype is inferred from fill_value.

size (int...) – a list, tuple, or torch.Size of integers defining the shape of the output tensor.

fill_value (Scalar) – the value to fill the output tensor with.

out (Tensor, optional) – the output tensor.

dtype (torch.dtype, optional) – the desired data type of returned tensor. Default: if None, uses a global default (see torch.set_default_dtype()).

layout (torch.layout, optional) – the desired layout of returned Tensor. Default: torch.strided.

device (torch.device, optional) – the desired device of returned tensor. Default: if None, uses the current device for the default tensor type (see torch.set_default_device()). device will be the CPU for CPU tensor types and the current CUDA device for CUDA tensor types.

requires_grad (bool, optional) – If autograd should record operations on the returned tensor. Default: False.