

```
#include <Wire.h>
```

```
#include <Adafruit_GFX.h>
```

```
#include <Adafruit_SSD1306.h>
```

```
#include <DHT.h>
```

```
#include <OneWire.h>
```

```
#include <DallasTemperature.h>
```

```
#define SCREEN_WIDTH 128
```

```
#define SCREEN_HEIGHT 64
```

```
Adafruit_SSD1306 display(SCREEN_WIDTH,  
SCREEN_HEIGHT, &Wire, -1);
```

```
// DHT11
```

```
#define DHTPIN 3
```

```
#define DHTTYPE DHT11
```

```
DHT dht(DHTPIN, DHTTYPE);
```

```
// DS18B20
```

```
#define TEMP_PIN 2
```

```
OneWire oneWire(TEMP_PIN);
```

```
DallasTemperature sensors(&oneWire);
```

```
// GSR
```

```
#define GSR_PIN A1
```

```
// LED & Buzzer
```

```
#define GREEN_LED 8
```

```
#define YELLOW_LED 9
```

```
#define BUZZER 10
```

```
void setup() {
```

```
Serial.begin(9600);
```

```
dht.begin();
```

```
sensors.begin();
```

```
pinMode(GREEN_LED, OUTPUT);
```

```
pinMode(YELLOW_LED, OUTPUT);
```

```
pinMode(BUZZER, OUTPUT);
```

```
if (!display.begin(SSD1306_SWITCHCAPVCC, 0x3C)) {
```

```
    while (1);
```

```
}
```

```
display.clearDisplay();
```

```
display.setTextSize(1);
```

```
display.setTextColor(SSD1306_WHITE);
```



```
int gsr = analogRead(GSR_PIN);
```

```
String status = "Hydrated";
```

```
if (temp > 38 || humidity > 70 || gsr > 700) {
```

```
    status = "Severe";
```

```
    digitalWrite(YELLOW_LED, HIGH);
```

```
    digitalWrite(GREEN_LED, LOW);
```

```
    tone(BUZZER, 1000);
```

```
}
```

```
else if (temp > 35 || humidity > 60 || gsr > 500) {
```

```
status = "Mild";
```

```
digitalWrite(YELLOW_LED, HIGH);
```

```
digitalWrite(GREEN_LED, LOW);
```

```
noTone(BUZZER);
```

```
}
```

```
else {
```

```
status = "Hydrated";
```

```
digitalWrite(GREEN_LED, HIGH);
```

```
digitalWrite(YELLOW_LED, LOW);
```

```
noTone(BUZZER);
```

```
}
```

```
Serial.print("Temp=");
```



```
display.print("GSR : ");
```

```
display.println(gsr);
```

```
display.print("Status:");
```

```
display.println(status);
```

```
display.display();
```

```
delay(1000);
```

```
}
```

