Project planning report

Saved project inputs and selected calculation results

2026-10-25 00:43:59.018907+00:00

Project

Project	Berlin · Beispielprojekt · PV und Speicher
Project reference	c7795bc2c1e14e389622015c809ace45
Input revision	14

This report presents saved project inputs and the original results of the selected calculations. Country-specific requirements, electrical design and installation checks remain open. It does not approve the complete installation.

Site and project inputs

Location	Berlin · Beispielstandort
Country	DE
Time zone	Europe/Berlin
Project note	Interaktives Beispiel mit echten JRC-Wetterdaten und nachgewiesenen Trina-Moduldaten; Dachgeometrie und Verbrauch sind Beispielannahmen.

Equipment checks

Assessment status	Further checks required

Country requirements are not assessed by the selected calculations.

Converter output

Assessment status	Checked requirements met
Result	10 kW
Source document · Page 2	10000 W https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf

Grid phases

Assessment status	Checked requirements met
Result	3
Requirement	3

PV input power

Assessment status	Checked requirements met
Result	20 kWp
Requirement	10 kWp
Source document · Page 2	20000 Wp https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf

PV strings and inputs

Assessment status	Further checks required

Required accessory

Assessment status	Checked requirements met
Result	SAJ BC2-HV1

Manufacturer pairing

Assessment status	Further checks required

Module count

Assessment status	Checked requirements met
Result	3

Parallel arrangement

Assessment status	Checked requirements met
Result	1

Battery voltage

Assessment status	Checked requirements met
Source document · Page 2	180~800 V https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf
Source document · Page 2	89.6-115.2 / 179.2-230.4 / 268.8-345.6 / 358.4-460.8 / 448-576.0 V https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf

Sales unit

Assessment status	Checked requirements met
Source document · Page 2	battery_module https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf

Usable energy

Assessment status	Checked requirements met
Result	13.5 kWh
Requirement	10 kWh
Source document · Page 2	4.5 kWh https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf

4.5 × 3 = 13.5 kWh

Continuous AC discharge power

Assessment status	Further checks required
Requirement	5 kW

Battery discharge path

Assessment status	Further checks required

Components and manufacturer conditions

Source document · Page 36	https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_10-30K_User-Manual_DE-EN_EU.pdf https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_10-30K_User-Manual_DE-EN_EU.pdf
Source document	https://de-linker.com/wp-content/uploads/2026/09/H2_HS2_HS3_AS2_AS3_Configuration_Instructions_V1.0_en.pdf https://de-linker.com/wp-content/uploads/2026/09/H2_HS2_HS3_AS2_AS3_Configuration_Instructions_V1.0_en.pdf
Source document	https://de-linker.com/wp-content/uploads/2026/10/B2-5.0-HV1-HV5-user-manual-EN-EU.pdf https://de-linker.com/wp-content/uploads/2026/10/B2-5.0-HV1-HV5-user-manual-EN-EU.pdf
Source document · Page 2	https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf
Source document · Page 37	https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_10-30K_User-Manual_DE-EN_EU.pdf https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_10-30K_User-Manual_DE-EN_EU.pdf

The H2 T3 ships with a smart meter, three current transformers and a 10 m meter communication cable (H2 manual, section 2.2 Unpacking, PDF p. 36 English / p. 7 German).

SAJ's B2 datasheet names B2-5.0 to B2-25.0 as one to five BU2-5.0 modules with one BC2-HV1 control module, and the B2 manual (V1.2, PDF p5) says the B2 can only be used as such a set: the control module is an article of its own.

SAJ's Configuration Instructions V1.0 (Section 2) give the H2 series system as H2 + BC2 + BU2. SAJ's B2 datasheet names B2-5.0 to B2-25.0 as one to five BU2-5.0 modules with one BC2-HV1 control module, and SAJ's B2 manual (V1.2, PDF p5) says the B2 can only be used as a set with SAJ's H2 high voltage series storage inverter. The listing does not cover the one-module B2-5.0, whose operating voltage lies below the H2 T3's battery voltage range.

One BU2-5.0 module alone operates at 89.6 to 115.2 V (SAJ's B2 datasheet gives this for the one-module B2-5.0), below the H2 T3's battery voltage range of 180 to 800 V; two modules operate at 179.2 to 230.4 V.

Provisional bill of materials

Quantity	Product	Reference
1	SAJ H2-10K-T3	DLK-SAJ-H210KT3
1	SAJ BC2-HV1	DLK-SAJ-BC2HV1
3	SAJ BU2-5.0-HV1	DLK-SAJ-BU250HV1

This provisional list comes from the selected saved equipment result. Quantities are shown only where established. It is not a complete installation bill of materials. Further components and open requirements need project-specific assessment.

PV generation scenario

PV generation	13,816.651 kWh
Calculation period (UTC)	2023-01-01T00:00:00+00:00 – 2024-01-01T00:00:00+00:00
Calculated intervals	8,760

This section presents the selected saved PV profile and its original assumptions. Detailed shading and electrical design require separate assessment.

Energy scenario

Simulated load demand	6,000 kWh
PV generation	13,816.651 kWh
Grid import	1,113.036 kWh
PV export	8,707.551 kWh
PV curtailment	0 kWh
Unserved simulated load	0 kWh
Solar share of gross demand	81.449 %
PV used or stored on site	36.978 %
Calculated intervals	8,760

These values come from the selected saved energy result and reflect its original scenario parameters. The general energy-flow model does not establish the performance of the selected equipment.

Saved calculation references

Data source	Beispielannahme · kein externer AC-Hilfsverbrauch
Data source	Deklariertes Beispiel: 10 kWh nutzbar, 5 kW AC, je Richtung 96 % Wirkungsgrad, keine Hilfs- oder Standverluste. Kein Produktdatenblatt und keine Gerätefreigabe.
Data source	Beispielverbrauch · 6.000 kWh pro Jahr
Data source	JRC PVGIS typical meteorological year
Calculation reference	10d121ed063349d49ab076753e52be11 · Input revision 13 · cb6e4681994c246ca40c639a3a0684bc6689bc9e583fd5479834076a5f55c68a
Calculation reference	f43b6f9410f14363902630800d565c20 · Input revision 11
Calculation reference	908626650f4549ddb5696cb162900a9a · Input revision 9