Project planning report

Saved project inputs and selected calculation results

2026-10-25 14:33:55.329667+00:00

Project

This report presents saved project inputs and the original results of the selected calculations. Country-specific requirements, electrical design and installation checks remain open. It does not approve the complete installation.

Project	Berlin · Beispielprojekt · PV und Speicher
Project reference	c7795bc2c1e14e389622015c809ace45
Input revision	20

Site and project inputs

Location	Berlin · Beispielstandort
Country	DE
Time zone	Europe/Berlin
Project note	Interaktives Beispiel mit echten JRC-Wetterdaten und nachgewiesenen Trina-Moduldaten; Dachgeometrie und Verbrauch sind Beispielannahmen.

Equipment checks

Country requirements are not assessed by the selected calculations.

Assessment status	Further checks required

Converter output

Assessment status	Checked requirements met
Result	10 kW
Source document · Page 2	10000 W https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf

Grid phases

Assessment status	Checked requirements met
Result	3
Requirement	3

PV input power

Assessment status	Checked requirements met
Result	20 kWp
Requirement	11.04 kWp
Source document · Page 2	20000 Wp https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf

PV strings and inputs

Assessment status	Further checks required

Required accessory

Assessment status	Checked requirements met
Result	SAJ BC2-HV1

Manufacturer pairing

Assessment status	Further checks required

Module count

Assessment status	Checked requirements met
Result	4

Parallel arrangement

Assessment status	Checked requirements met
Result	1

Battery voltage

Assessment status	Checked requirements met
Source document · Page 2	180~800 V https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf
Source document · Page 2	89.6-115.2 / 179.2-230.4 / 268.8-345.6 / 358.4-460.8 / 448-576.0 V https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf

Sales unit

Assessment status	Checked requirements met
Source document · Page 2	battery_module https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf

Usable energy

4.5 × 4 = 18 kWh

Assessment status	Checked requirements met
Result	18 kWh
Requirement	18 kWh
Source document · Page 2	4.5 kWh https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf

Continuous AC discharge power

Assessment status	Further checks required
Requirement	10 kW

Battery discharge path

Assessment status	Further checks required

Components and manufacturer conditions

The H2 T3 ships with a smart meter, three current transformers and a 10 m meter communication cable (H2 manual, section 2.2 Unpacking, PDF p. 36 English / p. 7 German).

SAJ's B2 datasheet names B2-5.0 to B2-25.0 as one to five BU2-5.0 modules with one BC2-HV1 control module, and the B2 manual (V1.2, PDF p5) says the B2 can only be used as such a set: the control module is an article of its own.

SAJ's Configuration Instructions V1.0 (Section 2) give the H2 series system as H2 + BC2 + BU2. SAJ's B2 datasheet names B2-5.0 to B2-25.0 as one to five BU2-5.0 modules with one BC2-HV1 control module, and SAJ's B2 manual (V1.2, PDF p5) says the B2 can only be used as a set with SAJ's H2 high voltage series storage inverter. The listing does not cover the one-module B2-5.0, whose operating voltage lies below the H2 T3's battery voltage range.

One BU2-5.0 module alone operates at 89.6 to 115.2 V (SAJ's B2 datasheet gives this for the one-module B2-5.0), below the H2 T3's battery voltage range of 180 to 800 V; two modules operate at 179.2 to 230.4 V.

Source document · Page 36	https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_10-30K_User-Manual_DE-EN_EU.pdf https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_10-30K_User-Manual_DE-EN_EU.pdf
Source document	https://de-linker.com/wp-content/uploads/2026/09/H2_HS2_HS3_AS2_AS3_Configuration_Instructions_V1.0_en.pdf https://de-linker.com/wp-content/uploads/2026/09/H2_HS2_HS3_AS2_AS3_Configuration_Instructions_V1.0_en.pdf
Source document	https://de-linker.com/wp-content/uploads/2026/10/B2-5.0-HV1-HV5-user-manual-EN-EU.pdf https://de-linker.com/wp-content/uploads/2026/10/B2-5.0-HV1-HV5-user-manual-EN-EU.pdf
Source document · Page 2	https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf
Source document · Page 37	https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_10-30K_User-Manual_DE-EN_EU.pdf https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_10-30K_User-Manual_DE-EN_EU.pdf

Provisional bill of materials

This provisional list comes from the selected saved equipment result. Quantities are shown only where established. It is not a complete installation bill of materials. Further components and open requirements need project-specific assessment.

Quantity	Product	Reference
1	SAJ H2-10K-T3	DLK-SAJ-H210KT3
1	SAJ BC2-HV1	DLK-SAJ-BC2HV1
4	SAJ BU2-5.0-HV1	DLK-SAJ-BU250HV1

PV modules used in the calculation

Module counts come from the saved layout of the selected generation result. The listed modules are design references; electrical and mounting suitability require project-specific assessment.

This list includes only the PV conversion group used by the selected DC calculation.

Input revision	9
PV nameplate power	11.04 kWp
Source document · Page 2	Trina Solar TSM-460NEG9R.28 https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf

Quantity	Model	Module power (STC)
24	Trina Solar TSM-460NEG9R.28	460 W

Energy scenario and selected equipment

These checks compare the saved scenario parameters with the equipment selected for this calculation. They do not establish manufacturer performance.

4.5 × 4 = 18 kWh

Assessment status	Further checks required
Model	SAJ BU2-5.0-HV1
Model	SAJ BC2-HV1
Model	SAJ H2-10K-T3
Module count	4
Parallel arrangement	1
Usable energy · Source document · Page 2	4.5 kWh https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf

Check	Assessment status	Result	Requirement
Usable energy	Checked requirements met	18 kWh	18 kWh
Continuous AC discharge power	Further checks required	—	10 kW
Scenario operating mode	Checked requirements met	—	—
Storage losses and operating conditions	Further checks required	—	—
Converter ports and system topology	Further checks required	—	—

Energy scenario

PV generation and curtailment are calculated at the DC bus; load supply and grid flows are calculated on the AC side. Storage results use the saved loss assumptions.

Battery temperature is a fixed scenario condition used to check the documented charging and discharging temperature ranges. It is not inferred from outdoor weather. This model uses fixed loss assumptions and does not simulate temperature changes.

Simulated load demand	1.103 kWh
PV generation (DC)	9.634 kWh
Grid import	0 kWh
PV export	0 kWh
PV curtailment (DC)	0 kWh
Unserved simulated load	0 kWh
Solar share of gross demand	100 %
PV used or stored on site	100 %
Calculated intervals	2
Battery temperature for this scenario	20 °C

Saved calculation references

Data source	Beispielannahme · kein externer AC-Hilfsverbrauch
Data source	Declared reference assumptions: DC/DC 98% each way, storage 99% each way, forward inverter 96%, fixed battery temperature 20 °C, zero internal and DC auxiliary demand and standing loss. No reverse charging. These are scenario assumptions, not manufacturer performance data.
Data source	Beispielverbrauch · 6.000 kWh pro Jahr
Data source	JRC PVGIS typical meteorological year
Calculation reference	4a89969354884bb79292f9ca000574c4 · Input revision 20